Elastic Wave Propagation in Nonlinear Two-dimensional Acoustic Metamaterials

Cheng Zhao

Northwestern Polytechnical University

Kai Zhang (✉ kzhang@nwpu.edu.cn)

Northwestern Polytechnical University

Pengcheng Zhao

Northwestern Polytechnical University

Zichen Deng

Northwestern Polytechnical University

Research Article

Keywords: Wave propagation, Acoustic metamaterials, Nonlinear, Perturbation method, Amplitude dependence

Posted Date: April 5th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-335256/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.
[Read Full License](#)

Version of Record: A version of this preprint was published at Nonlinear Dynamics on February 9th, 2022.
See the published version at <https://doi.org/10.1007/s11071-022-07259-z>.

Elastic wave propagation in nonlinear two-dimensional acoustic metamaterials

Cheng Zhao^{1,2}, Kai Zhang^{1,2*}, Pengcheng Zhao^{1,2}, Zichen Deng^{1,2}

1. School of Mechanics, Civil Engineering and Architecture, Northwestern

Polytechnical University, Xi'an 710072, P. R. China

2. MIIT Key Laboratory of Dynamics and Control of Complex Systems,

Northwestern Polytechnical University, Xi'an 710072, P. R. China

Abstract

This study describes the wave propagation in a periodic lattice which is formed by a spring-mass two-dimensional structure with local Duffing nonlinear resonators. The wave propagation characteristics of the system is evaluated by using the perturbation method and Floquet-Bloch theorem to determine the dispersion relationships and wave propagation characteristics in the nonlinear two-dimensional acoustic metamaterials (2D AM). A quantitative study of wave amplitude is carried out to reveal the limits of the proposed method. In particular, the harmonic balance method is introduced to investigate the frequency response and effective mass of the nonlinear systems. We find that the dispersion relations, group velocity, negative effective mass of unit-cell are related to wave amplitude. Furthermore, the dual wave vector, bifurcation of periodic solutions and chaotic band are observed in the nonlinear systems. The results can be used to tune wave propagation in the nonlinear acoustic metamaterials and provide some ideas for the study of nonlinear metamaterials.

Keywords

Wave propagation; Acoustic metamaterials; Nonlinear; Perturbation method; Amplitude dependence

* Corresponding author, Email: kzhang@nwpu.edu.cn (Kai Zhang)

1 Introduction

Lightweight periodic lattices [1] have been developed and used in disparate engineering applications for many decades [2] owing to their distinguished properties such as high specific strength, high stiffness, and multi-functional potential [3, 4]. In addition to their superior static properties, lattice structures also provide excellent dynamic properties. The wave propagation behaviors in periodic media are interesting and important dynamic phenomena and properties. Owing to the periodic properties, periodic structures show extraordinary behaviors for prohibiting wave propagation, at locations called "stop bands" in a specific frequency range. After past decades of researches, two types of stop bands can be identified in periodic systems. One type is represented by Bragg bandgaps, which are related to the material properties or the geometry of the unit cell using properties like hierarchical structures [5], auxetics [6] and structures with curved beams [7]. The other type of stop bands are the so-called locally resonant (LR) bandgaps, caused by a resonating system included in the periodic structure. The pioneering work of Liu et al. [8] has led to the generation of acoustic metamaterials (AM) which are typically artificial periodic media that has subwavelength characteristics of elastic waves based on mechanism of local resonance. At present, numerous studies focus on linear AM [9-12]. There has been an interest in designing AM to present negative mass effect [13]. Furthermore, LR bandgaps can happen at wavelengths which are much larger than the lattice size, yielding low-frequency vibration/noise attenuation and wave filtering [14, 15]. However, in such linear configurations, the resulting attenuation bandwidth and wave propagation in AM are limited by the parameters of material and structure, i.e. masses of local resonators [16], which is typically aimed to be minimized in most applications that require lightweight and the wave propagation of linear systems cannot be tuned in active or passive ways. Compared with linear systems, nonlinearity provides abundant dynamic characteristics, such as subharmonics, solitary waves, wave coupling, phase matching, self-collimation, multi-stable, non-reciprocal diodes, etc. [17-21]. In addition, nonlinear dynamic phenomena such as nonlinear resonance, modal coupling, chaos, etc. [22-24] are expected to provide new wave control mechanisms for nonlinear acoustic/elastic media.

The introduction of nonlinear factors into AM is expected to break the technical bottleneck of low-frequency, broadband, and high-efficiency vibration control of structures, which gradually become an emerging hot topic in the metamaterial research community.

At present, a few researchers [25-27] have reported the dispersion characteristics of nonlinear AM. In the field of energy harvesting, appropriately designed nonlinear oscillator can be used to enhance frequency bandwidth [28]. And a plethora of wideband dynamic behavior is discovered in bistable configuration that chaotic interwell vibrations depending on the input amplitudes [29, 30]. As for the nonlinear vibration suppression, Higashiyama et al. [31] studied the band-edge mode of the diatomic chain model under even-order nonlinearity. Cveticanin et al. [32] studied the equivalent negative mass characteristics of the Duffing nonlinear diatomic chain metamaterial model based on theory. Zhou et al. [33] established a diatomic chain metamaterial model with a linear oscillator attached to a nonlinear matrix structure. The space wave packet propagation characteristics in an infinite weakly nonlinear structure was studied and it was found that the transient wave packet has a significant frequency shift when propagating in the band gap due to the nonlinearity. Gantzounis et al. [34] attached a local resonator to a sphere of a granular crystal to form a nonlinear metamaterial, and studied its band gap and damping characteristics. Khajehtourian and Hussein [35] studied the approximate dispersion characteristics of a one-dimensional nonlinear locally resonant metamaterial rod based on the transfer matrix method. The nonlinearity of the system originates from the high-order deformation of the thin-walled rod. The position and width of the band gap vary with the wave amplitude. Bilal et al. [36] used the coupling of vibrator and magnetic force to induce nonlinearity, and realized a transistor-like phonon switching element at a single frequency of one-dimensional metamaterial.

However, previous researches on nonlinear acoustic metamaterials mainly focused on one-dimensional system, and rarely involved nonlinear two-dimensional acoustic metamaterials (2D AM). The reason is that the nonlinear two-dimensional systems have numerous coupling degrees of freedom which makes it difficult to establish and solve

the equation of motion, especially in a high-dimensional complex nonlinear system. This leads to a great gap in the study of nonlinear 2D AM. As well known, vibration suppression performance, static performance and wave propagation characteristics of AMs play an important role in applications. It is necessary to investigate these characteristics of nonlinear 2D AM.

This paper focus on the wave propagation, vibration, and static characteristics of nonlinear 2D AM and the organized as follows. In Section 2, the Floquet-Bloch theorem and Perturbation method is introduced to investigate the dispersion relationships for linear and nonlinear 2D AM. The peculiar phenomena accompanied with the amplitude-dependent iso-frequency contours and group velocity are also studied in Section 2. Section 3 mainly introduces the vibration response of nonlinear systems calculated by the harmonic balance method. The excitation amplitude-dependent is investigated in the vibration response. The effective mass of the nonlinear 2D AM has been studied in Section 4. Summarization and conclusion for nonlinear effects on the nonlinear 2D AM follow in Section 5.

2 Dispersion analysis of two-dimensional metamaterials

In this section, the calculation method of the dispersion relation of infinite two-dimensional metamaterials is mainly introduced. Firstly, the case of a linear spring mass resonator is considered, then further investigation is dedicated to the case of a nonlinear spring mass resonator.

2.1 Linear spring-mass resonator

Let us consider an infinite 2D periodic AM with a lattice constant l consisting of AM unit-cells and a series of springs as shown in Fig. 1(a). The unit-cells in our AM are arranged in a square configuration with each host medium connected to eight neighboring unit-cells through linear stiffness springs, among which four are diagonal. As shown in Fig. 1(b), the linear unit-cell is composed of the resonator m_3 , the host

114 medium m_1 , and connected by a linear stiffness k_3 spring. As for the connection
 115 between the host mediums, it is assumed that the stiffness of springs in the x-axis and
 116 y-axis directions as k_1 , and that of the diagonal ones as k_2 . The AM is infinite and the
 117 $(n, p)^{\text{th}}$ unit-cell is defined to apply the Floquet-Bloch Theorem.
 118 For the plane time harmonic propagation in the x-axis and y-axis directions with small
 119 displacements and the coupling of horizontal and vertical motion, the motion equation
 120 of the $(n, p)^{\text{th}}$ unit-cell in the system is given by:

(a)

(b)

(c)

Fig. 1 Configuration of the 2D infinite acoustic metamaterials. **a** Structurally model, **b** Representative linear unit-cell, **c** Representative nonlinear unit-cell.

$$\begin{aligned}
 m_1 \frac{\partial^2 u_{1(n,p)}}{\partial t^2} = & k_1 (u_{1(n+1,p)} + u_{1(n-1,p)} - 2u_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (u_{1(n+1,p+1)} + u_{1(n-1,p-1)} - 2u_{1(n,p)} + v_{1(n+1,p+1)} + v_{1(n-1,p-1)} - 2v_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (u_{1(n-1,p+1)} + u_{1(n+1,p-1)} - 2u_{1(n,p)} - v_{1(n-1,p+1)} - v_{1(n+1,p-1)} + 2v_{1(n,p)}) \\
 & + k_3 (u_{3(n,p)} - u_{1(n,p)}),
 \end{aligned} \tag{1}$$

$$m_3 \frac{\partial^2 u_{3(n,p)}}{\partial t^2} = k_3 (u_{1(n,p)} - u_{3(n,p)}), \tag{2}$$

$$\begin{aligned}
 m_1 \frac{\partial^2 v_{1(n,p)}}{\partial t^2} = & k_1 (v_{1(n,p+1)} + v_{1(n,p-1)} - 2v_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (v_{1(n+1,p+1)} + v_{1(n-1,p-1)} - 2v_{1(n,p)} + u_{1(n+1,p+1)} + u_{1(n-1,p-1)} - 2u_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (v_{1(n-1,p+1)} + v_{1(n+1,p-1)} - 2v_{1(n,p)} - u_{1(n-1,p+1)} - u_{1(n+1,p-1)} + 2u_{1(n,p)}) \\
 & + k_3 (v_{3(n,p)} - v_{1(n,p)}),
 \end{aligned} \tag{3}$$

$$m_3 \frac{\partial^2 v_{3(n,p)}}{\partial t^2} = k_3 (v_{1(n,p)} - v_{3(n,p)}), \tag{4}$$

where n and p are arbitrary integer numbers, u_1 and v_1 are the displacements of the host medium in x-axis and y-axis directions, u_3 and v_3 are the displacements of the resonator in x-axis and y-axis directions, respectively.

The wave solution is assumed as:

$$u_{r(n,p)} = A_r e^{i(nk_x + pk_y - \omega t)} \quad (r = 1, 3), \tag{5}$$

$$v_{r(n,p)} = B_r e^{i(nk_x + pk_y - \omega t)} \quad (r = 1, 3), \tag{6}$$

where A_r and B_r are the wave amplitudes, $i = \sqrt{-1}$ is the imaginary number, ω is the wave frequency, and $[k_x, k_y]$ is the two components of the wavevector $\mathbf{k}$.

Substituting the solution of Eqs. (5) and (6) into Eqs. (1) to (4), we get:

$$-m_1\omega^2 A_1 = 2k_1(\cos k_x - 1)A_1 + k_3(A_3 - A_1) + k_2(\cos(k_x + k_y) - 1)(A_1 + B_1) + k_2(\cos(k_x - k_y) - 1)(A_1 - B_1), \quad (7)$$

$$-m_3\omega^2 A_3 = k_3(A_1 - A_3), \quad (8)$$

$$-m_1\omega^2 A_1 = 2k_1(\cos k_y - 1)B_1 + k_3(B_3 - B_1) + k_2(\cos(k_x + k_y) - 1)(A_1 + B_1) + k_2(\cos(k_x - k_y) - 1)(B_1 - A_1), \quad (9)$$

$$-m_3\omega^2 B_3 = k_3(B_1 - B_3). \quad (10)$$

Eqs. (7) to (10) form an eigenvalue problem governed by:

$$[\mathbf{S}(k_x, k_y) - \omega^2 \mathbf{I}] \mathbf{U} = \mathbf{0}, \quad (11)$$

where $\mathbf{U} = [A_1, A_3, B_1, B_3]^T$, $\mathbf{S}(k_x, k_y)$ is a 4×4 matrix and $\mathbf{I}$ is an identity matrix. By using the condition of nontrivial solutions for Eq. (11), the relation between the wave frequency ω and wavevector components k_x and k_y can be obtained. Fig. 2(a) shows the first Brillouin zone of 2D periodic structures, the wavevector should be taken in the whole Brillouin zone in usual, while the unit-cell is square and symmetrical, the analysis can be restricted to the irreducible Brillouin zones (shadow areas). Furthermore, it is only necessary to search the boundary of shadow areas, i.e., along the path $\text{M}-\Gamma-\text{X}-\text{M}$, since the extremums of the wave frequencies are always found on the zone boundary. The dispersion curve of linear AM is shown in Fig. 2(b), with the specific parameters for $m_1 = m_3 = 1\text{kg}$, $k_1 = k_2 = k_3 = 1\text{N/m}$, and the normalized

frequency is defined as $\Omega = \frac{\omega}{\sqrt{k_1/m_1}}$. We can find that a local resonance band gap exists

between normalized frequency $\Omega = 0.95$ and $\Omega = 1.4$, including the natural frequency of the linear resonator ($\omega_3 = \sqrt{k_3/m_3} = 1$) within its range.

Fig. 2 **a** the first Brillouin zone and irreducible Brillouin zones (shadow area) and **b** Dispersion of 2-D metamaterials with linear resonator

2.2 Nonlinear spring-mass resonator

2.2.1 Perturbation method for nonlinear dispersion diagram

Now, considering the nonlinear resonator unit-cell, a Duffing spring-mass resonator (shown in Fig. 1(c)) has replaced the linear spring-mass resonator which is connected the host medium m . Here, the nonlinear force-displacement relationship of the springs is expressed as:

$$F_{nl} = k_3 \Delta x + k_n (\Delta x)^3, \quad (12)$$

where k_n is the nonlinear stiffness and $\Delta x = q_{3(n,p)} - q_{1(n,p)}$, ($q = u, v$) is the relative displacement of resonator m_3 and host medium m . Here, we focus on the weakly nonlinear system and adopt a perturbation approach to solve nonlinear equations while the approach used for the linear case could not be applicable for nonlinear two-dimension AM. Then, a perturbation parameter ε is introduced to express the nonlinear force-displacement relationship [37]:

$$F_{nl} = k_3 \Delta x + \varepsilon k_n (\Delta x)^3. \quad (13)$$

170 Replacing the linear restoring force $k_3 \Delta x$ by Eq. (13) in Eqs. (1) to (4), the
 171 governing equation of motion of nonlinear unit-cell can be written as:

$$\begin{aligned}
 m_1 \frac{\partial^2 u_{1(n,p)}}{\partial t^2} = & k_1 (u_{1(n+1,p)} + u_{1(n-1,p)} - 2u_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (u_{1(n+1,p+1)} + u_{1(n-1,p-1)} - 2u_{1(n,p)} + v_{1(n+1,p+1)} + v_{1(n-1,p-1)} - 2v_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (u_{1(n-1,p+1)} + u_{1(n+1,p-1)} - 2u_{1(n,p)} - v_{1(n-1,p+1)} - v_{1(n+1,p-1)} + 2v_{1(n,p)}) \\
 & + k_3 (u_{3(n,p)} - u_{1(n,p)}) + \varepsilon k_n (u_{3(n,p)} - u_{1(n,p)})^3,
 \end{aligned} \tag{14}$$

$$m_3 \frac{\partial^2 u_{3(n,p)}}{\partial t^2} = k_3 (u_{1(n,p)} - u_{3(n,p)}) + \varepsilon k_n (u_{1(n,p)} - u_{3(n,p)})^3, \tag{15}$$

$$\begin{aligned}
 m_1 \frac{\partial^2 v_{1(n,p)}}{\partial t^2} = & k_1 (v_{1(n,p+1)} + v_{1(n,p-1)} - 2v_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (v_{1(n+1,p+1)} + v_{1(n-1,p-1)} - 2v_{1(n,p)} + u_{1(n+1,p+1)} + u_{1(n-1,p-1)} - 2u_{1(n,p)}) \\
 & + \frac{1}{2} k_2 (v_{1(n-1,p+1)} + v_{1(n+1,p-1)} - 2v_{1(n,p)} - u_{1(n-1,p+1)} - u_{1(n+1,p-1)} + 2u_{1(n,p)}) \\
 & + k_3 (v_{3(n,p)} - v_{1(n,p)}) + \varepsilon k_n (v_{3(n,p)} - v_{1(n,p)})^3,
 \end{aligned} \tag{16}$$

$$m_3 \frac{\partial^2 v_{3(n,p)}}{\partial t^2} = k_3 (v_{1(n,p)} - v_{3(n,p)}) + \varepsilon k_n (v_{1(n,p)} - v_{3(n,p)})^3. \tag{17}$$

176 The next step here is to use the Lindstedt-Poincaré adapted method developed in [38]
 177 to determine the correction term in the dispersion relationship. The main goal is to
 178 generate a first-order asymptotic expansion on the displacement and frequency of the
 179 masses, corresponding to the following expression:

$$\begin{aligned}
 q_r &= q_r^{(0)} + \varepsilon q_r^{(1)} + o(\varepsilon^2), \\
 \omega &= \omega_0 + \varepsilon \omega_1 + o(\varepsilon^2).
 \end{aligned} \tag{18}$$

181 In the weakly nonlinear system (which is our main consideration here), the higher order
 182 terms such as ε^2 or ε^3 terms are very small compared to ε^0 or ε^1 terms.
 183 Substituting Eq. (18) into Eqs. (14) to (17), after development and separation of the
 184 equations in the ε^0 and ε^1 orders:

$$\begin{aligned}
& \left. \varepsilon^0: \left\{ \begin{aligned}
& \Omega_0^2 \frac{\partial^2 u^{(0)}}{\partial \tau^2} = u_{1(n+1,p)}^{(0)} + u_{1(n-1,p)}^{(0)} - 2u_{1(n,p)}^{(0)} + \beta \left(u_{3(n,p)}^{(0)} - u_{1(n,p)}^{(0)} \right) \\
& \quad + \frac{1}{2} \alpha \left(u_{1(n+1,p+1)}^{(0)} + u_{1(n-1,p-1)}^{(0)} - 2u_{1(n,p)}^{(0)} + v_{1(n+1,p+1)}^{(0)} + v_{1(n-1,p-1)}^{(0)} - 2v_{1(n,p)}^{(0)} \right) \\
& \quad + \frac{1}{2} \alpha \left(u_{1(n-1,p+1)}^{(0)} + u_{1(n+1,p-1)}^{(0)} - 2u_{1(n,p)}^{(0)} - v_{1(n-1,p+1)}^{(0)} - v_{1(n+1,p-1)}^{(0)} + 2v_{1(n,p)}^{(0)} \right) \\
& \gamma^2 \Omega_0^2 \frac{\partial^2 u^{(0)}}{\partial \tau^2} = u_{1(n,p)}^{(0)} - u_{3(n,p)}^{(0)} \\
& \Omega_0^2 \frac{\partial^2 v^{(0)}}{\partial \tau^2} = v_{1(n,p+1)}^{(0)} + v_{1(n,p-1)}^{(0)} - 2v_{1(n,p)}^{(0)} + \beta \left(v_{3(n,p)}^{(0)} - v_{1(n,p)}^{(0)} \right) \\
& \quad + \frac{1}{2} \alpha \left(v_{1(n+1,p+1)}^{(0)} + v_{1(n-1,p-1)}^{(0)} - 2v_{1(n,p)}^{(0)} + u_{1(n+1,p+1)}^{(0)} + u_{1(n-1,p-1)}^{(0)} - 2u_{1(n,p)}^{(0)} \right) \\
& \quad + \frac{1}{2} \alpha \left(v_{1(n-1,p+1)}^{(0)} + v_{1(n+1,p-1)}^{(0)} - 2v_{1(n,p)}^{(0)} - u_{1(n-1,p+1)}^{(0)} - u_{1(n+1,p-1)}^{(0)} + 2u_{1(n,p)}^{(0)} \right) \\
& \gamma^2 \Omega_0^2 \frac{\partial^2 v^{(0)}}{\partial \tau^2} = v_{1(n,p)}^{(0)} - v_{3(n,p)}^{(0)}
\end{aligned} \right\}, \tag{19}
\end{aligned}$$

185

186

$$\begin{aligned}
& \left. \varepsilon^1: \left\{ \begin{aligned}
& \Omega_0^2 \frac{\partial^2 u^{(1)}}{\partial \tau^2} + 2u_{1(n,p)}^{(1)} - u_{1(n+1,p)}^{(1)} - u_{1(n-1,p)}^{(1)} + \frac{1}{2} \alpha \left(2u_{1(n,p)}^{(1)} - u_{1(n+1,p+1)}^{(1)} - u_{1(n-1,p-1)}^{(1)} + 2v_{1(n,p)}^{(1)} - v_{1(n+1,p+1)}^{(1)} - v_{1(n-1,p-1)}^{(1)} \right) \\
& + \frac{1}{2} \alpha \left(2u_{1(n,p)}^{(1)} - u_{1(n-1,p+1)}^{(1)} - u_{1(n+1,p-1)}^{(1)} - 2v_{1(n,p)}^{(1)} + v_{1(n-1,p+1)}^{(1)} + v_{1(n+1,p-1)}^{(1)} \right) - \beta \left(u_{3(n,p)}^{(1)} - u_{1(n,p)}^{(1)} \right) \\
& = -2\Omega_0\Omega_1 \frac{\partial^2 u^{(0)}}{\partial \tau^2} + \overline{k_n} \left(u_{3(n,p)}^{(0)} - u_{1(n,p)}^{(0)} \right)^3 \\
& \gamma^2 \Omega_0^2 \frac{\partial^2 u^{(1)}}{\partial \tau^2} + u_{3(n,p)}^{(1)} - u_{1(n,p)}^{(1)} = \frac{\overline{k_n}}{\beta} \left(u_{1(n,p)}^{(0)} - u_{3(n,p)}^{(0)} \right)^3 - 2\gamma^2 \Omega_0\Omega_1 \frac{\partial^2 u^{(0)}}{\partial \tau^2} \\
& \Omega_0^2 \frac{\partial^2 v^{(1)}}{\partial \tau^2} + 2v_{1(n,p)}^{(1)} - v_{1(n+1,p+1)}^{(1)} - v_{1(n-1,p-1)}^{(1)} + \frac{1}{2} \alpha \left(2v_{1(n,p)}^{(1)} - v_{1(n+1,p+1)}^{(1)} - v_{1(n-1,p-1)}^{(1)} + 2u_{1(n,p)}^{(1)} - u_{1(n+1,p+1)}^{(1)} - u_{1(n-1,p-1)}^{(1)} \right) \\
& + \frac{1}{2} \alpha \left(2v_{1(n,p)}^{(1)} - v_{1(n-1,p+1)}^{(1)} - v_{1(n+1,p-1)}^{(1)} - 2u_{1(n,p)}^{(1)} + u_{1(n-1,p+1)}^{(1)} + u_{1(n+1,p-1)}^{(1)} \right) - \beta \left(v_{3(n,p)}^{(1)} - v_{1(n,p)}^{(1)} \right) \\
& = -2\Omega_0\Omega_1 \frac{\partial^2 v^{(0)}}{\partial \tau^2} + \overline{k_n} \left(v_{3(n,p)}^{(0)} - v_{1(n,p)}^{(0)} \right)^3 \\
& \gamma^2 \Omega_0^2 \frac{\partial^2 v^{(1)}}{\partial \tau^2} + v_{3(n,p)}^{(1)} - v_{1(n,p)}^{(1)} = \frac{\overline{k_n}}{\beta} \left(v_{1(n,p)}^{(0)} - v_{3(n,p)}^{(0)} \right)^3 - 2\gamma^2 \Omega_0\Omega_1 \frac{\partial^2 v^{(0)}}{\partial \tau^2}
\end{aligned} \right\}, \tag{20}
\end{aligned}$$

188

189 where $\Omega_z^2 = \frac{\omega_z}{k_1/m_1}$, $(z=0,1)$, $\alpha = \frac{k_2}{k_1}$, $\beta = \frac{k_3}{k_1}$, $\overline{k_n} = \frac{k_n}{k_1}$, $\gamma^2 = \frac{k_1/m_1}{k_3/m_3}$, $\tau = \omega t$. To

190 solve Eqs. (19) and (20) by assuming that the solution have reached an harmonic

191 regime, the displacement $u_{r(n,p)}^{(0)}$, $v_{r(n,p)}^{(0)}$ and the second order derivatives are then:

$$\begin{aligned}
 u_{r(n,p)}^{(0)} &= \frac{A_r}{2} e^{i(nk_x + pk_y - \omega t)} + c.c. \\
 v_{r(n,p)}^{(0)} &= \frac{B_r}{2} e^{i(nk_x + pk_y - \omega t)} + c.c. \\
 \frac{\partial^2 u_{r(n,p)}^{(0)}}{\partial \tau^2} &= -u_{r(n,p)}^{(0)} \quad \frac{\partial^2 v_{r(n,p)}^{(0)}}{\partial \tau^2} = -v_{r(n,p)}^{(0)},
 \end{aligned} \tag{21}$$

193 where $c.c.$ denotes the complex conjugate. Comparing Eq. (19) with Eqs. (1) to (4),
 194 we can find that they are equivalent at ε^0 order. This means that the solution at ε^0
 195 order is the solution of the linear part of the perturbation method, and the solution at
 196 ε^1 order is a correction to the linear solution. We can get the linear solution from Eq.
 197 (11).

198 As for the treatment of equations of the ε^1 order, we can adopt the same approach
 199 used during the linear part analysis, the corrected displacement $u_{3(n,p)}^{(1)}$ and $v_{3(n,p)}^{(1)}$
 200 should be isolate and submit them to $u_{1(n,p)}^{(1)}$ and $v_{1(n,p)}^{(1)}$ terms, respectively. For this
 201 purpose, the solution form of $u_{3(n,p)}^{(1)}$ and $v_{3(n,p)}^{(1)}$ should be determined by:

$$\begin{aligned}
 u_{3(n,p)}^{(1)} &= D e^{i(nk_x + pk_y - \omega t)} + c.c. \\
 v_{3(n,p)}^{(1)} &= E e^{i(nk_x + pk_y - \omega t)} + c.c.,
 \end{aligned} \tag{22}$$

203 where D and E are the corresponding wave amplitudes, while they could have no
 204 effect on the final solutions. Substituting Eqs. (21) and (22) into equation (20), we
 205 can get:

206

$$\varepsilon^1: \left\{ \begin{aligned}
 &\Omega_0^2 \frac{\partial^2 u_{1(n,p)}^{(1)}}{\partial \tau^2} + 2u_{1(n,p)}^{(1)} - u_{1(n+1,p)}^{(1)} - u_{1(n-1,p)}^{(1)} + \frac{1}{2} \alpha \left(2u_{1(n,p)}^{(1)} - u_{1(n+1,p+1)}^{(1)} - u_{1(n-1,p-1)}^{(1)} + 2v_{1(n,p)}^{(1)} - v_{1(n+1,p+1)}^{(1)} - v_{1(n-1,p-1)}^{(1)} \right) \\
 &+ \frac{1}{2} \alpha \left(2u_{1(n,p)}^{(1)} - u_{1(n-1,p+1)}^{(1)} - u_{1(n+1,p-1)}^{(1)} - 2v_{1(n,p)}^{(1)} + v_{1(n-1,p+1)}^{(1)} + v_{1(n+1,p-1)}^{(1)} \right) - \beta \frac{\gamma^2 \Omega_0^2}{1 - \gamma^2 \Omega_0^2} u_{1(n,p)}^{(1)} = FX \\
 &\Omega_0^2 \frac{\partial^2 v_{1(n,p)}^{(1)}}{\partial \tau^2} + 2v_{1(n,p)}^{(1)} - v_{1(n+1,p)}^{(1)} - v_{1(n-1,p)}^{(1)} + \frac{1}{2} \alpha \left(2v_{1(n,p)}^{(1)} - v_{1(n+1,p+1)}^{(1)} - v_{1(n-1,p-1)}^{(1)} + 2u_{1(n,p)}^{(1)} - u_{1(n+1,p+1)}^{(1)} - u_{1(n-1,p-1)}^{(1)} \right) \\
 &+ \frac{1}{2} \alpha \left(2v_{1(n,p)}^{(1)} - v_{1(n-1,p+1)}^{(1)} - v_{1(n+1,p-1)}^{(1)} - 2u_{1(n,p)}^{(1)} + u_{1(n-1,p+1)}^{(1)} + u_{1(n+1,p-1)}^{(1)} \right) - \beta \frac{\gamma^2 \Omega_0^2}{1 - \gamma^2 \Omega_0^2} v_{1(n,p)}^{(1)} = FY
 \end{aligned} \right. ,$$

$$(23)$$

with

$$\begin{aligned} FX &= \left(\Omega_0 \Omega_1 \frac{\beta \gamma^2 + (1 - \gamma^2 \Omega_0^2)^2}{(1 - \gamma^2 \Omega_0^2)^2} A_1 - \frac{3\bar{k}_n}{8} \left(\frac{\gamma^2 \Omega_0^2}{(1 - \gamma^2 \Omega_0^2)^2} \right)^4 A_1^3 \right) e^{i(nk_x + pk_y - \tau)} + J e^{3i(nk_x + pk_y - \tau)} + c.c. \\ FY &= \left(\Omega_0 \Omega_1 \frac{\beta \gamma^2 + (1 - \gamma^2 \Omega_0^2)^2}{(1 - \gamma^2 \Omega_0^2)^2} B_1 - \frac{3\bar{k}_n}{8} \left(\frac{\gamma^2 \Omega_0^2}{(1 - \gamma^2 \Omega_0^2)^2} \right)^4 B_1^3 \right) e^{i(nk_x + pk_y - \tau)} + J e^{3i(nk_x + pk_y - \tau)} + c.c.. \end{aligned}$$

$$(24)$$

It can be figured out that the coefficient of $e^{i(nk_x + pk_y - \tau)}$ should be zero, otherwise, the solution becomes a resonance solution that goes to infinite value. Assuming the wave amplitude $A_1 = B_1$, therefore, we can get the solution about Ω_1 :

$$\Omega_1 = \frac{3\bar{k}_n A_1^2}{8} \frac{\gamma^2 \Omega_0^7}{(1 - \gamma^2 \Omega_0^2)^2 (\beta \gamma^2 + (1 - \gamma^2 \Omega_0^2)^2)}. \quad (25)$$

According to Eqs. (11), (18) and (25), we can get the final expression describing the corrected dispersion relation for the nonlinear 2D AM:

$$\Omega = \Omega_0 + \varepsilon \Omega_1. \quad (26)$$

Eq. (26) gives the dispersion relationship of 2D AM with nonlinear resonator. It is indicated that the frequency is mainly affected by nonlinear stiffness $\bar{k}_n$, wave amplitude A_1 . For the following analysis, we will focus on these aspects.

The band structure of nonlinear AM with different nonlinear stiffness ($\bar{k}_n = -1$ (violet), $\bar{k}_n = 0$ (blue), $\bar{k}_n = 1$ (red)) which are obtained along the $M-\Gamma-X-M$ edges of the first Brillouin zone is shown in Fig. 3, where the parameter γ , β and A_1 are equal to 1. As shown in Fig. 3(a), we can observe that due to the existence of the resonator, the band structure of the three stiffnesses will produce a local resonance band gap between the second and third branch. Based on the linear dispersion (blue), as changing nonlinear stiffness, it can be observed that the band structure will also change

accordingly. Interestingly, the study found that only the second and third branches have
 obvious changes within a certain range, which shows that the frequency correction
 value of the nonlinear stiffness is larger in this area, while the correction value of other
 areas is smaller. As for the $\overline{k_n} = -1$ (violet), the frequencies of the first and second
 branches reduce relatively to linear case especially in the $\Gamma-X-M$ area. It means
 that the lower boundary of local resonance band gap decreases at $\overline{k_n} = -1$. And the
 frequency of the third branch also has a reduction around the point Γ , which represents
 the upper boundary of local resonance band gap. In the case of $\overline{k_n} = 1$ (red), the
 opposite phenomenon of $\overline{k_n} = -1$ occurs, the changing area of the two cases is
 basically the same, the trend of change in this case is that the frequency of the second
 and third order branches increases. We can find that in the second branch, the point X
 becomes the lower boundary of band gap, while the upper boundary in the point Γ
 has no obvious change in the third branch. It will narrow the band gap. Furthermore,
 the distributions of band gap for changing nonlinear stiffness $\overline{k_n}$ from -1 to 1 is
 investigated, as shown in Fig. 3 (b). The red and blue lines represent the maximum
 frequency of the second and the minimum frequency of third branch, and the black line
 denotes the width of band gap, respectively. It was indicated that with changing
 nonlinear stiffness from -1 to 1 , the frequency of the lower boundary of the band gap
 gradually rises while the frequency of the upper boundary increases slightly, resulting
 reduction of the width of the band gap. This phenomenon shows that the dispersion
 relationship is influenced by the nonlinear stiffness $\overline{k_n}$, the nonlinear band gap of
 nonlinear 2D AM can be controlled by adjusting the nonlinear stiffness.

Fig. 3 a Dispersion of the nonlinear AM for different nonlinear stiffness $\bar{k}_n = -1$ (violet), $\bar{k}_n = 0$ (blue), $\bar{k}_n = 1$ (red).

b Distributions of the band gap for changing $\bar{k}_n$ from -1 to 1 .

252

253 2.2.2 Domain of amplitude validity

254 Let us consider the details of Eq. (26) illustrates the nonlinear dispersion relationship.
 255 The value of Ω_1 will increase as the value of $\gamma^2 \Omega_0^2$ increases, however, as the value
 256 of $\gamma^2 \Omega_0^2$ gradually approaches to 1, the value of Ω_1 will become larger than the value
 257 of Ω_0 and tend to infinity which does not meet the assumptions of the perturbation
 258 method used here.

259 The perturbation analysis assumes an asymptotic development of the term Ω_1 to
 260 obtain the correct result of frequency. After normalizing the frequency ω , we can get
 261 the asymptotic development of term $\Omega^2 = (\Omega_0 + \varepsilon \Omega_1 + o(\varepsilon^2))^2 = \Omega_0^2 + 2\varepsilon \Omega_0 \Omega_1$. To
 262 ensure the Eq. (23) is true, the asymptotic development of term Ω^2 should be
 263 satisfied as $2\varepsilon \Omega_0 \Omega_1 = \Omega_0^2$, and submit the expression of Ω_1 , we can get the

264 relationship:

$$265 \quad \frac{3\varepsilon \bar{k}_n A_1^2}{4} \frac{\gamma^2 \Omega_0^6}{(1 - \gamma^2 \Omega_0^2)^2 (\beta \gamma^2 + (1 - \gamma^2 \Omega_0^2)^2)} = 1. \quad (27)$$

266 Because of the assuming perturbation parameter ε is small, the order of magnitude of
 267 ε is equal to ε . Then we can get the relationship between wave amplitude A_1 and
 268 nonlinear stiffness $\bar{k}_n$:

$$269 \quad A_1 < \frac{1}{C(\bar{k}_n)}, \quad (28)$$

$$C(\bar{k}_n) = \sqrt{\frac{3\varepsilon \bar{k}_n}{4} \frac{\gamma^2 \Omega_0^6}{(1 - \gamma^2 \Omega_0^2)^2 (\beta \gamma^2 + (1 - \gamma^2 \Omega_0^2)^2)}}.$$

270 For a given $\bar{k}_n$, we can get the domain of wave amplitude. The result of $\bar{k}_n = 1$ is
 271 plotted in Fig. 4. For convenience, we select the $M-\Gamma$ area for analysis. The maximum
 272 of wave amplitude for four branches have been calculated, the red dotted line denotes
 273 the minimum value of allowed amplitude A_1 for nonlinear effects in four branches.
 274 For the first (black) and second (red) branches, the minimum value of allowed
 275 amplitude A_1 approaches to a theoretical limit of 0.4 and 0.25 respectively at certain
 276 points and the allowed amplitude will increase as wave number increases. Furthermore,
 277 we can find that A_1 has a little nonlinear effect on the dispersion in the right sides of
 278 the point A and B in irreducible Brillouin zone. This means that the linearization
 279 assumption in the areas $A-\Gamma$ and $B-\Gamma$ remains true even for very high values of
 280 amplitude, respectively. This phenomenon can also be observed in Fig. 3(a), it is
 281 obvious to see that the first and second branches changes by different nonlinear stiffness
 282 $\bar{k}_n$ in the $M-A$ and $M-B$ areas while the branches have almost no change
 283 compared with linear band structure in the areas $A-\Gamma$ and $B-\Gamma$. However, as for
 284 the cases of the third (blue) and fourth (green) branches, the third branch get the
 285 maximum value 1.75 at point M while get the minimum value 0.55 at point Γ . And
 286 we can observe that the fourth branch have the same minimum value 0.55 and its

maximum value 2.45 was got between the points M and A. In order to analysis the influence of nonlinear effect on the four branches comprehensively, we determine the range of wave amplitude as 0-1.5 (shadow area) and the nonlinear stiffness $\overline{k_n} = 1$ to investigate the amplitude-dependent characteristics of dispersion relationship in the following analysis unless otherwise stated.

Fig. 4 Domain of wave amplitude in the area of M- Γ at $\overline{k_n} = 1$

2.3 Amplitude-dependent dispersion relationship

From above study, we have obtained the calculation formula of the nonlinear dispersion relationship. It is observed that there is an important parameter wave amplitude A_l which is quadratic in Eq. (26), and it is necessary to discuss the influence of wave amplitude A_l on the nonlinear band structures. Fig. 5(a) shows the nonlinear band structure for selected wave amplitude $A_l = 0.5$ (violet), 1(blue), 1.5(red). It can be found that the local resonance band gap exists between the second and third branch and the width will reduce as the wave amplitude A_l increases. We can also find that the effect of wave amplitude mostly occurs in local areas (around point X and M- Γ) is

the same as the trend of nonlinear stiffness in Fig. 3. Interestingly, there is a frequency range that the second branch have both with a positive slope and a negative slope around the point X caused by increasing wave amplitude. This frequency range, called the “dual wavevector” region, is plotted in Fig. 5 (a). This dual wavevector phenomenon cannot be observed in the general bragg gap or resonance gap is a unique phenomenon accompanying the amplitude-dependent bandgap. Note that at this frequency range, there can be a nonlinear interaction between two waves which have different wavevectors, which causes a complicated wave motion. Fig. 5 (b) shows the distributions of the band gap at varying wave amplitude A_1 from 0 to 1.5. The maximum frequency of the second branch (red) gradually increases as wave amplitude increases while the minimum frequency of the third branch just slightly increases with wave amplitude increases. We can also find that the band gap will reduce to zero when the wave amplitude reaches to around 1.3 from the black line. It can be observed that the wave amplitude plays an important role in nonlinear dispersion relationship of nonlinear 2D AM.

Fig. 5 a Amplitude-dependent dispersion relationship for $A_1 = 0.5$ (violet), 1 (blue), 1.5 (red), **b** Distributions of the band gap at varying wave amplitude A_1 from 0 to

1.5

2.4 Amplitude-dependent iso-frequency contours and group velocity

The obtained dispersion curves can be used to evaluate the wave properties of the considered nonlinear 2D AM. The group velocity provides important information regarding the directional energy flow and the anisotropic nature of the periodic structures at a specified frequency. The dependence of dispersion on wave amplitude directly affects the group velocity, which suggests how the occurrence of frequencies and directions of preferential propagation may be affected by the amplitude of wave motion. To further illustrate the wave propagation in nonlinear 2D AM as controlled by the wave amplitude, we study the group velocities of the considered nonlinear system at several specific normalized frequencies, on a set of values of wave amplitude A_1 .

The group velocity is defined as:

$$c_g^x = \frac{\partial \Omega}{\partial k_x}, c_g^y = \frac{\partial \Omega}{\partial k_y}. \quad (29)$$

The group velocity is evaluated by first determining the contour of the selected frequency on the dispersion surface, and the gradient of this contour provides the components of the group velocity. From above research, we discover that the wave amplitude mainly affects the second branch and we will focus on it.

Fig. 6 shows the three-dimensional representation of iso-frequency contours of the second branch at different wave amplitudes for linear case $A_1 = 0$, and nonlinear cases

$A_1 = 0.5, 1, 1.5$. From an overall point of view, the three-dimensional representation of iso-frequency contours in the four cases all present a shape of cone. In detail, we can find that all the cases maintain a nearly circular cone shape in the low frequency range, which shows that both linear and nonlinear structures exhibit isotropy in the low frequency range. In this case, the energy flow and directions of wave propagation is mainly to all directions. As for the high frequency range, Fig. 6 (a) shows the linear case, and it can be observed that the square shape of iso-frequency contours occurs. This means the structures present strong anisotropy in high frequency rang. With the addition of nonlinearity, it can be found that the wave amplitude mainly affects the iso-

frequency contours in high frequency range. From Figs. 6 (b) to 6 (d), we can discover that the iso-frequency contour of the highest frequency will rise with the increase of wave amplitude and gradually form peaks. It also shows strong anisotropy in high frequency range. This phenomenon implies the amplitude- dependent of iso-frequency contours in the nonlinear 2D AM.

Fig. 6 Three-dimensional representation of iso-frequency contour maps of the second branch at different wave amplitudes A_1 . **a** 0, **b** 0.5, **c** 1, and **d** 1.5.

The results for the group velocities corresponding to the second branch for different wave amplitude $A_1 = 0$ (blue ‘■’), $A_1 = 0.5$ (violet ‘●’), $A_1 = 1$ (green ‘▲’), $A_1 = 1.5$ (red ‘▼’) at desired frequency $\Omega = 0.5, \Omega = 0.8, \Omega = 0.93$ are shown in Fig. 7. As shown in Fig. 7 (a), we can find that the group velocities of four cases overlap with each other and the shape present nearly a circle. This means at $\Omega = 0.5$, the wave

amplitude has almost no effect on group velocity and the wave propagates along all
 directions. Increasing frequency to $\Omega=0.8$, as shown in Fig. 7 (b), we can find that
 the shapes of group velocities change to square in all cases while the wave amplitude
 only affects the amplitude of group velocity. At this time, the wave in the desired
 structure mainly propagates along the directions of 0° , 90° , 180° , 270° . As for
 $\Omega=0.93$, shown in Fig. 7 (c), we can find that the group velocities both shape as cross
 which indicate strong anisotropy in small wave amplitude $A_1=0$ and $A_1=0.5$.
 While the group velocities of larger wave amplitude $A_1=1$ and $A_1=1.5$ still shape
 as square. Compared with Figs. 7 (a), (b) and (c), we can find that as the frequency
 increases, the anisotropy of the group velocity becomes stronger. However, the addition
 of nonlinearity and changing of wave amplitude will restrain the anisotropy at the same
 frequency. This is a performance of amplitude-dependent group velocity.

(a)

(b)

Fig. 7 Group velocities of the nonlinear 2D AM for different wave amplitude A_l at selected frequency Ω : **a** $\Omega = 0.5$, **b** $\Omega = 0.8$, **c** $\Omega = 0.93$, where $A_l = 0$ (blue '■'), $A_l = 0.5$ (violet '●'), $A_l = 1$ (green '▲'), $A_l = 1.5$ (red '▼')

371

372 **3 Vibration response of finite nonlinear 2D AM**

373 In this section, we will investigate the vibration characteristics of the nonlinear system.

374 The harmonic balance method is introduced to calculate the vibration response of finite
375 nonlinear 2D AM.

376 Let us consider the finite nonlinear 2D AM with 5×5 unit-cells as shown in Fig. (1).

377 For the wave propagation along the x-direction, the equations of motion are given by

$$378 \quad \mathbf{M}\ddot{\mathbf{U}} + \mathbf{K}\mathbf{U} + \mathbf{K}_N(\bar{k}_n)\mathbf{U}^3 = \mathbf{F}, \quad (30)$$

379 where $\mathbf{U} = [u_{1(1,1)} \ q_{1(1,1)} \ u_{1(1,2)} \ q_{1(1,2)} \ \dots \ u_{1(n,p)} \ q_{1(n,p)}]^T$ is the displacement vector, which

380 contains the displacement $q_{1(n,p)} = u_{3(n,p)} - u_{1(n,p)}$. $\mathbf{M}$ denotes the mass matrix of

381 finite 2D AM, $\mathbf{K}$ and $\mathbf{K}_N(\bar{k}_n)$ is the linear and nonlinear stiffness matrix of the

382 nonlinear system. $\mathbf{F} = [f \cos(\omega t) \ 0 \ \dots \ 0]^T$ is the force vector. There is only one

383 harmonic excitation force acting on the $(1,1)^{\text{th}}$ unit-cell.

384 Applying the harmonic balance method to solve frequency response, the solution of the

385 system is assumed as:

$$386 \quad \mathbf{U} = \mathbf{a} \cos \omega t + \mathbf{b} \sin \omega t. \quad (31)$$

387 Submitting Eq. (31) to Eq. (30), we can obtain:

$$388 \quad (\mathbf{K} - \omega^2 \mathbf{M})(\mathbf{a} \cos \omega t + \mathbf{b} \sin \omega t) + \mathbf{K}_N(\overline{k_n})(\mathbf{a} \cos \omega t + \mathbf{b} \sin \omega t)^3 = \mathbf{F}, \quad (32)$$

389 then using the trigonometry relationships $(\sin^3(\omega t) = \frac{3}{4} \sin(\omega t) + \frac{1}{4} \sin(3\omega t))$,

390 $\cos^3(\omega t) = \frac{3}{4} \cos(\omega t) + \frac{1}{4} \cos(3\omega t)$ and ignoring the high-order harmonic terms, we

391 can get:

$$392 \quad \begin{cases} (\mathbf{K} - \omega^2 \mathbf{M})\mathbf{a} + \frac{3}{4} \mathbf{K}_N(\overline{k_n})((\mathbf{a}^2 + \mathbf{b}^2)\mathbf{a}) = f \\ (\mathbf{K} - \omega^2 \mathbf{M})\mathbf{b} + \frac{3}{4} \mathbf{K}_N(\overline{k_n})((\mathbf{a}^2 + \mathbf{b}^2)\mathbf{b}) = 0 \end{cases}. \quad (33)$$

393 Eq. (33) can be solved and the response amplitude under the excitation force is

394 $\mathbf{Y} = \sqrt{\mathbf{a}^2 + \mathbf{b}^2}$. Finally, we can get the frequency response T is defined by:

$$395 \quad T = 20 \log\left(\frac{Y_{out}}{Y_{inp}}\right), \quad (34)$$

396 where the Y_{out} and Y_{inp} are the amplitudes of output and excitation point, respectively.

397 Usually, we select the unit-cells of left boundary that the (1,1)th to (5,1)th unit-cell as
 398 the excitation point while unit-cells of right boundary as the output point. It should be
 399 noted that due to the different methods for nonlinear system, the parameters in this
 400 section are not exactly equal to the 2 section, but the trend of vibration characteristics
 401 affected by nonlinear effects should follow the same way.

402 Fig. 8 shows the frequency response with different excitation amplitude f , where

403 $f = 0$ (black) (linear), $f = 5$ (red), $f = 10$ (blue) and $\overline{k_n} = 1$. We can find that the

404 frequency response T of a linear system is independent of the excitation amplitude

405 while the excitation amplitude has an important influence on the nonlinear system. The

406 bifurcation of the periodic solution occurs in the low frequency range around $\Omega = 0.5$

407 which is a significant characteristic of nonlinear system. In other frequency ranges, the

408 amplitude of the resonance peak of the nonlinear system is smaller than that of the linear

system which is called chaotic band [39]. It is obvious to see that there is a strong
attenuation exists between $\Omega=1$ to $\Omega=1.5$ which present the band gap that elastic
waves cannot propagate. As increasing the excitation amplitude f , the frequency of
lower boundary of attenuation area will increase slightly. This excitation amplitude-
dependent behavior of nonlinear 2D AM is similar to the trend of wave amplitude-
dependent band structure in the previous study.

Fig. 8 Frequency response with different excitation amplitude f

$f = 0$ (black) , $f = 5$ (red) , and $f = 10$ (blue)

4 Effective mass of the nonlinear 2D AM

As well known, metamaterial is an artificially manufactured materials with superior
properties. The effective mass of the unit-cell of the AM may be negative based on the
concept of dynamic equivalent in the local resonance band gap. In this section, we will
analysis the negative effective mass characteristics of the nonlinear 2D AM system. The
effective mass of the nonlinear unit-cell can also be used in reflecting the vibration
characteristics of the nonlinear 2D AM.

Considering the wave propagation in the lattice with an effective unit-cell in the x-
direction, the equation of motion can be written as:

$$m_{eff} \frac{\partial^2 u_{1(n,p)}}{\partial t^2} = FF, \quad (35)$$

$$FF = k_1 (u_{1(n+1,p)} + u_{1(n-1,p)} - 2u_{1(n,p)}) \\ + \frac{1}{2} k_2 (u_{1(n+1,p+1)} + u_{1(n-1,p-1)} - 2u_{1(n,p)} + v_{1(n+1,p+1)} + v_{1(n-1,p-1)} - 2v_{1(n,p)}) \\ + \frac{1}{2} k_2 (u_{1(n-1,p+1)} + u_{1(n+1,p-1)} - 2u_{1(n,p)} - v_{1(n-1,p+1)} - v_{1(n+1,p-1)} + 2v_{1(n,p)}).$$

Then we can rewrite the equation of motion in x-direction for nonlinear unit-cell:

$$\begin{cases} m_1 \frac{\partial^2 u_{1(n,p)}}{\partial t^2} - K_L q_{1(n,p)} - K_N (\bar{k}_n) q_{1(n,p)}^3 = FF \\ m_3 \left(\frac{\partial^2 q_{1(n,p)}}{\partial t^2} + \frac{\partial^2 u_{1(n,p)}}{\partial t^2} \right) = -K_L q_{1(n,p)} - K_N (\bar{k}_n) q_{1(n,p)}^3 \end{cases}, \quad (36)$$

where K_L , K_N are the linear and nonlinear stiffness of nonlinear unit-cell. Assuming the solutions are $u_{1(n,p)} = a \cos \omega t$, $q_{1(n,p)} = b \cos \omega t$, and using the trigonometry relationships, Eq. (36) can be rewritten as:

$$\begin{cases} m_1 \frac{\partial^2 u_{1(n,p)}}{\partial t^2} + m_3 \left(\frac{\partial^2 q_{1(n,p)}}{\partial t^2} + \frac{\partial^2 u_{1(n,p)}}{\partial t^2} \right) = FF \\ q_{1(n,p)} = \frac{\omega^2 m_3}{K_L + \frac{3}{4} K_N b^2 - \omega^2 m_3} u_{1(n,p)} \end{cases}. \quad (37)$$

Comparing the results of Eq. (37) with Eq. (35), the effective mass m_{eff} of nonlinear unit-cell can be expressed as:

$$m_{eff} = m_1 + m_3 \frac{\omega^2}{\frac{K_L}{m_3} + \frac{3K_N b^2}{4m_3} - \omega^2}. \quad (38)$$

Eq. (38) indicates that nonlinear effective mass is controlled by wave amplitude b .

We can also get the linear effective mass $m_{eff}^L = m_1 + m_3 \frac{\omega^2}{K_L/m_3 - \omega^2}$ when $K_N = 0$.

The effective mass of nonlinear unit-cell for different wave amplitude $b = 0, 5, 10$ is shown in Fig. 9. In linear case, a region of negative effective mass appears start from the natural frequency of the resonator ($\Omega = 1$). The negativity of the effective mass comes from the movement of the resonators in opposite direction to that one of the

442 wave propagation [40, 41]. As for nonlinear unit-cell, there is also one region of
 443 negative effective mass while the negative effective mass region moves to high
 444 frequencies affect by the wave amplitude b . In particular, the offset of frequency
 445 increases with increasing wave amplitude b . The effective mass of nonlinear 2D AM
 446 also present the wave amplitude-dependent.

Fig. 9 Effective mass of nonlinear unit-cell for different wave amplitude b :
 $b = 0$ (black ‘solid line’), $b = 5$ (red ‘dotted line’) and $b = 10$ (blue ‘dot line’)

449 5 Conclusions

450 In this study, we consider a type of nonlinear two-dimensional acoustic metamaterials.
 451 The nonlinear systems made of basic linear two-dimensional spring-mass system and
 452 distributed Duffing resonators. The perturbation method is introduced to evaluate the
 453 nonlinear dispersion relationships and wave propagation characteristics. A quantitative
 454 study of the maximum admissible amplitude has been performed to provide an
 455 overview of the limits of the proposed method. Furthermore, the harmonic balance
 456 method is used to investigate the frequency response and effective mass of the nonlinear
 457 systems. The results show that the two-dimensional nonlinear acoustic metamaterials

can tune the characteristics of wave propagation and effective mass in the structures by adjusting the nonlinear stiffness and wave amplitude within a certain range. The main findings are listed below:

(1) Nonlinear stiffness and wave amplitude can significantly affect the dispersion curves. The influence of nonlinear stiffness and wave amplitude on the dispersion curve is similar. They mainly affect the second branch of band structure while have a little effect on other branches. The distributions of band gap indicate that increasing the nonlinear stiffness and wave amplitude will narrow the band gap.

(2) The iso-frequency contours and group velocity of nonlinear 2D AM both present amplitude-dependent. The iso-frequency contour of the highest frequency will rise with the increase of wave amplitude and gradually form peaks which represent the anisotropic behavior. While in the group velocity plots, increasing wave amplitudes will restrain the anisotropic behavior at the same frequency.

(3) The vibration response and effective mass of nonlinear 2D AM also present the amplitude-dependent. As increasing excitation amplitude, the bifurcation of the periodic solution and chaotic band occurs in the result. And the area of wave attenuation moves to higher frequency as increasing excitation amplitude. There is a negative mass region and its frequency range moves to higher frequency as increasing wave amplitude.

Acknowledgements

Funding for this work has been provided by the National Natural Science Foundation of China (Nos. 11872313 and 11972287).

Declarations

The authors declare that they have no known competing financial interests or personal relationships that could have appeared to influence the work reported in this paper.

References

1. Gibson, L.J., Ashby, M.F.: Cellular solids : structure and properties. Cambridge University Press. (1997)
2. Zelhofer, A.J., D.M. Kochmann.: On acoustic wave beaming in two-dimensional structural lattices. *Int J Solids Struct.* **115–116**:248-269 (2017)
3. Xu, G.D.: Mechanical response of carbon/epoxy composite sandwich structures with three-dimensional corrugated cores. *Compos Sci and Technol.* **156**, 296-304 (2018)
4. Arunkumar, M.P.: Vibro-acoustic response and sound transmission loss characteristics of truss core sandwich panel filled with foam. *Aerosp Sci Technol.* **78**, 1-11 (2018)
5. K.B.: Mechanics and band gaps in hierarchical auxetic rectangular perforated composite metamaterials. *Compos Struct.* **160**, 1024-1050 (2017)
6. Ruzzene, M.: Wave Propagation in Sandwich Plates with Periodic Auxetic Core. *J Intel Mat Syst Str.* **13**(9), 587-597 (2002)
7. Zhang, K., et al.: Wave propagation properties of rotationally symmetric lattices with curved beams. *J Acoust Soc Am.* **148**(3), 1567-1584 (2020)
8. Liu, Z., et al.: Locally resonant sonic materials. *Physica B.* **338**(5485), 201-205 (2000)
9. Zhao, P., et al.: Multi-resonator coupled metamaterials for broadband vibration suppression. *Appl Math Mech.* **42**(1), 53-64 (2021)
10. Wang, P., et al., Harnessing Buckling to Design Tunable Locally Resonant Acoustic Metamaterials. *Phys Rev Lett.* **113**(1), 014301 (2014)
11. Ma, G., et al.: Acoustic metasurface with hybrid resonances. *Nat Mater.* **13**(9), 873-878 (2014)
12. Li, J., C.T. Chan.: Double-negative acoustic metamaterial. *Phys Rev E.* **70**(5), 055602 (2004)
13. Yao, S., X. Zhou, G. Hu.: Experimental study on negative effective mass in a 1D mass–spring system. *New J Phys.* **10**(4), 043020 (2008)
14. Zhang, K., et al.: Tunable wave propagation in octa-chiral lattices with local resonators. *Compos Struct.* **220**, 114-126 (2019).
15. Yu, D., et al.: Flexural vibration band gaps in Timoshenko beams with locally resonant structures. *J Appl Phys.* **100**(12), 1734 (2006)
16. Sugino, C., et al.: A General Theory for Bandgap Estimation in Locally Resonant Metastructures. *J Sound Vib.* **406**, 104-123 (2017)
17. Amromin, E., S. Kovinskaya.: Vibration of cavitating elastic wing in a periodically perturbed flow: excitation of subharmonics. *J Fluid Struct.* **14**(5), 735-751 (2000)
18. Silling, S., A.: Solitary waves in a peridynamic elastic solid. *J Mech Phys Solids.* **96**, 121-132 (2016)
19. Liu, Y., et al.: Quasi-phase-matching of the dual-band nonlinear left-handed metamaterial. *Appl Phys Lett.* **105**(20), 037401 (2014)
20. Jo, S.H., et al.: Experimentally validated broadband self-collimation of elastic waves. *Int J Mech Sci.* **192**, 106131 (2021)
21. Nassar, H., et al.: Non-reciprocal wave propagation in modulated elastic

531 metamaterials. *P Roy Soc A-Math Phys.* **473**(2202), 20170188 (2017)

532 22. Ide, Y., K. Ito, H. Tanno.: Nonlinear resonance of low- and high-frequency waves
533 in a cooled hypersonic boundary-layer. *Fluid Dyn Res.* **52**(5) (2020).

534 23. Hickey, D., et al.: Higher-order spectra for identification of nonlinear modal
535 coupling. *Mech Syst Signal Pr.* **23**(4), 1037-1061 (2009)

536 24. Nayfeh, A.H., D.T. Mook, P. Holmes.: Nonlinear Oscillations. *J Appl Mech.* **47**(3),
537 692 (1980)

538 25. Geniet, F., J. Leon.: Energy transmission in the forbidden bandgap of a nonlinear
539 chain. *Phys Rev Lett.* **89**(13), 134102 (2002)

540 26. Meurer, T., J. Qu, L.J. Jacobs.: Wave propagation in nonlinear and hysteretic media
541 - A numerical study. *Int J Solids Struct.* **39**(21–22), 5585-5614 (2002)

542 27. Geniet, F., J. Leon.: Nonlinear Supratransmission. *J Phys-Condens Mat.* **15**(17),
543 2933 (2003)

544 28. Daqaq, M.F., et al.: On the Role of Nonlinearities in Vibratory Energy Harvesting:
545 A Critical Review and Discussion. *Appl Mech Rev.* **66**(4), 040801 (2014)

546 29. Erturk, A., J. Hoffmann, D.J. Inman.: A piezomagnetoelastic structure for
547 broadband vibration energy harvesting. *Appl Phys Lett.* **94**(25), 254102-254102-3
548 (2009)

549 30. Harne, R.L., K.W. Wang.: A review of the recent research on vibration energy
550 harvesting via bistable systems. *Smart Mater Struct.* **22**(2), 023001 (2013)

551 31. Higashiyama, N., Y. Doi, A. Nakatani.: Nonlinear dynamics of a model of acoustic
552 metamaterials with local resonators. *Nonlinear Theory and Its Applications IEICE.*
553 **8**(2), 129-145 (2017)

554 32. Cveticanin, L., M. Zukovic.: Negative effective mass in acoustic metamaterial with
555 nonlinear mass-in-mass subsystems. *Commun Nonlinear Sci.* **51**(OCT.), 89-104
556 (2017)

557 33. Zhou, W.J., et al.: Spectro-spatial analysis of wave packet propagation in nonlinear
558 acoustic metamaterials. *J Sound Vib.* **413**, 250-269 (2018)

559 34. Gantzounis, G., et al.: Granular metamaterials for vibration mitigation. *J Appl Phys.*
560 **114**(9), 093514 (2013)

561 35. Khajehtourian, R., M.I. Hussein.: Dispersion characteristics of a nonlinear elastic
562 metamaterial. *AIP Adv.* **4**(12), 124308 (2014)

563 36. Bilal, O.R., A. Foehr, C. Daraio.: Bistable metamaterial for switching and
564 cascading elastic vibrations. *P Natl A Sci.* **114**(12), 201618314 (2017)

565 37. Manktelow, K., et al.: Finite-element based perturbation analysis of wave
566 propagation in nonlinear periodic structures. *Mech Sys Signal Pr.* **39**(1-2), 32-46
567 (2013)

568 38. Narisetti, R.K., M. Ruzzene, M.J. Leamy.: A perturbation approach for analyzing
569 dispersion and group velocities in two-dimensional nonlinear periodic lattices. *J*
570 *Vib Acoust.* **133**(6), 061020 (2011)

571 39. Sheng, P., et al.: Vibration properties and optimized design of a nonlinear acoustic
572 metamaterial beam. *J Sound Vib.* **492**, 115739 (2021)

573 40. Huang, et al.: On the negative effective mass density in acoustic metamaterials. *Int*
574 *J Eng Sci.* **47**(4), 610-617 (2009)

575 41. Huang, H.H. and C.T. Sun: Wave attenuation mechanism in an acoustic
576 metamaterial with negative effective mass density. New J Phys. **11**(1), 013003
577 (2009)
578

Figures

(a)

(b)

(c)

Figure 1

Configuration of the 2D infinite acoustic metamaterials. a Structurally model, b Representative linear unit-cell, c Representative nonlinear unit-cell.

(a)

(b)

Figure 2

a the first Brillouin zone and irreducible Brillouin zones (shadow area) and b Dispersion of 2-D metamaterials with linear resonator

(a)

(b)

Figure 3

Please see the Manuscript PDF file for the complete figure caption

Figure 4

Please see the Manuscript PDF file for the complete figure caption

(a)

(b)

Figure 5

a Amplitude-dependent dispersion relationship for 0.5 (violet), 1 (blue), 1.5 (red), b Distributions of the band gap at varying wave amplitude from 0 to 1.5

(a)

(b)

(c)

(d)

Figure 6

Three-dimensional representation of iso-frequency contour maps of the second branch at different wave amplitudes . a 0, b 0.5, c 1, and d 1.5.

(a)

(b)

(c)

Figure 7

Please see the Manuscript PDF file for the complete figure caption

Figure 8

Please see the Manuscript PDF file for the complete figure caption

Figure 9

Please see the Manuscript PDF file for the complete figure caption