A Recurrent Wavelet based Brain Emotional Learning Network Controller for Nonlinear Systems

Juncheng Zhang

Department of Artificial Intelligence, School of Informatics, Xiamen University

Fei Chao

Department of Artificial Intelligence, School of Informatics, Xiamen University

Hualin Zeng (✉ hlzeng@xmu.edu.cn)

Department of Artificial Intelligence, School of Informatics, Xiamen University

Chih-Min Lin

Department of Electrical Engineering, Yuan Ze University

Longzhi Yang

Department of Computer and Information Sciences, Northumbria University

Research Article

Keywords: brain emotional learning network , neural network control systems, nonlinear systems, recurrent neural network

Posted Date: April 13th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-409277/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Version of Record: A version of this preprint was published at Soft Computing on November 12th, 2021.
See the published version at <https://doi.org/10.1007/s00500-021-06422-9>.

Graphical Abstract

A Recurrent Wavelet based Brain Emotional Learning Network Controller for Nonlinear Systems

Juncheng Zhang, Fei Chao, Hualin Zeng, Chih-Min Lin, Longzhi Yang

Highlights

A Recurrent Wavelet based Brain Emotional Learning Network Controller for Nonlinear Systems

Juncheng Zhang, Fei Chao, Hualin Zeng, Chih-Min Lin, Longzhi Yang

- Integrating a wavelet neural network to a brain emotional network to accelerate the learning rate.
- Sensitive sequential input detection by recurrent loop mechanisms leading to improved dynamic characteristics.

A Recurrent Wavelet based Brain Emotional Learning Network Controller for Nonlinear Systems^{*}

Juncheng Zhang^a, Fei Chao^{a,b}, Hualin Zeng^{a,*}, Chih-Min Lin^c and Longzhi Yang^d

^aDepartment of Artificial Intelligence, School of Informatics, Xiamen University, 361005 China

^bDepartment of Computer Science, Institute of Mathematics, Physics and Computer Science, Aberystwyth University, SY23 3DB, UK

^cDepartment of Electrical Engineering, Yuan Ze University, Taiwan

^dDepartment of Computer and Information Sciences, Northumbria University, UK

ARTICLE INFO

Keywords:

brain emotional learning network
neural network control systems
nonlinear systems
recurrent neural network

ABSTRACT

Conventional control systems often suffer from the co-existence of non-linearity and uncertainty. This paper proposes a novel brain emotional neural network to support addressing such challenges. The proposed network integrates a wavelet neural network into a conventional brain emotional learning network. This is further enhanced by the introduction of a recurrent structure to employ the two networks as the two channels of the brain emotional learning network. The proposed network therefore combines the advantages of the wavelet function, the recurrent mechanism, and the brain emotional learning system, for optimal performance on nonlinear problems under uncertain environments. The proposed network works with a bounding compensator to mimic an ideal controller, and the parameters are updated based on the laws derived from the Lyapunov stability analysis theory. The proposed system was applied to two uncertain nonlinear systems, including a Duffing-Homes chaotic system and a simulated 3-DOF spherical joint robot. The experiments demonstrated that the proposed system outperformed other popular neural-network-based control systems, indicating the superiority of the proposed system.

1. Introduction

Controlling of nonlinear systems has been one of the focuses in the research of control engineering. Nonlinear systems often operate in uncertain environments, and the controllers must simultaneously deal with both nonlinearly and uncertainty features of controlled plants Al-Dunainawi, Abbod and Jizany (2017); Fang, Chao, Lin, Zhou, Yang, Chang, Shen and Shang (2020). Based on the well understood difficulties of mathematical modeling for nonlinear and uncertain control problems Chao, Zhou, Lin, Yang, Zhou and Shang (2019); Lin, Huynh and Le (2019), artificial neural networks possess several intelligent features such as self-learning and auto-adaptation. Therefore, artificial neural network-based control systems have been recently extensively studied and rapidly developed, so as to obtain fast convergence and dynamic response Zhao and Lin (2019); Huynh, Lin, Le, Cho, Pham, Le and Chao (2019); Chao, Zhou, Lin, Zhou, Shi and Lin (2018); Elhaki and Shojaei (2020).

The integration of an adaptive sliding mode controller (SMC) with various neural networks leads to controllers enjoying the advantages of both constituent components Chen, Huang, Chen, Zhang, Sun, Chen, Gu and Zhu (2019); Uçak and Günel (2020); Fei and Lu (2018); Mishra and Mohanty (2020); Hadjaissa, Ameer and Boutoubat (2019), but such neural network-based control systems still face two main challenges. One challenge is sufficient nonlinear approximation ability of the neural network-based SMC to handle disturbance and uncertainties. This can be observed by the embedding of the radial basis function (RBF) networks in SMC-like controllers for nonlinear approximation improvement Lin and Boldbaatar (2017); Huynh, Le and Lin (2018). However, the short-term and low-range input noises often result to increased chattering to the network-based SMC controllers Huynh et al. (2019); Fang, Chao, Yang, Lin, Shang, Zhou and Shen (2019b). More investigation is therefore required on the transfer functions of neural networks.

^{*}This work was supported by the National Natural Science Foundation of China (No. 61673322, 61673326, and 91746103), Fundamental Research Funds for the Central Universities (No. 20720190142), and the Key Project of National Key R & D Project (No. 2017YFC1703303).

*Corresponding author

✉ 15034172520@163.com (J. Zhang); fchao@xmu.edu.cn (F. Chao); hlzeng@xmu.edu.cn (H. Zeng); cml@saturn.yzu.edu.tw (C. Lin); longzhi.yang@northumbria.ac.uk (L. Yang)

ORCID(s):

The other main challenge is the requirement of fast dynamic response of the controllers, to minimise system response latency. Some current studies on feed-forward network-based controllers apply the static mapping structure, which cannot effectively represent dynamic mappings. Alternatively, some other work introduce additional feedback mechanisms to the control systems to improve the dynamic response performance Zhou, Shi, Chao, Lin, Yang, Shang and Zhou (2018); Wu, Lin, Fang, Chao, Yang, Shang and Zhou (2018). However, such additional mechanisms make the controllers significantly complex, and thus adversely affect the performance. Therefore, a new type of neural network with strong approximation ability and prompt dynamic response is in demand to efficaciously approximate dynamic mappings of uncertain nonlinear problems.

This work proposes a recurrent wavelet function-based brain emotional learning network with an internal signals feedback loop embedded, for intelligent nonlinear control, to address the above challenges. The proposed network firstly integrates a wavelet neural network and a brain emotional learning network. The two recurrent loop mechanisms are then added into the two channels of the brain emotional learning network. The proposed network is further enhanced by a compensation controller to establish a network-based nonlinear control system working in an uncertain environment. The proposed control system features two main advantages: 1) accelerating the learning rate of the intelligent controller thanks to the fast convergence and efficient learning ability of the wavelet neural network; 2) sensitive sequential input detection by the recurrent loop mechanisms inside the wavelet neural network, leading to improved dynamic characteristics.

The remainder of this paper is organized as follows: Section 2 explains the basic structure of the brain emotional learning controller network. Section 3 specifies the proposed network and its implementation. Section 4 introduces the proposed intelligent controller. Section 5 reports and analyzes the experimental results. Section 6 concludes the paper and points out important future work.

2. Brain Emotional Learning Network

The conventional brain emotional learning (BEL) network is inspired by the emotional learning ability of a human brain Qutubuddin and Yadaiah (2017); Baghbani, Akbarzadeh-T, Naghibi-Sistani and Akbarzadeh (2020); Liu, Xie, Wu, Cao, Mei and Mao (2018), with its structure shown in Fig. 1. A BEL network consists of an orbitofrontal cortex and an amygdala channels. The orbitofrontal cortex channel is an emotional network and the amygdala channel is a sensory network. The output of the orbitofrontal channel, o , can be presented as $o = w \cdot SI$, where SI denotes the output of sensory cortex and w denotes the gain in the orbitofrontal channel. The output of the amygdala-like channel, a , is defined as $a = v \cdot SI$, where v indicates the gain in the amygdala channel. Thus, a single-output BEL network can be summarised as:

$$u_{BELC} = a - o = (v - w) \cdot SI, \quad (1)$$

$$SI = \exp\left(-\frac{(I - c)^2}{v^2}\right), \quad (2)$$

where I, c and v denote the inputs, means and variances of BEL.

The sensory channel has an adjustment rule, which is defined by:

$$\Delta v = \alpha \cdot (SI \times \max[0, d - a]), \quad (3)$$

where α is the learning rate in the sensory channel and d denotes an emotional cue. The emotional channel has an indirect impact on the sensory channel. Thus, the learning rule in the emotional channel is defined by:

$$\Delta w = \beta \cdot [SI \times (u_{BELC} - d)], \quad (4)$$

where β is the learning rate in the emotional channel, and d is expressed by:

$$d = b \cdot I + c \cdot u_{BELC}, \quad (5)$$

where b and c are gain parameters, usually empirically determined in practical control systems.

Figure 1: Structure of Conventional Brain Emotional Learning Controller Network

Due to the efficient learning rate of the BEL network, many variants of BEL have been rapidly developed Baghbani, Akbarzadeh-T and Sistani (2018). For example, previously, we designed a fuzzy BEL network and a recurrent CMAC network Fang et al. (2019b); Fang, Chao, Lin, Yang, Shang and Zhou (2019a). In contrast, this work focuses on bring the advantages of the wavelet function and the recurrent mechanism, to build a more powerful brain emotional learning system.

Figure 2: The architecture of the proposed RWBEL neural network.

3. Recurrent Wavelet-based Brain Emotional Learning Network

The proposed recurrent wavelet based brain emotional learning (RWBEL) network, is established by integrating a wavelet neural network and recurrent loop structures into a classical brain emotional learning network. The structure of the proposed network is therefore mainly formed by two channels, including a recurrent emotional (REN) channel and a recurrent wavelet (RWN) channel Oveisi, Jeronimo and NestoroviĀĖ (2018), as illustrated in Fig. 2. Following the discussion of BEL in Sec. 2, the output of the proposed network is $u_i = a_i - o_i$, where a_i and o_i denote the output of the REN and RWN, respectively.

Each channel of RWBEL is comprised of multiple process layers. In particular, the REN channel has an association memory channel (M_1), a weight memory layer (V), and a sub-output layer (A); the RWN channel is formed by association memory (M_2), receptive-field space (J), weight memory space (W), and sub-output space (O). Both channels share the same input (I) and output layers (U). The signal process and implementation of each layer are specified below.

3.1. REN Channel

Input layer The input $I = [I_1, I_2, \dots, I_m]^T \in R^m$ is a vector that are fed to both REN and RWN channels simultaneously; and m is the dimension of the input.

Association memory layer (M_1) M_1 consists of n_b blocks, each of which is represented as a Gaussian basis function. Thus the output of the first layer is defined as:

$$f_{ij} = \exp \left(-\frac{(I_{a_{ij}} - c_{ij})^2}{v_{ij}^2} \right), \quad (6)$$

where c_{ij} and v_{ij} denote the means and variances of REN, respectively; $i = 1, 2, \dots, m$; $j = 1, 2, \dots, n_b$; and $I_{a_{ij}}$ denotes the input of the recurrent structure of REN.

A block matrix of REN F is defined as:

$$F = \begin{bmatrix} f_{11} & \dots & f_{1n_b} & \dots & f_{l1} & \dots & f_{ln_b} \end{bmatrix}^T \in R^{mn_b}. \quad (7)$$

Weight memory layer (V) v_{ijk} denotes the weight of the i -th output, j -th input, k -th block of REN.

3.2. RWN Channel

Association memory layer (M_2) M_2 also consists of n_w blocks, each of which is represented as a wavelet function. The output of M_2 is defined as:

$$h_{ij} = -\left(\frac{I_{b_{ij}} - y_{ij}}{z_{ij}}\right) \exp\left(-\frac{\left(\frac{I_{b_{ij}} - y_{ij}}{z_{ij}}\right)^2}{2}\right), \quad (8)$$

where y_{ij} and z_{ij} denote the means and variances of RWN, respectively; $i = 1, 2, \dots, l$; $j = 1, 2, \dots, n_w$, and $I_{b_{ij}}$ represents the input of the recurrent structure of RWN.

Reception-field layer (J) Each block in the Reception-field layer is the product of the corresponding block of the association memory space M_2 . Thus, the input of each block in J is defined as:

$$\phi_j = \prod_{i=1}^m h_{ij}. \quad (9)$$

The block matrix of J is defined as:

$$\Phi = \begin{bmatrix} \phi_1 & \phi_2 & \dots & \phi_{n_w} \end{bmatrix}^T \in R^{n_f}. \quad (10)$$

Weight memory layer (W) w_{ij} represents the weight of the i -th output, j -th block of the Reception-field Space.

3.3. Output Layer

The output of the RWBEL is the integration of the sub-outputs of REN and RWN. These two sub-outputs are respectively defined as:

$$a_i = \sum_{j=1}^m \sum_{k=1}^{n_b} v_{ijk} f_{ij}, \quad (11)$$

$$o_i = \sum_{j=1}^{n_w} w_{ij} \phi_j, \quad (12)$$

where a_i is i -th output of REN, and o_i is i -th output of RWN. The output of the RWBEL is the aggregation of these two values, defined as:

$$u = a - o = V^T F - W^T \Phi. \quad (13)$$

3.4. Recurrent structure

Both associate memory layers M_1 and M_2 of the two channels imply a recurrent mechanism as shown in Fig. 3. The recurrent mechanism of M_1 and M_2 are identical. Each recurrent mechanism has two inputs: one is the recurrent

Figure 3: The recurrent loop mechanism

input $I(t)$ at time t ; and the another is the output of the recurrent structure at time $t - \Gamma$ (Γ is a delay time). Therefore, the inputs of the two recurrent mechanism ($I_{a_{ij}}$ and $I_{b_{ij}}$) are represented as follows:

$$I_{a_{ij}}(t) = I_i(t) + r_{ij}f_{ij}(t - \Gamma), \quad (14)$$

$$I_{b_{ij}}(t) = I_i(t) + q_{ij}h_{ij}(t - \Gamma), \quad (15)$$

where r and q are the recurrent weights of the REN and RWN, respectively.

4. Neural network based control system

Figure 4: Control system with proposed RWBEL

The proposed RWBEL network has been further developed as an nonlinear control system for improved performance. The structure of the RWBEL-based control system is shown in Fig. 4. The control system consists of a sliding surface, an RWBEL network, and a compensator controller. The input of the proposed controller is the errors of the uncertain nonlinear system. The error values are processed by the sliding surface and delivered to the RWBEL network and the compensator controller. In addition, parameters of the RWBEL and compensator controller are updated by adaptive laws that are derived from input errors.

To facilitate the description of the RWBEL-based control system, a nonlinear system with uncertainties is formulated as:

$$\mathbf{x}^{(n)}(t) = f(\mathbf{x}(t)) + g(\mathbf{x}(t))u(t) + d(t), \quad (16)$$

where $\mathbf{x}(t) = [x^{(n-1)}(t) \dots \dot{x}(t) x(t)]^T \in \mathbb{R}^{n \times l}$ denotes the state vector of the system; $u(t) = [u_1(t), u_2(t) \dots u_n(t)]^T \in \mathbb{R}^n$ denotes the output vector of the control system; $f(\mathbf{x}(t))$ and $g(\mathbf{x}(t))$ are unknown but bounded system models; and $d(t)$ is the unknown external disturbance.

Then, the nominal model of this type of a nonlinear system is defined as:

$$\mathbf{x}^{(n)}(t) = f_0(\mathbf{x}(t)) + g_0 u(t), \quad (17)$$

where $f_0(\mathbf{x}(t))$ and g_0 denote the nominal part of $f(\mathbf{x}(t))$ and $g(\mathbf{x}(t))$, respectively. Therefore, Eq. 17 can be re-expressed as:

$$\begin{aligned} \mathbf{x}^{(n)}(t) &= f_0(\mathbf{x}(t)) + \Delta f(\mathbf{x}(t)) + g_0 u(t) + \Delta g(\mathbf{x}(t))u(t) + d(t) \\ &= f_0(\mathbf{x}(t)) + g_0 u(t) + l(\mathbf{x}(t), t), \end{aligned} \quad (18)$$

where $l(\mathbf{x}(t), t) = \Delta f(\mathbf{x}(t)) + \Delta g(\mathbf{x}(t))u(t) + d(t)$ is referred to as the lumped uncertainty.

Assume the reference tracking state vector, $\mathbf{x}_d(t)$, is defined as $\mathbf{x}_d(t) = [x_d^{(n-1)}(t) \dots \dot{x}_d(t) x_d(t)]^T \in \mathbb{R}^{m \times n}$, the tracking error of the system is defined as:

$$\mathbf{e}(t) = \mathbf{x}_d(t) - \mathbf{x}(t). \quad (19)$$

Thus, the tracking error vector can be obtained by:

$$e(t) = [e^{(n-1)}(t) \dots \dot{e}(t) e(t)]^T. \quad (20)$$

If the nominal functions $f_0(x(t))$, g_0 and the lumped uncertainty $l(x(t), t)$ are exactly known, an ideal controller u^* can be designed as:

$$u^*(t) = g_0^{-1} \left[x_d^{(n)}(t) - f_0(x(t)) - l(x(t), t) + H^T e(t) \right], \quad (21)$$

where $H = [H_n \dots H_2, H_1]^T$ is the feedback gain vector.

Substituting the ideal controller Eq. 21 in Eq. 18 leads to the error dynamic equation:

$$e^{(n)}(t) + H^T e(t) = 0. \quad (22)$$

If H is chosen to correspond to the coefficients of a Hurwitz polynomial, it implies that $\lim_{t \rightarrow \infty} e(t) = 0$. However, since $l(x(t), t)$ is not known accurately, the ideal controller u^* is unobtainable. Thus, the RWBEL network is developed to approximate the ideal controller. To achieve this, a sliding surface is defined as:

$$s(t) = e^{(n-1)}(t) + H_1 e^{(n-2)}(t) + \dots + H_n \int e(t) dt. \quad (23)$$

Then the derivative of Eq. 23 is:

$$\begin{aligned} \dot{s}(t) &= e^{(n)}(t) + H^T e(t) \\ &= x_d^{(n)}(t) - f_0(x(t)) - g_0 u(t) - l(x(t), t) + H^T e(t). \end{aligned} \quad (24)$$

An approximate error, $\varepsilon(t) = u^*(t) - u_{RWBEL}(t)$, exists between the proposed controller and the ideal controller. Then, the following can be derived:

$$\dot{s}(t) = g_0 [u^*(t) - u(t)], \quad (25)$$

where $u(t) = u_{RWBEL}(t) + u_{RC}(t)$, u_{RWBEL} is the controller of RWBEL; u_{RC} is a robust controller, employed to suppress the influence of residual approximation errors between the RWBEL controller and the ideal controller.

Assume that an optimal RWBEL controller exists in the ideal sliding model controller u^* :

$$u^* = u_{RWBEL}^*(t) + \varepsilon = V^{*T} \hat{f} - W^{*T} \Phi^* + \varepsilon \quad (26)$$

where ε is a minimum error vector, V^* , W^* , f^* , and Φ^* are optimal parameter matrixes and vectors of V , W , f , and Φ , respectively. However, the optimal controller is hardly achievable; an estimated controller is used to approach the optimal controller. The estimated controller is defined as:

$$u = u_{RWBEL} + u_{RC} = \hat{V}^T \hat{f} - \hat{W}^T \hat{\Phi} + u_{RC}, \quad (27)$$

where $\hat{V}$, $\hat{W}$, $\hat{f}$, and $\hat{\Phi}$ denotes the estimated values of the optimal parameter matrix and vectors of V^* , W^* , f^* , and Φ^* , respectively.

Subtracting Eq. 26 from Eq. 27 gives the estimation error:

$$\begin{aligned} \tilde{u} &= u^* - u = V^{*T} \hat{f} - W^{*T} \Phi^* + \varepsilon - \hat{V}^T \hat{f} + \hat{W}^T \hat{\Phi} - u_{RC} \\ &= \tilde{V}^T f^* + \hat{V}^T \tilde{f} - \tilde{W}^T \Phi^* - \hat{W}^T \tilde{\Phi} + \varepsilon - u_{RC}, \end{aligned} \quad (28)$$

where $\tilde{V} = V^* - \hat{V}$, $\tilde{f} = f^* - \hat{f}$, $\tilde{W} = W^* - \hat{W}$, and $\tilde{\Phi} = \Phi^* - \hat{\Phi}$. The expansion of $\tilde{f}$ in the Taylor series can be

obtained as:

$$\begin{aligned}
 \tilde{f} &= \begin{pmatrix} \tilde{f}_1 \\ \vdots \\ \tilde{f}_{n_d} \end{pmatrix} = \begin{pmatrix} \left(\frac{\partial f_1}{\partial c} \right)^T \\ \vdots \\ \left(\frac{\partial f_{n_d}}{\partial c} \right)^T \end{pmatrix} \Bigg|_{c=\hat{c}} (c^* - \hat{c}) \\
 &+ \begin{pmatrix} \left(\frac{\partial f_1}{\partial v} \right)^T \\ \vdots \\ \left(\frac{\partial f_{n_d}}{\partial v} \right)^T \end{pmatrix} \Bigg|_{v=\hat{v}} (v^* - \hat{v}) \\
 &+ \begin{pmatrix} \left(\frac{\partial f_1}{\partial r} \right)^T \\ \vdots \\ \left(\frac{\partial f_{n_d}}{\partial r} \right)^T \end{pmatrix} \Bigg|_{r=\hat{r}} (r^* - \hat{r}) + O_{t1} \\
 &= F_c \tilde{c} + F_v \tilde{v} + F_r \tilde{r} + O_{t1},
 \end{aligned} \tag{29}$$

where F_c , F_v , and F_r are defined by:

$$\begin{aligned}
 F_c &= \left[\frac{\partial f_1}{\partial c}, \dots, \frac{\partial f_{n_d}}{\partial c} \right]^T \Bigg|_{c=\hat{c}} \\
 F_v &= \left[\frac{\partial f_1}{\partial v}, \dots, \frac{\partial f_{n_d}}{\partial v} \right]^T \Bigg|_{v=\hat{v}} \\
 F_r &= \left[\frac{\partial f_1}{\partial r}, \dots, \frac{\partial f_{n_d}}{\partial r} \right]^T \Bigg|_{r=\hat{r}}
 \end{aligned} \tag{30}$$

where $\tilde{c} = c^* - \hat{c}$, $\tilde{v} = v^* - \hat{v}$, $\tilde{r} = r^* - \hat{r}$; and O_{t1} is a vector with higher order terms. Thus, the following holds:

$$f^* = \hat{f} + \tilde{f} = \hat{f} + F_c \tilde{c} + F_v \tilde{v} + F_r \tilde{r} + O_{t1}. \tag{31}$$

Also, the expansion of $\tilde{\Phi}$ in the Taylor series can be obtained as:

$$\begin{aligned}
 \tilde{\Phi} &= \begin{pmatrix} \tilde{\phi}_1 \\ \vdots \\ \tilde{\phi}_{n_d} \end{pmatrix} = \begin{pmatrix} \left(\frac{\partial \phi_1}{\partial y} \right)^T \\ \vdots \\ \left(\frac{\partial \phi_{n_d}}{\partial y} \right)^T \end{pmatrix} \Bigg|_{y=\hat{y}} (y^* - \hat{y}) \\
 &+ \begin{pmatrix} \left(\frac{\partial \phi_1}{\partial z} \right)^T \\ \vdots \\ \left(\frac{\partial \phi_{n_d}}{\partial z} \right)^T \end{pmatrix} \Bigg|_{z=\hat{z}} (z^* - \hat{z}) \\
 &+ \begin{pmatrix} \left(\frac{\partial \phi_1}{\partial q} \right)^T \\ \vdots \\ \left(\frac{\partial \phi_{n_d}}{\partial q} \right)^T \end{pmatrix} \Bigg|_{q=\hat{q}} (q^* - \hat{q}) + O_{t2} \\
 &= \Phi_y \tilde{y} + \Phi_z \tilde{z} + \Phi_q \tilde{q} + O_{t2}.
 \end{aligned} \tag{32}$$

In particular, Φ_y , Φ_z , and Φ_q are defined as:

$$\begin{aligned}\Phi_y &= \left[\frac{\partial \phi_1}{\partial y}, \dots, \frac{\partial \phi_{n_d}}{\partial y} \right]^T \bigg|_{y=\tilde{y}} \\ \Phi_z &= \left[\frac{\partial \phi_1}{\partial z}, \dots, \frac{\partial \phi_{n_d}}{\partial z} \right]^T \bigg|_{z=\tilde{z}} \\ \Phi_q &= \left[\frac{\partial \phi_1}{\partial q}, \dots, \frac{\partial \phi_{n_d}}{\partial q} \right]^T \bigg|_{q=\tilde{q}}\end{aligned}\quad (33)$$

where $\tilde{y} = y^* - \hat{y}$, $\tilde{z} = z^* - \hat{z}$, and $\tilde{q} = q^* - \hat{q}$; and O_{t2} is a vector with higher order terms. Thus:

$$\Phi^* = \hat{\Phi} + \tilde{\Phi} = \hat{\Phi} + \Phi_y \tilde{y} + \Phi_z \tilde{z} + \Phi_q \tilde{q} + O_{t2}. \quad (34)$$

Substituting Eq. 34 and Eq. 31 to Eq. 28 and Eq. 25, yields

$$\begin{aligned}\dot{s}(t) &= g_0 \left[\tilde{V}^T (\hat{f} + F_c \tilde{c} + F_v \tilde{v} + F_r \tilde{r} + O_{t1}) + \right. \\ &\quad \hat{V}^T (F_c \tilde{c} + F_v \tilde{v} + F_r \tilde{r} + O_{t1}) \\ &\quad - \tilde{W}^T (\hat{\Phi} + \Phi_y \tilde{y} + \Phi_z \tilde{z} + \Phi_q \tilde{q} + o_{t2}) \\ &\quad \left. - \widehat{W}^T (\Phi_y \tilde{y} + \Phi_z \tilde{z} + \Phi_q \tilde{q} + o_{t2}) + \varepsilon - u_{RC} \right] \\ &= g_0 \left[\hat{V}^T (F_c \tilde{c} + F_v \tilde{v} + F_r \tilde{r}) - \widehat{W}^T (\Phi_y \tilde{y} + \Phi_z \tilde{z} + \Phi_q \tilde{q}) \right. \\ &\quad \left. + \tilde{V}^T \hat{f} - \tilde{W}^T \hat{\Phi} + \theta - u_{RC} \right],\end{aligned}\quad (35)$$

where θ is a combined error, which is defined by:

$$\begin{aligned}\theta &= \tilde{V}^T O_{t1} - \tilde{W}^T O_{t2} + \varepsilon + \tilde{V}^T (\hat{f} + F_c \tilde{c} + F_v \tilde{v} + F_r \tilde{r}) \\ &\quad - \tilde{W}^T (\hat{\Phi} + \Phi_y \tilde{y} + \Phi_z \tilde{z} + \Phi_q \tilde{q})\end{aligned}\quad (36)$$

where $\tilde{V} = V^* - \hat{V} = [\tilde{v}_1, \tilde{v}_2, \dots, \tilde{v}_m]$ is an approximation error weight matrix of the REN.

A kind of H_∞ tracking performance is designed as:

$$\begin{aligned}\sum_{i=1}^m \int_0^T s_i^2(t) dt &\leq s^T(0) g_0^{-1} s(0) + \tilde{c}^T(0) \eta_c^{-1} \tilde{c}(0) \\ &\quad + \tilde{v}^T(0) \eta_v^{-1} \tilde{v}(0) + \tilde{r}^T(0) \eta_r^{-1} \tilde{r}(0) \\ &\quad + \tilde{y}^T(0) \eta_y^{-1} \tilde{y}(0) + \tilde{z}^T(0) \eta_z^{-1} \tilde{z}(0) \\ &\quad + \tilde{q}^T(0) \eta_q^{-1} \tilde{q}(0) + \text{tr} \left[\tilde{W}^T(0) \eta_W^{-1} \tilde{W}(0) \right] \\ &\quad + \sum_{i=1}^m \lambda_i^2 \int_0^T \theta_i^2(t) dt + \sum_{i=1}^m \int_0^T \tilde{v}_i^2(t) dt\end{aligned}\quad (37)$$

where η_c , η_v , η_r , η_y , η_z , and η_q are diagonal positive constant learning rates; and λ_i is an attenuation constant. The initial conditions of the system are set as $s(0) = 0$, $\tilde{c}(0) = 0$, $\tilde{v}(0) = 0$, $\tilde{r}(0) = 0$, $\tilde{y}(0) = 0$, $\tilde{z}(0) = 0$, $\tilde{q}(0) = 0$. Then Eq. 37 can be re-written as:

$$\sum_{i=1}^m \int_0^T s_i^2(t) dt \leq \sum_{i=1}^m \lambda_i^2 \int_0^T \theta_i^2(t) dt + \sum_{i=1}^m \int_0^T \tilde{v}_i^2(t) dt. \quad (38)$$

Assume that the approximation error between the proposed RWBEL and an ideal controller are bounded, which means $\theta \in L_2 [0, M_1]$, $\tilde{v} \in L_2 [0, M_2]$, $\forall M_1, M_2 \in [0, \infty)$. Therefore $\sum_{i=1}^m \int_0^T \theta_i^2(t) dt \leq N_1$, $\sum_{i=1}^m \int_0^T \tilde{k}_i^2(t) dt \leq N_2$, where N_1 and N_2 are positive constants. If $\sum_{i=1}^m \int_0^T s_i^2(t) dt = \infty$, the system will be unstable. Therefore, the following mathematical expression must be guaranteed, so as to make sure the controlled system is stable:

$$\sum_{i=1}^m \int_0^T s_i^2(t) dt \leq \|\lambda\|^2 N_1 + N_2 < \infty. \quad (39)$$

In order to ensure the stability of the system, the update rules of the RWBEL network and the compensator controllers must follow the Lyapunov stability theory.

Theorem: For the uncertain nonlinear system represented by Eq. 16, the adaptive laws of REN channel are:

$$\dot{\hat{V}} = \alpha [F \times \max(0, D - b)] \quad (40)$$

$$D = \gamma \times I + \mu \times u_{RWBEL}, \quad (41)$$

where α denotes a learning rate; D is comprised of the input I , output u_{RWBEL} , and γ ; and μ is the learning rate. All the adaptive laws of the RWBEL network are summarised as:

$$\dot{\hat{c}} = \eta_c F_c^T \hat{V} s^T(t) \quad (42)$$

$$\dot{\hat{v}} = \eta_v F_v^T \hat{V} s^T(t) \quad (43)$$

$$\dot{\hat{r}} = \eta_r F_r^T \hat{V} s^T(t) \quad (44)$$

$$\dot{\hat{W}} = -\eta_w \hat{\Phi} s^T(t) \quad (45)$$

$$\dot{\hat{y}} = -\eta_y \Phi_y^T \hat{W} s^T(t) \quad (46)$$

$$\dot{\hat{z}} = -\eta_z \Phi_z^T \hat{W} s^T(t) \quad (47)$$

$$\dot{\hat{q}} = -\eta_q \Phi_q^T \hat{W} s^T(t). \quad (48)$$

In addition, the compensator controller is designed as:

$$u_{RC} = (2R^2)^{-1} [(I + F^2) V^2 + I] s^T(t), \quad (49)$$

where $R = \text{diag} [\lambda_1 \lambda_2 \dots \lambda_m]$ is a diagonal matrix of robust controller.

Proof: The Lyapunov function of the proposed RWBEL based control system is defined by:

$$\begin{aligned} L(s(t), \tilde{V}, \tilde{W}, \tilde{c}, \tilde{v}, \tilde{r}, \tilde{y}, \tilde{z}, \tilde{q}) = & \frac{1}{2} [s^T(t) g_0^{-1} s(t) + \\ & \text{tr} [\tilde{V}^T \alpha^{-1} \tilde{V}] + \tilde{c}^T \eta_c^{-1} \tilde{c} + \tilde{v}^T \eta_v^{-1} \tilde{v} + \tilde{r}^T \eta_r^{-1} \tilde{r} \\ & + \tilde{y}^T \eta_y^{-1} \tilde{y} + \tilde{z}^T \eta_z^{-1} \tilde{z} + \tilde{q}^T \eta_q^{-1} \tilde{q} + \text{tr} [\tilde{W}^T \eta_w^{-1} \tilde{W}]]. \end{aligned} \quad (50)$$

Taking the derivative of the Lyapunov function, yields:

$$\begin{aligned}
 \dot{L}(s(t), \tilde{V}, \tilde{W}, \tilde{c}, \tilde{v}, \tilde{r}, \tilde{y}, \tilde{z}, \tilde{q}) &= s^T(t)g_0^{-1}\dot{s}(t) + \text{tr} \left[\tilde{V}^T \alpha^{-1} \dot{\tilde{V}} \right] + \tilde{c}^T \eta_c^{-1} \dot{\tilde{c}} + \tilde{v}^T \eta_v^{-1} \dot{\tilde{v}} \\
 &+ \tilde{r}^T \eta_r^{-1} \dot{\tilde{r}} + \tilde{y}^T \eta_y^{-1} \dot{\tilde{y}} + \tilde{z}^T \eta_z^{-1} \dot{\tilde{z}} + \tilde{q}^T \eta_q^{-1} \dot{\tilde{q}} + \text{tr} \left[\tilde{W}^T \eta_W^{-1} \dot{\tilde{W}} \right] \\
 &= s^T(t)g_0^{-1}\dot{s}(t) - \text{tr} \left[\tilde{V}^T \alpha^{-1} \dot{\tilde{V}} \right] - \tilde{c}^T \eta_c^{-1} \dot{\tilde{c}} - \tilde{v}^T \eta_v^{-1} \dot{\tilde{v}} \\
 &- \tilde{r}^T \eta_r^{-1} \dot{\tilde{r}} - \tilde{y}^T \eta_y^{-1} \dot{\tilde{y}} - \tilde{z}^T \eta_z^{-1} \dot{\tilde{z}} - \tilde{q}^T \eta_q^{-1} \dot{\tilde{q}} - \text{tr} \left[\tilde{W}^T \eta_W^{-1} \dot{\tilde{W}} \right] \\
 &= s^T(t)\tilde{V}\hat{f} - s^T(t)\tilde{W}\hat{\Phi} + s^T(t)\hat{V} (F_c\tilde{c} + F_v\tilde{v} + F_r\tilde{r}) \\
 &- s^T(t)\tilde{W} (\Phi_y\tilde{y} + \Phi_z\tilde{z} + \Phi_q\tilde{q}) - \text{tr} \left[\tilde{V}^T \alpha^{-1} \dot{\tilde{V}} \right] - \tilde{c}^T \eta_c^{-1} \dot{\tilde{c}} \\
 &- \tilde{v}^T \eta_v^{-1} \dot{\tilde{v}} - \tilde{r}^T \eta_r^{-1} \dot{\tilde{r}} - \tilde{y}^T \eta_y^{-1} \dot{\tilde{y}} - \tilde{z}^T \eta_z^{-1} \dot{\tilde{z}} - \tilde{q}^T \eta_q^{-1} \dot{\tilde{q}} \\
 &- \text{tr} \left[\tilde{W}^T \eta_W^{-1} \dot{\tilde{W}} \right] + s^T(t) (\epsilon - u_{RC}) - s^T(t)g_0^{-1} \sigma \text{sgn}(s(t)) \\
 &\leq s^T(t)\tilde{V}\hat{f} + s^T(t) (\epsilon - u_{RC}) + \tilde{c} \left[s^T(t)\hat{V}_{F_c} - \eta_c^{-1} \dot{\tilde{c}} \right] \\
 &+ \tilde{v} \left[s^T(t)\hat{V}_{F_v} - \eta_v^{-1} \dot{\tilde{v}} \right] + \tilde{r} \left[s^T(t)\hat{V}_{F_r} - \eta_r^{-1} \dot{\tilde{r}} \right] \\
 &- \tilde{y} \left[s^T(t)\tilde{W}\Phi_y + \eta_y^{-1} \dot{\tilde{y}} \right] - \tilde{z} \left[s^T(t)\tilde{W}\Phi_z + \eta_z^{-1} \dot{\tilde{z}} \right] \\
 &- \tilde{q} \left[s^T(t)\tilde{W}\Phi_q + \eta_q^{-1} \dot{\tilde{q}} \right] - \text{tr} \left[\tilde{W}^T s(t)\hat{\Phi} + \eta_W^{-1} \dot{\tilde{W}} \right].
 \end{aligned} \tag{51}$$

Eq. 40 indicates that: If $d-b \leq 0$, then $\dot{V} = 0$; and if $d-b > 0$ then $\dot{V} = \alpha[F \times (d-b)] > 0$. Given that $\tilde{V} \in L_2[0, M_2]$, it can be derived that $-\text{tr} \left[\tilde{V}^T \alpha^{-1} \dot{\tilde{V}} \right] \leq 0$. Substituting Eqs. 42-48 into Eq. 51, yields:

$$\begin{aligned}
 \dot{L}(s(t), \tilde{V}, \tilde{W}, \tilde{c}, \tilde{v}, \tilde{r}, \tilde{y}, \tilde{z}, \tilde{q}) &\leq s^T(t)\tilde{V}\hat{f} + s^T(t) (\epsilon - u_{RC}) \\
 &= s^T(t)\tilde{V}\hat{f} + s^T(t)\epsilon - \frac{1}{2}s^T(t)s(t) - \frac{1}{2}\frac{s^T(t)s(t)}{\lambda^2} \\
 &- \frac{1}{2}s^T(t)s(t)\hat{f}\hat{f}^T \\
 &= -\frac{1}{2}s^T(t)s(t) - \frac{1}{2}\left[\frac{s(t)}{\lambda} - \lambda\epsilon\right] - \frac{1}{2}\left[s^T(t)\hat{\epsilon} - \tilde{V}\right]^2 + \frac{1}{2}\lambda^2\epsilon^2 \\
 &+ \frac{1}{2}\tilde{V}^T\tilde{V} \\
 &\leq -\frac{1}{2}s^T(t)s(t) + \frac{1}{2}\lambda^2\epsilon^2 + \frac{1}{2}\tilde{V}^T\tilde{V}.
 \end{aligned} \tag{52}$$

Integrating Eq. 52 from $t = 0$ to $t = T$, yields:

$$\begin{aligned}
 L(T) - L(0) &= -\frac{1}{2}\sum_{i=1}^m \int_0^T s_i^2(t)dt + \frac{1}{2}\sum_{i=1}^m \lambda_i^2 \int_0^T \theta_i^2(t)dt \\
 &+ \frac{1}{2}\sum_{i=1}^m \int_0^T \tilde{v}_i^2(t)dt.
 \end{aligned} \tag{53}$$

Since $V(T) > 0$ and $V(0) > 0$, Eqs. 38 and 39 indicate that $\sum_{i=1}^m \int_0^T s_i^2(t)dt < \infty$, which means the cumulative error is not divergent, but bounded. Therefore, the stability of the proposed system is proved.

Table 1
Parameters of RWBEL and RECMAC

Parameters	RWBEL	RECMAC
Number of M	10	10
Learning rates of α, γ, μ and η_w	0.01	0.01
Learning rates of η_c and η_y	0.01	0.01
Learning rates of η_v and η_z	0.01	0.01
Learning rates of η_r and η_q	0.01	0.01

5. Experimentation

In this section, an ablation experiment was built to verify the effectiveness of the wavelet function for neural networks. Then, to validate the proposed control system and evaluate its effectiveness, a Duffing-Holmes chaotic system and a simulated three degrees-of-freedom spherical joint robotic system were employed in the experimentation. Also, to enable a systematic comparative study of the proposed RWBEL control system, four reference comparison control systems, including PID controller, SMC with recurrent emotional CMAC neural network (RECMAC) control system Fang et al. (2019b), SMC with fuzzy cerebellar model articulation controller (FCMAC) control system Lin, Chen and Lin (2019), and SMC with wavelet fuzzy brain emotional learning (WBEL) controller, were also applied to the chaotic system and the robotic manipulator system.

5.1. Approximation Comparison of RWBEL and RECMAC

In order to verify the effectiveness of the wavelet function, a piecewise function is used to compare our RWBEL with RECMAC. The main difference between these two networks is RWBEL owns a wavelet function layer. The piecewise function is defined as:

$$f(x) = \begin{cases} -2.186x - 12.864, & -10 \leq x < -2 \\ 4.246x, & -2 \leq x < 0 \\ 10e^{-0.05x-0.5} \sin[(0.03x + 0.7)x], & 0 \leq x \leq 10 \end{cases} \quad (54)$$

The piecewise function is chosen due to the following two reasons: the function has (1) a turning point ($x = -2$); and (2) a coexistence of linearity and nonlinearity. Such function is suitable to evaluate the performance of the two networks in the dynamic response and nonlinear mapping ability. In this experiment, we sampled 400 points distributed uniformly over $[-10, 10]$ as training data. Both RWBEL and RECMAC have the same initialization and learning rates which are detailed in Table. 1.

Fig. 5 shows the complete tracking responses and Fig. 6 illustrates the tracking errors (e^2) of the two networks over the entire domain. In these two figures, the two networks have achieved successful results in approximation the piecewise function; however, at around the turning pointing of the piecewise function, the RECMAC network cannot well follow the piecewise function. In order to clearly show the differences, Fig. 7 shows the enlargement picture of the approximation errors in the interval of $[-2, 2]$. Thus, the jitter amplitude of RWBEL is much less than that of RECMAC.

5.2. Duffing-Holmes Chaotic System

The Duffing-Holmes chaotic system is a typical complex and uncertain nonlinear system, and the chaotic system is formed by two subsystems: 1) drive subsystem and 2) response subsystem. These two subsystems are defined as follows:

$$\begin{aligned} \ddot{x}_d(t) &= f(x_d) \\ &= -0.25\dot{x}_d + x_d - x_d^3 + 0.1\sqrt{x_d^2 + \dot{x}_d^2} \sin(t) + 0.3 \cos(t) \end{aligned} \quad (55)$$

Figure 5: The piecewise function and tracking responses of RWBEL and RECMAC

Figure 6: tracking errors (e^2) in $[-10, 10]$

$$\begin{aligned}
 \ddot{x}(t) &= f(x) + u(t) + \Delta f(x) + d(t) \\
 &= -0.25x_d + x_d - x_d^3 + 0.1\sqrt{x_d^2 + \dot{x}_d^2} \sin(t) + 0.3 \cos(t) \\
 &\quad + u(t) + \Delta f(x) + d(t),
 \end{aligned} \tag{56}$$

Figure 7: Enlargement of tracking errors (e^2) in $[-2, 2]$

Figure 8: Trajectory phase portrait

where x_d and x denote the system states of the drive and response subsystems, respectively; u is the control input; $\Delta f(x)$ indicates an unknown uncertain term; and $d(t)$ expresses the external disturbance.

In this experiment, the initial conditions were $x_d(0) = [x_d \quad \dot{x}_d]^T = [1 \quad 1]^T$, $x(0) = [x \quad \dot{x}]^T = [0.2 \quad 0.2]^T$. The sliding surface is designed as: $s(e(t)) = 2e + 1.5\dot{e}(t)$, the external disturbance $d(t) = 0.2\sin(t)$.

The simulation results of the four control systems is shown in Fig. 8. The red solid line denotes the reference

 (a) Tracking response of x_d and x

 (b) Tracking response of x_d and x during the first two seconds

(c) Tracking error from 0s to 50s

(d) Tracking error from 0s to 5s

Figure 9: State of x_d and x for the Duffing-Holmes Chaotic System

trajectory of the drive system; the green solid line, the magenta dotted line, and the black dash line represent the tracking trajectory generated by the PID, RECMAC, FCMAC, WFBEL and RWBEL control systems, respectively. In Fig. 8, all the five trajectories generated by the five control systems can successfully track chaotic trajectories, but the trajectory of the RWBEL control system reached the reference earlier than the rest control systems. Also, the RWBEL control system had less overshoot amplitudes.

The complete tracking responses of x_d and x are shown in Fig. 9(a), to demonstrate the tracking performance. In this figure, all the five control systems can well follow the target reference x_d . The performance differences only existed at the beginning of the tracking. Therefore, the tracking trajectory in the first two seconds is summarised in Fig. 9(b). The RWBEL achieved a favorable tracking performance. After a few adjustments, the RWBEL can quickly catch the reference trajectory, and closely follow the reference. In contrast, the trajectories of PID, RECMAC, FCMAC and WFBEL required a longer time to approximate the target trajectory.

Fig. 9(c) illustrates the tracking errors of the five control systems from 0 second to 50 second, and Fig. 9(d) shows the tracking errors during the first five seconds. In these two sub-figures, all the control systems can have a stable performance; however, the RWBEL controller demonstrates a faster and smoother curve to converge. In particular, the fast converge situation was very clear during the first five seconds as shown in Fig. 9(d).

Table 2 summarises the accumulated RMSE values of the tracking error for all the controllers, to show the performance difference. From this table, the performance of PID and FCMAC were very close; in contrast, due to the recurrent loop structure and wavelet, RECMAC and WFBEL had a better performance than FCMAC. Nevertheless,

Table 2

Comparison of PID, RECMAC, FCMAC, WFBEL and RWBEL controllers

	PID	RECMAC	FCMAC	WFBEL	RWBEL
RMSE	6.9659e-02	6.5321e-02	6.9299e-02	6.7194e-02	6.3328e-02

Table 3

Parameters of REN and RWN

Parameters	REN	RWN
Number of M_1 and M_2	8	8
Number of J	N/A	8
Number of V and W	24	8
Number of A and O	3	3
Initialization range of c and y	[-1.0 1.0]	[-2.0 2.0]
Initial value of v and z	0.1	1
Learning rates of α, γ, μ and η_w	0.01 0.1 0.1	10
Learning rates of η_c and η_y	0.1	0.1
Learning rates of η_v and η_z	0.1	0.1
Learning rates of η_r and η_q	0.1	0.1

the RWBEL had the smallest RMSE across the board in this experiment. According to Fig. 9, RWBEL reached the reference trajectory faster than other controllers, and the tracking error did not change significantly during the rest of the tracking process. Therefore, it can be concluded that the RWBEL-based control system outperformed other control systems in this experiment.

5.3. Spherical Coordinate Robot Simulation

A spherical robot simulation system was used to evaluate the control performance of the RWBEL based control system. The dynamic equation of the spherical coordinate robot is presented as:

$$M(q)\ddot{q} + C(q, \dot{q})\dot{q} + g(q) = u + \tau_d, \quad (57)$$

where q , $\dot{q}$, and $\ddot{q} \in R^3$, represent the position, velocity and acceleration, respectively; $M(q) \in R^{3 \times 3}$ is an inertia matrix; $C(q, \dot{q}) \in R^{3 \times 3}$ is the Coriolis/Centripetal matrix; and $g(q) \in R^3$ is the gravity vector. In this experiment, $g(q) \equiv 0$, τ_d denotes the external disturbance. The initial state is $q = [0.2, 0, 0.1]^T$, $\dot{q} = [0, 0, 0]^T$, $\ddot{q} = [0, 0, 0]^T$.

To evaluate the robustness of the proposed control system, the target tracking trajectory was converted from one pattern to another pattern at the 15-th second. The trajectory within the first 15 seconds was defined as:

$$L_1 = 0.5 * [0.2 * \sin(2t + 0.6) + 0.15 * \cos(t + 1), \\ 0.1 * \sin(0.5\pi t), 0.2 * (\cos(2t) - \sin t)]^T. \quad (58)$$

After 15s, the reference trajectories was sacrificed as:

$$L_2 = 0.5 * [0.3 \sin t + 0.2 \cos(2t + 0.5) - 0.2, \\ 0.3 \sin t + 0.5 \sin(2t + 1), 0.25 - 0.1 \sin(t + 1) + \sin(2t)]^T. \quad (59)$$

The external disturbance is $\tau_d = k * [\sin(2t); \cos(2t); \sin(t)]$, where k denotes the disturbance constant. During the simulation, k was set to various values, so as to show the converge abilities of all the control systems. The sliding surface of the control system was designed as: $s(e(t)) = 2e + 2e(t)$; the compensator controller was designed as: $R = 0.08I_{3 \times 3}$. The parameters of REN and RWN are summarised in Table 3.

The tracking performances of the robot's three joints is illustrated in Fig. 10. Each sub-figure in Fig. 10 includes two plots: the upper row indicates the tracking trajectories and the bottom row shows the tracking errors in joint

Table 4

Comparison of PID, RECMAC, FCMAC, WFBEL and RWBEL controllers

	Error	PID	RECMAC	FCMAC	WFBEL	RWBEL
1	Joint-1	3.6237e-03	3.3973e-03	3.4450e-03	3.455e-03	3.3685e-03
	Joint-2	4.2596e-03	4.0359e-03	4.1174e-03	3.9861e-03	3.8851e-03
	Joint-3	4.0043e-03	2.2511e-03	2.3343e-03	2.2318e-03	2.1505e-03
5	Joint-1	1.0102e-02	4.6553e-03	5.5054e-03	4.8088e-03	3.4397e-03
	Joint-2	1.0583e-02	5.6287e-03	6.4735e-03	5.6132e-03	4.1425e-03
	Joint-3	1.6361e-02	3.6129e-03	4.4984e-03	3.4002e-03	2.2804e-03
10	Joint-1	2.0016e-02	6.6272e-03	8.3463e-03	7.4739e-03	3.7359e-03
	Joint-2	2.0198e-02	7.7088e-03	9.3793e-03	8.4858e-03	4.5920e-03
	Joint-3	3.2359e-02	5.2975e-03	6.9587e-03	5.6235e-03	2.6283e-03

angles. This figure reveals that the error oscillation of the PID controller was large than those of the rest controllers; It is noteworthy that the error performance of RECMAC and WFBEL was close to each other and both are better than FCMAC. In contrast, the performance of the RWBEL control system was much more stable than those of other control systems.

In order to clearly compare the robustness of the controllers in response to the pattern changing at the 15-th second, three sub-figures in Fig. 11 illustrate the magnified versions of the tracking trajectories of the three joints from the 14-th second to 16-th second, respectively. The plotting setup of Fig. 11 is identical with that of Fig. 10. In Fig. 11, the trajectory performance (shown in the upper row of each sub-figure) of the three network-based control systems are close; however, the superiority of RWBEL based control system is significant when it comes to the tracking errors (shown in the bottom row of each sub-figure). In addition, the response speed of the RWBEL control system is the fastest of all three network-based control systems.

To demonstrate the disturbance resistance ability of the proposed RWBEL network control system, quantitative performance comparisons of the four control systems under the three levels of disturbance are summarized in Table 4. The level of disturbance, k , was set to 1, 5, and 10, respectively. This table, showing a similar phenomenon with that in Figs. 10 and 11, proved that the proposed RWBEL network-based control system can have better performance.

(a) Joint 1

(b) Joint 2

(c) Joint 3

Figure 10: Trajectory responses and tracking errors of Joints 1,2 and 3

(a) Joint 1

(b) Joint 2

(c) Joint 3

Figure 11: Trajectory responses and tracking errors from 14s to 16s of Joints 1, 2, and 3

6. Conclusion

This paper reports a new type of recurrent neural network that integrates the key components of the recurrent mechanism, wavelet neural network, and brain emotional learning network, to address the uncertainties of nonlinear systems. The proposed network has been combined with a compensator controller to form a new network-based control system. The parameters of the controller were adjusted by using the Lyapunov theorem. The simulated results based on two uncertain nonlinear systems demonstrate the effectiveness and efficiency of the proposed control system. Despite the promising experimental results, this work can be further improved. First, it is worthwhile to investigate the application of other feedback methods to replace the dual channels in the brain emotional learning network. Also, the proposed controller is required to be further evaluated using real-world applications, especially multiple degrees-of-freedom robotic systems, to explore its full potential.

Conflict of Interest

The authors have no conflicts of interest to declare that are relevant to the content of this article.

CRedit authorship contribution statement

Juncheng Zhang: Methodology, Software, Writing - Original draft preparation. **Fei Chao:** Conceptualization of this study, Methodology, Investigation. **Hualin Zeng:** Formal analysis, Writing - Original draft preparation. **Chih-Min Lin:** Conceptualization of this study. **Longzhi Yang:** Writing - Review & Editing.

References

- Al-Dunainawi, Y., Abbod, M.F., Jizany, A., 2017. A new mimo anfis-pso based narma-l2 controller for nonlinear dynamic systems. *Engineering Applications of Artificial Intelligence* 62, 265–275. URL: <http://www.sciencedirect.com/science/article/pii/S0952197617300805>, doi:<https://doi.org/10.1016/j.engappai.2017.04.016>.
- Baghbani, F., Akbarzadeh-T, M.R., Naghibi-Sistani, M.B., Akbarzadeh, A., 2020. Emotional neural networks with universal approximation property for stable direct adaptive nonlinear control systems. *Engineering Applications of Artificial Intelligence* 89, 103447. URL: <http://www.sciencedirect.com/science/article/pii/S0952197619303422>, doi:<https://doi.org/10.1016/j.engappai.2019.103447>.
- Baghbani, F., Akbarzadeh-T, M.R., Sistani, M.B.N., 2018. Stable robust adaptive radial basis emotional neurocontrol for a class of uncertain nonlinear systems. *Neurocomputing* 309, 11–26. URL: <http://www.sciencedirect.com/science/article/pii/S09525231218304399>, doi:<https://doi.org/10.1016/j.neucom.2018.03.051>.
- Chao, F., Zhou, D., Lin, C., Yang, L., Zhou, C., Shang, C., 2019. Type-2 fuzzy hybrid controller network for robotic systems. *IEEE Transactions on Cybernetics*, 1–15doi:10.1109/TCYB.2019.2919128.
- Chao, F., Zhou, D., Lin, C.M., Zhou, C., Shi, M., Lin, D., 2018. Fuzzy cerebellar model articulation controller network optimization via self-adaptive global best harmony search algorithm. *Soft Computing* 22, 3141–3153.
- Chen, Z., Huang, F., Chen, W., Zhang, J., Sun, W., Chen, J., Gu, J., Zhu, S., 2019. RBFNN-based adaptive sliding mode control design for delayed nonlinear multilateral tele-robotic system with cooperative manipulation. *IEEE Transactions on Industrial Informatics*, 1–1.
- Elhaki, O., Shojaei, K., 2020. A robust neural network approximation-based prescribed performance output-feedback controller for autonomous underwater vehicles with actuators saturation. *Engineering Applications of Artificial Intelligence* 88, 103382. URL: <http://www.sciencedirect.com/science/article/pii/S0952197619303033>, doi:<https://doi.org/10.1016/j.engappai.2019.103382>.
- Fang, W., Chao, F., Lin, C., Zhou, D., Yang, L., Chang, X., Shen, Q., Shang, C., 2020. Visual-guided robotic object grasping using dual neural network controllers. *IEEE Transactions on Industrial Informatics*, 1–1.
- Fang, W., Chao, F., Lin, C.M., Yang, L., Shang, C., Zhou, C., 2019a. An improved fuzzy brain emotional learning model network controller for humanoid robots. *Frontiers in Neurorobotics* 13, 2. URL: <https://www.frontiersin.org/article/10.3389/fnbot.2019.00002>, doi:10.3389/fnbot.2019.00002.
- Fang, W., Chao, F., Yang, L., Lin, C.M., Shang, C., Zhou, C., Shen, Q., 2019b. A recurrent emotional cmac neural network controller for vision-based mobile robots. *Neurocomputing* 334, 227–238.
- Fei, J., Lu, C., 2018. Adaptive sliding mode control of dynamic systems using double loop recurrent neural network structure. *IEEE Transactions on Neural Networks and Learning Systems* 29, 1275–1286.
- Hadjaissa, A., Ameer, K., Boutoubat, M., 2019. A wca-based optimization of a fuzzy sliding-mode controller for stand-alone hybrid renewable power system. *Soft Comput.* 23, 7831–7842.
- Huynh, T., Lin, C., Le, T., Cho, H., Pham, T.T., Le, N., Chao, F., 2019. A new self-organizing fuzzy cerebellar model articulation controller for uncertain nonlinear systems using overlapped gaussian membership functions. *IEEE Transactions on Industrial Electronics*, 1–1doi:10.1109/TIE.2019.2952790.
- Huynh, T.T., Le, T.L., Lin, C.M., 2018. A topsis multi-criteria decision method-based intelligent recurrent wavelet cmac control system design for mimo uncertain nonlinear systems. *Neural Computing and Applications* 32, 4025–4043.
- Lin, C., Boldbaatar, E., 2017. Fault accommodation control for a biped robot using a recurrent wavelet Elman neural network. *IEEE Systems Journal* 11, 2882–2893.

- Lin, C.M., Huynh, T.T., Le, T.L., 2019. Adaptive topsis fuzzy cmac back-stepping control system design for nonlinear systems. *Soft Computing* 23, 6947â€”6966.
- Lin, Q., Chen, S., Lin, C., 2019. Parametric fault diagnosis based on fuzzy cerebellar model neural networks. *IEEE Transactions on Industrial Electronics* 66, 8104â€”8115.
- Liu, Z.T., Xie, Q., Wu, M., Cao, W.H., Mei, Y., Mao, J.W., 2018. Speech emotion recognition based on an improved brain emotion learning model. *Neurocomputing* 309, 145 â€” 156. URL: <http://www.sciencedirect.com/science/article/pii/S0925231218305344>, doi:<https://doi.org/10.1016/j.neucom.2018.05.005>.
- Mishra, R.N., Mohanty, K.B., 2020. Development and implementation of induction motor drive using sliding-mode based simplified neuro-fuzzy control. *Engineering Applications of Artificial Intelligence* 91, 103593. URL: <http://www.sciencedirect.com/science/article/pii/S095219762030066X>, doi:<https://doi.org/10.1016/j.engappai.2020.103593>.
- Oveisi, A., Jeronimo, M.B., NestoroviÄŒ, T., 2018. Nonlinear observer-based recurrent wavelet neuro-controller in disturbance rejection control of flexible structures. *Engineering Applications of Artificial Intelligence* 69, 50 â€” 64. URL: <http://www.sciencedirect.com/science/article/pii/S0952197617303044>, doi:<https://doi.org/10.1016/j.engappai.2017.12.009>.
- Qutubuddin, M., Yadaiah, N., 2017. Modeling and implementation of brain emotional controller for permanent magnet synchronous motor drive. *Engineering Applications of Artificial Intelligence* 60, 193 â€” 203. URL: <http://www.sciencedirect.com/science/article/pii/S0952197617300301>, doi:<https://doi.org/10.1016/j.engappai.2017.02.007>.
- UÇak, K., Günel, G.Ö., 2020. An adaptive sliding mode controller based on online support vector regression for nonlinear systems. *Soft Comput.* 24, 4623â€”4643.
- Wu, Q., Lin, C., Fang, W., Chao, F., Yang, L., Shang, C., Zhou, C., 2018. Self-organizing brain emotional learning controller network for intelligent control system of mobile robots. *IEEE Access* 6, 59096â€”59108.
- Zhao, J., Lin, C., 2019. Wavelet-tsk-type fuzzy cerebellar model neural network for uncertain nonlinear systems. *IEEE Transactions on Fuzzy Systems* 27, 549â€”558.
- Zhou, D., Shi, M., Chao, F., Lin, C.M., Yang, L., Shang, C., Zhou, C., 2018. Use of human gestures for controlling a mobile robot via adaptive cmac network and fuzzy logic controller. *Neurocomputing* 282, 218 â€” 231. doi:<https://doi.org/10.1016/j.neucom.2017.12.016>.

Figures

Figure 1

Please see the Manuscript PDF file for the complete figure caption

Figure 2

Please see the Manuscript PDF file for the complete figure caption

Figure 3

Please see the Manuscript PDF file for the complete figure caption

Figure 4

Please see the Manuscript PDF file for the complete figure caption

Figure 5

Please see the Manuscript PDF file for the complete figure caption

Figure 6

Please see the Manuscript PDF file for the complete figure caption

Figure 7

Please see the Manuscript PDF file for the complete figure caption

Figure 8

Please see the Manuscript PDF file for the complete figure caption

(a) Tracking response of x_d and x

(b) Tracking response of x_d and x during the first two seconds

(c) Tracking error form 0s to 50s

(d) Tracking error form 0s to 5s

Figure 9

Please see the Manuscript PDF file for the complete figure caption

(a) Joint 1

(b) Joint 2

(c) Joint 3

Figure 10

Please see the Manuscript PDF file for the complete figure caption

(a) Joint 1

(b) Joint 2

(c) Joint 3

Figure 11

Please see the Manuscript PDF file for the complete figure caption