Band Gap of Two-dimensional Layered Cylindrical Photonic Crystal Slab and Slow Light of W1 Waveguide

Zhi-Wei Wang

Nanjing University of Posts and Telecommunications

Ya-Ting Xiang

Nanjing University of Posts and Telecommunications

Hai-Feng Zhang (✉ hanlor@163.com)

Nanjing University of Aeronautics and Astronautics

Research Article

Keywords: Two-dimensional photonic crystals slab, Photonic crystal waveguide, Photonic band gap, Slow light, Plane wave expansion method

Posted Date: July 12th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-596967/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Band gap of two-dimensional layered cylindrical photonic crystal slab and slow light of W1 waveguide

Zhi-Wei Wang¹, Ya-Ting Xiang¹ and Hai-Feng Zhang^{1*}

¹College of Electronic and Optical Engineering & College of Microelectronics, Nanjing University of Posts and Telecommunications, Nanjing 210023, China

Abstract: In this paper, we apply the scatterers of cylindrical rings to a two-dimensional photonic crystals (PCs) slab. The effects of the number of layers, the thickness, the index, and the height of the cylindrical layers on the photonic band gaps (PBGs) of such slab with different lattice arrangements are studied. It turns out that our new structure helps to obtain a large range of the PBGs. The maximum bandwidth is obtained with the value of $0.1497(2\pi c/a)$. The PBGs are moved to the lower frequencies with the augment of thickness, refractive index, and height. The choice of height, refractive index, and thickness is a trade-off, and adding the number of dielectric layers is not always positively correlated with the area of PBGs. In addition, in the W1 waveguide with a triangular lattice layout, we obtain a slow light of $0.026 \times c$. Compared with the square lattice, the triangular lattice is more suitable for slowing down the speed of light.

Keyword: Two-dimensional photonic crystals slab; Photonic crystal waveguide; Photonic band gap; Slow light; Plane wave expansion method

1. Introduction

Photonic crystals (PCs) are a new concept proposed based on the study of the propagating characteristics of light in periodic dielectric materials [1, 2]. This special structure, which can be artificially changed and manufactured, has attracted much attention since its appearance in 1987. The periodic potential creates a band gap in the Bloch plane, and the PCs prevent the waves falling on this gap from propagating through its structure. This property, known as the photonic band gaps (PBGs), is the most fundamental property of PCs. Researchers have proposed many optical devices based on the PBGs peculiarity of PCs, just like filters [3], low-threshold lasers [4], sensors [5], waveguides [6], and antennas [7]. We can set the dielectric periodically in different dimensions, and PCs are thus divided into three dimensions. One-dimensional PCs (1D-PCs) [8] have been fully discussed and studied in the past 30 years. The tremendous traits of three-dimensional PCs (3D-PCs) enable them to have wider application prospects [9]. However, manufacturing 3D-PCs is difficult to realize. In this way, studying the two-dimensional PCs (2D-PCs) is of real significance. The problems of the traditional 2D-PCs require that the medium has an infinite height in the third dimension, which cannot be satisfied in reality. As a consequence, it is more practical to research the two-dimensional PCs slab (2D-PCS) [10]. Although 2D-PCS are arranged periodically in two dimensions, this is actually a three-dimensional problem. The PBGs of 2D-PCS refer to the frequency range where no guided modes exist, which differ from the traditional 2D-PCs [11]. Hereinafter, the plane-wave expansion (PWE) method is used to analyze the PBGs characteristics of 2D-PCS. The light cone is the essential feature of the 2D-PCS, which is different from the ordinary 2D-PCs. It can be treated as the lowest energy band in the system,

*Corresponding author at: College of Electronic and Optical Engineering & College of Microelectronics, Nanjing University of Posts and Telecommunications, Nanjing, 210023, China
E-mail: hanlor@163.com (Hai-Feng Zhang)

and only the band below the light cone can be considered to propagate in the slab [11]. In general, the inversion symmetry of the guided modes in the system is the problem we need to pay attention to. We can distinguish the parity of the guided modes according to whether the symmetry is odd or even. Odd symmetry corresponds to odd modes, and even symmetry corresponds to even, and the even and odd modes are the analog of the TM and TE modes, respectively. [11] (In this paper, the even modes are called TM-like modes, the odd modes are called TE-like modes, and the definition of TE mode and TM mode will be mentioned later.)

Previous applications of 2D-PCS are mostly focused on the defect states, and there are few reports on the tuning of the slab mode gap by structural parameters in recent years. In 2005, S. Y. Shi *et al.* presented a revised formulation of plane wave method for band structure calculation of PCs for dispersive material which provided a theoretical basis for subsequent studies [12]. At the same time, I. S. Maksymov *et al.* studied the PBGs in nonlinear PCS, they focus on the red-shifted phenomenon in the Kerr-nonlinear PCS, but unfortunately, no large bandwidth was obtained [13]. In 2013, T. F. Khalkhali *et al.* researched the PCS of circular air holes in an anisotropic Te background. However, in their work, the maximum bandwidth is $0.061 (2\pi c/a)$ [14]. In the same year, D. Liu *et al.* studied the PBGs in PCS of core-shell-type dielectric nanorod heterostructures, they only discussed the structure of one layer of rings and did not extend the structure to multiple layers of rings [15].

As early as 1992, Erdogan *et al.* studied the propagation features of TE mode in one-dimensional cylindrical PCs [16]. In 1994, Ping *et al.* extended his work to the sphere and studied the propagation and application of electromagnetic waves in the system of planar, cylindrical, and spherical dielectric layers [17]. Their work laid the foundation for subsequent research, which was carried out one after another [18-20]. So far, this kind of 1D-PCs has not been investigated of the two-dimensional case, so it is necessary to study the PBGs features of the 2D-PCS with the scatterers of cylindrical rings.

As shown in Fig.1(a), the cylinder is proposed against an air background. In former studies, researchers were keen on introducing defects into the slab [21-23]. In this paper, we not only study the tuning effect of different structural parameters on different mode gaps but also introduce line defects into the 2D-PCS to observe the propagation of light in line defects. The W1 waveguide is constructed by introducing circuit defects in the perfect PCs. This waveguide provides two forms for realizing slow light [24]. The first form is called backscattering. When the amplitude and phases of backward and forward propagating light meet the coherent conditions, standing waves will be formed. Light in the waveguide behaves as if it was taking three steps forward and two steps back. The second form of slow light is omnidirectional reflection. The light is reflected back and forth perpendicular to the direction of the wave's advance. The result of this phenomenon is that the forward component of the light is very small. As is known to all, the 2D-PCS restricts the light obviously, and the total reflection is used to limit the behavior of light in the third dimension. Theoretically, the W1-type waveguide composed of the 2D-PCS is suitable for realizing slow light.

Thus, it is still of practical consequence to study the PBGs peculiarities of the cylindrical stratified structure PCs and the group velocity in the W1 waveguide. In this work, the composition of the scatterer is GaAs. The PWE method is used to study the effects of different structural parameters on the different modes of the 2D-PCS, and compare the traits of the PBGs in the triangular and square lattices. After introducing the line defect, the group velocity of $0.026 \times c$ in the triangular lattice is obtained.

2. Structure design and simulation

2.1 Band structure theory

As mentioned above, the scatterer is placed against an air background and the height of the cylinder along the y -axis is h . The structure of each scatterer is shown in Fig.1(b), and the dielectric constant of the structure presents a periodic distribution along any axis of the x - z plane. Meanwhile, the single scatterer is placed in the form of

2D-PCS as shown in Fig.1(a). The lattice constant is a , R_N is the outer radius of the N th shell, and the inner radius is r_N . The red area is GaAs, the blue is air, and the thickness of the GaAs column in each layer is $R_N - r_N = d = 0.05 \times a$. Schematic diagrams of scatterers with five dielectric layers arranged into the square lattice and triangular lattice are shown in Figs.1(c) and (d), respectively. It can be seen that when the number of layers is $N=5$, each scatterer is tangent to the other. In this paper, the maximum value of N is 5. The curve of the dielectric constant of GaAs changing with wavelength is shown in Fig.1(e), when the wavelength of incident light is light $\lambda=1\mu\text{m}$, the dielectric constant of GaAs is 12.3131, the refractive index n of GaAs is 3.502.

Fig.1 (a) The schematic diagram of photonic crystal slab in an air background with finite height, (b) the structure of scatterers, the schematic diagram of (c) the square lattice arrangement, (d) the triangular lattice arrangement with five layers ($N=5$) of dielectric and its first Brillouin zone, and (e) the curve of the dielectric constant of GaAs changing with the wavelength.

Many ways can be used to calculate the structures of energy bands, such as the transfer matrix method, finite-difference time-domain method, finite-difference frequency-domain method, and PWE [25]. Hereinafter, we will use the PWE method to solve problems.

In PCs, Maxwell's equations can be used in describing the propagation of electromagnetic waves

$$\nabla \times \vec{E} = -\frac{\partial \vec{B}}{\partial t} \quad (1-a)$$

$$\nabla \cdot \vec{B} = 0 \quad (1-b)$$

$$\nabla \times \vec{H} = \frac{\partial \vec{D}}{\partial t} + \vec{j} \quad (1-c)$$

$$\nabla \cdot \vec{D} = \rho \quad (1-d)$$

In our discussions, the scatterer is composed of GaAs, which is linear and isotropic, and we can get:

$$\vec{D} = \epsilon_0 \epsilon(x) \vec{E}(x) \exp(-i\omega t) \quad (2-a)$$

$$\vec{B} = \mu_0 \vec{H}(x) \exp(-i\omega t) \quad (2-b)$$

Combining Eq.(2-a) and Eq.(2-b) with Maxwell's equations, the vectorial Helmholtz equation can be written as

$$\nabla \times \left[\frac{1}{\epsilon(x)} \cdot \nabla \times \right] \vec{H} = \frac{\omega^2}{c^2} \vec{H}(x) \quad (3-a)$$

$$\nabla \times \left[\frac{1}{\epsilon(x)} \cdot \nabla \times \right] \vec{E} = \frac{\omega^2}{c^2} \vec{E}(x) \quad (3-b)$$

The solutions to Eq.(3-a) and Eq.(3-b) are the dispersion relationship between vector $\vec{k}$ and frequency ω . The medium dielectric constant can be expressed by ϵ_m , and the dielectric constant of air is 1, so we get

$$\epsilon(\vec{r}) - 1 = (\epsilon_m - 1) \sum_{\vec{R}} u(\vec{r} - \vec{R}) \quad (4)$$

When $(\vec{r} - \vec{R})$ outside the cycle column, $u(\vec{r} - \vec{R}) = 0$, otherwise, $u(\vec{r} - \vec{R}) = 1$.

$$s \cdot \epsilon(\vec{G}) = \int_s \epsilon(\vec{r}) \cdot e^{-i\vec{G} \cdot \vec{r}} d\vec{r} \quad (5)$$

We assume that the dielectric constant is independent of the y axis, the TE modes use nonzero $(\vec{H}_x, \vec{H}_z, \vec{E}_y)$ form, while TM modes with nonzero $(\vec{H}_y, \vec{E}_x, \vec{E}_z)$. Hence, we get the solution to the scalar wave equation by TE modes:

$$(\nabla_t^2 + \frac{\omega^2}{c^2} \varepsilon) E = 0 \quad (6-a)$$

while, TM-like modes satisfy the relationship:

$$\nabla_t \cdot \left(\frac{1}{\varepsilon} \cdot \nabla_t \cdot H_y \right) + \frac{\omega^2}{c^2} H_y = 0 \quad (6-b)$$

Due to $\varepsilon_r(\vec{r}) = \varepsilon_r(\vec{r} + \vec{R})$, we take the Fourier expansion of this relation, and get H_y equation:

$$\frac{\partial}{\partial t} \cdot \left[\frac{1}{\varepsilon(\vec{r})} \cdot \frac{\partial H_z(\vec{r})}{\partial x} \right] + \frac{\partial}{\partial y} \left[\frac{1}{\varepsilon(\vec{r})} \cdot \frac{\partial H_z(\vec{r})}{\partial y} \right] = \frac{\omega^2}{c^2} H_z(\vec{r}) \quad (7)$$

From Bloch's theorem:

$$H_z(\vec{r}) = \sum_{\vec{R}} H(\vec{k} + \vec{G}) \cdot \exp \left[i \cdot \left(\vec{k} + \vec{G} \right) \cdot \vec{r} \right] \quad (8)$$

substitute Eq.(6-a) and Eq.(8) into Eq.(7), and the eigenequation of the TM will be expressed as:

$$\sum_{\vec{G}} \left(\vec{k} + \vec{G} \right) \cdot \left(\vec{k} + \vec{G} \right) \varepsilon^{-1} \left(\vec{G} - \vec{G} \right) \cdot H \left(\vec{k} + \vec{G} \right) = \frac{\omega^2}{c^2} H \left(\vec{k} + \vec{G} \right) \quad (9-a)$$

The intrinsic equation of the TE mode is

$$\sum_{\vec{G}} \left| \vec{k} + \vec{G} \right| \cdot \varepsilon^{-1} \cdot \left(\vec{G} + \vec{G} \right) \cdot E \left(\vec{k} + \vec{G} \right) = \frac{\omega^2}{c^2} E \left(\vec{k} + \vec{G} \right) \quad (9-b)$$

2.2 Slow light theory

As shown in Fig.2, we replaced the middle row of columns with a solid cuboid as the defect column with the same height of h . Its side lengths in the x - z cross-section are Dx and Dz , corresponding to the x -axis and z -axis respectively.

It is acknowledged that the group velocity is used to describe the slow light [26, 27]. The group velocity can be obtained by derivative of the dispersion relation, the propagation velocity and direction of the amplitude envelope and can be expressed by Eq.(10).

$$v_g = \frac{d\omega}{dk} = \frac{c}{n_g} \quad (10)$$

where, c represents the speed of light in vacuum, n_g is used to express the group index, ω is the angular frequency, and k on behalf of the wave vector. The group index can be portrayed by Eq.(11).

$$n_g = c \cdot \frac{dk}{d\omega} \quad (11)$$

Fig.2 (a) The schematic diagram of waveguide structure in $N=3$ with line defects introduced, and (b) the scatterer structure in $N=1$, 2 and $N=4$, 5.

3. Analysis and discussion

3.1 The discussions of the characteristics of PBGs

A. The influences of N on the band structures of the square and triangular cases

Fig.3 displays the dispersion relation of even modes in a square lattice arrangement with the wavelength of incident light $\lambda=a$. We can see that when there is only a hollow cylinder, only three bands exist, and they are close to the light cone. As shown in Fig.3(a), only one PBG with a width of $0.0171 (2\pi c/a)$ appears, which is distributed among 0.6817 - $0.6988 (2\pi c/a)$. From Fig.3(b), when N adds to 2, the number of PBGs also increases to two, with widths of $0.0587 (2\pi c/a)$ and $0.0127 (2\pi c/a)$, respectively, distributed at 0.6318 - $0.6905 (2\pi c/a)$ and 0.6934 - $0.7061 (2\pi c/a)$. Figs.3(c)-(e) demonstrate the PBGs characteristics at the case of $N=3,4,5$. The results exhibit that the PBGs occur a redshift with the augment of the number of dielectric layers. However, the gap width does not always accession with the increase in N . If $N=4$, the maximum frequency range of the PBG distribution is 0.6131 - $0.6790 (2\pi c/a)$, and the width is $0.0659 (2\pi c/a)$; while at $N=5$, the corresponding frequency scope covers 0.6026 - $0.6615 (2\pi c/a)$, and the width is dipped to $0.0588 (2\pi c/a)$. However, despite this, the width in the low-frequency area reaches the maximum value at the case of $N=5$, with a width of $0.0481 (2\pi c/a)$ and extends $0.3762 (2\pi c/a)$ from $0.4243 (2\pi c/a)$.

Fig.3 The dispersion relations of the even mode when the inserted scatterers are arranged in the square lattice. (a) $N=1$, (b) $N=2$, (c) $N=3$, (d) $N=4$ and (e) $N=5$.

Fig.4 manifests the dispersion relation of the odd modes of the square lattice in $N=1,2,3,4$. Similar to Fig.3(a), Fig.4(a) presents that when the filling rate is small, there are fewer modes that can propagate in the slab, and a gap is located in $0.6992-0.7070 (2\pi c/a)$ is produced. The band is close to that of the light cone which due to the light interacts with the medium so little that most of the light is leaked out of the system. In Figs.4 (b) and (c), the width of the PBG, whose location is covered in $0.6012-0.6995 (2\pi c/a)$, increases to $0.0983 (2\pi c/a)$ regarding $N=2$; as N grows to 3, the number of PBGs fortifies with 3, which distributed among $0.4976-0.5489 (2\pi c/a)$, $0.5566-0.6057 (2\pi c/a)$ and $0.6109-0.6331 (2\pi c/a)$, and the width of each PBG is smaller than that when $N=2$. Fig.4(d) describes the dispersion relationship if $N=4$, a gap of $0.076 (2\pi c/a)$ width comes out in the high-frequency range, the others are situated in $0.4663-0.4924 (2\pi c/a)$ and $0.4450-0.4624 (2\pi c/a)$. Unfortunately, no PBG is reported at the case of $N=5$.

Fig.4 The band structures of the odd Mode in different medium layers N , thickness of medium layer $d=0.05 \times a$. (a) $N=1$, (b) $N=2$, (c) $N=3$, and (d) $N=4$.

Without changing the parameters of the structure, the wavelength of the incident light is still a , and the scatterers are arranged into triangular lattice form. Fig.5 illustrates the situation of PBGs in even modes under a triangular lattice setting. Fig.5(a) tells us that in terms of $N=1$, a PBG extends from $0.6463 (2\pi c/a)$ to $0.6610 (2\pi c/a)$, with a width of $0.0147 (2\pi c/a)$. However, no PBGs are found in the case of $N=2$ in Fig.5(b). It can be seen from Fig.5(c) that four PBGs come into being, and their frequency scope is $0.5222-0.5327 (2\pi c/a)$, $0.5509-0.5852 (2\pi c/a)$, $0.6460-0.6647 (2\pi c/a)$, respectively. And the widest one is covered $0.6055-0.6458 (2\pi c/a)$ with a width of $0.0404 (2\pi c/a)$. To keep boosting the value of N , and the PBGs will degrade and move to the low-frequency sphere. Fig.5(e) illustrates the case of $N=5$, the number of the PBGs decreases to 3, the locations of the PBGs are $0.4065-0.4196 (2\pi c/a)$, $0.5573-0.5712 (2\pi c/a)$ and $0.6064-0.6194 (2\pi c/a)$.

Fig.5 The dispersion relationships of the even mode when the medium column is arranged in the triangular lattice, the thickness of the medium layer of $d=0.05 \times a$. (a) $N=1$, (b) $N=2$, (c) $N=3$, (d) $N=4$, and (e) $N=5$.

Fig.6 The dispersion relationships of the odd mode when the medium column is arranged in the triangular lattice, the thickness of the medium layer of $d=0.05 \times a$. (a) $N=1$, (b) $N=2$, (c) $N=3$, (d) $N=4$, and (e) $N=5$.

The odd modes of triangular lattice arrangement are slightly different from that of the square lattice. First of all, it can be seen from Fig.6(a) that the PBG width somewhat increases, but it is no longer near the top of the light cone, and distributed at $0.5372\text{--}0.5732$ ($2\pi c/a$) with a bandwidth of 0.0359 ($2\pi c/a$). Figs.6(b)-(c) demonstrate the width of the PBGs and the number of PBGs are increased, and the PBGs are caused a redshift. If $N=2$, a PBG in the range of $0.4525\text{--}0.5180$ ($2\pi c/a$) will be reported. With regard to $N=3$, the number of the PBGs grows to 3, which is located in $0.4097\text{--}0.4188$ ($2\pi c/a$), $0.4991\text{--}0.5521$ ($2\pi c/a$) and $0.5561\text{--}0.6085$ ($2\pi c/a$), respectively. As N gets larger, the PBGs blue shift, and the width and number tail off simultaneously. In the case of $N=4$, as displayed in Fig.6(d), three PBGs are observed with the scope of $0.4933\text{--}0.5095$ ($2\pi c/a$), $0.5649\text{--}0.5745$ ($2\pi c/a$) and $0.6354\text{--}0.6422$ ($2\pi c/a$). As N adds to 5 in Fig.6(e), the number of PBGs reduces to 2, whose locations are $0.5347\text{--}0.5476$ ($2\pi c/a$).

B. The influences of the height of dielectric layer h on the PBGs of square and triangular cases

Fig.7 exhibits the tuning effect of the cylinder height on the first (1st) PBG. In this discussion, $n=3.502$, $d=0.05 \times a$, $N=2$, h is changed as a variable. The results tell the truths that the bandwidths will increase with the augment of h , but when h adds to a certain value, the bandwidths will gradually decrease. This is consistent with the Ref. [11] when the height is too low, only a small amount of energy is confined in the system; however, when the height is too high, the higher-order mode is slightly higher than the lower order mode, thus preventing the generation of PBGs.

Fig.7 (a) shows how the bandwidth of the first PBG changes with h under the square lattice arrangement. For the even modes, the maximum bandwidth is 0.089 ($2\pi c/a$), corresponding to a height of $1.02 \times a$. For the case of the odd modes, the maximum bandwidth is located in $(2.34, 0.07)$. The results of the triangular lattice arrangement are

described in Fig.7(b). The maximum bandwidth of the even modes is obtained at $1.28 \times a$. When $h=2.225 \times a$, the maximum bandwidth is obtained with the value of $0.117 (2\pi c/a)$.

Fig.7 The features of PBGs varying with the height under different lattice arrangement, $d=0.05 \times a$, $N=2$ (a) square lattice, and (b) triangular lattice.

C. The influences of the thickness of dielectric layer d on the PBGs of square and triangular cases

Fig.8 The features of PBGs varying with the d under different lattice arrangement, $h=a$, $N=2$ (a) square lattice, and (b) triangular lattice.

In this part, the value of N is still 2, h is set to the value of the lattice constant a , $n=3.502$, and the value of d is changed. It is found that the value of d is a trade-off consideration, and increasing the value of d is not conducive to the fortify of the bandwidth.

Fig.8(a) demonstrates the effect of changing d on bandwidth under the layout of the square lattice. The 1st PBG of the odd modes only occurs when $d=0.1 \times a$, and its range is small, the bandwidth slowly diminishes as d increases. For the convenience of discussion, the second (2nd) PBG of the even modes and the odd modes are selected here as the research objects. However, the 1st PBG is more conducive to study for the mixed modes. For the 2nd PBG of the even modes, the vertex of the curve is located in $(0.044, 0.0399)$. Regarding the case of the 2nd PBG of the odd modes the corresponding vertex coordinate is $(0.0506, 0.1005)$. In terms of the mixed modes, the maximum bandwidth is $0.055 (2\pi c/a)$ and the corresponding d is $0.048 \times a$.

The situation of a triangular lattice is shown in Fig.8(b). And just like the square lattice, there's an optimal value for d for the triangular lattice arrangement. In this part, the 1st PBG of the even modes and the odd modes are discussed, while the 2nd PBG is given priority to the mixed modes. The peak value of the odd modes, the even modes, and the mixed modes is located in (0.041, 0.0715), (0.084, 0.0352), and (0.106, 0.0574), respectively.

D. The influences of the index of dielectric layer n on the PBGs of square and triangular cases

Fig.9 The features of PBGs varying with the n under different lattice arrangement, $h=a$, $N=2$ (a) square lattice, and (b) triangular lattice.

The influence of refractive index change on PBG is shown in Fig.9. In this discussion, $d=0.05 \times a$, $h=a$, $N=2$. The third PBG of the even modes, odd modes, and the mixed modes are exhibited in Fig.9(a). The PBGs of the mixed modes are almost determined by the even modes, which have the same maximum with the location of (3.5, 0.0583). The maximum width of the odd modes with a value of 0.1497 ($2\pi c/a$) is also reported at $n=3.5$. For the case of the triangular lattice layout, the 1st PBG of the even and odd modes will be discussed. When it comes to mixed modes, the 2nd PBG is considered. Similarly, the bandwidth of the odd modes obtained under the triangular lattice arrangement is still large, while the variation trend of the mixed modes is determined by the even modes. As illustrated in Fig.9(b), the maximum bandwidth of the odd modes is suited in (4.0, 0.1354). When $n=6.0$, the maximum bandwidth of the even modes is 0.0412 ($2\pi c/a$) and the maximum bandwidth of the mixed modes is 0.0332 ($2\pi c/a$).

3.2 Group velocity discussion of introducing line defects

The semiconductor processing technology is becoming more and more mature. In this paper, GaAs is selected as the material to make waveguides. The lattice constants $a=1 \mu\text{m}$, $N=3$, $d=0.05 \times a=0.05 \mu\text{m}$, $\lambda=1 \times a=1 \mu\text{m}$. At this wavelength, the refractive index of GaAs is 3.509. The height $h=2 \times a=2 \mu\text{m}$ in the square lattice arrangement and $h=1.5 \times a=1.5 \mu\text{m}$ in the triangular lattice form. As the above parameters are set, we find a PBG among 0.3462-0.3657 ($2\pi c/a$) in the case of square lattice layout, and a PBG over 0.3629-0.3946 ($2\pi c/a$) in the case of triangular lattice settlement. Line defects as shown in Fig.2(a) are introduced into the slab, and the values of D_x and D_z are changed to calculate the group velocity of the guided modes.

Fig.10 (a) The guided modes of waveguide in a square lattice arrangement, (b) the group velocity for square lattice arrangement, (c) the guided modes of waveguide in a triangular lattice arrangement, (d) the group velocity for triangular lattice arrangement.

In the case of the square lattice layout, the slow light with the minimum peak value of $0.072 \times c$ in the waveguide is achieved, and the corresponding normalized frequency is $0.352 (2\pi c/a)$, where $Dx=0.5 \times a=0.5 \mu\text{m}$, $Dz=0.7 \times a=0.7 \mu\text{m}$.

If $Dx=Dz=0.6 \times a=0.6 \mu\text{m}$, the peak value of the v_g is $0.078 \times c$ with the normalized frequency is $0.349 (2\pi c/a)$. At the normalized frequency $0.359 (2\pi c/a)$, the peak value of $0.119 \times c$ is observed with $Dx=Dz=0.6 \times a=0.9 \mu\text{m}$. At the case of $Dx=Dz=0.6 \times a=0.8 \mu\text{m}$, the peak value is located in $(0.348, 0.118)$, and when $Dx=0.5 \times a=0.5 \mu\text{m}$, $Dz=0.7 \times a=0.8 \mu\text{m}$, the peak value of $0.19 \times c$ will come into being with the location of $0.352 (2\pi c/a)$.

Because of the existence of the light cone, the starting point of the guided modes of the planar waveguide is not at the boundary of the Brillouin zone, so the group velocities of the guided modes do not always arise from 0. Since the position of the guided mode appears close to $M=(\pi/a, 0)$ and is approaching the Brillouin zone boundary, the group velocities of the most guided modes are maximized at the beginning and then gradually die down.

The triangular lattice is more beneficial for slowing the speed of the light than the case of the square lattice. The minimum group velocity peak value of $0.026 \times c$ is acquired at the normalized frequency of $0.372 (2\pi c/a)$, corresponding to $Dx=Dz=0.6 \times a=0.6 \mu\text{m}$. When $Dx=Dz=0.6 \times a=0.7 \mu\text{m}$ and $Dx=Dz=0.6 \times a=0.8 \mu\text{m}$, the peak value

of the v_g is suited in (0.367, 0.065) and (0.385, 0.084). In the context of $Dx=0.5 \times a=0.6 \mu\text{m}$, $Dz=0.7 \times a=0.8 \mu\text{m}$, the coordinates of peak value is (0.378, 0.088), and if $Dx=0.5 \times a=0.6 \mu\text{m}$ and $Dz=0.7 \times a=0.9 \mu\text{m}$, the peak value of the v_g is located in (0.372, 0.085).

Then, the FDTD method is used to analyze the distribution of the electric field in the waveguide. The waveguide is arranged in square lattice and the side length of the line defect column $Dx=Dz=0.6 \times a=0.6 \mu\text{m}$. The perfectly matched layers are used to be the boundary conditions. This high-loss material will absorb all electromagnetic waves without reflection [28-30]. In this model, the light incident at a frequency of 0.354 ($2\pi c/a$). Fig.10 illustrates the spatial distribution of the electric field component E_y . The width of the field source is the same as that of the waveguides in the z -axis. We can see that the electromagnetic wave is well restricted around the defect column. And only the electromagnetic waves that propagate along the line defects in the waveguide can travel through the system, while light from other locations is reflected. This proves the practical value of the proposed waveguide.

Fig.11 The electric field distribution of the waveguide and the transmission curve.

4. Conclusion

In this paper, the one-dimensional cylindrical PCs are extended to the two-dimensional level, GaAs material is chosen to fabricate the structure, and the effects of different structural parameters and the variation of incident wavelength on the PBGs characteristics of 2D-PCS are discussed in details. The height, index, and thickness of the cylinder layer are compromised consideration, and the PBGs width will first augment and then reduce with the increase in the height index and thickness, and the PBGs will move to the low frequencies. In our model, the maximum bandwidth is obtained with a value of 0.1497 ($2\pi c/a$). Finally, the line defect is introduced into the slab to construct the W1 waveguide. In the case of square lattice arrangement, the minimum group velocity peak value is $0.072 \times c$, and in the case of triangular lattice layout, it is $0.026 \times c$. As it turns out, the triangular lattice arrangement is more suitable for slowing down the speed of light. The results of FDTD show that the defect mode can propagate well along the defect line.

References

- [1] E. Yablonovitch, "Inhibited Spontaneous Emission in Solid-State Physics and Electronics," *Physical Review Letters*, **58**(20):2059(1987).
- [2] S. John, "Strong localization of photons in certain disordered dielectric superlattices," *Physical Review Letters*, **58**(23):2486-2489(1987).
- [3] H. Takano, B. S. Song, T. Asano, S. Noda, "Highly efficient multi-channel drop filter in a two-dimensional hetero photonic crystal," *Applied Physics Letters*, **86**(24):2059(2005).
- [4] B. Ellis, M. A. Mayer, G. Shambat, T. Sarmiento, J. Vukovi, "Ultra-low Threshold electrically pumped quantum dot photonic crystal nanocavity laser," *Nature Photonics*, **5**(5):297-300(2011).
- [5] E. Chow, A. Grot, L. W. Mirkarimi, M. Sigalas, G. Girolami, "Ultracompact biochemical sensor built with two-dimensional photonic crystal microcavity," *Optics Letters*, **29**(10):1093-1095(2005).
- [6] S. McNab, N. Moll, Y. Vlasov, "Ultra-low loss photonic integrated circuit with membrane-type photonic crystal waveguides," *Optics Express*, **11**(22):2927-2939(2003).
- [7] B. Temelkuran, M. Bayindir, E. Ozbay, R. Biswas, M. M. Sigalas, G. Tuttle, K. M. Ho, "Photonic crystal-based resonant antenna with a very high directivity," *Journal of Applied Physics*, **87**(1):603-605(2000).
- [8] J. N. Winn, Y. Fink, S. Fan, J. D. Joannopoulos, "Omnidirectional reflection from a one-dimensional photonic crystal," *Optics Letters*, **23**(20):1573-5(1998).
- [9] S. Y. Lin, J. G. Fleming, D. L. Hetherington, B. K. Smith, R. Biswas, K. M. Ho, M. M. Sigalas, W. Zubrzycki, S. R. Kurtz, J. Bur, "A three-dimensional photonic crystal operating at infrared wavelengths," *Nature*, **394**(6690):251-253(1998).
- [10] E. Chow, S. Y. Lin, S. G. Johnson, P. R. Villeneuve, J. D. Joannopoulos, J. R. Wendt, G. A. Vawter, W. Zubrzycki, H. Hou, A. Alleman, "Three-dimensional control of light in a two-dimensional photonic crystal slab," *Nature*, **407**(6807):983-986(2000).
- [11] S. G. Johnson, S. Fan, P. R. Villeneuve, J. D. Joannopoulos, L. A. Kolodziejski, "Guided modes in photonic crystal slabs," *Physical Review B Condensed Matter*, **60**(8):5751-5758(1999).
- [12] S. Shi, C. Chen, D. W. Prather, "Revised plane wave method for dispersive material and its application to band structure calculations of photonic crystal slabs," *Applied Physics Letters*, **86**(4):211-232(2005).
- [13] I. S. Maksymov, L. F. Marsal, J. Pallarès, "Band structures in nonlinear photonic crystal slabs," *Optical & Quantum Electronics*, **37**:161-169(2005).
- [14] T. F. Khalkhali, B. Rezaei, A. S. Vala, M. Kalafi, "Investigation of the effect of noncircular scatterers on the band structure of anisotropic photonic crystal slabs," *Applied Optics*, **52**(16):3745-3752(2013).
- [15] D. Liu, H. Liu, Y. Gao, "Photonic band gaps in square photonic crystal slabs of core-shell-type dielectric nanorod heterostructures," *Solid State Communications*, **172**:10-14(2013).
- [16] T. Erdogan, D. G. Hall, "Circularly Symmetric Distributed Feedback Laser: Coupled Mode Treatment of TEVector Fields," *IEEE Journal of Quantum Electronics*, **28**(3):612-623(1992).
- [17] E. X. Ping, "Transmission of electromagnetic waves in planar, cylindrical, and spherical dielectric layer systems and their applications", *Journal of Applied Physics*, **76**(11):7188-7194(1994).
- [18] M. S. Chen, C. J. Wu, T. J. Yang, "Wave properties of an annular periodic multilayer structure containing the single-negative materials," *Physics Letters A*, **373**(39):3594-3600(2009).
- [19] M. S. Chen, C. J. Wu, T. J. Yang, "Optical properties of a superconducting annular periodic multilayer structure," *Solid State Communications*, **149**(43-44):1888-1893(2009).
- [20] S. P. Li, J. P. Zhu, X. D. Deng, T. T. Tang, "Multilayer dielectric cylindrical mirrors based on omnidirectional reflection from a one-dimensional photonic crystal," *Optics Communication*, **284**(24):5655-5661(2011).

- [21] A. Säynätjoki, M. Mulo, J. Ahopelto, H. Lipsanen, "Dispersion engineering of photonic crystal waveguides with ring-shaped holes," *Optics Express*, **15**(13):8323-8328(2007).
- [22] M. Mulo, A. Säynätjoki, S. Arpiainen, H. Lipsanen, J. Ahopelto, "Slow light propagation in photonic crystal waveguides with ring-shaped holes," *Journal of Optics A Pure & Applied Optics*, **9**(9): S415(2007).
- [23] K. Kiyota, T. Kise, N. Yokouchi, T. Ide, T. Baba, "Various low group velocity effects in photonic crystal line defect waveguides and their demonstration by laser oscillation," *Applied Physics Letters*, **88**(20):201904(2006).
- [24] T. F. Krauss, "Slow light in photonic crystal waveguides," *Journal of Physics D Applied Physics*, **40**(9):2666(2007).
- [25] V. Kuzmiak, A. A. Maradudin, "Photonic band structures of one- and two-dimensional periodic systems with metallic components in the presence of dissipation," *Physical Review B*, **55**(12):7427-7444(1997).
- [26] H. Gersen, T. J. Karle, R. J. P. Engelen, W. Bogaerts, J. P. Korterik, N. F. V. Hulst, T. F. Krauss, L. Kuipers, "Real-Space Observation of Ultraslow Light in Photonic Crystal Waveguide," *Physical Review Letters*, **94**(7):073903(2005).
- [27] J. Li, T. P. White, L. O'Faolain, A. Gomez-Iglesias, T. F. Krauss, "Systematic design of flat band slow light in photonic crystal waveguides," *Optics Express*, **16**(9):6227-32(2008).
- [28] Q. Chen, M. Katsurai, P. H. Aoyagi, "An FDTD formulation for dispersive media using a current density," *Antennas & Propagation IEEE Transactions on*, **46**(11):1739-1746(1998).
- [29] J. P. Berenger, "Improved PML for the FDTD solution of wave-structure interaction problems," *Antennas & Propagation IEEE Transactions on*, **45**(3):466-473(1997).
- [30] S. Shi, C. Chen, D. W. Prather, "Plane-wave expansion method for calculating band structure of photonic crystal slabs with perfectly matched layers," *Journal of the Optical Society of America A*, **21**(9):1769-1775(2004).