GAMP-SBL Based Channel Estimation for Millimeter-Wave MIMO Systems

Jianfeng Shao

Hainan University

Xianpeng Wang (✉ wxpeng1986@126.com)

Hainan University

Xiang Lan

Hainan University <https://orcid.org/0000-0002-4769-3639>

Zhiguang Han

Hainan University

Ting Su

Hainan University

Research Article

Keywords: Channel estimation, mmWave MIMO, sparse Bayesian learning (SBL), DGAMP

Posted Date: July 6th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-637648/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

RESEARCH

GAMP-SBL Based Channel Estimation for Millimeter-Wave MIMO Systems

Jianfeng Shao, Xianpeng Wang*, Xiang Lan*, Zhiguang Han and Ting Su

*Correspondence:

wxpeng1986@126.com;

xlan@hainanu.edu.cn

College of Information and
Communication Engineering,
University of Hainan, Haikou,
China

Full list of author information is
available at the end of the article

Abstract

Based on the finite scattering characters of the millimeter-wave multiple-input multiple-output (mmWave MIMO) channel, the mmWave channel estimation problem can be considered as a sparse signal recovery problem. However, most traditional channel estimation methods depend on grid search, which may lead to considerable precision loss. To improve the channel estimation accuracy, we propose a high-precision two-stage millimeter-wave MIMO system channel estimation algorithm. Since the traditional expectation-maximization based sparse Bayesian learning (EM-SBL) algorithm can be applied to handle this problem, however, it spends lots of time to calculate the E-step which needs to compute the inversion of a high dimensional matrix. To avoid the high computation of matrix inversion, we combine damp generalized approximate message passing (DGAMP) with the E-step in SBL. We then improve a refined algorithm to handle the dictionary matrix mismatching problem in sparse representation. Numerical simulations show that the estimation time of the proposed algorithm is greatly reduced compared with the traditional SBL algorithm and better estimation performance is obtained at the same time.

Keywords: Channel estimation; mmWave MIMO; sparse Bayesian learning (SBL); DGAMP

1 Introduction

In the 5G cellular communication, millimeter wave (mmWave) has been drawing enormous attention from academia, colleges and governments due to the wide available spectrum [1, 2]. However, challenges also exist in the application of mmWave [3, 4]. With frequency increasing, various attenuation losses of the mmWave channel, for example the path loss and shadowing effects, become more hostile. One solution to the power loss problem in the channel is to use large MIMO antennas. For both the base station and the mobile station, large antennas are equipped to get transceiver powerful communication. However, another challenge is that the conventional training overhead for the channel state information (CSI) acquisition grows proportionally with the BS and MS antenna size. Fortunately, the massive MIMO system has a high correlation due to the finite number of scatters in the propagation path, so that the effective dimension is much less than the actual dimension [5]. Hence, with the uniform linear array (ULA) assumption, the mmWave channel can be approximately transformed into the sparse representation under the discrete Fourier transform (DFT) basis when large scale antennas are equipped [6–8]. Compressive Sensing (CS) theory was developed by Candes *et al* [9] and Donoho [10] which can be very useful when signals are sparse or compressible. Exploiting

such hidden sparsity, several algorithms have been presented in [5] and [11–13]. The above methods contribute to achieving a significant reduction of the training overhead. However, there are still some limits in the algorithms. For example, in the expectation-maximization (EM) sparse Bayesian learning algorithm, the computation complexity increases exponentially with the signal dimension [14], which may meet great challenges in practical implementations. Another generally existed problem is that, although the sparse algorithms can achieve super estimation performance for sparse signals, there also exists a grid mismatch issue. Some super-resolution (off-grid) compressed sensing methods and two-stage channel estimation algorithms have been applied to improve channel estimation accuracy [14–20], which aim to overcome the grid mismatch caused by conventional compressed sensing techniques. However, the super-resolution dictionary learning algorithm has two main shortcomings: the convergence of the results cannot be guaranteed; a large amount of prior training is required for the sparse dictionary. These two shortcomings limit the practical design and implementation.

In this paper, we adopt a two-step algorithm. The first step is coarse channel estimate by the SBL algorithm, which simplifies operations using DGAMP. The second step is an accurate angle estimate by the interpolation of three 2-DFT spectral lines. The following summarizes the contributions of this paper.

- We formulate a sparse recovery problem and develop a DGAMP-SBL algorithm for coarse estimation channel of the hybrid MIMO system. Based on the algorithm, we accelerate the computation speed of the original EM sparse Bayesian learning algorithm for mmWave channel estimation. The computation complexity shows that we significantly reduce operation time comparing to the original SBL algorithm with large scale transmission and reception antennas.
- To address the sparse reconstruction based channel estimation schemes suffering from grid-off problem, we improve a fast refined algorithm without iteration. In the discrete Fourier transform domain, the influence of Gaussian noise decreases with the increasing antenna number, which helps to obtain a more accurate angle estimation.

The rest of the paper is organized as follows. The system and channel model are discussed in Section II. We formulate the sparse recovery based channel estimation with the proposed DGAMP-SBL algorithm and get more accurate channel estimation using a refined algorithm in Section III. The performance of the proposed algorithm is compared with that of the existing algorithms, and the superiority of the proposed algorithm is concluded in IV. At the end of the paper, a conclusion is given in Section V.

Notations: In the following paper, the italic bold lowercase letters denote a vector and the italic bold uppercase letters denote a matrix. Superscript $[\cdot]^*$ denotes the conjugate, superscript $[\cdot]^H$ denotes the conjugate transpose, superscript $[\cdot]^T$ denotes the transpose, superscript $[\cdot]^{-1}$ denotes the inverse. $\|\mathbf{X}\|_F$ and $\|\mathbf{x}\|_2$ are the Frobenius norm of $\mathbf{X}$ and l_2 norm of $\mathbf{x}$, respectively. $\otimes$ denotes the Kronecker product and $\odot$ denotes Khatri-Rao product. $\text{diag}(\mathbf{x})$ is a diagonal matrix with elements of $\mathbf{x}$ on its diagonal and $\text{diag}(\mathbf{X})$ denotes a block diagonal matrix with subblocks of $\mathbf{X}$ on its block diagonal if $\mathbf{X}$ is made up of multiple subblocks. $\text{vec}(\mathbf{X})$ denotes

the vectorization operation of $\mathbf{X}$. $\text{vecd}(\mathbf{X})$ denotes the vectorization operation of $\text{diag}(\mathbf{X})$. $\text{Re}\{\cdot\}$ and $\text{Im}\{\cdot\}$ denote the real part and imaginary part of the corresponding arguments, respectively. The expectation and determinant operators are denoted by $E(\cdot)$ and $\det(\cdot)$, respectively.

2 METHOD

In this section, an off-grid channel model is implied for sparse representation of massive mmWave MIMO systems, and was propose a computationally efficient and accurate mmwave channel estimation algorithm. Generalized approximate message passing (GAMP) is an extension of the approximate message passing algorithm [21] to more comprehensive scenarios involving arbitrary priors and observation noise [22]. We use a GAMP based low complexity SBL algorithm to avoid the high dimension matrix inversion. This algorithm can be embedded in the expectation-maximization (EM) framework to provide an approximation of the true posterior distribution of sparse. Then we improve a fast refined algorithm which utilizes the interpolation of three 2-DFT spectral lines to improve the accuracy of the algorithm. Significantly, the improved algorithm can get accurate angles of departures/arrivals (AoAs/AoDs) estimation without iterations. Consequently, we can obtain both computational efficiency and estimation precision. Finally, the lower bound of normalized mean square error of the proposed algorithm is derived analytically: the lower bound of estimation is derived by the least square (LS) algorithm with the assumption that the angles of AoAs/AoDs are known. And then, we estimate the channel by using the LS algorithm. The result indicates our proposed algorithm is close to the lower-bound at high signal-to-noise ratios.

3 SYSTEM MODEL

In this paper, we consider a typical hybrid mmWave MIMO systems consisting of a BS and a MS, where the BS and MS are equipped with N_t and N_r antennas, respectively. Let N_t^{RF} and N_r^{RF} be the number of transmitter RF chain and receiver RF chain, respectively. We consider a hybrid analog-digital communication system that has inherent sparse characteristics as shown in Fig. 1. For mmWave massive MIMO with hybrid precoding, the amount of RF chains is far less than the amount of antennas, i.e., $N_t^{RF} < N_t$, $N_r^{RF} < N_r$ [23–25]. We assume that $\mathbf{F} = \mathbf{F}_{RF}\mathbf{F}_{BB}$ is the $N_t \times N_s^t$ hybrid precoding matrix in BS, where $\mathbf{F}_{RF} \in \mathbb{C}^{N_t \times N_t^{RF}}$ and $\mathbf{F}_{BB} \in \mathbb{C}^{N_t^{RF} \times N_s^t}$ denote the analog and digital precoders, respectively. $\mathbf{W} = \mathbf{W}_{RF}\mathbf{W}_{BB} \in$

$\mathbb{C}^{N_r \times N_s^r}$ is the hybrid combiner. $\mathbf{W}_{RF} \in \mathbb{C}^{N_r \times N_r^{RF}}$ and $\mathbf{W}_{BB} \in \mathbb{C}^{N_r^{RF} \times N_s^r}$ denote the analog and digital combiners, respectively, and the received signal $\mathbf{r} \in \mathbb{C}^{N_s^r \times 1}$ can be rewritten as

$$\begin{aligned} \mathbf{r} &= \mathbf{W}_{BB}^H \mathbf{W}_{RF}^H \mathbf{H} \mathbf{F}_{RF} \mathbf{F}_{BB} \mathbf{s} + \mathbf{W}_{BB}^H \mathbf{W}_{RF}^H \mathbf{n} \\ &= \mathbf{W}^H \mathbf{H} \mathbf{F} \mathbf{s} + \mathbf{W}^H \mathbf{n} \end{aligned} \quad (1)$$

where $\mathbf{r} \in \mathbb{C}^{N_s^r \times 1}$ is the received vector, $\mathbf{H} \in \mathbb{C}^{N_r \times N_t}$ is the channel matrix, $\mathbf{s} \in \mathbb{C}^{N_s^t \times 1}$ and $\mathbf{n} \in \mathbb{C}^{N_s^r \times 1}$ is the Gaussian noise matrix.

Using $\mathbf{x} = \mathbf{F} \mathbf{s} \in \mathbb{C}^{N_t \times 1}$ to denote the transmit signal, and the transmit vector elements correspond to the transmit antennas position. Firstly the channel estimation is considered in M time slots, and the channel matrix remains unchanged during the M time slots. N_x ($N_x < N_t$) pilot sequences $\mathbf{x}_1, \mathbf{x}_2, \dots, \mathbf{x}_{N_x}$ are sent by transmitters, and we also use N_y dimensional received pilot $\mathbf{y}_p$ by receiving antennas for each transmits pilot sequence $\mathbf{x}_p$ ($1 \leq p \leq N_x$)

$$\mathbf{y}_p = \mathbf{W}_r^H \mathbf{H} \mathbf{x}_p + \mathbf{W}_r^H \mathbf{n}_p \quad (2)$$

Where $\mathbf{W}_r = [\mathbf{W}_1, \mathbf{W}_2, \dots, \mathbf{W}_M] \in \mathbb{C}^{N_r \times N_y}$, $\mathbf{n}_p \in \mathbb{C}^{N_y \times 1}$ is the noise. Denote $\mathbf{Y} = [\mathbf{y}_1, \mathbf{y}_2, \dots, \mathbf{y}_{N_x}]$, $\mathbf{X} = [\mathbf{x}_1, \mathbf{x}_2, \dots, \mathbf{x}_{N_x}]$, $\mathbf{N} = [\mathbf{n}_1, \mathbf{n}_2, \dots, \mathbf{n}_{N_x}]$, we have

$$\mathbf{Y} = \mathbf{W}_r^H \mathbf{H} \mathbf{X} + \widehat{\mathbf{N}}, \quad (3)$$

where $\widehat{\mathbf{N}} = \mathbf{W}_r^H \mathbf{N}$ and $\mathbf{N}$ represents the noise matrix with each entry following the distribution $\mathcal{CN}(0, \sigma_n^2)$. In this paper, we suppose that the matrices $\mathbf{W}_r$ and $\mathbf{X}$ are known as prior knowledge at the receiver without loss of generality. For the sake of simplicity, the entries in $\mathbf{W}_r$ and $\mathbf{X}$ are optimally chosen from the set $w_{i,j} = \sqrt{1/N_t} e^{jw_{i,j}}$, $x_{i,j} = \sqrt{\rho/N_t} e^{jw_{i,j}}$ which is mentioned in [16]. This assumption is also employed in [26, 27]. Further details of how to design $\mathbf{W}_r$ and $\mathbf{X}$ can be found from [28].

It is not available to observe $\mathbf{H}$ directly. Instead, a noisy edition $\mathbf{W}_r^H \mathbf{H} \mathbf{X}$ can be observed from the receiver. This is referred to as the channel subspace sampling and a detailed analysis can be found in [29, 30]. Fortunately, as mentioned above, the channel estimation problem can be solved as a sparse signal recovery. The typical model of mmWave channel is modeled as [31]

$$\mathbf{H} = \sum_{l=1}^{\tilde{L}} \alpha_l \mathbf{a}_r(\theta_l) \mathbf{a}_t^H(\phi_l) \quad (4)$$

where $\tilde{L}$ denotes the number of communication paths. There are usually a few reflected path clusters in mmWave multipath propagation channel [26–28]. Therefore, we usually have $\tilde{L} \ll \min\{N_r, N_t\}$. α_l is the complex-valued gain corresponding to the l -th communication path. $\theta_l \in [-\pi, \pi]$ and $\phi_l \in [-\pi, \pi]$ are the corresponding azimuth AoAs and AoDs [32–34] respectively, and $\mathbf{a}_r \in \mathbb{C}^{N_r \times 1}$ ($\mathbf{a}_t \in \mathbb{C}^{N_t \times 1}$) is the array response vector corresponding to the receiver (transmitter).

In this paper, we employ ULA both at the transmitter and the receiver. Then the steering vectors at the BS and MS can be written as

$$\mathbf{a}_r(\theta_l) = \left[1, e^{-j2\pi \frac{d}{\lambda} \sin(\theta_l)}, \dots, e^{-j2\pi \frac{(N_r-1)d}{\lambda} \sin(\theta_l)}\right]^T \quad (5)$$

$$\mathbf{a}_t(\phi_l) = \left[1, e^{-j2\pi \frac{d}{\lambda} \sin(\phi_l)}, \dots, e^{-j2\pi \frac{(N_t-1)d}{\lambda} \sin(\phi_l)}\right]^T \quad (6)$$

where λ is the signal wavelength and d denotes the spacing between every two adjacent antenna elements with $d = \lambda/2$. For convenience, each scatterer is assumed to possess a transmission path, and the channel gains are modeled as independent identically distributed random variables with the distribution $\mathcal{CN}(0, \sigma_\alpha^2)$. By defining the steering matrices $\mathbf{\Phi}_r = [\mathbf{a}_r(\theta_1), \dots, \mathbf{a}_r(\theta_{\tilde{L}})] \in \mathbb{C}^{N_r \times \tilde{L}}$, $\mathbf{\Phi}_t = [\mathbf{a}_t(\phi_1), \dots, \mathbf{a}_t(\phi_{\tilde{L}})] \in \mathbb{C}^{N_t \times \tilde{L}}$ in a matrix form, the mmWave channel matrix $\mathbf{H}$ in (4) can be rewritten in a matrix form as follow

$$\mathbf{H} = \mathbf{\Phi}_r \mathbf{H}_v \mathbf{\Phi}_t^H \quad (7)$$

where $\mathbf{H}_v$ is a diagonal matrix with diagonal elements $\boldsymbol{\alpha} = [\alpha_1, \dots, \alpha_{\tilde{L}}]^T$. To transform the signal estimation problem into the sparse recovery problem, we firstly express the channel in a sparse matrix form

$$\mathbf{H} = \mathbf{A}_r \mathbf{C} \mathbf{A}_t^H \quad (8)$$

where both $\mathbf{A}_r \triangleq \frac{1}{\sqrt{N_r}} [\mathbf{a}_r(\psi_1) \dots \mathbf{a}_r(\psi_{N_1})] \in \mathbb{C}^{N_r \times N_1}$ and $\mathbf{A}_t \triangleq \frac{1}{\sqrt{N_t}} [\mathbf{a}_t(\omega_1) \dots \mathbf{a}_t(\omega_{N_2})] \in \mathbb{C}^{N_t \times N_2}$ are overcomplete beamforming matrices ($N_1 \geq N_r, N_2 \geq N_t$) which are assumed as channel-invariant unitary DFT matrices, and $\mathbf{A}_r \mathbf{A}_r^H = \mathbf{I}_{N_1}$, $\mathbf{A}_t \mathbf{A}_t^H = \mathbf{I}_{N_2}$, respectively. $\mathbf{C} \in \mathbb{C}^{N_1 \times N_2}$ is a sparse representation matrix of mmWave channel with the $\tilde{L}$ non-zero elements correspond to each scatterer under the condition that each AoA/AoD is defined in quantization grids. Note that the practical direction is usually invalid to locate on the predefined grids, so it is actually that the quantizing error exists in the sparse channel matrix. Hence a refined channel estimation scheme is given in the later sections to solve the off-grid problem. What is more, it is worth noting that $\mathbf{C}$ is no longer diagonal.

The signal model in (3) can be further denoted as follow

$$\begin{aligned} \mathbf{y} &= \sqrt{P} \text{vec}(\mathbf{W}_r^H \mathbf{H} \mathbf{X}) + \text{vec}(\hat{\mathbf{N}}) \\ &= \sqrt{P} (\mathbf{X}^T \otimes \mathbf{W}_r^H) \text{vec}(\mathbf{H}) + \hat{\mathbf{n}} \\ &= \sqrt{P} (\mathbf{X}^T \mathbf{A}_t^* \otimes \mathbf{W}_r^H \mathbf{A}_r) \mathbf{c} + \hat{\mathbf{n}} \end{aligned} \quad (9)$$

where $\mathbf{c} = \text{vec}(\mathbf{C})$, $\mathbf{y} = \text{vec}(\mathbf{Y}) \in \mathbb{C}^{N_x N_y \times 1}$ and $\hat{\mathbf{n}} = \text{vec}(\hat{\mathbf{N}})$. The estimation of $\mathbf{c}$ can be handled as a sparse signal recovery problem with 2D dictionary matrix $(\mathbf{A}_t^* \otimes \mathbf{A}_r)$, and the sensing matrix also can be denoted as $\mathbf{\Phi} = \mathbf{F}_t^T \mathbf{A}_t^* \otimes \mathbf{W}_r^H \mathbf{A}_r$. We consider the number of grids $N_1 = N_2$ for simplicity, and the channel estimation

problem can be summarized as compressed sensing problem as follow

$$\arg \min_{\mathbf{c}} \|\mathbf{c}\|_0 \quad \text{subject to} \left\| \mathbf{y} - \sqrt{P}\Phi\mathbf{c} \right\|_2 < \zeta \quad (10)$$

where ζ is a tolerance constant which is determined by noise power. Since recovery signal from l_0 -norm is a NP hard question, we replace the l_1 -norm with l_0 -norm as follow

$$\arg \min_{\mathbf{c}} \|\mathbf{c}\|_1 \quad \text{subject to} \left\| \mathbf{y} - \sqrt{P}\Phi\mathbf{c} \right\|_2 < \zeta \quad (11)$$

4 PROPOSED GAMP-SBL BASED HIGH PRECISION CHANNEL ESTIMATION

This section describes the proposed SBL scheme for sparse beamspace channel vector estimation. We begin by introducing the proposed hierarchical prior model. Then, we use the DGAMP-SBL to estimate the mmWave channel. After that, we propose a refined algorithm to get the accurate estimation of AoAs and AoDs. And then we propose a refined algorithm to accurately estimate the AoAs and AoDs. Finally, we analyze the computation complexity of the proposed algorithm, and make a comparison to the complexity of SBL.

4.1 HIERARCHICAL PRIOR MODEL

We have the follow results using the assumption of circular symmetric complex Gaussian noises

$$p(\mathbf{y}|\mathbf{c}, \lambda) = \mathcal{CN}(\mathbf{y}|\Phi\mathbf{c}, \lambda^{-1}\mathbf{I}) \quad (12)$$

where $\lambda = \sigma^{-2}$ stands for the noise precision. In order to leverage the sparse structure of the underlying mmWave channel, we enforce sparsity constraints on the channel vector which is commonly used in sparse bayesian model. The sparse channel vector $\mathbf{c}$ is assumed to follow a two hierarchical prior Gaussian distribution. In the first layer, $\mathbf{c}$ is assumed that the entries of $\mathbf{c}$ are independent and identically distributed, i.e.

$$p(\mathbf{c}|\boldsymbol{\gamma}) \sim \prod_{i=1}^{N_1 N_2} \mathcal{CN}(c_i; 0, \gamma_i^{-1}) \quad (13)$$

where γ_i denotes the inverse variance, and $\boldsymbol{\gamma} = [\gamma_1, \gamma_2, \dots, \gamma_{N_1 N_2}]$. Meanwhile, a Gamma prior is employed for the inverse variance vector

$$\begin{aligned} p(\boldsymbol{\gamma}) &= \prod_{i=1}^{N_1 N_2} \text{Gamma}(\gamma_i | a + 1, b) \\ &= \prod_{i=1}^{N_1 N_2} \Gamma^{-1}(a + 1) b^a \gamma_i^a e^{-b\gamma_i} \end{aligned} \quad (14)$$

where a, b are parameters associated with the above distribution, and $\Gamma(a) = \int_0^\infty t^{a-1} e^{-t}$ is the Gamma function. Besides, $\hat{\mathbf{n}}$ is Gaussian noise with zero mean and

covariance matrix $(1/\lambda) \mathbf{I}$. We set a Gamma hyperprior over λ : $p(\lambda) = \text{Gamma}(\lambda \mid c + 1, d) = \Gamma(c + 1)^{-1} d^{(c+1)} \lambda^c e^{-d\lambda}$.

To obtain a broad hyperprior, we set $a, b \rightarrow 0$ [35, 36]. This two-stage hierarchical prior gives

$$p(c_i) = \int_0^\infty p(c_i \mid \gamma_i^{-1}) p(\gamma_i) d\gamma_i \quad (15)$$

which is helpful to obtain sparse solutions due to the sharp peak and heavy tails with small a and b . Actually, according to paper [37], the maximum posterior estimation of $\mathbf{c}$ is consistent with l_0 -norm solution in formula (10) by FOCUSS with $p \rightarrow 0$. To update the parameter $\boldsymbol{\theta} = \{\gamma, \lambda\}$, we can also use maximum posteriori estimation to achieve the most probable values, i.e.,

$$(\gamma^*, \lambda^*) = \arg \max_{\gamma, \lambda} p(\gamma, \lambda \mid \mathbf{y}) \quad (16)$$

Or, equivalently,

$$(\gamma^*, \lambda^*) = \arg \max_{\gamma, \lambda} \ln p(\gamma, \lambda, \mathbf{y}) \quad (17)$$

Then the EM-SBL algorithm is employed to learn the sparse vector $\mathbf{c}$ and iteratively update the hyper-parameters $\boldsymbol{\theta} = \{\gamma, \lambda\}$. Note that the key step is to update the hyper-parameters $p(\gamma, \lambda \mid \mathbf{y})$ by maximizing the posterior probability when the EM-SBL is in the updating phase. And in the stage of E-step, the likelihood function can be written as follow

$$p(\mathbf{y} \mid \mathbf{c}; \sigma^2) = \frac{1}{(2\pi\sigma^2)^{N_x N_y}} \exp \left(-\frac{1}{2\sigma^2} \|\mathbf{y} - \Phi \mathbf{c}^2\| \right) \quad (18)$$

As noted before, the conditional density $p(\mathbf{c} \mid \mathbf{r})$ shows $\mathbf{c}$ is Gaussian distribution. When we treat $\mathbf{c}$ as a hidden variable, its posterior distribution we need to compute conditioned on the observed vector $\mathbf{y}$ and the updated hyper-parameters $\boldsymbol{\theta}$ is a complex Gaussian [35] function

$$\begin{aligned} p(\mathbf{c} \mid \mathbf{y}, \gamma^{(t)}, \lambda^{(t)}) &= \frac{p(\mathbf{c} \mid \gamma^{(t)}) p(\mathbf{y} \mid \mathbf{c}, \lambda^{(t)})}{p(\mathbf{y} \mid \gamma^{(t)}, \lambda^{(t)})} \\ &= (2\pi)^{-\frac{(N_1 N_2 + 1)}{2}} |\boldsymbol{\Sigma}_c|^{-\frac{1}{2}} \exp \left\{ -\frac{1}{2} (\mathbf{c} - \boldsymbol{\mu}_c)^T \boldsymbol{\Sigma}^{-1} (\mathbf{c} - \boldsymbol{\mu}_c) \right\} \end{aligned} \quad (19)$$

Where the posterior covariance $\boldsymbol{\Sigma}_c$ and mean $\boldsymbol{\mu}_c$ are given respectively

$$\begin{aligned} \boldsymbol{\Sigma}_c &= (\lambda \Phi^T \Phi + \mathbf{D})^{-1} \\ \boldsymbol{\mu}_c &= \lambda \boldsymbol{\Sigma} \Phi^T \mathbf{y} \end{aligned} \quad (20)$$

where $\mathbf{D} = \text{diag}(\gamma_0, \gamma_1, \dots, \gamma_{N_1 N_2})$, $\boldsymbol{\Sigma}_c$ and $\boldsymbol{\mu}_c$ are the posterior mean and variance with relevant for $p(\mathbf{c} \mid \mathbf{y}, \gamma^{(t)}, \lambda^{(t)})$, respectively. We assume that $\boldsymbol{\tau}_c$ is the vector whose elements are composed of the diagonal of the covariance matrix $\boldsymbol{\Sigma}_c$. As

mentioned above, in the EM algorithm iterative process, the hyper-parameters are updated by iteratively maximizing the R -function, i.e.

$$\begin{aligned}\boldsymbol{\theta}^{(t+1)} &\triangleq \arg \max_{\boldsymbol{\theta}} R(\boldsymbol{\theta}|\boldsymbol{\theta}^{(t)}) \\ &\triangleq \arg \max_{\boldsymbol{\theta}} E_{\mathbf{c}|\mathbf{y},\boldsymbol{\theta}^{(t)}} [\log p(\boldsymbol{\theta}|\mathbf{c}, \mathbf{y})]\end{aligned}\quad (21)$$

Using Bayesian rule, (21) can be rewritten by ignoring part unrelated to $\boldsymbol{\theta}$ as follow

$$\begin{aligned}E_{\mathbf{c}|\mathbf{y};\boldsymbol{\gamma}^t,\lambda} [\log p(\boldsymbol{\gamma}^t, \lambda|\mathbf{c}, \mathbf{y})] = \\ E_{\mathbf{c}|\mathbf{y};\boldsymbol{\gamma}^t,\lambda} [-\log p(\mathbf{y}|\mathbf{c}; \lambda) - \log p(\mathbf{c}|\boldsymbol{\gamma}) - \log p(\boldsymbol{\gamma})]\end{aligned}\quad (22)$$

Firstly the algorithm carries out the M-step for the hyperparameters $\{\gamma_n\}$. We take the partial derivative of the R-function with respect to γ_n with eliminating independent terms. Since the first term in (22) does not depend on $\boldsymbol{\gamma}$, it can be ignored as it will not be relevant for the M-Step. The objective function in (22) becomes

$$\begin{aligned}E_{\mathbf{c}|\mathbf{y},\boldsymbol{\theta}^{(t)}} [\log p(\boldsymbol{\theta}|\mathbf{c}, \mathbf{y})] \\ = E_{\mathbf{c}|\mathbf{y},\boldsymbol{\theta}^{(t)}} [-\log p(\mathbf{c}|\boldsymbol{\gamma}) - \log p(\boldsymbol{\gamma})] \\ = \sum_{n=1}^{N_1 N_2} \left(\frac{\gamma_n (\hat{c}_n^2 + \tau_{c_n})}{2} - \frac{1}{2} \log \gamma_n + \log p(\gamma_n) \right) \\ = \sum_{n=1}^{N_1 N_2} \left(\left(\frac{\gamma_n (\hat{c}_n^2 + \tau_{c_n})}{2} - \frac{1}{2} \log \gamma_n + a \log \gamma_n - b \gamma_n \right) \right)\end{aligned}\quad (23)$$

We take the partial derivative of the R-function with respect to γ_n with eliminating independent terms, and the iteration of γ_n can be denoted by

$$\gamma_n^{i+1} = \arg \min_{\gamma_n} \left(\frac{\gamma_n (\hat{c}_n^2 + \tau_{c_n})}{2} + \log p(\gamma_n) - \frac{1}{2} \log \gamma_n \right) \quad (24)$$

According to the hyperprior $p(\gamma_n)$ which possesses a non-informative when the parameter a and b tend to zero, we can simplify the update formalization as

$$\gamma_n^{i+1} = \frac{1}{\hat{c}_n^2 + \tau_{c_n}} \quad (25)$$

Similarly, we then compute the estimation of the scalar hyper-parameter λ and it can be updated as

$$\begin{aligned}\lambda^{i+1} &= \arg \max_{\lambda} E_{\mathbf{c}|\mathbf{y},\boldsymbol{\gamma};\lambda} [p(\mathbf{y}, \mathbf{c}, \boldsymbol{\gamma}; \lambda)] \\ &= \frac{\|\mathbf{y} - \boldsymbol{\Phi} \mathbf{c}\|^2 + (\lambda)^i \sum_{n=1}^{N_1 N_2} (1 - \frac{\tau_{c_n}}{\gamma_n})}{N}\end{aligned}\quad (26)$$

where $N = N_x N_y$ represents the dimension of $\mathbf{y}$. Accord to the references and practical implementation tips, we can consistently set the constant as follows: $a = b = c = d = 0.0001$, since the result of constant initialization has little effect on estimation performance.

4.2 Update by DGAMP

As mentioned earlier, it is obvious that the calculation of the posterior mean and posterior variance which involve the inversion of high dimensional matrices is very large. Hence, the high computational complexity characteristic of the EM-SBL algorithm causes that it is impractical to be adopted by the massive MIMO channel estimation. For the purpose of simplifying the calculation, we replace posterior calculation with the GAMP algorithm which is a very-low-complexity Bayesian iterative technique. It is noted that the hyper-parameters $\{\gamma, \lambda\}$ are considered as known constants during the iterative process of the GAMP algorithm.

GAMP is a fast heuristic algorithm and can be utilized for simplifying matrix inversion within the SBL framework [38, 39]. GAMP algorithm obtains the maximum posterior estimation of $\mathbf{c}$ by Taylor approximation. Specifically, the process of iteratively computing the marginal posterior $p(c_n | \mathbf{y}, \gamma, \lambda)$ is performed by message passing on the GAMP factor graph. By utilizing the condition that all posteriors are Gauss, the process can be simplified by replacing posterior probability with expectation and variance of the sparse variables $\{c_n\}$ and mixture variables $\{z_m\}$ whose elements are denoted by $\mathbf{z} = \Phi \mathbf{c}$. To detour the convergence of GAMP whose measurement matrix satisfies independent Gaussian distribution, paper [40] proposes a DGAMP algorithm to improve the robustness of the measurement matrix through importing damping factors $\rho_s, \rho_c \in (0, 1]$, but it will also slows down the convergence speed. Nevertheless, the process is computationally efficient since that it only contains scalar operations. Then we summarize the key steps of DGAMP in Algorithm 1. The readers can refer to [22] to learn more about details of the derivation of DGAMP.

There are two versions which are the max-sum version and sum-product versions damp-GAMP algorithm. The input and output functions $g_s(\mathbf{p}, \boldsymbol{\tau}_p)$ and output functions $g_x(\mathbf{r}, \boldsymbol{\tau}_r)$ in Algorithm 1 are distinguished according to whether the max-sum or the sum-product version of GAMP. Coincidentally, both the sum-product and max-sum version simplify the same equation. We only introduce the functions of the input and output about the sum-product, and readers can refer [41] to get further detail. The intermediate variables $\mathbf{r}$ and $\mathbf{p}$ are explained as approximations of Gaussian noise corrupted of $\mathbf{c}$ and $\mathbf{z} = \Phi \mathbf{c}$ with the noise levels of $\boldsymbol{\tau}_r$ and $\boldsymbol{\tau}_p$ respectively. The difference between the sum-product and max-sum version is the estimation strategy, and the sum-product version uses the vector MMSE estimation which is reduced to a sequence of scalar MMSE estimation. The input and output function are shown as follows

$$[g_s(\mathbf{p}, \boldsymbol{\tau}_p)]_m = \frac{\int z_m p(y_m | z_m) \mathcal{N}\left(z_m; \frac{p_m}{\tau_{pm}}, \frac{1}{\tau_{pm}}\right) dz_m}{\int p(y_m | z_m) \mathcal{N}\left(z_m; \frac{p_m}{\tau_{pm}}, \frac{1}{\tau_{pm}}\right) dz_m} \quad (27)$$

Algorithm 1 DGAMP-SBL Algorithm

```

1: Initialization
2:  $\mathbf{S} \leftarrow |\Phi^2|$ 
3: Initialize  $\tau_c^0, \gamma^0, \lambda^0 > 0$ 
4:  $\tilde{\mathbf{s}}, \tilde{\mathbf{c}} \leftarrow \mathbf{0}$ 
5: for  $i = 1, 2, \dots, I_{\max}$ 
6:  $\tau_c^1 \leftarrow \tilde{\tau}_c^{i-1}, \hat{\mathbf{c}}^1 \leftarrow \tilde{\mathbf{c}}^{i-1}, \mathbf{s}^1 \leftarrow \tilde{\mathbf{s}}^{i-1}$ 
7: E-Step
8: for  $k = 1, 2, \dots, K_{\max}$ 
9:  $1/\tau_p^k \leftarrow \mathbf{S} \tau_x^k$ 
10:  $\mathbf{p}^k \leftarrow \mathbf{s}^{k-1} + \tau_p^k \Phi \hat{\mathbf{c}}^k$ 
11:  $\tau_s^k \leftarrow \tau_p^k g'_s(\mathbf{p}^k, \tau_p^k)$ 
12:  $\mathbf{s}^k \leftarrow (1 - \theta_s) \mathbf{s}^{k-1} + \theta_s g_s(\mathbf{p}^k, \tau_p^k)$ 
13:  $1/\tau_r^k \leftarrow \mathbf{S}^T \tau_s^k$ 
14:  $\mathbf{r}^k \leftarrow \hat{\mathbf{c}}^k - \tau_r^k \Phi^T \mathbf{s}^k$ 
15:  $\tau_c^{k+1} \leftarrow \tau_r^k g'_c(\mathbf{r}^k, \tau_r^k)$ 
16:  $\hat{\mathbf{c}}^{k+1} \leftarrow (1 - \theta_x) \hat{\mathbf{c}}^k + \theta_x g_c(\mathbf{r}^k, \tau_r^k)$ 
17:  $\|\hat{\mathbf{c}}^{k+1} - \hat{\mathbf{c}}^k\|^2 / \|\hat{\mathbf{c}}^{k+1}\|^2 < \varepsilon_{gamp}$ 
18:  $\tilde{\mathbf{s}}^i \leftarrow \mathbf{s}^k, \tilde{\mathbf{c}}^i \leftarrow \hat{\mathbf{c}}^{k+1}, \tilde{\tau}_c^i \leftarrow \tau_c^{k+1}$ 
19: M-Step
20:  $\gamma^{i+1} \leftarrow \|\tilde{\mathbf{c}}^i\|^2 + \tilde{\tau}_c^i$ 
21:  $(\sigma^2)^{i+1} \leftarrow \frac{\|\mathbf{y} - \Phi \tilde{\mathbf{c}}^i\|^2 + \lambda^i \sum_{n=1}^N \left(1 - \frac{\tilde{\tau}_c^i}{\gamma_n^i}\right)}{M}$ 
22: if  $\|\tilde{\mathbf{c}}^i - \mathbf{c}^{i-1}\|^2 / \|\tilde{\mathbf{c}}^i\|^2 < \varepsilon_{em}, \text{break}$ 
23: end

```

$$[g_c(\mathbf{r}, \tau_r)]_n = \frac{\int c_n p(c_n) \mathcal{N}(c_n; r_n, \tau_{r_n}) dc_n}{\int p(c_n) \mathcal{N}(c_n; r_n, \tau_{r_n}) dc_n} \quad (28)$$

According to the (9)-(12) which are the prior information and the posterior information we imposed on $\mathbf{c}$ and $p(\mathbf{y}|\mathbf{c})$ respectively, the input function (25) and its derivative function can be rewritten as follow

$$g_c(\mathbf{r}, \tau_r) = \frac{\gamma}{\gamma + \tau_r} \mathbf{r} \quad (29)$$

$$g'_c(\mathbf{r}, \tau_r) = \frac{\gamma}{\gamma + \tau_r} \quad (30)$$

Similarly, the output functions and its derivative function can be rewritten as follow

$$g_s(\mathbf{p}, \tau_p) = \frac{(\mathbf{p}/\tau_p - \mathbf{y})}{(\lambda + 1/\tau_p)} \quad (31)$$

$$g'_s(\mathbf{p}, \tau_p) = \frac{\lambda^{-1}}{\lambda^{-1} + \tau_p} \quad (32)$$

Upon convergence, DGAMP-SBL yields a sparse estimate of $\mathbf{c}$ according to the prior information given by the posterior mean. This also gets a coarse estimate of the channel matrix, which can be represented by a paired frequency of AoAs and AoDs using multiplying the steering vectors. The initial channel estimate can be obtained as

$$\hat{\mathbf{H}}^{(0)} = \mathbf{A}_r \hat{\mathbf{C}} \mathbf{A}_t^H \quad (33)$$

where $\hat{\mathbf{C}}$ denote order by columns as $\mathbf{H}$.

It is worth noting that GAMP is a low complexity algorithm which transforms the vector estimation into the scalar estimation, therefore (27) (28) and the algorithm in the Algorithm 1, all vector squares, divisions and multiplications are taken element wise. The Fig. 2 represents sparse channel matrix based on discrete Fourier basis, and the Fig. 3 represents the SBL-GAMP algorithm estimation without considering the sparse off-grid problem when the number of grids are chosen as $N_1 = N_2 = 180$ for comparison.

4.3 Refined Estimation

In the following, we propose an exact and fast 2D frequency estimation method base on the interpolation of three 2-DFT spectral lines [42]. The SBL-DGAMP algorithm, represented by the frequency estimate $\hat{\mathbf{f}} = \{\hat{f}_1, \hat{f}_2, \dots, \hat{f}_{\tilde{L}}\}$ where the $\hat{f}_i = \{f_{i1}, f_{i2}\}$ ($i = 1, 2, \dots, \tilde{L}$), is only a coarse estimate due to grid mismatch.

For $(k, j) \in [(k_1, j_1), (k_2, j_2) \dots, (k_{\tilde{L}}, j_{\tilde{L}})]$ related to the corresponding index set of the coarse estimate frequency. And then we present a interpolation on Fractional Fourier Coefficient. The Fractional Fourier transform can be formulated as follows

$$D(k, j) = \sum_{m=0}^{N_r} \sum_{n=0}^{N_t} [\tilde{H}]_{n,m} e^{-j2\pi(im+kn)/N_{DFT}} \quad (34)$$

$$D(k \pm \delta, j) = \sum_{m=0}^{N_r} \sum_{n=0}^{N_t} [\tilde{H}]_{n,m} e^{-j2\pi(im + (k \pm \delta)n)/N_{DFT}} \quad (35)$$

$$D(k, \delta \pm j) = \sum_{m=0}^{N_r} \sum_{n=0}^{N_t} [\tilde{H}]_{n,m} e^{-j2\pi(i(m \pm \delta) + kn)/N_{DFT}} \quad (36)$$

where δ is a real number, and we formulate the $D(k, j)$, $D(k \pm \delta, j)$, $D(k, j \pm \delta)$ as D , $D_{K+\delta}$, $D_{K-\delta}$, $D_{J+\delta}$, $D_{J-\delta}$, respectively. Then we propose the interpolation algorithm as follow

$$\hat{\lambda}_x = \frac{N_r}{\pi} \tan^{-1} \left(\operatorname{Re} \left\{ \frac{(D_{K+\delta} E_r^+ - D_{K-\delta} E_r^-) \cdot \sin(\pi i / N_r)}{(D_{K+\delta} E_r^+ + D_{K-\delta} E_r^-) \cdot \cos(\pi i / N_r) - 2D \cos(\pi i)} \right\} \right) \quad (37)$$

$$\hat{\lambda}_y = \frac{N_t}{\pi} \tan^{-1} \left(\operatorname{Re} \left\{ \frac{(D_{J+\delta} E_t^+ - D_{J-\delta} E_t^-) \cdot \sin(\pi i / N_t)}{(D_{J+\delta} E_t^+ + D_{J-\delta} E_t^-) \cdot \cos(\pi i / N_t) - 2D \cos(\pi i)} \right\} \right) \quad (38)$$

where $\hat{\lambda}_x, \hat{\lambda}_y$ are frequency deviation normalized by grid distance Δf which is defined by $\Delta f = 1/(N_{DFT}/2)$.

And then we could get the frequency estimations that

$$\hat{f}_x = \begin{cases} -(\hat{\lambda}_x + k)/(N_{DFT}/2) & k < N_{DFT}/2 \\ 2 - (\hat{\lambda}_x + k)/(N_{DFT}/2) & k \geq N_{DFT}/2 \end{cases} \quad (39)$$

Algorithm 2 PROPOSED CHANNEL ESTIMATION SCHEME

First stage:Initialization:

- 1: Based on Algorithm 1, we use the DGAMP-SBL to obtain $\hat{c}$;
- 2: Use (31) to obtain the initial channel estimate $\hat{\mathbf{H}}^{(0)}$;

Second stage:Refine:

- 1: According to the coarse estimation $\hat{\mathbf{H}}^{(0)}$ to get the frequency initial $\hat{f} = \{\hat{f}_1, \hat{f}_2, \dots, \hat{f}_{\tilde{L}}\}$;
 - 2: Compute the 2DFT, update the frequency $\hat{f}_x$ and $\hat{f}_y$ using (37) and (38);
 - 3: Compute, recoder the final frequency θ_x^{fin} and θ_y^{fin} by (39), obtain the AoAs and AoDs $\{\hat{\theta}_l\}_{l=1}^{\tilde{L}}$ and $\{\hat{\phi}_l\}_{l=1}^{\tilde{L}}$;
 - 4: Runing (42) to obtain $\mathbf{h}_v$, and obtain $\hat{\mathbf{H}} = \Phi_r \text{diag}(\mathbf{h}_v) \Phi_t^H$;
 - 5: End
-

and

$$\hat{f}_y = \begin{cases} (\hat{\lambda}_y + j)/(N_{DFT}/2) & j < N_{DFT}/2 \\ -(2 - (\hat{\lambda}_y + j)/(N_{DFT}/2)) & j \geq N_{DFT}/2 \end{cases} \quad (40)$$

According to [43], in order to get a more accurate frequency estimate, we adopt a parabolic interpolation algorithm. For each frequency dimension $d \in \{x, y\}$, we calculate three periodogram sample D_{d1} , D_{d2} and D_{d3} at frequency $\theta_{d1} = \hat{f}_d - \Delta_d$, $\theta_{d2} = \hat{f}_d$ and $\theta_{d3} = \hat{f}_d + \Delta_d$. Middle frequency $\hat{f}_d$ given by (39) and (40), and the sides of frequency θ_{d1} and θ_{d3} are excused by Δ_d which is chosen to satisfy $\Delta_d \in (0, \frac{1}{2N_{DFT}})$, as well as high estimation accuracy. The last step of frequency estimation along the d -th dimension is achieved by calculating the vertex of a parabola fitted through points (θ_{d1}, D_{d1}) , (θ_{d2}, D_{d2}) and (θ_{d3}, D_{d3}) , i.e.

$$\theta_d^{fin} = \frac{1}{2} \frac{\theta_{d3}^2 (\Delta_{12}) + \theta_{d2}^2 (\Delta_{31}) + \theta_{d1}^2 (\Delta_{23})}{\theta_{d3} (\Delta_{12}) + \theta_{d2} (\Delta_{31}) + \theta_{d1} (\Delta_{23})} \quad (41)$$

where $d = x, y$, $\Delta_{12} = (D_{d1} - D_{d2})$, $\Delta_{31} = D_{d3} - D_{d1}$, $\Delta_{23} = D_{d2} - D_{d3}$. Eventually, according to (41) the final estimation frequency, the accurate angles AoAs and AoDs can be obtained, i.e. $\{\hat{\theta}_l\}_{l=1}^{\tilde{L}}$ and $\{\hat{\phi}_l\}_{l=1}^{\tilde{L}}$.

4.4 Reconstruct mmWave MIMO Channel

In this subsection, according to the obtained AoAs $\{\hat{\theta}_l\}_{l=1}^{\tilde{L}}$ and AoDs $\{\hat{\phi}_l\}_{l=1}^{\tilde{L}}$, the mmWave MIMO channel will be reconstructed as follow. Firstly, we recover the steering vectors $\mathbf{a}_r(\hat{\theta}_l)$ and $\mathbf{a}_t(\hat{\phi}_l)$ in (5) and (6) using the estimated AoAs and AoDs. Secondly, we rewrite the expression (6) as follow

$$\mathbf{H} = (\Phi_t^* \odot \Phi_r) \text{vecd}(\mathbf{H}_v) \quad (42)$$

Thus the receive signal also can be rewritten using vector form as follow

$$\begin{aligned} \mathbf{y} &= \sqrt{P} \mathbf{W}_r^H ((\Phi_t^* \odot \Phi_r) \text{vecd}(\mathbf{H}_v)) \mathbf{X} + \hat{\mathbf{n}} \\ &= \sqrt{P} (\mathbf{X}^T \Phi_t^* \odot \mathbf{W}_r^H \Phi_r) \mathbf{h}_v + \hat{\mathbf{n}} \\ &= \sqrt{P} \mathbf{Q}^o \mathbf{h}_v + \hat{\mathbf{n}} \end{aligned} \quad (43)$$

where $\mathbf{h}_v = \text{vecd}(\mathbf{H}_v)$, $\mathbf{Q}^o = \mathbf{X}^T \Phi_t^* \odot \mathbf{W}_r^H \Phi_r$. The estimator estimates $\mathbf{h}_v$ in the LS sense. From (35), the LS estimate of $\mathbf{h}_v$, denoted as $\hat{\mathbf{h}}_v$, is given as follow

$$\hat{\mathbf{h}}_v = \frac{1}{\sqrt{P}} \left((\mathbf{Q}^o)^H \mathbf{Q}^o \right)^{-1} (\mathbf{Q}^o)^H \mathbf{y} \quad (44)$$

Finally, according to the obtained exact angle estimation, and the gains of path $\hat{\mathbf{h}}_v$ above, we can recover the high-dimensional mmWave MIMO channel as $\hat{\mathbf{H}} = \Phi_r \text{diag}(\mathbf{h}_v) \Phi_t^H$.

4.5 Analysis of Computational Complexity

We will analyze the computational complexity. Apparently, the complexity of the DGAMP-SBL algorithm is dominated by the E-step, and the matrix multiplications is a big part of it which matrix multiplications by $\mathbf{S}$, $\mathbf{S}^T$, Φ and Φ^T at each iteration. The complexity of each iteration is $O(4 \cdot N_1 N_2 (N_x N_y))$, since we should convert the complex signal to real signal. It is worth noting that separate operations can reduce the Single time, so we also can neglect the coefficient 4. Nonetheless it is mentioned above that the multiplications operation in Algorithm 1 are taken element-wise, the complexity is much smaller than $O(N_1 N_2 (N_x N_y)^2)$, the complexity of sparse Bayesian learning iteration when the dimension of $N_x N_y$ is large. And the refined part does not need iteration, so the complex can be ignored.

5 Results and Discussion

In this section, we will prove the performance of the proposed algorithm superiority based channel estimation scheme through matlab simulation with the following parameters. The transmitter and the receiver are equipped with $N_r = N_t \in \{32, 64\}$, $N_{RF} = N_t^{RF} = N_r^{RF} = 2$, $N_x = N_y \in \{24, 32\}$ and $N_1 = N_2 = 120$. Each item of the transmitted pilots $\mathbf{X}$ is defined as $x_{i,j} = \sqrt{\rho/N_t} e^{jw_{i,j}}$, where ρ is the transmitted power, $w_{i,j}$ is the random phase uniformly distributed in $[0, 2\pi)$. The signal-to-noise (SNR) is defined by $\text{SNR} = \frac{\rho \sigma_s^2}{\sigma_n^2}$. We consider the ULA geometry, and we take the following algorithm as comparison algorithms, i.e. the OMP-based channel estimation [44], the iterative reweight (IR)-based superresolution channel estimation scheme [16], the Oracle estimator in [44] and the LS estimator. The normalized mean square error (NMSE) which is denoted as $E \left[\frac{\|\mathbf{H} - \hat{\mathbf{H}}\|_F^2}{\|\mathbf{H}\|_F^2} \right]$ is used for performance comparison. And the achievable spectral efficiency efficiency (ASE) can be defined as $\log_2 \left| \mathbf{I}_{N_{RF}} + \frac{P}{N_{RF}} \mathbf{R}_n^{-1} \tilde{\mathbf{W}}^H \mathbf{H} \tilde{\mathbf{F}} \tilde{\mathbf{F}}^H \mathbf{H}^H \tilde{\mathbf{W}} \right|$, for the channel estimation $\hat{\mathbf{H}}$. And $\tilde{\mathbf{F}}$ and $\tilde{\mathbf{W}}$ are defined as the optimal precoder and combiner, respectively which are designed via the singular value decomposition of $\hat{\mathbf{H}}$, denoted as $\hat{\mathbf{H}} = \hat{\mathbf{U}} \hat{\mathbf{\Sigma}} \hat{\mathbf{V}}^H$. Here the diagonal entries of the singular value matrix $\hat{\mathbf{\Sigma}}$ are arranged in decreasing order. $\tilde{\mathbf{F}}$ and $\tilde{\mathbf{W}}$ consist of the first N_{RF} columns of $\hat{\mathbf{V}}$ and $\hat{\mathbf{U}}$, respectively. The $\mathbf{R}_n$ can be defined as $\mathbf{R}_n \doteq \sigma^2 \tilde{\mathbf{W}}^H \tilde{\mathbf{W}}$. The results in this simulation are all obtained through 200 Monte Carlo experiments [45, 46].

Fig. 4 and Fig. 5 compare NMSE performance against SNR with $N_r = N_t = 32$, $N_x = 24$ and $N_r = N_t = 64$, $N_x = 32$, respectively. In both scenarios, it is apparent that the curves of the proposed algorithm are below that of comparing algorithms

Figure 4 NMSE performance comparison of different schemes against SNR, when $N_x = N_y = 32$, $N_t = N_r = 64$ are considered respectively.

Figure 5 NMSE performance comparison of different schemes against SNR, when $N_x = N_y = 24$, $N_t = N_r = 32$ are considered respectively.

under most circumstances. Comparison results indicate that the proposed scheme has remarkable performance improvement. Note that our proposed scheme almost coincides with the curve of Oracle in the condition of high SNR. Under the same SNR, our algorithm achieves a huge advantage, since our algorithm considers the off-grid influence which can estimate a more accurate angle. Through comparing Fig. 4, our proposed algorithm achieves a great advantage all of SNR. And with the increase of SNR, the advantage of our proposed algorithm performance over OMP becomes greater. Moreover, our proposed algorithm is superior to IR algorithm, and it almost coincides with the Oracle curve. The NMSE performance degrades in low SNR levels because the suffer noise interference exists. And under the low SNR, our proposed algorithm coarse estimation face a challenge which is brought by noise and off-grid, so the performance does not achieve the expectation. Although the number of antenna and pilot decline, our proposed algorithm still have superior performance. Taking the SNR of 10dB, 15dB, 20dB as an example, our proposed algorithm is also very close to the Oracle curve. It can be seen that the channel estimation accuracy

Figure 6 NMSE performance against the number of training beams when $N_y = 32$, $N_t = N_r = 64$ are considered respectively.

Figure 7 Running time against the number of grids when $N_y = 32$, $N_t = N_r = 64$ are considered respectively.

based on our proposed algorithm is better than that of comparing algorithm, which verifies the advantages of our proposed schemes. To summarize, the proposed scheme is superior to other scheme in channel estimation accuracy regardless of the antennas and pilots are more or less.

Fig. 6 compares the NMSE performance against the number of training beams when SNR=10dB, $N_t = N_r = 64$. As the number of training beams with N_x increases, the NMSE of all algorithms decrease monotonically. It is obvious that the comparing algorithm curves tend to decrease slowly. Even so, our proposed algorithm still achieves a huge advantage under different pilots. When the SNR is 10dB, our proposed algorithm achieves high estimation accuracy, and it is very close to the Oracle curve. And we have tested that our algorithm may get an accurate result when N_x is very small, but there exists a probability of failure comparing with high N_x . Again, among the comparing algorithm, the proposed algorithm still performs better outperforms than others.

Figure 8 NMSE performance against the number of grids when $N_x = N_y = 32$, $N_t = N_r = 64$ are considered respectively.

Figure 9 ASE performance against SNR when $N_x = N_y = 32$, $N_t = N_r = 64$, $N_r^{RF} = N_t^{RF} = 2$ are considered respectively.

Fig. 7 compares the difference in runtimes between the original SBL and the proposed scheme. In order to facilitate comparison, we fix the number of iterations 200 times. Note that although we apply 200 iterations, the algorithm convergence only needs 100 times and even less in most cases. It is obvious that the proposed algorithm needs much less time than the original SBL algorithm as the dimension increases, which suggests that the proposed algorithm is more practical for large-size sparse matrix recovery.

Fig. 8 shows the NMSE curves against the number of grids $N_1 = N_2$. The proposed algorithm outperforms the IR when $N_1 = N_2 \geq 100$. After the number of grids is greater than 100, the NMSE of the proposed algorithm is slightly down. The NMSEs of the sparse matrix algorithms monotonically decreases with the number of the grids increasing. It is interesting that the number of grids only need to set 120 to balance the complexity of the computation and the accuracy of estimation. For comparison, the NMSEs of the Oracle, LS and IR algorithms remain unchanged for different values of grids, since all of those work without grid.

Fig. 9 compares the ASE against SNR when different channel estimation schemes are used with $N_r = N_t = 64$, $N_x = 32$. We introduce a perfect CSI as a reference upper limit curve. It is noted that although the performance of our proposed algorithm is slightly worse than IR scheme at -5dB, the ASE curve of the proposed scheme almost overlap that of CSI for high SNR values.

6 CONCLUSION

In this paper, we have proposed a high-precision channel estimation scheme for mmWave massive MIMO with hybrid precoding. Specifically, a two-stage strategy is used to estimate the channel. In the first phase of the algorithm, the DGAMP-SBL which simplifies operations is used to coarsely estimate the mmWave MIMO channel. In the second phase of the algorithm, the previously obtained channel which considers off-grid error is refined by 2DFT-interpolation algorithm. Experimental results have indicated that the proposed high-precision channel estimation strategy can achieve better performance than the state-of-art in estimation precision. For future work, we focus on the sparse channel estimation 2D high dimension matrix reduction, since the sparse recovery problem still be limited by the 2D sparse dictionary matrix which has a huge matrix dimensions.

Abbreviations

EM-SBL: expectation-maximization sparse Bayesian learning; DGAMP: damp generalized approximate message passing; mmWave MIMO: millimeter-wave multiple-input multiple-output; SBL: sparse Bayesian learning; AoDs/AoAs: angles of departures/arrivals; CSI: channel state information; UL: uniform linear array; DFT: discrete Fourier transform; CS: Compressive Sensing; EM: expectation-maximization; GAMP: Generalized approximate message passing; LS: least square; IR: iterative reweight; NMSE: normalized mean square error; ASE: spectral efficiency efficiency

Acknowledgements

This work was supported by the Hainan University.

Funding

This work was supported by the National Natural Science Foundation of China (No. 61861015 and 61961013), Key Research and Development Program of Hainan Province (No. ZDYF2019011), National Key Research and Development Program of China (No. 2019CXTD400), Young Elite Scientists Sponsorship Program by CAST (No. 2018QNR001), and the Scientific Research Setup Fund of Hainan University (No. KYQD(ZR) 1731).

Availability of data and materials

The datasets simulated and/or analyzed during the current study are available from the corresponding author on reasonable request.

Competing interests

The authors declare that they have no competing interests.

Ethics approval and consent to participate

Not applicable.

Authors' contributions

JS wrote the manuscript, simulated and modified the experiments; XW and XL helped to conceive the idea and revise the manuscript, the theory and article writing; ZH and TS contributed to the development of the ideas. All authors read and approved the final manuscript.

Author details

College of Information and Communication Engineering, University of Hainan, Haikou, China.

References

1. Hemadeh, I.A., Satyanarayana, K., El-Hajjar, M., Hanzo, L.: Millimeter-wave communications: Physical channel models, design considerations, antenna constructions, and link-budget. *IEEE Communications Surveys & Tutorials* **20**(2), 870–913 (2017)
2. Xue, C., He, S., Huang, Y., Wu, Y., Yang, L.: An efficient beam-training scheme for the optimally designed subarray structure in mmwave los mimo systems. *EURASIP Journal on Wireless Communications and Networking* **2017**(1), 1–12 (2017)

3. Heath, R.W., Gonzalez-Prelcic, N., Rangan, S., Roh, W., Sayeed, A.M.: An overview of signal processing techniques for millimeter wave mimo systems. *IEEE journal of selected topics in signal processing* **10**(3), 436–453 (2016)
4. Kim, I.-s., Choi, J.: Channel estimation via gradient pursuit for mmwave massive mimo systems with one-bit adcs. *EURASIP Journal on Wireless Communications and Networking* **2019**(1), 1–16 (2019)
5. Dai, J., Zhou, L., Chang, C., Xu, W.: Robust bayesian learning approach for massive mimo channel estimation. *Signal Processing* **168**, 107345 (2020)
6. Rao, X., Lau, V.K.: Distributed compressive csit estimation and feedback for fdd multi-user massive mimo systems. *IEEE Transactions on Signal Processing* **62**(12), 3261–3271 (2014)
7. Chen, Z., Yang, C.: Pilot decontamination in wideband massive mimo systems by exploiting channel sparsity. *IEEE Transactions on Wireless Communications* **15**(7), 5087–5100 (2016)
8. Shen, J.-C., Zhang, J., Alsusa, E., Letaief, K.B.: Compressed csi acquisition in fdd massive mimo: How much training is needed? *IEEE Transactions on Wireless Communications* **15**(6), 4145–4156 (2016)
9. Candès, E.J., Romberg, J., Tao, T.: Robust uncertainty principles: Exact signal reconstruction from highly incomplete frequency information. *IEEE Transactions on information theory* **52**(2), 489–509 (2006)
10. Tsaig, Y., Donoho, D.L.: Compressed sensing (2004)
11. Huang, C., Liu, L., Yuen, C., Sun, S.: Iterative channel estimation using lse and sparse message passing for mmwave mimo systems. *IEEE Transactions on Signal Processing* **67**(1), 245–259 (2018)
12. Zhang, Z., Rao, B.D.: Sparse signal recovery with temporally correlated source vectors using sparse bayesian learning. *IEEE Journal of Selected Topics in Signal Processing* **5**(5), 912–926 (2011)
13. Tibshirani, R.: Regression shrinkage and selection via the lasso. *Journal of the Royal Statistical Society: Series B (Methodological)* **58**(1), 267–288 (1996)
14. Dai, J., Liu, A., Lau, V.K.: Fdd massive mimo channel estimation with arbitrary 2d-array geometry. *IEEE Transactions on Signal Processing* **66**(10), 2584–2599 (2018)
15. Fang, J., Wang, F., Shen, Y., Li, H., Blum, R.S.: Super-resolution compressed sensing for line spectral estimation: An iterative reweighted approach. *IEEE Transactions on Signal Processing* **64**(18), 4649–4662 (2016)
16. Hu, C., Dai, L., Mir, T., Gao, Z., Fang, J.: Super-resolution channel estimation for mmwave massive mimo with hybrid precoding. *IEEE Transactions on Vehicular Technology* **67**(9), 8954–8958 (2018)
17. Cheng, X., Tang, C., Zhang, Z.: Accurate channel estimation for millimeter-wave mimo systems. *IEEE Transactions on Vehicular Technology* **68**(5), 5159–5163 (2019)
18. Wan, L., Kong, X., Xia, F.: Joint range-doppler-angle estimation for intelligent tracking of moving aerial targets. *IEEE Internet of Things Journal* **5**(3), 1625–1636 (2017)
19. Wang, X., Yang, L.T., Meng, D., Dong, M., Ota, K., Wang, H.: Multi-uav cooperative localization for marine targets based on weighted subspace fitting in sagin environment. *IEEE Internet of Things Journal* (2021)
20. Wan, L., Sun, Y., Sun, L., Ning, Z., Rodrigues, J.J.: Deep learning based autonomous vehicle super resolution doa estimation for safety driving. *IEEE Transactions on Intelligent Transportation Systems* (2020)
21. Donoho, D.L., Maleki, A., Montanari, A.: Message-passing algorithms for compressed sensing. *Proceedings of the National Academy of Sciences* **106**(45), 18914–18919 (2009)
22. Rangan, S.: Generalized approximate message passing for estimation with random linear mixing. In: 2011 IEEE International Symposium on Information Theory Proceedings, pp. 2168–2172 (2011). IEEE
23. Mumtaz, S., Rodriguez, J., Dai, L.: MmWave Massive MIMO: a Paradigm for 5G. Academic Press, ??? (2016)
24. El Ayach, O., Rajagopal, S., Abu-Surra, S., Pi, Z., Heath, R.W.: Spatially sparse precoding in millimeter wave mimo systems. *IEEE transactions on wireless communications* **13**(3), 1499–1513 (2014)
25. Gao, X., Dai, L., Han, S., Chih-Lin, I., Heath, R.W.: Energy-efficient hybrid analog and digital precoding for mmwave mimo systems with large antenna arrays. *IEEE Journal on Selected Areas in Communications* **34**(4), 998–1009 (2016)
26. Méndez-Rial, R., Rusu, C., Alkhateeb, A., González-Prelcic, N., Heath, R.W.: Channel estimation and hybrid combining for mmwave: Phase shifters or switches? In: 2015 Information Theory and Applications Workshop (ITA), pp. 90–97 (2015). IEEE
27. Méndez-Rial, R., Rusu, C., González-Prelcic, N., Alkhateeb, A., Heath, R.W.: Hybrid mimo architectures for millimeter wave communications: Phase shifters or switches? *IEEE access* **4**, 247–267 (2016)
28. Cheng, X., Wang, M., Li, S.: Compressive sensing-based beamforming for millimeter-wave ofdm systems. *IEEE Transactions on Communications* **65**(1), 371–386 (2016)
29. Hur, S., Kim, T., Love, D.J., Krogmeier, J.V., Thomas, T.A., Ghosh, A.: Millimeter wave beamforming for wireless backhaul and access in small cell networks. *IEEE transactions on communications* **61**(10), 4391–4403 (2013)
30. Kim, T., Love, D.J.: Virtual aoa and aod estimation for sparse millimeter wave mimo channels. In: 2015 IEEE 16th International Workshop on Signal Processing Advances in Wireless Communications (SPAWC), pp. 146–150 (2015). IEEE
31. Alkhateeb, A., El Ayach, O., Leus, G., Heath, R.W.: Channel estimation and hybrid precoding for millimeter wave cellular systems. *IEEE journal of selected topics in signal processing* **8**(5), 831–846 (2014)
32. Shi, J., Wen, F., Liu, T.: Nested mimo radar: coarrays, tensor modeling and angle estimation. *IEEE Transactions on Aerospace and Electronic Systems* (2020)
33. Wang, X., Huang, M., Wan, L.: Joint 2d-dod and 2d-doa estimation for coprime emvs-mimo radar. *Circuits, Systems, and Signal Processing*, 1–17 (2021)
34. Wan, L., Liu, K., Liang, Y.-C., Zhu, T.: Doa and polarization estimation for non-circular signals in 3-d millimeter wave polarized massive mimo systems. *IEEE Transactions on Wireless Communications* **20**(5), 3152–3167 (2021)
35. Tipping, M.E.: Sparse bayesian learning and the relevance vector machine. *Journal of machine learning research* **1**(Jun), 211–244 (2001)
36. Ji, S., Xue, Y., Carin, L.: Bayesian compressive sensing. *IEEE Transactions on signal processing* **56**(6),

- 2346–2356 (2008)
37. Rao, B.D., Kreutz-Delgado, K.: An affine scaling methodology for best basis selection. *IEEE Transactions on signal processing* **47**(1), 187–200 (1999)
38. Al-Shoukairi, M., Rao, B.: Sparse bayesian learning using approximate message passing. In: 2014 48th Asilomar Conference on Signals, Systems and Computers, pp. 1957–1961 (2014). IEEE
39. Li, F., Fang, J., Duan, H., Chen, Z., Li, H.: Computationally efficient sparse bayesian learning via generalized approximate message passing. *arXiv preprint arXiv:1501.04762* (2015)
40. Rangan, S., Schniter, P., Fletcher, A.K., Sarkar, S.: On the convergence of approximate message passing with arbitrary matrices. *IEEE Transactions on Information Theory* **65**(9), 5339–5351 (2019)
41. Al-Shoukairi, M., Schniter, P., Rao, B.D.: A gamp-based low complexity sparse bayesian learning algorithm. *IEEE Transactions on Signal Processing* **66**(2), 294–308 (2017)
42. Fan, L., Qi, G.: Frequency estimator of sinusoid based on interpolation of three dft spectral lines. *Signal Processing* **144**, 52–60 (2018)
43. Popović-Bugarin, V., Djukanović, S.: A low complexity model order and frequency estimation of multiple 2-d complex sinusoids. *Digital Signal Processing* **104**, 102794 (2020)
44. Lee, J., Gil, G.-T., Lee, Y.H.: Channel estimation via orthogonal matching pursuit for hybrid mimo systems in millimeter wave communications. *IEEE Transactions on Communications* **64**(6), 2370–2386 (2016)
45. Cong, J., Wang, X., Huang, M., Wan, L.: Robust doa estimation method for mimo radar via deep neural networks. *IEEE Sensors Journal* (2020)
46. Cong, J., Wang, X., Lan, X., Huang, M., Wan, L.: Fast target localization method for fmcw mimo radar via vdsr neural network. *Remote Sensing* **13**(10), 1956 (2021)