Non-line-of-sight imaging of moving objects obscured by a random corridor

Tian Shi

Beijing Institute of Technology <https://orcid.org/0000-0002-4634-5472>

Li Liangsheng

Science and Technology on Electromagnetic Scattering Laboratory <https://orcid.org/0000-0003-4351-1815>

He Cai

Science and Technology on Electromagnetic Scattering Laboratory

Xianli Zhu

Science and Technology on Electromagnetic Scattering Laboratory

Qingfan Shi

Beijing Institute of Technology

Ning Zheng (✉ ningzheng@bit.edu.cn)

Beijing Institute of Technology

Article

Keywords: NLOS imaging, random corridor, RSESIC, correlation fidelity

Posted Date: August 18th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-798484/v1>

License: This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Version of Record: A version of this preprint was published at Nature Communications on July 14th, 2022. See the published version at <https://doi.org/10.1038/s41467-022-31669-7>.

Non-line-of-sight imaging of moving objects obscured by a random corridor

Tian Shi^{1,2}, Liangsheng Li^{2,*}, He Cai², Xianli Zhu², Qingfan Shi¹, and Ning Zheng^{1,*}

¹School of Physics, Beijing Institute of Technology, Beijing, China

²Science and Technology on Electromagnetic Scattering Laboratory, Beijing, China

*Correspondence and requests for materials should be addressed to N.Z. (email: ningzheng@bit.edu.cn) or to L.L. (email: liliangshengbitip@163.com)

ABSTRACT

Non-line-of-sight (NLOS) imaging makes it possible to reconstruct hidden objects around corners, which is of fundamental importance in various fields. Despite recent advances, NLOS imaging has not been studied in certain typical random scenarios, such as tortuous corridors filled with random media. We dub such a category of complex environment ‘random corridor’, and propose a reduced spatial- and ensemble-speckle intensity correlation (RSESIC) method to image a moving object obscured by a random corridor. Experimental results show that the method can reconstruct image of a centimeter-sized hidden object with a sub-millimeter resolution by a low-cost digital camera. The imaging capability depends on three system parameters and can be characterized by the correlation fidelity (CF). Furthermore, the RSESIC method is able to recover the image of objects even for a single pixel containing the contribution of about 10^2 speckle grains, which overcomes the theoretical limitation of traditional speckle imaging methods. Last but not least, when the power attenuation of speckle intensity leads to the serious deterioration of CF, the image of hidden objects can still be reconstructed by the corrected intensity correlation.

Introduction

Relying on its ability to reconstruct the object hidden beyond the direct line of sight of a camera, non-line-of-sight (NLOS) imaging has recently attracted more and more interest^{1–3}. The potential application of NLOS imaging ranges from robotic vision, autonomous driving, disaster relief, to medical imaging¹. In the typical imaging scene widely studied previously, NLOS imaging always requires a relay surface located in the field of view of both the hidden object and the camera³. Methods such as backprojection^{4–7}, light-cone transform⁸, and phasor field^{9,10} is able to reconstruct the hidden object with the time-of-flight information of scattered light from the relay surface. On the other hand, speckle correlations^{11,12}, wavefront-shaping¹³, computational periscope¹⁴, and spatial coherence analysis^{15,16} is capable of imaging the hidden object with only the spatial information of scattered light from the relay surface. The novel principle and technology greatly improve the efficiency, economy, minimum resolution and maximum working distance of NLOS imaging^{8,9,14,17,18}. In spite of recent advances, challenging but important NLOS imaging in another type of complex environment ‘random corridor’ has received little attention. Random corridor represents a kind of tortuous corridors filled with random media, which often exists in rescue scenes such as dusty mines, smoke-filled ventilation ducts and building corridors¹⁹. Imaging rescue targets obscured by a random corridor can greatly improve the rescue efficiency and protect rescue crews.

In this paper, we propose a new NLOS method, called reduced spatial- and ensemble-speckle intensity correlation (RSESIC), to image a moving object obscured by a random corridor. Experimental results show that this method can re-

construct the sub-millimeter resolution image of a centimeter sized hidden object with a low-cost digital camera, whether the object is obscured by a random corridor with one or two corners. A correlation fidelity (CF) is defined to characterize the imaging capability of the system, and the dependences of the imaging capability on three system parameters: subspace side length, pixel number of a camera and size ratio of pixel to speckle are investigated. If these parameters are inappropriately chosen, the CF will be poor and even unacceptable, resulting in NLOS imaging failure. Then the parameter range in which the RSESIC method can correctly image the hidden object is shown. The deterioration of CF caused by speckle intensity power attenuation is also studied. Based on the experimental and theoretical analysis, we demonstrate that the image of hidden objects can still be reconstructed after additional correlation renormalization.

Results

Imaging in a random corridor with one corner

Fig. 1a shows the schematic for an experimental NLOS imaging system. The hidden object is out of the camera’s line of sight and obscured by a random corridor. The random corridor is an L-shaped white plexiglass with one corner, as shown in the insets. The black dotted line represents an open boundary of the random corridor. The relay surface is not present for this scenario, and thus the laser incident on the hidden object can only propagate into the camera’s field of view through the random corridor. The hidden object is a metal plate with three equally spaced slits mounted on an optical mobile platform [see Fig. 1e] and moves in the XY plane. The position vector of the hidden object is denoted as

Figure 1. Imaging in a random corridor with one corner. a, Schematic of an experimental setup. b, Speckle intensity images $I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta\boldsymbol{\rho})$ that evolve with $\Delta\boldsymbol{\rho}$, which allow us to restore the image of the real hidden object. c, Cross-correlation of the $I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta\boldsymbol{\rho})$ in b, clearly revealing distinctive patterns. d, Object image reconstructed from the cross-correlation in c by a phase-retrieval algorithm. e, A metal plate with three equally spaced slits. f-h, As in c–e for a different object with a more complex shape. System parameters for imaging: $\hat{l}_{\text{sub}} = 50$, $R = 2.87$ and $N = 10^4$. Scale bar: 1mm.

$\mathbf{r}_o$. The displacement vector of the hidden object is denoted as $\Delta\boldsymbol{\rho}$, where $|\Delta\boldsymbol{\rho}| = \sqrt{\Delta x^2 + \Delta y^2}$. Δx and Δy are the projections of $\Delta\boldsymbol{\rho}$ on the X and Y axes, respectively. A series of speckle intensity patterns that varies with $\Delta\boldsymbol{\rho}$ is recorded by a digital camera (Sony A6300).

We denote the recorded speckle intensity images as $I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta\boldsymbol{\rho})$, where $\mathbf{r}_c$ is the position vector on the sensor of the camera. Fig. 1b shows $I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta\boldsymbol{\rho})$ for a hidden object [see Fig. 1e] at different positions. The speckle intensity images are recorded on the sensor ranging from 200 pixels $\times$ 200 pixels. x_c and z_c are projections of $\mathbf{r}_c$ on X and Z axes, respectively. The photographic parameters and image processing method are detailed in the section of **Methods**. It can be clearly seen in Fig. 1b that the transmitted light field illuminating on the hidden object is completely randomized when it propagates into the camera's field of view, indicating that the hidden object cannot be directly imaged.

In order to decode the information carried by the speckle

intensity images, a spatial speckle intensity correlation (SSIC) method was introduced in the past^{20,21}. The method uses spatial average cross-correlation of speckle intensity images that vary with the position of hidden objects to approximate the transmitted field autocorrelation of hidden objects $C_{ho}(\Delta\boldsymbol{\rho})$. When the object is hidden behind a thick random medium, the SSIC method accurately recovers $C_{ho}(\Delta\boldsymbol{\rho})$. Therefore, the image of the hidden object can be successfully reconstructed with $C_{ho}(\Delta\boldsymbol{\rho})$ and an iterative phase recovery algorithm²². However, the SSIC method failed to recover $C_{ho}(\Delta\boldsymbol{\rho})$ under the NLOS conditions.

Thus, we propose a RSESIC method to deal with the challenge of NLOS imaging hidden objects obscured by a random corridor. The RSESIC is defined as,

$$C_{rd}(\Delta\boldsymbol{\rho}) = \left\langle \frac{[I_{rd}(\mathbf{r}_c; \mathbf{r}_o) - \bar{I}_{rd}][I_{rd}(\mathbf{r}_c; \mathbf{r}_o + \Delta\boldsymbol{\rho}) - \bar{I}_{rd}]}{\sigma_{rd}\sigma_{rd}} \right\rangle_{\mathbf{r}_c, \mathbf{r}_o} \quad (1)$$

where I_{rd} is the subspace reduced speckle intensity, $\langle \dots \rangle_{\mathbf{r}_c}$

indicates spatial average and $\langle \dots \rangle_{\mathbf{r}_o}$ indicates ensemble average. Spatial average means the average over $\mathbf{r}_c$. Ensemble average means the average over $\mathbf{r}_o$ (more information is provided in the **Methods** section). $\bar{I}_{rd} = \langle I_{rd}(\mathbf{r}_c) \rangle_{\mathbf{r}_c}$ and $\sigma_{rd} = \sqrt{\langle I_{rd}^2(\mathbf{r}_c) \rangle_{\mathbf{r}_c} - \langle I_{rd}(\mathbf{r}_c) \rangle_{\mathbf{r}_c}^2}$ denote the mean and standard deviation of I_{rd} , respectively. I_{rd} is defined as,

$$I_{rd}(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho) = \frac{I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho)}{\sigma_s(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho)} \quad (2)$$

where $\sigma_s(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho)$ is the subspace standard deviation of $I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho)$ and can be calculated from the subspace average,

$$\sigma_s(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho) = \sqrt{\langle I_s^2(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho) \rangle_{\text{sub}} - \langle I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta \rho) \rangle_{\text{sub}}^2} \quad (3)$$

Here $\langle \dots \rangle_{\text{sub}}$ represents the average of the I_s in a square subspace area on the camera sensor. The square subspace is centered at a given position vector $\mathbf{r}_c$. The side length of the square subspace is denoted as l_{sub} . For convenience, we further define a reduced subspace length $\hat{l}_{\text{sub}} = l_{\text{sub}}/l_{\text{pixel}}$, where l_{pixel} represents the pixel side length of a camera.

The RSESIC method eliminates the spatial dependence of the standard deviation of the speckle intensity by subspace reduction. Therefore, $C_{rd}(\Delta \rho)$ is independent of the spatial position of the observed speckle intensity pattern and the shape of random medium. Furthermore, the average over $\mathbf{r}_o$ greatly improves the recovery efficiency.

In a random corridor with static random media, $C_{rd}(\Delta \rho)$ is approximately equivalent to $C_{ho}(\Delta \rho)$, which allows the RSESIC method to be used to image hidden objects (Supplementary Note 1). The $C_{rd}(\Delta \rho)$ for the hidden object in Fig. 1e is plotted, as shown in Fig. 1c, clearly revealing characteristic patterns. The resolution of the patterns is determined by the product of the moving speed of the hidden object $|\mathbf{v}|$ and the time interval of two photographs $\Delta \tau$. As mentioned before, the image of the hidden object can be reconstructed with $C_{rd}(\Delta \rho)$ and an iterative phase recovery algorithm^{22,23} (more information is provided in the **Methods** section). The reconstructed image of the hidden object is plotted in Fig. 1d, which clearly demonstrates that the size and geometry of the hidden object are accurately restored. Similarly, Fig. 1f-h exhibit the imaging result of another hidden object, but with a complex shape. This further confirms the imaging competence of the RSESIC method for a random corridor with one corner.

For the RSESIC method, the consistency between $C_{rd}(\Delta \rho)$ and $C_{ho}(\Delta \rho)$, namely CF, determines the fidelity of the reconstructed image. The CF of the RSESIC method is dependent on three system parameters including reduced subspace length $\hat{l}_{\text{sub}}$, pixel number of a camera N and size ratio of pixel to speckle R . If these parameters are inappropriately chosen, the CF will be poor and even unacceptable, resulting in imaging failure of hidden objects. We explore the dependences of CF

on $\hat{l}_{\text{sub}}$, R and N for the range of the parameters in which the RSESIC method can validly image the hidden object.

The size ratio of pixel to speckle on a camera is defined as,

$$R = \frac{l_{\text{pixel}}}{d_{\text{speckle}}} \quad (4)$$

Here d_{speckle} is the average diameter of the speckle grain on the camera sensor. R determines the ability of the camera to resolve a single speckle grain. When $R \ll 1$, the morphology of the speckle grains can be clearly photographed by the camera. However, when $R \geq 1$, the contribution of multiple speckle grains will overlap in one pixel, so the morphology information of speckle grains will be lost completely. In our experiment, $l_{\text{pixel}} \approx 3.90 \mu\text{m}$, d_{speckle} is the product of the average diameter of the speckle grain on the surface of the white plexiglass and the overall magnification of camera zoom lens. Theory and simulation show that the average diameter of the speckle grain on the surface of the random media is equal to a half wavelength^{24,25}. The overall magnification of the camera zoom lens in the experiment is approximately equal to 4.31. Therefore, $d_{\text{speckle}} \approx 1.36 \mu\text{m}$ and the minimum value of R is 2.87.

We apply Eq. (1) to calculate $C_{rd}(\Delta x)$ for different parameters $\hat{l}_{\text{sub}}$, R and N . The hidden object is a hollow metal plate

Figure 2. a, Effects of $\hat{l}_{\text{sub}}$, N and R on $C_{rd}(\Delta x)$ are shown, and the black solid line denotes $C_{ho}(\Delta x)$. b, Color maps of $d(C_{ho}, C_{rd})$ as a function of R and N for $\hat{l}_{\text{sub}} = 100$ and $= 10$, and the white dashed line is a contour line with $d(C_{ho}, C_{rd}) = 0.91$.

Figure 3. Imaging in a random corridor with two corners. a, Schematic of an experimental setup. b, C_{rd} , normalized $\tilde{C}_{rd}$ and C_{ho} vs Δx . C_{ho} denotes the transmitted field autocorrelation of the hidden object. c, Normalized $\tilde{C}_{rd}(\Delta x, \Delta y)$. d, Object image reconstructed from $\tilde{C}_{rd}(\Delta x, \Delta y)$ by a phase-retrieval algorithm. The system parameters and scale bar length are the same as those in Fig. 1.

shown in Fig. 1e and moves along the X direction. Since the camera position and the focal length of the zoom lens (50mm) are fixed, R is increased by merging the pixels of the speckle intensity image. For example, R increases from 2.87 to 8.61 when nine pixels is merged into one.

We first show the influences of $\hat{l}_{sub}$, R and N on the CF by directly comparing $C_{rd}(\Delta x)$ and $C_{ho}(\Delta x)$ in Fig. 2a, where $C_{ho}(\Delta x)$ is numerically calculated from the transmitted field of the hidden object (Supplementary Note 2). It can be found from Fig. 2a that the CF is proportional to N , and inversely proportional to $\hat{l}_{sub}$ and R . The decrease of N gives rise to random fluctuations in $C_{rd}(\Delta x)$, and the increase of $\hat{l}_{sub}$ or R causes positive background correlation in $C_{rd}(\Delta x)$. This suggests that the influences of $\hat{l}_{sub}$ and R on $C_{rd}(\Delta x)$ are similar, but the effect from N is different.

The Euclidean distance²⁶ is introduced to quantify the deviation between $C_{rd}(\Delta \rho)$ and $C_{ho}(\Delta \rho)$. Therefore, the CF of the RSESIC method $d(C_{ho}, C_{rd})$ can be quantitatively calculated by the following definitions,

$$d(C_{ho}, C_{rd}) = 1 - \frac{\|C_{ho}(\Delta \rho) - C_{rd}(\Delta \rho)\|_2}{\|C_{ho}(\Delta \rho)\|_2 + \|C_{rd}(\Delta \rho)\|_2} \quad (5)$$

where $\|\dots\|_2$ represents the Euclidean norm. When $C_{rd}(\Delta \rho) = C_{ho}(\Delta \rho)$, $d(C_{ho}, C_{rd}) = 1$. Otherwise, $0 < d(C_{ho}, C_{rd}) < 1$. The values of $d(C_{ho}, C_{rd})$ calculated by Eq. (5) are shown in the legend in Fig. 2a, which directly reflect the dependences of CF on $\hat{l}_{sub}$, R and N . Since the curves of $C_{rd}(\Delta x)$ and $C_{ho}(\Delta x)$ almost overlap for $d(C_{ho}, C_{rd}) \geq 0.91$, it is reasonable to choose $d(C_{ho}, C_{rd}) = 0.91$ as a lower threshold of the validity of the RSESIC method.

The color maps in Fig. 2b shows $d(C_{ho}, C_{rd})$ for various R and N when $\hat{l}_{sub}$ is equal to 100 and 10, respectively, which fur-

ther demonstrates the dependences of the CF on $\hat{l}_{sub}$, R and N . The region surrounded by a contour line $d(C_{ho}, C_{rd}) = 0.91$ and two coordinate axes indicates the parameter range in which the RSESIC method can accurately recover $C_{ho}(\Delta x)$ and reconstruct the image of hidden objects. By comparing the two color maps, it can be found that reduction in $\hat{l}_{sub}$ significantly enlarges the optimal imaging region of R and N . We also notice that the RSESIC method even holds for $R = 15$ when $\hat{l}_{sub} = 10$ and $N = 10^4$. This result breaks through the limit ($R < 1$) of previous speckle correlation methods^{11,20,21}, and provides an insight into speckle-based imaging methods. In addition, when $\hat{l}_{sub} = 10$ and $R < 15$, $C_{ho}(\Delta x)$ can be accurately recovered only with $N = 10^3$ pixels, indicating that the imaging method is valid with a low-pixel camera.

Imaging in a random corridor with two corners

When an object is hidden behind several corners in a random corridor, the scattering of the corners and random media makes the light propagate from the hidden object through a very complex path to the observation point. In this case, it is extremely difficult to simulate the propagation of light. Besides, the power attenuation of the scattered light significantly enhances the influence of noise. Therefore, imaging objects hidden in such random corridors is very challenging. However, the RSESIC method does not need to solve the model for light propagation, and can eliminate the influence of ambient noise on the speckle intensity cross-correlation through extrapolation, thus solving the imaging difficulty (Supplementary Note 3).

The schematic diagram to image objects hidden in a random corridor with two corners is shown in Fig. 3a. The hidden object is the metal plate with three slits, which moves in the

XY plane. The illustration shows the side and front view of the random corridor, which is a Z-shaped metal tube filled with white plexiglass. The first function of the metal tube is to increase the transmittance of incident light in the random corridor, so that the speckle intensity pattern behind the two corners can be detected by the camera. The second function of the metal tube is to enhance the scattering of incident light by the random corridor wall, so as to test the imaging performance of the RSESIC method under the coupling interference of the corridor wall and random medium.

We make a comparison between $C_{rd}(\Delta x)$ and $C_{ho}(\Delta x)$ in Fig. 3b. $C_{rd}(\Delta x)$ is calculated from the measured images of speckle intensity through the RSESIC method. Due to the influence of fast time-dependent noise, $C_{rd}(\Delta x)$ sharply drops at small displacement and significantly deviates from $C_{ho}(\Delta x)$, causing CF to decrease to $d(C_{ho}, C_{rd}) = 0.55$. Therefore, C_{rd} cannot be directly used to reconstruct the image of the hidden object. However, the positions of peaks and valleys in $C_{rd}(\Delta x)$ and $C_{ho}(\Delta x)$ are identical, which implies that C_{rd} still contains the information about C_{ho} . Fortunately, it is found that the adverse effect of ambient noise on the C_{rd} can be eliminated by extrapolation and normalization, and then obtain a correlation $\tilde{C}_{rd}$ approximately equivalent to C_{ho} . Here $C_{rd}(\Delta x, \Delta y)$ is normalized by $C_{rd}(0, 0)$ that is corrected by using extrapolation. The good consistency between $\tilde{C}_{rd}(\Delta x, \Delta y)$ and $C_{ho}(\Delta x, \Delta y)$ demonstrates that the RSESIC method can correctly restore the transmitted field autocorrelation of the hidden object behind two corners, see Fig. 3b. Then with the normalized $\tilde{C}_{rd}(\Delta x, \Delta y)$ in Fig. 3c, the image of the hidden object was reconstructed by phase-retrieval, as shown in Fig. 3d. By comparing Fig. 1e with Fig. 3d, it clearly shows that the size and geometric characteristics of the hidden object are accurately restored, which confirms the ability of the RSESIC method to

image in a random corridor with two corners.

In addition, the RSESIC method is further examined by imaging an object 'S' [see Fig. 4d] obscured by a random corridor with two corners. The area of 'S' is approximately equal to $30.79mm^2$, which is much smaller than that of the three equally spaced slits shown in Fig. 1e, $60mm^2$. Due to stronger attenuation of speckle intensity power, imaging of 'S' is supposed to be more difficult. The imaging results demonstrate that the hidden object can still be imaged robustly, as shown in Fig. 4.

Discussion

When an object is obscured by a random corridor, the difficulty of imaging the object is that the ballistic light is blocked and the relay surface is absent. We propose the RSESIC method to cope with this NLOS imaging challenge. Experimental results demonstrate that the method can reconstruct the image of the object obscured by a random corridor, only using speckle intensity images recorded by a digital camera. Applicable conditions for the method are as follows: the random medium is static, the hidden object radiates coherent light, and motion information of the object is known.

Being different from most existing NLOS imaging methods, the RSESIC method can image the hidden objects behind multiple corners without the spatiotemporal information of diffusion light reflected from a relay surface^{3,8,9}, and the reconstructed image is independent of the measurement position of multiple scattering light. Therefore, the method is complementary to the existing NLOS imaging methods and will promote further research on NLOS imaging in more complex scenes. In addition, the RSESIC method restores the image from the intensity cross-correlation of multiple scattering light rather than from solving a light propagation model, so the computation and complexity of the method are independent of the thickness of random media and the number of corners. The ability of the RSESIC method to image objects behind multiple corners makes it promising to be applied to many fields such as disaster relief and automatic driving. If the moving distance of the hidden object and the measurement time of the camera are large enough, the RSESIC method can image the hidden object of any size. The actual imaging resolution of the method is determined by the product of the moving speed $|\mathbf{v}|$ of the hidden object and the time interval of two photographs $\Delta\tau$.

We analyze the effects of $\hat{l}_{sub}$, R and N on the CF of the RSESIC method and use a color map to point out an applicable parameter range for the method. The optimal combination of these three parameters can ensure the CF of the RSESIC method, which greatly reduces the requirement of this method for measuring instruments. For instance, with appropriate $\hat{l}_{sub}$ and N , the RSESIC method can accurately recover C_{ho} and the image of the hidden object even for $R = 15$. This finding breaks through the limit ($R < 1$) of previous speckle correlation methods and proves that the speckle correlation method can image hidden objects when the speckle grains are

Figure 4. Imaging of a hidden object 'S' in a random corridor with two corners. The system parameters and scale bar are the same as those in Fig. 1.

not well resolved by a camera. Similarly, if $\hat{l}_{\text{sub}}$ and R are appropriate, an average of $N = 10^3$ camera pixels is enough to make C_{rd} and C_{ho} match well. This result indicates that RSESIC method is suitable for low pixel cameras and has low requirements for storage and computing.

When the transmitted light of the hidden object is strongly attenuated during the propagation, ambient noise causes the C_{rd} calculated by the RSESIC method to deviate significantly from C_{ho} . Therefore, the CF sharply deteriorates, resulting in imaging failure of hidden objects. Based on the experimental and theoretical analysis, we find that the mixture of correlation characteristic of fast time-varying ambient noise and of correlation of transmitted field of hidden objects leads to an abrupt decline in C_{rd} . We show that using an extrapolation method, the influence of noise in C_{rd} can be eliminated, and then the image of hidden objects can be reconstructed. This confirms the adaptability of the RSESIC method in a noise environment.

As a final note, the application of the RSESIC method is not only limited to imaging by laser, but also applicable for other types of coherent waves, such as acoustic wave, quantum wave and electromagnetic wave with other frequencies. Therefore, NLOS imaging with the similar difficulty in other fields are expected to be addressed.

Methods

Experimental setup. The experimental system consists of a 632.991 nm laser source (Thorlabs, HRS015B), a lens, a hidden object, a random corridor and a digital camera (Sony A6300). The zoom lens of the digital camera is set to a focal length of 50mm. The distance between the zoom lens and random media is 1mm. A speckle intensity pattern in an approximately $5.45\text{mm} \times 3.64\text{mm}$ region of the white plexiglass surface is imaged on the 14-bit CMOS sensor of the camera. For imaging objects hidden behind one (two) corner(s), the shooting parameters of the camera are set to exposure time=1/30 (1/10) s, aperture factor=5.6, and ISO=500 (6400), respectively.

Image processing. The photographs in RAW format were exported from the camera and further processed. Each photographic file is a 14-bit, 6024×4024 -pixels raw image of which the color channels interleave according to the RGBG mode of a Bayer filter. Since the light emitted by the He-Ne laser is red, the data in the red channel of RAW files are extracted and used as the actual images of the speckle intensity. The size of speckle intensity image is 3012×2012 -pixels.

Spatial- and ensemble-speckle intensity correlation. In Eq. (1), $\langle \dots \rangle_{\mathbf{r}_c}$ is the average over the pixels of recorded speckle intensity images. Each speckle intensity image contains 3012×2012 intensity values, so the maximum spatial average times is 6060144 which is much larger than that required by the RSESIC method. From the definition of

Eq. (1), it can be explicitly seen that the cross-correlation of speckle intensity reflects the similarity between a series of evolutionary speckle intensity images $I_s(\mathbf{r}_c; \mathbf{r}_o + \Delta\boldsymbol{\rho})$ for a moving hidden object and the reference speckle intensity image $I_s(\mathbf{r}_c; \mathbf{r}_o)$. When $\Delta\boldsymbol{\rho}$ is given, m reference images of speckle intensity can be obtained by changing $\mathbf{r}_o$, and then m correlation values can be calculated. $\langle \dots \rangle_{\mathbf{r}_o}$ is the average of the m correlation values. The intensity cross-correlations shown in Fig. 1, Fig. 3 and Fig. 4 are all calculated by 10^4 spatial average and 9 ensemble average. That is to say, the image of the hidden object is reconstructed from the data of speckle intensity measured on an area of 100×100 -pixels of the CMOS sensor.

Image reconstruction of hidden objects. Autocorrelation of the transmitted field of a hidden object is defined as (Supplementary Note 1),

$$\begin{aligned} C_{\text{ho}}(\Delta\boldsymbol{\rho}) &= \left| \frac{\int \int E_{\text{ho}}(x, y; \mathbf{r}_o) E_{\text{ho}}^*(x, y; \mathbf{r}_o + \Delta\boldsymbol{\rho}) dx dy}{\int \int |E_{\text{ho}}(x, y; \mathbf{r}_o)|^2 dx dy} \right|^2 \\ &= \left| \int \int \hat{E}_{\text{ho}}(x, y; \mathbf{r}_o) \hat{E}_{\text{ho}}^*(x, y; \mathbf{r}_o + \Delta\boldsymbol{\rho}) dx dy \right|^2 \\ &= |\mathcal{F}^{-1}\{|\mathcal{F}\{\hat{E}_{\text{ho}}(x, y)\}|^2\}|^2 \end{aligned}$$

Here E_{ho} denotes the transmitted field of a hidden object, $\hat{E}_{\text{ho}}$ denotes the reduced dimensionless transmitted field, which is defined as,

$$\hat{E}_{\text{ho}}(x, y; \mathbf{r}_o + \Delta\boldsymbol{\rho}) = \frac{E_{\text{ho}}(x, y; \mathbf{r}_o + \Delta\boldsymbol{\rho})}{\sqrt{\int \int |E_{\text{ho}}(x, y; \mathbf{r}_o)|^2 dx dy}}$$

By the approximate relation $C_{\text{rd}}(\Delta\boldsymbol{\rho}) \approx C_{\text{ho}}(\Delta\boldsymbol{\rho})$, we have,

$$|\hat{E}_{\text{ho}}(k_x, k_y)| = |\mathcal{F}\{\hat{E}_{\text{ho}}(x, y)\}| \approx |\sqrt{\mathcal{F}\{C_{\text{rd}}(\Delta\boldsymbol{\rho})\}}|$$

The Fourier amplitude $|\hat{E}_{\text{ho}}(k_x, k_y)|$ of the reduced dimensionless transmitted field of a hidden object can be directly achieved. With substituting $|\hat{E}_{\text{ho}}(k_x, k_y)|$ and appropriate real-space support domain into the iterative phase recovery algorithm, $\hat{E}_{\text{ho}}(x, y)$ is reconstructed. Finally, $|\hat{E}_{\text{ho}}(x, y)|$ is the image of hidden object.

Data availability. The data that support the findings of this study are available from the corresponding author upon reasonable request.

References

- Freund, I. Looking through walls and around corners. *Phys. A: Stat. Mech. its Appl.* **168**, 49–65 (1990).
- Altmann, Y. *et al.* Quantum-inspired computational imaging. *Science* **361**, eaat2298 (2018).
- Faccio, D., Velten, A. & Wetzstein, G. Non-line-of-sight imaging. *Nat. Rev. Phys.* **2**, 318–327 (2020).

4. Gupta, O., Willwacher, T., Velten, A., Veeraraghavan, A. & Raskar, R. Reconstruction of hidden 3d shapes using diffuse reflections. *Opt. Express* **20**, 19096–19108 (2012).
5. Velten, A. *et al.* Recovering three-dimensional shape around a corner using ultrafast time-of-flight imaging. *Nat. Commun.* **3**, 745–753 (2012).
6. Buttafava, M., Zeman, J., Tosi, A., Eliceiri, K. & Velten, A. Non-line-of-sight imaging using a time-gated single photon avalanche diode. *Opt. Express* **23**, 20997–21011 (2015).
7. Musarra, G. *et al.* Non-line-of-sight three-dimensional imaging with a single-pixel camera. *Phys. Rev. Appl.* **12**, 011002 (2019).
8. O'Toole, M., Lindell, D. B. & Wetzstein, G. Confocal non-line-of-sight imaging based on the light-cone transform. *Nature* **555**, 338 (2018).
9. Liu, X. *et al.* Non-line-of-sight imaging using phasor-field virtual waveoptics. *Nature* **572**, 620–623 (2019).
10. Liu, X., Bauer, S. & Velten, A. Phasor field diffraction based reconstruction for fast non-line-of-sight imaging systems. *Nat. Commun.* **11**, 1645 (2020).
11. Katz, O., Heidmann, P., Fink, M. & Gigan, S. Non-invasive single-shot imaging through scattering layers and around corners via speckle correlations. *Nat. Photonics* **8**, 784–790 (2014).
12. Shawn, D., Dennis, F. G. & Abbie, T. W. Imaging around corners in the mid-infrared using speckle correlations. *Opt. Express* **28**, 11051–11064 (2020).
13. Katz, O., Small, E. & Silberberg, Y. Looking around corners and through thin turbid layers in real time with scattered incoherent light. *Nat. Photonics* **6**, 549–553 (2012).
14. Saunders, C., Murray-Bruce, J. & Goyal, V. K. Computational periscopy with an ordinary digital camera. *Nature* **565**, 472–475 (2019).
15. Batarseh, M. *et al.* Passive sensing around the corner using spatial coherence. *Nat. Commun.* **9**, 3629 (2018).
16. Starshynov, I., Ghafur, O., Fitches, J. & Faccio, D. Coherent control of light for non-line-of-sight imaging. *Phys. Rev. Appl.* **12**, 064045 (2019).
17. Wang, B. *et al.* Non-line-of-sight imaging with picosecond temporal resolution. *Phys. Rev. Lett.* **127**, 053602 (2021).
18. Wu, C. *et al.* Non-line-of-sight imaging over 1.43 km. *Proc. Natl. Acad. Sci.* **118**, e2024468118 (2021).
19. Waugh, W. L. *Living with Hazards, Dealing with Disasters: An Introduction to Emergency Management* (Routledge, 1998), 1st edn.
20. Newman, J. A. & Webb, K. J. Imaging optical fields through heavily scattering media. *Phys. Rev. Lett.* **113**, 263903 (2014).
21. Webb, K. J. & Luo, Q. Theory of speckle intensity correlations over object position in a heavily scattering random medium. *Phys. Rev. A* **101**, 063827 (2020).
22. Fienup, J. R. Reconstruction of a complex-valued object from the modulus of its fourier transform using a support constraint. *J. Opt. Soc. Am. A* **4**, 118–123 (1987).
23. Meihua, L. *et al.* Improving reconstruction of speckle correlation imaging by using a modified phase retrieval algorithm with the number of nonzero-pixels constraint. *Appl. Opt.* **58**, 473–478 (2019).
24. Carminati, R. Subwavelength spatial correlations in near-field speckle patterns. *Phys. Rev. A* **81**, 053804 (2010).
25. Shi, T., Li, Y., Shi, Q., Li, L. & Zheng, N. The kullback–leibler divergence evolution of randomized electromagnetic field. *Opt. Commun.* 126411 (2020).
26. Michel, M. D. & Elena, D. *Encyclopedia of Distances* (Springer-Verlag Berlin Heidelberg, 2016), 4st edn.

Acknowledgements

This work was supported by the National Natural Science Foundation of China (NSF) (11974044) and National Key Research and Development Program of China (2016YFC1401001).

Author contributions statement

L.L. and N.Z. and Q.S. conceived the idea, T.S. and L.L. designed the experiments and performed numerical simulations. T.S. and H.C. and X.Z. conducted the experiments and analyzed the data. T.S. and N.Z. wrote the paper.

Additional information

Competing interests: The authors declare no competing interests.

Supplementary Files

This is a list of supplementary files associated with this preprint. Click to download.

- [3SupplementaryInformation.pdf](#)