Dynamic Modeling and Parameter Identification for a Gantry-type Automated Fiber Placement Machine

Liang Cheng

Zhejiang University

Jianbo Wu (✉ wujianbo1011@zju.edu.cn)

Zhejiang University <https://orcid.org/0000-0002-8682-454X>

Yingjie Guo

Zhejiang University

Jiangxiong Li

Zhejiang University

Yinglin Ke

Zhejiang University

Research Article

Keywords: dynamic modeling, Newton-Euler method, multi-body system, minimum inertial parameter, parameter identification, gantry-type automated fiber placement machine

Posted Date: September 3rd, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-863580/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Version of Record: A version of this preprint was published at The International Journal of Advanced Manufacturing Technology on January 24th, 2022. See the published version at <https://doi.org/10.1007/s00170-021-08557-3>.

Title page

Author Information

The names of the authors:

Liang Cheng^{1,2} · Jianbo Wu^{1,2} · Yingjie Guo^{1,2} · Jiangxiong Li^{1,2} · Yinglin Ke^{1,2}

The affiliations of the authors:

¹ State Key Lab of Fluid Power Transmission and Mechatronic Systems,
Zhejiang University, Hangzhou, 310027, China

² Key Laboratory of Advanced Manufacturing Technology of Zhejiang Province, School of Mechanical Engineering, Zhejiang University, Hangzhou, 310027, China

Address:

School of Mechanical Engineering, Zhejiang University
No.38 Zheda Road, Xihu District, Hangzhou
310027 China

Authors contact details

Name: Liang Cheng

E-mail address: chengliang@zju.edu.cn

ORCID: 0000-0002-2899-329X

Name: Jianbo Wu (Corresponding author)

E-mail address: wujianbo1011@zju.edu.cn

Fax and telephone number: +86 571 87953929

Mobile phone: +86 17794539273

ORCID: 0000-0002-8682-454X

Name: Yingjie Guo

E-mail address: zju_gyj@zju.edu.cn

Name: Jiangxiong Li

E-mail address: ljxiong@zju.edu.cn

Name: Yinglin Ke

E-mail address: ylke@zju.edu.cn

Dynamic modeling and parameter identification for a gantry-type automated fiber placement machine

Abstract

Dynamic models play a critical role in the design of model-based controllers, and therefore have a significant effect on the dynamic characteristics of motion equipment. We mainly focus on the dynamic modeling and parameter identification for a gantry-type automated fiber placement (AFP) machine in this paper. First, a dynamic modeling process combining prismatic axes and revolute axes is conducted by the Newton-Euler method, in which the effects of friction and hydraulic balance system are also considered. Then, as the convenience for parameter identification and the application in linearity control, the methods of dynamic model linearization and determination of minimum inertial parameters based on the multi-body system (MBS) theory are proposed, and a dynamic model in the form of linearized minimum inertial parameters is consequently established. To identify the parameters in the model, key issues regarding excitation trajectory, filtering, and identification algorithm are discussed in detail. Finally, corresponding experiments are performed on the AFP machine, and experimental results show that there is a good agreement between the prediction of the model and the measurement in actuality. Data analysis shows that except for Z-axis, the relative error rates of the others are not greater than 5%, which proves the effectiveness of the established dynamic model and the identified parameters.

Keywords

dynamic modeling; Newton-Euler method; multi-body system; minimum inertial parameter; parameter identification; gantry-type automated fiber placement machine

1. Introduction

Advanced carbon fiber reinforced composite (CFRP) materials have been extensively used in the aerospace field due to their performance over traditional metal materials, and their usage has reached 50% in advanced civil aircraft such as Airbus A350 and Boeing B787 [1,2]. Automatic fiber placement (AFP) machines are the key equipment for the industrial manufacturing of composite components, which mainly consists of a set of motion equipment and a self-contained fiber placement head. A fiber placement head can independently clamp, refeeding and cut several (8-32) composite tows to form a tape, and then heat and compact them on mould surface simultaneously [1,3,4]. It is thus flexible and suitable for the placement of complex composite components. Since the movement of the fiber placement head is provided by the motion equipment, there is no doubt that the dynamic characteristics of the motion equipment directly determine the efficiency and quality of the composite component manufacturing.

With the continuous pursuit of the fiber placement efficiency, the speed of the AFP machine is also increasing, which has been reached 50 m/min. Such high speed requires the driving force of the motion axis can be able to change rapidly in a large range. However, limited by the performance of traditional controllers, problems such as low control accuracy and slow response speed are inevitable to be introduced, which seriously deteriorate the dynamic characteristics of the motion equipment. Due to this, advanced controllers based on dynamic models have attracted widespread attention and become a focus in control field [5-8]. As the basis of these advanced controllers, the dynamic model of the motion equipment has to be studied first.

Of all the dynamic modeling methods, the two most frequently used are the Newton-Euler method and the Lagrangian method. Among them, the Newton-Euler method is based on the idea of iteration, which has a clear physical meaning and high computational efficiency, and the Lagrangian method is based on the idea of energy balance, which avoids the derivation of internal force of joints and reduces the difficulty of modeling. But the dynamic equations established by these two methods are equivalent. Hwang et al. [9] developed a recursive formulation for flexible dynamic manufacturing analysis of open-loop systems with the Newton-Euler method. Lee et al. [10] presented the dynamic analysis of a 3-degree-of-freedom (DOF) in-parallel actuated manipulator using the Lagrangian approach. These two methods are also widely used in the dynamic modeling of robotics [11-14]. Besides, Mahmoud [15] pointed out that the dynamic model established by the Newton-Euler method was more appropriate to be linearized. Indeed, with the advantage of clear physical meaning, the dynamic equation established by the Newton-Euler method can be converted into a linear form of multiplication of inertia parameters and kinematic parameters through appropriate derivation, which is more suitable for the application in parameter identification and linearity control.

In addition, inertia parameters in the dynamic model of the linear form above can be further linearly combined to generate the minimum inertial parameters. This is an essential property of the dynamic equation, which has great advantages in simplifying the dynamic calculation, inertia parameter identification, and control system design and analysis, etc. [16]. There are many attempts have been made to determine the minimum inertial parameters in robot fields. At the end of the 20th century, Gautier M [17-19] and W Khalil et al. [20,21] proposed recursive formulations to directly calculate the minimum inertial parameters of robots with D-H parameters. As time goes, professional toolkits such as Symoro [22,23] and Pybotics [24] are developed for robots, which bring great convenience to researchers in the calculation. Unfortunately, the calculation method of the minimum inertia parameters is highly determined by the definition of a joint coordinate system. Different from the D-H method for robots, the joint coordinate systems of the AFP machine are established by the multi-body system (MBS) theory. Therefore, the recursive formulations in the above literature are no longer applicable and need to be re-derived.

After the dynamic model in the form of linearized minimum inertial parameters is established, how to acquire the inertia parameters is an essential problem that has a great impact on the accuracy

of the dynamic model. Due to the existence of manufacture errors, assembly errors as well as friction during the motion, the inertia parameters are generally not obtained from the CAD model directly, but by means of parameter identification [25-27]. A standard parameter identification procedure consists of modeling, experiment design, data acquisition, signal processing, parameter estimation, and model validation. Atkeson et al. [28] selected the fifth-order polynomial in joint space as the excitation trajectory and used the least-square method for parameter estimation; Swevers et al. [29] proposed an excitation trajectory based on a finite Fourier series, which was periodic and could average multiple sampled data to improve the signal-to-noise ratio; Olsen et al. [30] adopted the maximum likelihood method to estimate dynamic parameters with measurement noise successfully. In this paper, the improved finite Fourier series is selected as the excitation trajectory, and the weighted least-squares (WLS) method is adopted as the parameter estimation algorithm.

Dynamic modeling and parameter identification have been widely studied in robot fields, and the methods that involve dynamic model linearization and determination of minimum inertial parameters are mature. However, in the fields of traditional machine tools, whose kinematic and dynamic modeling is generally utilizing the MBS theory, because of their low operating speed, the dynamic models of the machine tools seem less important, hence the methods for dynamic model linearization and determination of minimum inertial parameters based on MBS theory are rarely mentioned in past literature. In contrast, as far as the AFP machine is concerned, the dynamic model is indispensable to get the high performance under high speed, therefore, issues about the dynamic modeling and parameter identification for a gantry-type AFP machine are studied, and remains are organized as follows: Section 2 is devoted to the dynamic modeling process of the AFP machine and analyses the methods of dynamic model linearization and determination of minimum inertial parameters; Section 3 investigates the excitation trajectory and the parameter identification method; Section 4 develops the corresponding experiments and discusses the results, and Section 5 concludes the paper and proposes the direction of future.

2. Dynamic modeling of the AFP machine

The gantry-type AFP machine, as shown in Fig.1, has the characteristics of large strokes, large spans, and heavy loads, and it is suitable for the manufacture of large-size composite components such as wing panels. This is a 6-DOF equipment composed of three prismatic axes, three revolute axes, and a fiber placement head with 16 groups of tow control mechanisms. Furthermore, the height of the gantry frame is nearly 7.9 m, the span of the beam reaches 12.7 m, and the head weighs up to 1000 kg.

Among the six motion axes of the gantry-type AFP machine, the first three are prismatic axes named X-, Y-, and Z-axis, and they are perpendicular to each other. The last three are revolute axes called B-, A-, C-axis, and they rotate around Y-axis, X-axis and Z-axis respectively. It is worth mentioning that the Z-axis adopts a hydraulic balance system to reduce the influence of gravity on the drive motors. Moreover, the B-axis is designed as an arc guide rail structure to reduce the

distance between the A-axis rotation center and the tail end of the fiber placement head, thus improving the flexibility of the machine.

Several coordinate systems are established by MBS theory to describe the motion of the axes, which are the base coordinate system $\{O_{Base}\}$, the local coordinate system on each motion axis $\{O_X\}$, $\{O_Y\}$, $\{O_Z\}$, $\{O_B\}$, $\{O_A\}$, $\{O_C\}$, and the head coordinate system $\{O_H\}$, and their origin locations are shown in Fig.1. In addition, L_a and L_h are the offset lengths between coordinate systems.

Fig.1 The gantry-type AFP machine and its coordinate systems

For efficient placement of large size composite components, three prismatic axes of the gantry-type AFP machine are designed with large strokes and high speeds. According to the design indexes, the motion parameters of each axis are shown in Table 1.

Table 1 Motion parameters of each axis

Axis	Stroke	Max velocity	Max acceleration
X	-8900~8970 (mm)	500 (mm/s)	750 (mm/s ²)
Y	-3500~3500 (mm)	500 (mm/s)	750 (mm/s ²)
Z	-235~1990 (mm)	500 (mm/s)	750 (mm/s ²)
B	-90~90 (°)	20 (°/s)	50 (°/s ²)
A	-20~20 (°)	50 (°/s)	120 (°/s ²)
C	-180~180 (°)	50 (°/s)	250 (°/s ²)

2.1 Dynamic modeling process based on the Newton-Euler method

The Newton-Euler method is adopted to establish the dynamic model of the AFP machine. In order to simplify the calculation, the motion of the C-axis is ignored during the modeling process for the following reasons: (a) The head has a symmetrical structure and uniform mass along the rotation centerline of the C-axis, therefore, the offset torque generated by the C-axis motion is small; (b) Due to the material properties of composite tows, a small turning radius of the head in placing

direction may cause defects such as wrinkles, therefore, the C-axis cannot rotate rapidly. In a summary, the dynamic model of the AFP machine is reduced to five axes.

Based on the coordinate systems established in Fig.1, a dynamic modeling process of the AFP machine combining prismatic axes and revolute axes is introduced. At first, axes of the AFP machine are numbered, 1, 2, 3, 4, 5 for X, Y, Z, B, A, and then, forward kinematic recursion and reverse dynamic recursion are conducted.

The forward kinematic recursion mainly calculates the angular velocity, angular acceleration and linear acceleration of each axis, where the prismatic axis and the revolute axis should be distinguished.

For prismatic axis

$$\begin{cases} {}^{i+1}\boldsymbol{\omega}_{i+1} = {}^iR^{i+1} \boldsymbol{\omega}_i \\ {}^{i+1}\dot{\boldsymbol{\omega}}_{i+1} = {}^iR^{i+1} \dot{\boldsymbol{\omega}}_i \\ {}^{i+1}\dot{\boldsymbol{v}}_{i+1} = {}^iR^{i+1} \left(\dot{\boldsymbol{\omega}}_i \times {}^iP_{i+1} + \boldsymbol{\omega}_i \times (\boldsymbol{\omega}_i \times {}^iP_{i+1}) + \dot{\boldsymbol{v}}_i \right) \\ \quad + 2 {}^{i+1}\boldsymbol{\omega}_{i+1} \times \dot{\boldsymbol{d}}_{i+1} + \ddot{\boldsymbol{d}}_{i+1} \end{cases} \quad (1)$$

For revolute axis

$$\begin{cases} {}^{i+1}\boldsymbol{\omega}_{i+1} = {}^iR^{i+1} \boldsymbol{\omega}_i + \dot{\boldsymbol{\theta}}_{i+1} \\ {}^{i+1}\dot{\boldsymbol{\omega}}_{i+1} = {}^iR^{i+1} \dot{\boldsymbol{\omega}}_i + {}^iR^{i+1} \boldsymbol{\omega}_i \times \dot{\boldsymbol{\theta}}_{i+1} + \ddot{\boldsymbol{\theta}}_{i+1} \\ {}^{i+1}\dot{\boldsymbol{v}}_{i+1} = {}^iR^{i+1} \left(\dot{\boldsymbol{\omega}}_i \times {}^iP_{i+1} + \boldsymbol{\omega}_i \times (\boldsymbol{\omega}_i \times {}^iP_{i+1}) + \dot{\boldsymbol{v}}_i \right) \end{cases} \quad (2)$$

where ${}^{i+1}\boldsymbol{\omega}_{i+1}$, ${}^{i+1}\dot{\boldsymbol{\omega}}_{i+1}$ and ${}^{i+1}\dot{\boldsymbol{v}}_{i+1}$ are the 3×1 vector of angular velocity, angular acceleration and linear acceleration of axis $i+1$ in the coordinate system $i+1$ respectively; ${}^iR^{i+1}$ and ${}^iP_{i+1}$ are the 3×3 rotation matrix and the 3×1 position vector of the coordinate system i to the coordinate system $i+1$; $\dot{\boldsymbol{d}}_{i+1}$ and $\ddot{\boldsymbol{d}}_{i+1}$ are the 3×1 vector of translation velocity and acceleration of the prismatic axis; $\dot{\boldsymbol{\theta}}_{i+1}$ and $\ddot{\boldsymbol{\theta}}_{i+1}$ are the 3×1 vector of rotation velocity and acceleration of the revolute axis.

According to the above two equations, the translation acceleration at the center of mass of each axis can be deduced

$${}^{i+1}\dot{\boldsymbol{v}}_{C_{i+1}} = {}^{i+1}\dot{\boldsymbol{\omega}}_{i+1} \times {}^{i+1}P_{C_{i+1}} + {}^{i+1}\boldsymbol{\omega}_{i+1} \times (\boldsymbol{\omega}_{i+1} \times {}^{i+1}P_{C_{i+1}}) + {}^{i+1}\dot{\boldsymbol{v}}_{i+1} \quad (3)$$

where ${}^{i+1}P_{C_{i+1}}$ is the 3×1 position vector of the center of mass of axis $i+1$ in the coordinate system $i+1$.

By substituting ${}^{i+1}\dot{\boldsymbol{v}}_{C_{i+1}}$, ${}^{i+1}\boldsymbol{\omega}_{i+1}$ and ${}^{i+1}\dot{\boldsymbol{\omega}}_{i+1}$ into the Newton-Euler equation, the inertial force ${}^{i+1}\boldsymbol{F}_{C_{i+1}}$ and inertia torque ${}^{i+1}\boldsymbol{N}_{C_{i+1}}$ at the center of mass of each axis are obtained

$$\begin{cases} {}^{i+1}\mathbf{F}_{C_{i+1}} = m_{i+1} {}^{i+1}\dot{\mathbf{v}}_{C_{i+1}} \\ {}^{i+1}\mathbf{N}_{C_{i+1}} = {}^{C_{i+1}}\mathbf{I}_{i+1} {}^{i+1}\dot{\boldsymbol{\omega}}_{i+1} + {}^{i+1}\boldsymbol{\omega}_{i+1} \times {}^{C_{i+1}}\mathbf{I}_{i+1} {}^{i+1}\boldsymbol{\omega}_{i+1} \end{cases} \quad (4)$$

where m_{i+1} and ${}^{C_{i+1}}\mathbf{I}_{i+1}$ is the mass and the symmetric inertia matrix in the coordinate system of the center of mass of axis $i+1$.

Finally, transfers of the force and the torque of each axis are calculated by reverse dynamic recursion

$$\begin{cases} {}^i\mathbf{f}_i = {}^i\mathbf{F}_{C_i} + {}^{i+1}\mathbf{R} {}^{i+1}\mathbf{f}_{i+1} \\ {}^i\mathbf{n}_i = {}^i\mathbf{N}_{C_i} + {}^{i+1}\mathbf{R} {}^{i+1}\mathbf{n}_{i+1} + {}^i\mathbf{P}_{C_i} \times {}^i\mathbf{F}_{C_i} + {}^i\mathbf{P}_{i+1} \times {}^{i+1}\mathbf{R} {}^{i+1}\mathbf{f}_{i+1} \end{cases} \quad (5)$$

where ${}^i\mathbf{f}_i$ and ${}^i\mathbf{n}_i$ is the resultant force and resultant torque of axis i . The component of ${}^i\mathbf{f}_i$ in the direction of prismatic axis is the driving force if_i , and the component of ${}^i\mathbf{n}_i$ in the direction of revolute axis is the driving torque in_i .

According to equation (1) ~ equation (5), the dynamic modeling process of the gantry-type AFP machine combining prismatic axes and revolute axes is shown in Fig.2, where n is the number of axes, and g is the acceleration of gravity.

Fig.2 Dynamic modeling process of the AFP machine

From the modeling process in Fig.2, a dynamic model of the AFP machine can be summarized as a second-order differential equation

$$\mathbf{M}(\mathbf{q})\ddot{\mathbf{q}} + \mathbf{C}(\mathbf{q}, \dot{\mathbf{q}}) + \mathbf{G}(\mathbf{q}) = \boldsymbol{\tau}_d \quad (6)$$

where $\mathbf{q} = [x \ y \ z \ b \ a]^T$ is the position vector, $\mathbf{M}(\mathbf{q})$ is the mass matrix, $\mathbf{C}(\mathbf{q}, \dot{\mathbf{q}})$ is the centrifugal force and Coriolis force, $\mathbf{G}(\mathbf{q})$ is the gravity component and $\boldsymbol{\tau}_d = [f_x \ f_y \ f_z \ n_b \ n_a]^T$ is the generalized driving force vector.

2.2 Considering friction and hydraulic balance system

When the actual situations of the AFP machine are considered, the dynamic equation needs some modifications, to be specific, the effect of friction and the hydraulic balance system.

Friction should be treated as an additional factor since it is always regarded as the main error of motion. Although friction is a complex nonlinear phenomenon, its linear approximation model including Coulomb and viscous friction can guarantee accuracy, which is extensively used and can be expressed as [12]

$$\tau_f = f_c \text{sign}(\dot{q}) + f_v \dot{q} \quad (7)$$

where f_c is the coefficient of Coulomb friction, f_v is the coefficient of viscous friction, $\dot{q}$ is the velocity of axis, and sign is a symbolic function

$$\text{sign}(\dot{q}) = \begin{cases} 1 & \dot{q} > 0 \\ -1 & \dot{q} < 0 \end{cases} \quad (8)$$

Therefore, the dynamic model considering friction is revised as follows

$$M(q)\ddot{q} + C(q, \dot{q}) + G(q) + F_f(\dot{q}) = \tau_d \quad (9)$$

where $F_f(\dot{q})$ is the component of friction.

In addition to friction, the hydraulic balance system also has a great impact on the Z-axis. Since the total weight of the Z-axis, B-axis, A-axis, C-axis and the fiber placement head exceeds 10 t, the Z-axis servo drive system will always maintain a large unilateral force if there is no gravity balance method taken, and this unilateral force severely limits the Z-axis motion performance and shortens the life of the Z-axis motor. This problem can be effectively alleviated by the use of the hydraulic balance system, and the driving force of the Z-axis can be expressed as

$$\begin{cases} f_z^s = f_z^s + f_z^h \\ f_z^h = PA \end{cases} \quad (10)$$

where f_z^s is the driving force provided by the servo drive system, f_z^h is the driving force provided by the hydraulic balance system, P is the hydraulic pressure which can be obtained from the pressure sensor, and A is the effective area of the hydraulic cylinder piston. So far, the establishment of the dynamic model is completed.

This dynamic model characterizes the relationship between the motion and the driving force or torque of the AFP machine. However, it is a nonlinear equation where the inertial parameters and the kinematic parameters are coupled and less convenient for parameter identification and application in linearity control. Thus, to linearize the dynamic model to separate the inertial parameters and the kinematic parameters should be done.

2.3 Dynamic model linearization and determination of minimum inertial parameters

With the help of the parallel axis theorem, the symmetric inertia matrix of each axis in the coordinate

system of the center of mass can be transformed into a representation in the joint coordinate system, by this way, the dynamic model can be written as a linear form of inertia parameters

$$\boldsymbol{\tau}_d = \mathbf{Y}\mathbf{P} \quad (11)$$

this is an important property of the dynamic equation, where $\mathbf{Y}$ is an observation matrix composed of the kinematic parameters, including the position, velocity, acceleration of each axis, and the offset lengths between coordinate systems; $\mathbf{P}$ is an inertia vector composed of the inertial parameters, including the symmetric inertia matrix, mass, position of the center of mass and friction coefficients of each axis. Due to the complicated process, the specific derivation of the linear form based on the MBS theory for the dynamic equation is presented in Appendix A.

However, not every inertial parameter in $\mathbf{P}$ has an impact on the dynamic model [17,18], in other word, there are column vectors of zero or linearly dependent columns in the observation matrix $\mathbf{Y}$, which make the matrix $\mathbf{Y}$ not full-rank. Therefore, the inertial vector $\mathbf{P}$ needs to be simplified through recombining some inertial parameters by certain linear relationships or using simple closed-form rules to eliminate some inertial parameters to obtain minimum inertial parameters.

For this reason, recursive formulations of the determination of minimum inertial parameters based on the MBS theory are proposed. Similarly, a detailed derivation process is shown in Appendix B for concision of the body of the paper. Finally, the dynamic equation of the AFP machine in the form of linearized minimum inertia parameters is obtained

$$\boldsymbol{\tau}_d = \mathbf{Y}_m \mathbf{P}_m \quad (12)$$

this equation is completely equivalent to equation (9) and equation (11), and it is a linear form, where redundant items are removed by linear combination, therefore, it not only dramatically reduces the calculation of the equation, but also has a huge advantage in the identification of $\mathbf{P}_m$.

Each axis has 10 inertia parameters and two friction coefficients, and the AFP machine therefore has a total of 60 dynamic parameters in vector $\mathbf{P}$. After calculation of the minimum inertial parameters, there are only 23 parameters left in the minimum parameter vector $\mathbf{P}_m$, 13 of which are the combined inertial parameters, and the remaining 10 are the friction coefficients.

By combining equation (12) with N sampled data on a trajectory, a statically indeterminate linear equation is obtained

$$\boldsymbol{\tau}_d^N = \begin{bmatrix} \boldsymbol{\tau}_d(t_1) \\ \boldsymbol{\tau}_d(t_2) \\ \vdots \\ \boldsymbol{\tau}_d(t_N) \end{bmatrix} = \begin{bmatrix} \mathbf{Y}_m(t_1) \\ \mathbf{Y}_m(t_2) \\ \vdots \\ \mathbf{Y}_m(t_N) \end{bmatrix} \mathbf{P}_m = \mathbf{Y}_m^N \mathbf{P}_m \quad (13)$$

where $\mathbf{Y}_m^N$ is the measurement matrix of $5N \times 23$, and $\boldsymbol{\tau}_d^N$ is the generalized driving force vector of $5N \times 1$. Since this equation is linear, the parameters in the vector $\mathbf{P}_m$ can be easily calculated as long as the values of the $\mathbf{Y}_m^N$ and the $\boldsymbol{\tau}_d^N$ are collected from the experiment.

3. Excitation trajectory and parameter identification

As the dynamic equation in the form of linearized minimum inertia parameters is established above, the determination of the inertial parameter values becomes a key issue, which directly affects the accuracy of the dynamic model. In the actual situations, due to the additional weight of cables, actuators, guide rails, sliding blocks, drive motors and guard bars, as well as the influence of manufacture errors, friction, etc., the accuracy of the dynamic model established by the theoretical inertia parameters is poor. Using the method of parameter identification to obtain a set of comprehensive parameters that meet the accuracy of dynamic calculation, is one of the effective ways to improve the accuracy of the dynamic model.

The main process of parameter identification is as follows: (a) Design an excitation trajectory to drive the machine; (b) Collect necessary data while the machine is moving; (c) Process the collected data; (d) Substitute the processed data into the dynamic model and identify the inertial parameters with parameter estimation algorithm; (e) Verify the identified parameters.

3.1 Excitation trajectory

The result of parameter identification depends on the quality of the excitation trajectory. In order to identify all the unknown parameters of the model, the excitation trajectory should be able to excite the whole system, otherwise, some parameters may be unable to be identified or sensitive to measurement noise.

In this paper, an improved finite Fourier series is used as the excitation trajectory of each axis

$$q_i(t) = \sum_{k=0}^n c_{i,k} t^k + \sum_{k=1}^n \left(\frac{a_{i,k}}{k\omega_f} \sin(k\omega_f t) + \frac{b_{i,k}}{k\omega_f} \cos(k\omega_f t) \right) \quad (14)$$

where t is time, ω_f is fundamental frequency, n is the harmonic item number of Fourier series, usually 5 is adopted, $a_{i,k}$, $b_{i,k}$, $c_{i,k}$ are the harmonic or polynomial coefficients, and the velocity and acceleration can be calculated by differentiating this equation.

Define the boundary conditions of the trajectory to guarantee the velocity and acceleration at the start and stop of the trajectory are zero

$$\begin{cases} q_i(0) = q_{i1} & q_i(2\pi / \omega_f) = q_{i2} \\ \dot{q}_i(0) = 0 & \dot{q}_i(2\pi / \omega_f) = 0 \\ \ddot{q}_i(0) = 0 & \ddot{q}_i(2\pi / \omega_f) = 0 \end{cases} \quad (15)$$

where q_{i1} and q_{i2} are the positions of the start and stop of the trajectory, respectively, and the coefficients $c_{i,k}$ can be eliminated by solving the above six equations. The improved finite Fourier series excitation trajectory adopts a polynomial to replace the constant term of traditional finite Fourier series to realize the constraint of boundary conditions, thus reducing the start-stop shock and improving the validity of the measurement data of the entire trajectory.

Unmodeled errors and measurement noise will affect the accuracy of parameter identification, and their influence can be reduced by optimizing the excitation trajectory coefficients. According to the statically indeterminate linear equation (13), the condition number of the measurement matrix $\mathbf{Y}_m^N$ reflects the anti-noise ability of the identification method and the convergence rate of parameter estimation when calculation, the smaller the value, the smaller the influence of the disturbance on the identification result. Therefore, its condition number is defined as the objective function of the excitation trajectory coefficient optimization

$$J = \min \left\{ \text{cond}(\mathbf{Y}_m^N) \right\} \quad s.t. \begin{cases} \mathbf{q}_{\min} \leq \mathbf{q}(t) \leq \mathbf{q}_{\max} \\ \dot{\mathbf{q}}_{\min} \leq \dot{\mathbf{q}}(t) \leq \dot{\mathbf{q}}_{\max} \\ \ddot{\mathbf{q}}_{\min} \leq \ddot{\mathbf{q}}(t) \leq \ddot{\mathbf{q}}_{\max} \end{cases} \quad (16)$$

where $\mathbf{q}_{\min}$, $\mathbf{q}_{\max}$, $\dot{\mathbf{q}}_{\min}$, $\dot{\mathbf{q}}_{\max}$, $\ddot{\mathbf{q}}_{\min}$, $\ddot{\mathbf{q}}_{\max}$ are the constraints of position, velocity and acceleration, see Table 1 for specific values. To solve this multi-objective optimization problem with inequality constraints, the “fmincon” function in MATLAB is adopted to calculate the optimal coefficients of the excitation trajectory.

3.2 Measurement data processing

After the excitation trajectory is optimized, the AFP machine should track it repeatedly. At the same time, the relevant data are sampled at a constant, user-specified frequency. Subsequently, as the sampled data are often polluted by noise, they need to be processed accordingly to improve their validity.

Since the improved finite Fourier series is used as the excitation trajectory in this paper, the signal-to-noise ratio of the sampled data can be improved by the time-domain averaging method, so that the contingency of the identification results is reduced

$$\begin{cases} \bar{q}_i(k) = \frac{1}{M} \sum_{j=1}^M q_{ij}(k) \\ \bar{\tau}_i(k) = \frac{1}{M} \sum_{j=1}^M \tau_{ij}(k) \end{cases} \quad (17)$$

where M is the times of repetition, k represents the k^{th} sampling.

A five-point triple smoothing method is further adopted to filter the sampled data, and the high-frequency random noise in the sampled data can be effectively removed

$$\begin{cases} \bar{y}_1 = [69y_1 + 4(y_2 + y_4) - 6y_3 - y_5] / 70 \\ \bar{y}_2 = [2(y_1 + y_5) + 27y_2 + 12y_3 - 8y_4] / 35 \\ \bar{y}_i = [-3(y_{i-2} + y_{i+2}) + 12(y_{i-1} + y_{i+1}) + 17y_i] / 35 \\ \bar{y}_{m-1} = [2(y_{m-4} + y_m) - 8y_{m-3} + 12y_{m-2} + 27y_{m-1}] / 35 \\ \bar{y}_m = [-y_{m-4} + 4(y_{m-3} + y_{m-1}) - 6y_{m-2} + 69y_m] / 70 \end{cases} \quad (18)$$

where $\mathbf{y} = [y_1 \ y_2 \ \cdots \ y_m]$ are the original sampled data, and $\bar{\mathbf{y}} = [\bar{y}_1 \ \bar{y}_2 \ \cdots \ \bar{y}_m]$ are the filtered data.

In order to avoid noise being amplified in direct difference process, an analytical approach [29] is employed to estimate the velocity and acceleration of each axis. The premise of this approach is that each axis of the machine can accurately track the excitation trajectory, and specific steps are as follows: (a) Fit the data of position to Fourier series via least-square method; (b) Differentiate the fitting Fourier series to get the velocity and acceleration. This approach can effectively decrease noise.

3.3 Parameter identification

Next, the unknown parameters in the dynamic model can be identified. Parameter identification is the method that combines model and measurement data, and then calculates the parameters with an identification algorithm. Consequently, by substituting the processed measurement data into equation (13), an overdetermined linear equation is constructed

$$\boldsymbol{\tau}_d^N = \mathbf{Y}_m^N (\mathbf{q}, \dot{\mathbf{q}}, \ddot{\mathbf{q}}) \mathbf{P}_m + \boldsymbol{\xi} \quad (19)$$

where $\mathbf{P}_m$ is the minimum parameter vector that needs to be identified, and $\boldsymbol{\xi}$ represents the measurement error noise with zero mean normal distribution.

The classic least-square method is the universal method in solving overdetermined systems of linear equations, and as follows

$$\mathbf{P}_m = \left((\mathbf{Y}_m^N)^T \mathbf{Y}_m^N \right)^{-1} (\mathbf{Y}_m^N)^T \boldsymbol{\tau}_d^N \quad (20)$$

but this method assumes that measurement torque is polluted by white Gaussian noise and all standard deviation of actuator torque noise is the same. This assumption cannot be met, resulting in less accuracy of estimation of parameters. However, due to its simplicity, the least-square method is still widely used in many applications.

The improvement of the least-square method is the WLS method, whose error is weighted by a weighted matrix, thereby the accurate and inaccurate data can be distinguished

$$\mathbf{P}_m = \left((\mathbf{Y}_m^N)^T \boldsymbol{\Sigma}^{-1} \mathbf{Y}_m^N \right)^{-1} (\mathbf{Y}_m^N)^T \boldsymbol{\Sigma}^{-1} \boldsymbol{\tau}_d^N \quad (21)$$

where $\boldsymbol{\Sigma}$ is the weighted matrix. Therefore, the WLS method is selected as the parameter estimation method in this paper.

3.4 Model verification

The effectiveness of the identification method and the accuracy of the identified parameters must be demonstrated in convincing ways. Generally, corresponding verification experiments need to be performed, as illustrated in Fig.3.

Fig.3 Identification and verification process

The prediction error of the dynamic model is quantified by calculating the residual root mean square (RMS), and the calculation formula is as follows

$$RMS = \sqrt{\frac{1}{n} \sum_{i=1}^n (\tau_m(i) - \tau_d(i))^2} \quad (22)$$

where n is sampling times, $\tau_m(i)$ is the i^{th} measured value of the verification trajectory, $\tau_d(i)$ is the i^{th} predictive value of the dynamic model.

The absolute value of the prediction error can be reflected by the RMS, while the relative value can be described by the relative error rate

$$\sigma = \frac{RMS}{\text{Max}(\tau_m) - \text{Min}(\tau_m)} \times 100\% \quad (23)$$

τ_m is a vector of measurement data. The RMS and the relative error rate represent the uncertainty of the prediction error, the smaller their value, the better the model prediction.

4. Experiment and discussion

To identify the inertial parameters, as well as verify the effectiveness of the established dynamic model and the parameter identification method, corresponding experiments were carried out on the self-developed gantry-type AFP machine, whose control system is developed based on the

TwinCAT3 of Beckhoff company. The experimental platform is shown in Fig.4, including a gantry-type AFP machine and an operating console.

Fig.4 Experimental platform

The first one performed was the identification experiment, in which the basic frequency of the excitation trajectory was selected as $\omega_f = 0.08\pi$ Hz, and the motion period was thereby 25 s. After optimization calculation, an optimal excitation trajectory with the condition number of the measurement matrix of 505.8 was obtained. The excitation trajectory was discretized every 0.01 s (FIFO period is 0.01 s) to create an executable file, which was then imported into the FIFO of the control system to drive the AFP machine. Meanwhile, the position of each axis, the torque of each axis drive motor, and the hydraulic pressure were sampled in real-time with a sampling interval of 0.01 s. By the way, the AFP machine was operated to repeated the excitation trajectory 10 times.

Took the average value of the 10 groups of sampled data, and the measurement trajectory of each axis was compared with the excitation trajectory, as shown in Fig.5. It can be found from the figures that the measurement trajectory is highly coincident with the excitation trajectory, and the condition number of the measurement trajectory is 569.0, which is very close to that of the excitation trajectory, indicating that the axes of the AFP machine track the excitation trajectory well. Subsequently, the velocity and the acceleration of each axis were calculated by the analytical approach mentioned in Section 3.

Fig.5 Comparison of the excitation trajectory and the measurement trajectory

For the output torque in the sampled data, in addition to the average processing, they must be filtered and then multiplied by the reduction ratio of each axis respectively. Moreover, the torque of the prismatic axes also needed to divide by the gear index circle radius to get the driving force, and the servo force of the Z-axis should additionally add the averaged hydraulic force. Finally, the driving force of the three prismatic axes and the driving torque of the two revolute axes before and after filtering were obtained, as shown in Fig.6.

Fig.6 Force or torque of each axis before and after filtering

With all the necessary data obtained above, the minimum parameters of the AFP machine were identified, as shown in Table 2, where the theoretical values of combined inertial parameters were also listed to facilitate comparison.

Table 2 Minimum parameters of the gantry-type AFP machine

Combined inertial parameter	Identification value	Theoretical value	Friction coefficient	Identification value
m_x (kg)	42082.82	38596.12	f_{cx} (N)	2171.53
m_y (kg)	4704.92	3757.60	f_{vx} (N·s/m)	28749.51
$m_z + m_b + m_a$ (kg)	10592.81	9120.87	f_{cy} (N)	912.89

$m_a L_a^2 + I_b^{yy} + I_a^{zz}$ (kg·m)	3218.99	1747.07	f_{vy} (N·s/m)	6910.98
$m_b r_b^{cx} + m_a r_a^{cx}$ (kg·m)	88.29	16.06	f_{cz} (N)	2156.44
$m_b r_b^{cz} + L_a m_a$ (kg·m)	-894.99	-683.84	f_{vz} (N·s/m)	23868.97
I_a^{xx} (kg·m ²)	4667.69	1309.73	f_{cb} (N)	1040.34
I_a^{xy} (kg·m ²)	276.12	0.004	f_{vb} (N·s/rad)	3544.07
I_a^{xz} (kg·m ²)	-240.30	1.43	f_{ca} (N)	697.46
$I_a^{yy} - I_a^{zz}$ (kg·m ²)	3681.01	904.81	f_{va} (N·s/rad)	4859.98
I_a^{yz} (kg·m ²)	397.16	-0.006		
$m_a r_a^{cy}$ (kg·m)	112.35	0		
$m_a r_a^{zy}$ (kg·m)	1445.68	927.3		

From Table 2, we can see that the identification values of the inertia parameter are slightly larger than the theoretical values. Since the theoretical values are obtained from the CAD model, which ignores the quality of servo motors, electrical hardware, cables, accumulators, and oil circuit, etc., the identification result can be considered credible.

What is more, it also can be found that the friction coefficients of X- and Z-axis are significantly larger than those of other axes, whose coefficients of viscous friction all exceed 20000 N·s/m, which implies these two axes are under great friction during the movement and may need some lubrication.

The identified parameters were then substituted into the equation (12), and a complete dynamic model of the gantry-type AFP machine was established.

To further verify the accuracy of the identified parameters, the concept of cross-validation was adopted and two verification trajectories different from the above-mentioned excitation trajectory were designed to drive the AFP machine. Each verification trajectory was repeated 5 times.

After the sampled data were processed accordingly, the measured values of the driving force and driving torque of each axis were obtained. At the same time, the predictive values of the driving force and driving torque of each axis were also calculated through the dynamic model and the identified parameters. Subsequently, the measured values and the predictive values were compared, and a comparison of the verification trajectory I was shown in Fig.7, comparison of the verification trajectory II was shown in Fig.8.

Fig.7 Comparison of verification trajectory I

Fig.8 Comparison of verification trajectory II

Fig.7 and Fig.8 illustrate that the predictive curves are highly consistent with the measured curves, which efficiently proves the accuracy of the dynamic model and the identified parameters. However, when observing the difference curve of each figure, we can discover that the prediction errors are small but there are some jump values. The reason for this phenomenon is that the static continuous linear friction model used in this paper cannot represent the actual no-linear friction at low velocity, leading to large prediction errors and affecting identification accuracy.

Particularly, it should be pointed out that there are apparent errors at the corner between the predictive curves and the measured curves of the Z-axis (red circles in the figures). Because the driving force of the Z-axis is provided by both the hydraulic balance system and the servo drive system, the hydraulic system responds slowly while the servo system responds fast, the difference between them may have significant effects on the prediction accuracy of the Z-axis, introducing a huge error when the direction of the driving force switches.

Finally, the RMS and the relative error rate of the excitation trajectory and two verification trajectories were calculated, and the results were shown in Table 3. It can be seen that, except for Z-axis, the RMS of each axis in three trajectories is relatively small, and the relative error rates are

only within 5%, which further verify the good performance of the identification result. Although the relative error rates of the Z-axis are relatively large, they still do not exceed 10%.

Table 3 the RMS and the relative error rate of each axis

Axis	Excitation trajectory		Verification trajectory I		Verification trajectory II	
	RMS	σ	RMS	σ	RMS	σ
X	531.41 (N)	4.03%	620.08 (N)	4.36%	554.00 (N)	4.96%
Y	198.47 (N)	3.15%	217.54 (N)	3.99%	208.38 (N)	3.86%
Z	1142.0 (N)	9.30%	816.94 (N)	7.59%	921.12 (N)	8.06%
B	332.44 (N·m)	2.11%	358.64 (N·m)	3.63%	365.37 (N·m)	2.89%
A	356.72 (N·m)	2.32%	284.58 (N·m)	1.88%	345.79 (N·m)	2.34%

Through the analysis of the above figures and tables, it can be concluded that in spite the friction model used in this paper does not reflect the actual situation well, and there is a mismatch between the response speed of the hydraulic system and the servo system, the established dynamic model and the identified dynamic parameters still have high accuracy.

5. Conclusions

Dynamic modeling and parameter identification of a gantry-type AFP machine are studies in this paper, and the research results can provide a model foundation for the model-based controllers. The main contribution of this paper is proposing recursive formulations of the dynamic model linearization and the determination of minimum inertial parameters based on the MBS theory. The methods studied in this paper can also provide guidance for dynamic modeling and inertial parameter identification for other high-speed machine tools.

Firstly, the Newton-Euler method is adopted to establish the dynamic model of the gantry-type AFP machine, in which friction and the hydraulic balance system are also considered. Secondly, based on the MBS theory, the recursive formulations of the dynamic model linearization and the determination of minimum inertial parameters are deduced, which bring great convenience for subsequent parameter identification. Thirdly, discuss the problems of parameter identification including excitation trajectory, filtering, parameter identification, and verification. Finally, experiments have been carried out on the gantry-type AFP machine, and the dynamic parameters are identified and verified successfully. The experimental results show that, although the friction model used in this paper cannot reflect the actual situation well, except for Z-axis, the prediction relative error rates of others still do not exceed 5%, which proves the accuracy of the dynamic model and the identified parameters.

Satisfactory results indeed are obtained in this paper, however, due to the lack of research about the hydraulic balance system, the problem that large prediction errors of Z-axis driving force has not been solved yet, which will be the study focus in the future.

Appendix A: Dynamic equation linearization

The key to linearization of the dynamic equation is the separation of kinematic parameters and inertial parameters. Observing the dynamic modeling process, we found that these two parts of the parameters are coupled in the Newton-Euler equation and the reverse torque recursion process. Therefore, as long as these equations are linearized, the entire dynamic equation can be linearized.

Firstly, define 10 inertia parameters for each axis

$$\mathbf{P}_i = \begin{bmatrix} I_i^{xx} & I_i^{xy} & I_i^{xz} & I_i^{yy} & I_i^{yz} & I_i^{zz} & m_i r_i^{cx} & m_i r_i^{cy} & m_i r_i^{cz} & m_i \end{bmatrix}^T \quad (24)$$

where $I_i^{xx} \square I_i^{zz}$ are the parameters in the symmetric inertia matrix expressed in the coordinate system of the center of mass of axis i ; $m_i r_i^{cx} \square m_i r_i^{cz}$ are the product of the axis mass m_i and the center of mass coordinate vector ${}^i\mathbf{P}_{C_i}$, m_i is the mass of the axis i .

For Newton's equation

$${}^i\mathbf{F}_{C_i} = m_i {}^i\dot{\mathbf{v}}_{C_i} = {}^i\dot{\boldsymbol{\omega}}_i \times m_i {}^i\mathbf{P}_{C_i} + {}^i\boldsymbol{\omega}_i \times ({}^i\boldsymbol{\omega}_i \times m_i {}^i\mathbf{P}_{C_i}) + m_i {}^i\dot{\mathbf{v}}_i \quad (25)$$

the cross product in the above formulation can be expressed in the form of the cross-product matrix

$$\begin{aligned} {}^i\mathbf{F}_{C_i} &= S({}^i\dot{\boldsymbol{\omega}}_i) m_i {}^i\mathbf{P}_{C_i} + S({}^i\boldsymbol{\omega}_i) S({}^i\boldsymbol{\omega}_i) m_i {}^i\mathbf{P}_{C_i} + m_i {}^i\dot{\mathbf{v}}_i \\ &= \begin{bmatrix} \mathbf{0}_{3 \times 6} & S({}^i\dot{\boldsymbol{\omega}}_i) + S({}^i\boldsymbol{\omega}_i) S({}^i\boldsymbol{\omega}_i) \end{bmatrix} {}^i\dot{\mathbf{v}}_i \\ &= \mathbf{H}_i \mathbf{P}_i \end{aligned} \quad (26)$$

where $S(\boldsymbol{\omega}) = \begin{bmatrix} 0 & -\omega_z & \omega_y \\ \omega_z & 0 & -\omega_x \\ -\omega_y & \omega_x & 0 \end{bmatrix}$, and the linearization of Newton's equation is completed.

For Euler's equation and reverse torque recursion equation, since the existence of ${}^i\mathbf{P}_{C_i} \times {}^i\mathbf{F}_{C_i}$ in the equations, they become nonlinear. However, with the help of the parallel axis theorem, the symmetric inertia matrix in the coordinate system of the center of mass can be transformed into a representation in the joint coordinate system $\{i\}$. By this way, two items in Euler's equation can be expressed

$$\begin{aligned} & {}^i\mathbf{N}_{C_i} + {}^i\mathbf{P}_{C_i} \times {}^i\mathbf{F}_{C_i} \\ &= {}^c\mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times {}^c\mathbf{I}_i {}^i\boldsymbol{\omega}_i + {}^i\mathbf{P}_{C_i} \times m_i {}^i\dot{\mathbf{v}}_{C_i} \\ &= {}^c\mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times {}^c\mathbf{I}_i {}^i\boldsymbol{\omega}_i + m_i {}^i\mathbf{P}_{C_i} \times ({}^i\dot{\boldsymbol{\omega}}_i \times {}^i\mathbf{P}_{C_i} + {}^i\boldsymbol{\omega}_i \times ({}^i\boldsymbol{\omega}_i \times {}^i\mathbf{P}_{C_i}) + {}^i\dot{\mathbf{v}}_i) \\ &= {}^c\mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times {}^c\mathbf{I}_i {}^i\boldsymbol{\omega}_i + m_i {}^i\mathbf{P}_{C_i} \times ({}^i\dot{\boldsymbol{\omega}}_i \times {}^i\mathbf{P}_{C_i}) \\ &\quad + m_i {}^i\mathbf{P}_{C_i} \times ({}^i\boldsymbol{\omega}_i \times ({}^i\boldsymbol{\omega}_i \times {}^i\mathbf{P}_{C_i})) + m_i {}^i\mathbf{P}_{C_i} \times {}^i\dot{\mathbf{v}}_i \\ &= {}^c\mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times {}^c\mathbf{I}_i {}^i\boldsymbol{\omega}_i + m_i ({}^i\mathbf{P}_{C_i}^T {}^i\mathbf{P}_{C_i} \mathbf{E} - {}^i\mathbf{P}_{C_i} {}^i\mathbf{P}_{C_i}^T) {}^i\dot{\boldsymbol{\omega}}_i \\ &\quad + {}^i\boldsymbol{\omega}_i \times (m_i ({}^i\mathbf{P}_{C_i}^T {}^i\mathbf{P}_{C_i} \mathbf{E} - {}^i\mathbf{P}_{C_i} {}^i\mathbf{P}_{C_i}^T) {}^i\boldsymbol{\omega}_i) + m_i {}^i\mathbf{P}_{C_i} \times {}^i\dot{\mathbf{v}}_i \\ &= {}^i\mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times {}^i\mathbf{I}_i {}^i\boldsymbol{\omega}_i + m_i {}^i\mathbf{P}_{C_i} \times {}^i\dot{\mathbf{v}}_i \\ &= {}^i\mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times {}^i\mathbf{I}_i {}^i\boldsymbol{\omega}_i - {}^i\dot{\mathbf{v}}_i \times m_i {}^i\mathbf{P}_{C_i} \end{aligned} \quad (27)$$

With the relationship

$$\mathbf{I}\boldsymbol{\omega} = \begin{bmatrix} \omega_x & \omega_y & \omega_z & 0 & 0 & 0 \\ 0 & \omega_x & 0 & \omega_y & \omega_z & 0 \\ 0 & 0 & \omega_x & 0 & \omega_y & \omega_z \end{bmatrix} \begin{bmatrix} I^{xx} \\ I^{xy} \\ I^{xz} \\ I^{yy} \\ I^{yz} \\ I^{zz} \end{bmatrix} \quad (28)$$

define $K(\boldsymbol{\omega}) = \begin{bmatrix} \omega_x & \omega_y & \omega_z & 0 & 0 & 0 \\ 0 & \omega_x & 0 & \omega_y & \omega_z & 0 \\ 0 & 0 & \omega_x & 0 & \omega_y & \omega_z \end{bmatrix}$, and two items in Euler's equation mentioned above

can be expressed

$$\begin{aligned} & {}^i\mathbf{N}_{C_i} + {}^i\mathbf{P}_{C_i} \times {}^i\mathbf{F}_{C_i} \\ &= \mathbf{I}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times \mathbf{I}_i {}^i\boldsymbol{\omega}_i - {}^i\dot{\mathbf{v}}_i \times m_i {}^i\mathbf{P}_{C_i} \\ &= \left[K({}^i\dot{\boldsymbol{\omega}}_i) + S({}^i\boldsymbol{\omega}_i)K({}^i\boldsymbol{\omega}_i) \quad -S({}^i\dot{\mathbf{v}}_i) \quad \mathbf{0}_{3 \times 1} \right] \mathbf{P}_i \\ &= \mathbf{A}_i \mathbf{P}_i \end{aligned} \quad (29)$$

and the linearization of Euler's equation and reverse torque recursion equation is completed.

By combining all the inertial parameters in the dynamic equation into a matrix, the inertia matrix $\mathbf{P}$ in equation $\boldsymbol{\tau}_d = \mathbf{Y}\mathbf{P}$ can be formed

$$\mathbf{P} = \begin{bmatrix} \mathbf{P}_x^T & \mathbf{P}_y^T & \mathbf{P}_z^T & \mathbf{P}_b^T & \mathbf{P}_a^T \end{bmatrix}^T \quad (30)$$

With the reverse dynamic recursion, the force of each axis is reversed

$$\begin{aligned} \mathbf{f}_a &= \begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{H}_a \end{bmatrix} \mathbf{P} = \mathbf{Y}_a^f \mathbf{P} \\ \mathbf{f}_b &= \left[\begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{H}_b & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^b\mathbf{R}\mathbf{Y}_a^f \right] \mathbf{P} = \mathbf{Y}_b^f \mathbf{P} \\ \mathbf{f}_z &= \left[\begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{H}_z & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^a\mathbf{R}\mathbf{Y}_b^f \right] \mathbf{P} = \mathbf{Y}_z^f \mathbf{P} \\ \mathbf{f}_y &= \left[\begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{H}_y & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^z\mathbf{R}\mathbf{Y}_z^f \right] \mathbf{P} = \mathbf{Y}_y^f \mathbf{P} \\ \mathbf{f}_x &= \left[\begin{bmatrix} \mathbf{H}_x & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^y\mathbf{R}\mathbf{Y}_y^f \right] \mathbf{P} = \mathbf{Y}_x^f \mathbf{P} \end{aligned} \quad (31)$$

and the torque of each axis is reversed

$$\begin{aligned} \mathbf{n}_a &= \begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{A}_a \end{bmatrix} \mathbf{P} = \mathbf{Y}_a^n \mathbf{P} \\ \mathbf{n}_b &= \left[\begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{A}_b & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^b\mathbf{R}\mathbf{Y}_a^n + S({}^b\mathbf{P}_a) {}^b\mathbf{R}\mathbf{Y}_a^f \right] \mathbf{P} = \mathbf{Y}_b^n \mathbf{P} \\ \mathbf{n}_z &= \left[\begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{A}_z & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^a\mathbf{R}\mathbf{Y}_b^n + S({}^a\mathbf{P}_z) {}^a\mathbf{R}\mathbf{Y}_b^f \right] \mathbf{P} = \mathbf{Y}_z^n \mathbf{P} \\ \mathbf{n}_y &= \left[\begin{bmatrix} \mathbf{0}_{3 \times 10} & \mathbf{A}_y & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^z\mathbf{R}\mathbf{Y}_z^n + S({}^z\mathbf{P}_y) {}^z\mathbf{R}\mathbf{Y}_z^f \right] \mathbf{P} = \mathbf{Y}_y^n \mathbf{P} \\ \mathbf{n}_x &= \left[\begin{bmatrix} \mathbf{A}_x & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} & \mathbf{0}_{3 \times 10} \end{bmatrix} + {}^y\mathbf{R}\mathbf{Y}_y^n + S({}^y\mathbf{P}_x) {}^y\mathbf{R}\mathbf{Y}_y^f \right] \mathbf{P} = \mathbf{Y}_x^n \mathbf{P} \end{aligned} \quad (32)$$

finally, the observation matrix $\mathbf{Y}$ in equation $\boldsymbol{\tau}_d = \mathbf{Y}\mathbf{P}$ is

$$\mathbf{Y} = \begin{bmatrix} \mathbf{Y}_x^f(1,:); \mathbf{Y}_y^f(2,:); \mathbf{Y}_z^f(3,:); \mathbf{Y}_b^n(2,:); \mathbf{Y}_a^n(1,:) \end{bmatrix} \quad (33)$$

The dynamic model established by the Newton-Euler method therefore is written as a linear

form of inertia parameters

$$\boldsymbol{\tau}_d = \mathbf{Y}\mathbf{P} \quad (34)$$

The friction model of each axis is also expressed in linear form

$$\tau_f = f_c \text{sign}(\dot{q}) + f_v \dot{q} = \mathbf{Y}_f \mathbf{P}_f \quad (35)$$

by adding $\mathbf{Y}_f = [\text{sign}(\dot{q}) \quad \dot{q}]$ to the observation matrix and $\mathbf{P}_f = [f_c \quad f_v]^T$ to the inertia matrix, the linear form of the dynamic equation considering friction is obtained.

Appendix B: Minimum inertial parameters calculation based on the MBS theory

From equation $\boldsymbol{\tau}_d = \mathbf{Y}\mathbf{P}$, it is obvious that the inertial parameters of axis i only affect $\tau_1 \dots \tau_i$, rather than $\tau_{i+1} \dots \tau_n$. Therefore, the main idea of calculation the minimum parameters of axis i is: (a) Let ${}^{i+1}\mathbf{f}_{i+1} = {}^{i+1}\mathbf{n}_{i+1} = [0 \quad 0 \quad 0]^T$, and calculate the identifiable inertial parameters and the unidentifiable inertial parameters of τ_i ; (b) Integrate the unidentifiable inertial parameters into the inertial parameter of axis $i-1$ by the reverse dynamic recursion.

The calculation process of the minimum parameters for the prismatic axis and the revolute axis is different.

For the prismatic axis, let ${}^{i+1}\mathbf{f}_{i+1} = {}^{i+1}\mathbf{n}_{i+1} = [0 \quad 0 \quad 0]^T$, and according to force recursion formula

$${}^i\mathbf{f}_i = M_i {}^i\dot{\mathbf{v}}_{C_i} = M_i \left({}^i\dot{\boldsymbol{\omega}}_i \times {}^i\mathbf{P}_{C_i} + {}^i\boldsymbol{\omega}_i \times ({}^i\boldsymbol{\omega}_i \times {}^i\mathbf{P}_{C_i}) + {}^i\dot{\mathbf{v}}_i \right) \quad (36)$$

since the angular velocity and angular acceleration of the prismatic axis are both zero, that is ${}^i\boldsymbol{\omega}_i = {}^i\dot{\boldsymbol{\omega}}_i = [0 \quad 0 \quad 0]^T$, therefore

$${}^i\mathbf{f}_i = M_i {}^i\dot{\mathbf{v}}_i \quad (37)$$

it can be seen that M_i is an identifiable parameter of τ_i , and the remaining inertial parameters of axis i can be combined into the inertial parameters of axis $i-1$ through reverse dynamic recursion.

Suppose that the unidentifiable parameters of τ_i in the inertia parameters of axis i are zero, which means they have no effect on equation, and the above equation can be expressed as

$${}^i\mathbf{f}_i^* = M_i {}^i\dot{\mathbf{v}}_i \quad (38)$$

then add the unidentifiable part

$${}^i\mathbf{f}_i = {}^i\mathbf{f}_i^* + M_i \left({}^i\dot{\boldsymbol{\omega}}_i \times {}^i\mathbf{P}_{C_i} + {}^i\boldsymbol{\omega}_i \times ({}^i\boldsymbol{\omega}_i \times {}^i\mathbf{P}_{C_i}) \right) \quad (39)$$

substitute it into the reverse recursion formulation

$$\begin{aligned}
{}^{i-1}\mathbf{f}_{i-1} &= {}^{i-1}\mathbf{R}^i \mathbf{f}_i + M_{i-1} {}^{i-1}\dot{\mathbf{v}}_{C_{i-1}} \\
&= {}^{i-1}\mathbf{R}^i \mathbf{f}_i^* + {}^{i-1}\mathbf{R} M_i \left({}^i\dot{\boldsymbol{\omega}} \times {}^i\mathbf{P}_{C_i} + {}^i\boldsymbol{\omega} \times \left({}^i\boldsymbol{\omega} \times {}^i\mathbf{P}_{C_i} \right) \right) \\
&\quad + M_{i-1} \left({}^{i-1}\dot{\boldsymbol{\omega}}_{i-1} \times {}^{i-1}\mathbf{P}_{C_{i-1}} + {}^{i-1}\boldsymbol{\omega}_{i-1} \times \left({}^{i-1}\boldsymbol{\omega}_{i-1} \times {}^{i-1}\mathbf{P}_{C_{i-1}} \right) + {}^{i-1}\dot{\mathbf{v}}_{i-1} \right)
\end{aligned} \tag{40}$$

since ${}^{i-1}\dot{\boldsymbol{\omega}}_{i-1} = {}^{i-1}\mathbf{R}^i \dot{\boldsymbol{\omega}}_i = [0 \ 0 \ 0]^T$, ${}^{i-1}\boldsymbol{\omega}_{i-1} = {}^{i-1}\mathbf{R}^i \boldsymbol{\omega}_i = [0 \ 0 \ 0]^T$, therefore

$${}^{i-1}\mathbf{f}_{i-1} = {}^{i-1}\mathbf{R}^i \mathbf{f}_i^* + m_{i-1} {}^{i-1}\dot{\mathbf{v}}_{i-1} \tag{41}$$

and the combined inertia parameter of axis $i-1$ is

$$M_{i-1} = m_{i-1} \tag{42}$$

For the revolute axis, firstly, define $\mathbf{MS}_i = [MX_i \ MY_i \ MZ_i]^T$, $\mathbf{J}_i = \begin{bmatrix} XX_i & XY_i & XZ_i \\ XY_i & YY_i & YZ_i \\ XZ_i & YZ_i & ZZ_i \end{bmatrix}$,

$$\mathbf{E} = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}, \quad {}^i\dot{\boldsymbol{\omega}}_i = [\varepsilon_x \ \varepsilon_y \ \varepsilon_z]^T, \quad {}^i\boldsymbol{\omega}_i = [\omega_x \ \omega_y \ \omega_z]^T, \quad {}^i\dot{\mathbf{v}}_i = [a_x \ a_y \ a_z]^T.$$

Let ${}^{i+1}\mathbf{f}_{i+1} = {}^{i+1}\mathbf{n}_{i+1} = [0 \ 0 \ 0]^T$, and according to torque recursion formula

$${}^i\mathbf{n}_i = \mathbf{J}_i {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times \mathbf{J}_i {}^i\boldsymbol{\omega}_i + \mathbf{MS}_i \times {}^i\dot{\mathbf{v}}_i \tag{43}$$

Expand the above equation

$$\begin{cases}
{}^i n_i^x = \varepsilon_x XX_i + (\varepsilon_y - \omega_x \omega_z) XY_i + (\varepsilon_z + \omega_x \omega_y) XZ_i - \omega_y \omega_z (YY_i - ZZ_i) + (\omega_y^2 - \omega_z^2) YZ_i + a_z MY_i - a_y MZ_i \\
{}^i n_i^y = (\varepsilon_x + \omega_y \omega_z) XY_i + (\omega_x^2 - \omega_z^2) XZ_i + \varepsilon_y YY_i + (\varepsilon_z - \omega_x \omega_y) YZ_i - \omega_x \omega_z (ZZ_i - XX_i) - a_z MX_i + a_x MZ_i \\
{}^i n_i^z = -\omega_x \omega_y (XX_i - YY_i) + (\omega_x^2 - \omega_y^2) XY_i + (\varepsilon_x - \omega_y \omega_z) XZ_i + (\varepsilon_y + \omega_x \omega_z) YZ_i + \varepsilon_z ZZ_i - a_y MX_i + a_x MY_i
\end{cases} \tag{44}$$

Because the joint coordinate system is established based on the MBS theory, it can be found that the identifiable parameters vary with the direction of the revolute axis. This is the biggest difference between robots, which lead to inapplicability of the methods and the toolkits mentioned in literature [17-24].

When axis i rotates around the X-axis, its identifiable parameters are

$$\{XX_i \ XY_i \ XZ_i \ YY_i^* = YY_i - ZZ_i \ YZ_i \ MY_i \ MZ_i\} \tag{45}$$

When axis i rotates around the Y-axis, its identifiable parameters are

$$\{XY_i \ XZ_i \ YY_i \ YZ_i \ ZZ_i^* = ZZ_i - XX_i \ MX_i \ MZ_i\} \tag{46}$$

When axis i rotates around the Z-axis, its identifiable parameters are

$$\{XX_i^* = XX_i - YY_i \ XY_i \ XZ_i \ YZ_i \ ZZ_i \ MX_i \ MY_i\} \tag{47}$$

Suppose that the unidentifiable parameters of τ_i in the inertia parameters of axis i are zero, which means they have no effect on equation, and the above equation can be expressed as

$${}^i\mathbf{f}_i^* = {}^i\dot{\boldsymbol{\omega}}_i \times (\mathbf{E} - \mathbf{U}) \mathbf{MS}_i + {}^i\boldsymbol{\omega}_i \times ({}^i\boldsymbol{\omega}_i \times (\mathbf{E} - \mathbf{U}) \mathbf{MS}_i) \tag{48}$$

$${}^i\mathbf{n}_i^* = (\mathbf{J}_i - p(\mathbf{E} - \mathbf{U})) {}^i\dot{\boldsymbol{\omega}}_i + {}^i\boldsymbol{\omega}_i \times (\mathbf{J}_i - p(\mathbf{E} - \mathbf{U})) {}^i\boldsymbol{\omega}_i + ((\mathbf{E} - \mathbf{U}) \mathbf{MS}_i) \times {}^i\dot{\mathbf{v}}_i \tag{49}$$

when axis i rotates around the X-axis, $U = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix}$, $p = ZZ_i$;

when axis i rotates around the Y-axis, $U = \begin{bmatrix} 0 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 0 \end{bmatrix}$, $p = XX_i$;

when axis i rotates around the Z-axis, $U = \begin{bmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 1 \end{bmatrix}$, $p = YY_i$.

then add the unidentifiable part

$${}^i f_i = {}^i f_i^* + {}^i \dot{\omega}_i \times UMS_i + {}^i \omega_i \times ({}^i \omega_i \times UMS_i) + {}^i \dot{v}_i M_i \quad (50)$$

$${}^i n_i = {}^i n_i^* + p(E - U) {}^i \dot{\omega}_i + {}^i \omega_i \times p(E - U) {}^i \omega_i + UMS_i \times {}^i \dot{v}_i \quad (51)$$

substitute them into the reverse recursion formulation and the combined inertia parameter of axis $i - 1$ is [16]

$$\begin{aligned} M_{i-1} &= m_{i-1} + M_i \\ MS_{i-1} &= m_{i-1} {}^{i-1} P_{C_{i-1}} + {}^{i-1} R UMS_i + M_i {}^{i-1} P_i \\ J_{i-1} &= J_i + p {}^{i-1} R (E - U) {}^{i-1} R + 2 ({}^{i-1} P_i^T {}^{i-1} R UMS_i) E \\ &\quad - {}^{i-1} R UMS_i {}^{i-1} P_i^T - {}^{i-1} P_i ({}^{i-1} R UMS_i)^T \\ &\quad + M_i ({}^{i-1} P_i^T {}^{i-1} P_i E - {}^{i-1} P_i {}^{i-1} P_i^T) \end{aligned} \quad (52)$$

In a summary, the procedure of using τ_i to derive the minimum inertia parameters is as follows:

1. Let $i = n$, and set the initial value of the minimum inertia parameters of the last axis i

$$\begin{aligned} &\{XX_n \quad XY_n \quad XZ_n \quad YY_n \quad YZ_n \quad ZZ_n \quad MX_n \quad MY_n \quad MZ_n \quad M_n\} \\ &\square \{I_n^{xx} \quad I_n^{xy} \quad I_n^{xz} \quad I_n^{yy} \quad I_n^{yz} \quad I_n^{zz} \quad m_n r_n^{cx} \quad m_n r_n^{cy} \quad m_n r_n^{cz} \quad m_n\} \end{aligned};$$

2. Since the inertial parameters of axis i do not affect $\tau_{i+1} \dots \tau_n$, let

$${}^{i+1} f_{i+1} = {}^{i+1} n_{i+1} = [0 \quad 0 \quad 0]^T, \text{ and find identifiable parameters of } \tau_i \text{ from all inertial parameters of axis } i;$$

3. Prove that the unidentifiable parameters of the i axis or the parameters that have no effect on the dynamic equation or the parameters that can be combined into the inertial parameters of the axis $i - 1$ are the parameters that can be eliminated;
4. If $i = 1$, stop; otherwise, set $i = i - 1$ and go to step 2.

Author contribution Liang Cheng: supervision, experiment, formal analysis, writing—review and editing; Jianbo Wu: methodology, programming, experiment, formal analysis, writing—original draft; Yingjie Guo: writing—review and editing; Jiangxiong Li: conceptualization, writing—review

and editing; Yinglin Ke: conceptualization, writing—review and editing.

Funding This work was supported by Natural Science Foundation of Zhejiang Province (LQ20E050019), National Natural Science Foundation of China (No. 52105535), Major program of the National Natural Science Foundation of China (No. 91948301), and Zhejiang Provincial Key Research and Development Program (2020C01039).

Availability of data and material The datasets used or analyzed during the current study are available from the corresponding author on reasonable request.

Code availability The codes used in this study are available from the corresponding author on reasonable request.

Declarations

Ethics approval Not applicable.

Consent for participate Not applicable.

Consent for publication The authors agree with the publication.

Conflicts of interest The authors declare no competing interests.

Reference

1. Leutz D, Vermilyea M, Bel S, Hinterhölzl R (2016) Forming Simulation of Thick AFP Laminates and Comparison with Live CT Imaging. *Applied Composite Materials* 23 (4):583-600. <https://doi.org/10.1007/s10443-016-9475-6>
2. Middendorf P, Metzner C (2011) 18 - Aerospace applications of non-crimp fabric composites. In: Lomov SV (ed) *Non-Crimp Fabric Composites*. Woodhead Publishing, pp 441-449e. doi:<https://doi.org/10.1533/9780857092533.4.441>
3. Wu J, Cheng L, Bi Y, Li J, Ke Y (2021) Kinematic modeling and parameter identification for a heavy gantry-type automated fiber placement machine considering gravity deformation. *Proceedings of the Institution of Mechanical Engineers, Part C: Journal of Mechanical Engineering Science* 235 (8):1418-1431. <https://doi.org/10.1177/0954406220945728>
4. Lichtinger R, Lacalle J, Hinterhoelzl R, Beier U, Drechsler K (2015) Simulation and experimental validation of gaps and bridging in the automated fiber placement process. *Science and Engineering of Composite Materials* 22. <https://doi.org/10.1515/secm-2013-0158>
5. Denkena B, Heimann B, Abdellatif H, Holz C (2005) Design, modeling and advanced control of the innovative parallel manipulator PaLiDA, vol 1. <https://doi:10.1109/AIM.2005.1511053>
6. Abdellatif H, Heimann B (2006) Model-Based Control for Industrial Robots: Uniform Approaches for Serial and Parallel Structures. In. <https://doi:10.5772/5037>
7. Rachedi M (2017) Model based control of 3 DOF parallel delta robot using inverse dynamic model. <https://doi:10.1109/ICMA.2017.8015814>
8. Garcia-herreros I, Kestelyn X, Gomand J, Barre P-J (2010) Model-based control of a dual-drive H-type gantry stage on a decoupling base. <https://doi:10.1109/ICIT.2010.5472741>

9. Hwang Y-L (2006) Recursive newton-euler formulation for flexible dynamic manufacturing analysis of open-loop robotic systems. The International Journal of Advanced Manufacturing Technology 29 (5):598-604. <https://doi.org/10.1007/BF02729114>
10. Lee K, Shah DK (1988) Dynamic analysis of a three-degrees-of-freedom in-parallel actuated manipulator. IEEE Journal on Robotics and Automation 4 (3):361-367. <https://doi.org/10.1109/56.797>
11. Stueckelmaier P, Grotjahn M, Fraeger C Identification of the Inverse Dynamics of a Serial Robot for Robot Drive Control. In: IKMT 2015; 10. ETG/GMM-Symposium Innovative small Drives and Micro-Motor Systems, 14-15 Sept. 2015 2015. pp 1-8
12. Jiang S, Jiang M, Cao Y, Hua D, Wu H, Ding Y, Chen B (2017) A typical dynamic parameter identification method of 6-degree-of-freedom industrial robot. Proceedings of the Institution of Mechanical Engineers, Part I: Journal of Systems and Control Engineering 231:095965181772647. <https://doi.org/10.1177/0959651817726477>
13. Djuric AM, ElMaraghy WH (2010) Automatic separation method for generation of reconfigurable 6R robot dynamics equations. The International Journal of Advanced Manufacturing Technology 46 (5):831-842. <https://doi.org/10.1007/s00170-009-2156-y>
14. Peter JK, Müller A, Liu S (2008) Dynamic Modeling and Identification of a Complex-structured Parallel Robot. IFAC Proceedings Volumes 41 (2):4361-4366. <https://doi.org/https://doi.org/10.3182/20080706-5-KR-1001.00735>
15. Mahmoud Z, Arvan MR, Nekoukar V, Rezaei M (2021) A comparative study of two inverse dynamic models of 6 degree-of-freedom rotary Stewart-Gough parallel robot. International Journal of Dynamics and Control. <https://doi.org/10.1007/s40435-021-00820-5>
16. Müller P (1992) Robot dynamics and control. Automatica 28. [https://doi.org/10.1016/0005-1098\(92\)90197-n](https://doi.org/10.1016/0005-1098(92)90197-n)
17. Gautier M, Khalil W Identification of the minimum inertial parameters of robots. In: Proceedings, 1989 International Conference on Robotics and Automation, 14-19 May 1989 1989. pp 1529-1534 vol.1523. <https://doi:10.1109/ROBOT.1989.100196>
18. Gautier M, Khalil W A direct determination of minimum inertial parameters of robots. In: Proceedings. 1988 IEEE International Conference on Robotics and Automation, 24-29 April 1988 1988. pp 1682-1687 vol.1683. <https://doi:10.1109/ROBOT.1988.12308>
19. Gautier M, Khalil W On the identification of the inertial parameters of robots. In: Proceedings of the 27th IEEE Conference on Decision and Control, 7-9 Dec. 1988 1988. pp 2264-2269 vol.2263. <https://doi:10.1109/CDC.1988.194738>
20. Gautier M, Khalil W (1990) Direct Calculation of Minimum Set of Inertial Parameters of Serial Robots. Robotics and Automation, IEEE Transactions on 6:368-373. <https://doi.org/10.1109/70.56655>
21. Khalil W, Bennis F (1994) Comments on "Direct Calculation of Minimum Set of Inertial Parameters of Serial Robots". Robotics and Automation, IEEE Transactions on 10:78-79. <https://doi.org/10.1109/70.285599>
22. Khalil W, Creusot D (1997) SYMORO+: A system for the symbolic modelling of robots. Robotica 15. <https://doi.org/10.1017/S0263574797000180>
23. Khalil W, Vijayalingam A, Khomutenko B, Mukhanov I, Lemoine P, Écorchard G (2014) OpenSYMORO: An open-source software package for Symbolic Modelling of Robots. <https://doi:10.1109/AIM.2014.6878246>
24. Nadeau N (2019) Pybotics: Python Toolbox for Robotics. Journal of Open Source Software 4:1738. <https://doi.org/10.21105/joss.01738>
25. Antonelli G, Caccavale F, Chiacchio P (1999) Systematic procedure for the identification of dynamic parameters of robot manipulators. Robotica 17:427-435. <https://doi.org/10.1017/S026357479900140X>
26. Wu J, Wang J, You Z (2010) An overview of dynamic parameter identification of robots. Robotics and Computer-Integrated Manufacturing 26 (5):414-419. <https://doi.org/https://doi.org/10.1016/j.rcim.2010.03.013>
27. Swevers J, Verdonck W, Schutter J (2007) Dynamic Model Identification for Industrial Robots. Control Systems, IEEE 27:58-71. <https://doi.org/10.1109/MCS.2007.904659>
28. Atkeson CG, An CH, Hollerbach JM (1986) Estimation of Inertial Parameters of Manipulator Loads and Links. The International Journal of Robotics Research 5 (3):101-119. <https://doi.org/10.1177/027836498600500306>

29. Swevers J, Ganseman C, De Schutter J, Van Brussel H (1996) EXPERIMENTAL ROBOT IDENTIFICATION USING OPTIMISED PERIODIC TRAJECTORIES. Mechanical Systems and Signal Processing 10 (5):561-577. <https://doi.org/https://doi.org/10.1006/mssp.1996.0039>
30. Olsen M, Petersen H (2001) A new method for estimating parameters of a dynamic robot model. Robotics and Automation, IEEE Transactions on 17:95-100. <https://doi.org/10.1109/70.917088>