Simulation design of acceleration sensor with multi-stage induction system

Jiacheng Feng (✉ fengjiacheng@china-icv.cn)

Original Article

Keywords: intelligent acceleration sensor, magnetic-mechanical coupling mechanism, multiple thresholds

Posted Date: May 14th, 2020

DOI: <https://doi.org/10.21203/rs.3.rs-26057/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Simulation design of acceleration sensor with multi-stage induction system

Jiacheng Feng

Validation, Test and Construction Department, China Intelligent and Connected Vehicles (Beijing) Research Institute Co.Ltd, H5, Aviation International Plaza, Daxing District, Beijing, China

fengjiacheng@china-icv.cn

Abstract. Acceleration sensor can monitor acceleration and trigger switches in a dynamic environment. Based on the coupling mechanism of magneto-mechanical, this paper presents the design of an acceleration sensor. With the characteristics of integrated mechanism of perception and triggering, no power consumption and high robustness, it can be widely used in active and passive vehicle safety, robot and dynamic monitoring system. In order to improve the robustness of system, the closing and holding mechanism of switch is designed. Considering the comprehensive effects of elastic element, suction contact and permanent magnet, the paper built the mathematical model of sensor and the threshold searching algorithm. The simulation results show that the acceleration switch has the characteristic of sensitivity in specific dynamic signal, and it works well in overload and vibration disturbance environment. In conclusion, the paper presents a new design model and method for bilateral multi-stage acceleration sensor.

Key words: intelligent acceleration sensor; magnetic-mechanical coupling mechanism; multiple thresholds

1. Introduction

Acceleration monitoring is significant in dynamic environment awareness, especially in active and passive vehicle safety, safety system of robot and engineering machinery. Acceleration sensor belongs to inertial sensor for acceleration perception, and the acceleration sensor designed in this paper belongs to a kind of intelligent acceleration switch. The acceleration sensor has different acceleration thresholds, and it is triggered under certain dynamic conditions. This paper presents the design of the multi-stage acceleration sensor by numerical analysis, and research on the physical characteristics.

A lot of scientific research institution have proposed the design of acceleration sensors in recent years, which mechanism and principle are different. Du Liquan et al.^[1] designed a low-g MEMS inertial switch, the mass-spring system include archimedes' spirals and a single circular proof mass, which can monitor different directions acceleration in XOY plane. Keren Dai et al.^[2] developed a self-powered high-g acceleration sensor with a triboelectric nanogenerator which is applied in the field of military equipment and automobiles. A accelerometer is designed with the function of monitoring bidirectional acceleration through beam mechanism^[3]. Ahmad Abdalwareth et al. designed a two-axis fiber optical acceleration sensor, which base on a glass fiber as flexible beam to release the sensing function^[4]. In short, acceleration sensors usually work through beam mechanism or mono-structure, most of them lack of multilevel perception characteristic, and the performance of anti-overload ability is weak.

In order to realize multi-stage induction function and solve the problems of unstable closing state and response lag, a new type of bidirectional acceleration switch is proposed with the function of self-locking and five steady-state. An absorbable contact is designed to improve contact stability of the switch. The mathematical model of the acceleration sensor is set up considering the magneto-mechanical coupling mechanism and the magnetism elastic contact structure. The analysis results show that the acceleration switch exhibits four thresholds characteristic and fast response ability in dynamic condition. The paper provides a numerical simulation model for multi-stage sensing acceleration sensor with magneto-mechanical coupling mechanism.

2. Design of acceleration switch structure

Fig 1 is the structural chart of the acceleration sensor, which is composed of mass, extension spring of mass, guide rail, first stage contact, second stage contact, pressure spring of first and second stage contact, moving magnetic block, fixed magnetic block and base. It can be seen from the structural chart that magnetic blocks are arranged in a line. The movable magnetic block inlaid in mass block and towards fixed magnet. The mass block can move up and down along the guide rail under the constraint of extension spring. First and second stage contacts is connected to the base by pressure springs. All springs are arranged in a coaxial line. The magnetic-mechanical nonlinear system realizes the multi-stable function. The sensor can keep in different steady-state without energy consumption. The magnetic contact beam can realize close hold function and excellent closure stability.

Fig. 1. Structural chart

The mass moves in acceleration shock environment. If external acceleration exceeds the thresholds of switch, the mass will switch to other steady-state. Under different levels of acceleration shock, the mass will suction with corresponding contact to realize the multistage sensing function. Based on the analysis of switch structure and mechanism kinematics, the mathematical model under dynamic environment are established. Combined with the performance objective, material properties and structural dimensions are calculated to meet the design requirements.

3. Modeling and analysis

3.1 Physical model and performance design

In the following studies, the moving magnetic block is designated as analysis object. In difference states between the mass and contacts, establish three analysis models. In the following formulas, F_t is the resultant force of mass, F_s is press spring resultant force, F_{cl} and F_{ch} are contact force of first and second stage, F_{mb} is the magnetic resultant force between magnetic blocks, F_{ml} is the magnetic force between mass and first stage contact, F_{mh} is the magnetic force between mass and second stage contact^[5-8].

The first situation is that all magnetic contacts are not suctioned, the formula (1) condition is $F_{cl}=0$ and $F_{ch}=0$. When only the first stage contact is suctioned, the formula (1) condition is $F_{cl}>0$ and $F_{ch}=0$. When all contacts in the same direction are suctioned, the formula (1) condition is $F_{cl}>0$ and $F_{ch}>0$.

$$\begin{cases} F_t = F_s + F_{mb} + F_{ml} & F_{cl}=0; F_{ch}=0 \\ F_t = F_s + F_{cl} + F_{mb} + F_{mh} & F_{cl}>0; F_{ch}=0 \\ F_t = F_s + F_{cl} + F_{ch} + F_{mb} & F_{cl}>0; F_{ch}>0 \end{cases} \quad (1)$$

In order to meet the performance requirement, the dimensions of magnetic components, elastic components, and the spacing between different components are calculated based on design threshold. We define a_e as input

acceleration pulse, a_t as design threshold, F_s as the minimum stable suction force, T_r as the max response time, and the minimum suction time as T_{min} . The technical requirements are as follows:

- (1) If $a_e < a_t$, the switch is not working (shown in Table 1).
- (2) If $a_e \geq a_t$, the switch is triggered, and the response time should be less than T_r ($T_r=20\text{ms}$).
- (3) If the switch is triggered, the contact suction force should be greater than F_s , and the stable closing time should be longer than T_{min} ($T_{min}=200\text{ms}$).

Based on the sensor design parameters and acceleration excitation, the calculation method of dynamic acceleration threshold is proposed. The threshold is obtained by increasing the amplitude of acceleration pulse in a certain range, and the algorithm logic is shown in Figure 2. The step length of iteration affects the accuracy and run time of calculation. Considering the application scenario, set the iteration step to 1m/s^2 , the pulse width is 10ms , and the search scope is $10\text{-}100\text{ m/s}^2$.

Fig. 3. Threshold analysis method

Through the iterative computation, we find the different acceleration thresholds under certain pulse width (pulse width is 10ms), as shown in Table 1. In this paper, the sensor adopts bi-direction same threshold design.

Table 1. Dynamic threshold of acceleration switch

Mass upward movement		Mass downward movement	
Threshold	acceleration	Threshold	acceleration
a_{d1}	4.18g	a_{d4}	4.18g
a_{d2}	6.22g	a_{d5}	6.22g

3.2 Operating conditions analysis

Dynamic analysis under different working conditions is necessary for the sensor. The mass is coupled with different forces, such as elastic force, magnetic force, inertial force, damping force and external force $F(t)$ under dynamic condition. According to different switch status, the dynamic model is established as follows:

When all magnetic contacts are not suctioned, the formula (2) condition is $F_{cl}=0$ and $F_{ch}=0$. When only the first stage contact is suctioned, the formula (2) condition is $F_{cl}>0$ and $F_{ch}=0$. When all contacts in the same direction are suctioned, the formula (2) condition is $F_{cl}>0$ and $F_{ch}>0$.^[5-8]

$$\begin{cases} m\ddot{x} + c\dot{x} + k_s x = F(t) + F_{mb} + F_{ml} & F_{cl}=0; F_{ch}=0 \\ m\ddot{x} + c\dot{x} + k_s x + k_l x = F(t) + F_{mb} + F_{mh} & F_{cl}>0; F_{ch}=0 \\ m\ddot{x} + c\dot{x} + k_s x + k_l x + k_h x = F(t) + F_{mb} & F_{cl}>0; F_{ch}>0 \end{cases} \quad (2)$$

Thus we write: where x is the movement displacement of mass block, m is the mass of mass block, K_s is the stiffness coefficient of elasticity, K_l and K_h are the stiffness coefficient of first and second stage contact, C is damping coefficient.

According to the dynamic model, conduct the research on dynamic response of switch under the excitation of different amplitude and the consistent pulse width acceleration. In upward motion, acceleration pulse as shown in Fig 3, the mass moves under excitation and the motion displacement shown in Fig 4.

Fig. 3. Acceleration excitation

If the excitation reaches the designed threshold value a_{d1} , the displacement curve is shown in Fig 4 (solid line), the mass block switch to adjacent steady-state, then the switch triggered. If the acceleration amplitude reaches the designed threshold value a_{d2} , the displacement curve is shown in Fig 4 (dotted line), the mass snaps from initial position to another steady-state.

Fig. 4. Displacement of the mass

Fig. 5 and Fig. 6 are the contact force of first and second stage contact which reflect the switch stability. From the graph we can see the mass block is rapidly suctioned and the stable closing. When the acceleration pulse width is 10ms, the maximum trigger time is 18ms. The simulation result reflects the sensor has a good dynamic response performance.

Fig. 5. Contact force of the two contacts (first stage)

Fig. 6. Contact force of the two contacts (second stage)

In order to verify the overload performance of the sensor, increase excitation amplitude to $1.3a_{d2}$ (8.16g). The simulation results (Fig. 7) show that the switch keep stable closed and not disconnected, which reflects the good reliability of the sensor under overload condition.

Fig. 7. Contact force of the two contacts (overload)

In order to verify the stability under vibration disturbance, the sensor is continuously loaded with sin function excitation as shown in Fig 8 (left picture). The frequency is 50Hz and amplitude is 1g. As the Fig.8 (right picture) and Fig.9 show that the sensor moves in a certain range in the vibration environment. During vibration, the contact force of the two contacts is 0, and the sensor keep off state.

Fig. 8. Interference environment response

Fig. 9. Contact force of the two contacts (interference)

4. Conclusion

- (1) A coupling mechanism of magneto-mechanical is designed which perform nonlinear characteristics, combined with the function demand of multi-stage perception, a multistage acceleration sensor is designed.
- (2) Considering the comprehensive effect of magnetic force, elastic force and structural damping, establish the dynamic model and threshold search algorithm.
- (3) Establishing the mathematical model of dynamic, the response of the switch under different working conditions is analyzed. It is verified by simulation that the dynamic performance meets the design requirements.
- (4) The overload and vibration disturbance tests ensure the robustness of the mechanical system.

Declarations

The author declares that he has no competing interests and no fund applicable. Jiacheng Feng designed and analyzed the acceleration sensor and performed the examination of the program and data. This research was supported by Automotive college of Dalian university of Technology and China Intelligent and Connected Vehicle (Beijing) Research.

References

- [1] Liqun D , Yu L , Jian Z , et al. A low-g MEMS inertial switch with a novel radial electrode for uniform omnidirectional sensitivity[J]. Sensors and Actuators A Physical, 2018, 270:214-222.
- [2] Dai K , Wang X , Yi F , et al. Triboelectric nanogenerators as self-powered acceleration sensor under high- g, impact[J]. Nano Energy, 2018, 45:84-93.
- [3] Kim H, Jang Y H, Kim Y K, et al. MEMS acceleration switch with bi-directionally tunable threshold[J]. Sensors and Actuators A: Physical, 2014, 208: 120-129.
- [4] Ahmad Abdalwareth, Alexander Doering, et al. Two-axis fiber optical acceleration sensor based on cladding waveguide gratings[C]. Bragg Gratings, Photosensitivity and Poling in Glass Waveguides and Materials, January 2018.
- [5] David H. Allen. Mechanics of Materials[M]. Springer New York, 2013.
- [6] Besson J, Chaboche J L, Cailletaud G, et al. Non-Linear Mechanics of Materials[J]. 2010, 167(12):341-369.
- [7] Oller S. Nonlinear Dynamics of Structures[M]. 2014.
- [8] Buschow K H J, F. R. de Boer. Physics of Magnetism and Magnetic Materials[M]. 2013.

Figures

Figure 1

Structural chart

Figure 2

Threshold analysis method

Figure 3

Acceleration excitation

Figure 4

Displacement of the mass

Figure 5

Contact force of the two contacts (first stage)

Figure 6

Contact force of the two contacts (second stage)

Figure 7

Contact force of the two contacts (overload)

Figure 8

Interference environment response

Figure 9

Contact force of the two contacts (interference)