Structure, Defects and Microwave Dielectric Properties of Al-doped and Al/Nd Co-doped Ba₄Nd_{9.33}Ti₁₈O₅₄ Ceramics

WeiJia Guo (✉ guoweijia0315@163.com)

Tsinghua University <https://orcid.org/0000-0003-2481-3527>

Zhiyu Ma

Tsinghua University

Yu Luo

Tsinghua University

Yugu Chen

Tsinghua University

Zhenxing Yue

Tsinghua University

Longtu Li

Tsinghua University

Research Article

Keywords: microwave dielectric ceramics, Ba₄Nd_{9.33}Ti₁₈O₅₄, Al and Al/Nd doping, defects

Posted Date: August 11th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-783511/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Abstract

$\text{Ba}_4\text{Nd}_{9.33}\text{Ti}_{18-z}\text{Al}_{4z/3}\text{O}_{54}$ (BNT-A, $0 \leq z \leq 2$) and $\text{Ba}_4\text{Nd}_{9.33+z/3}\text{Ti}_{18-z}\text{Al}_z\text{O}_{54}$ (BNT-AN, $0 \leq z \leq 2$) ceramics were prepared by solid state method, and the effects of the two doping methods on microwave dielectric properties were compared. As the doping amount z increased, the relative dielectric constant (ϵ_r) and the temperature coefficient of resonant frequency (τ_f) values of the ceramics decreased, and the quality factor (Q , usually expressed by $Q \times f$, where f is the resonant frequency) of the ceramics obviously increased when $z \leq 1.5$. With the same z value, the ϵ_r and $Q \times f$ values of Al/Nd co-doped ceramics are both higher than those of Al-doped ceramics. Rietveld refinement, Raman spectroscopy and thermally stimulated depolarization current (TSDC) technique were applied to clarify the relationship among the structure, defects and microwave dielectric properties. It is shown that the $Q \times f$ values of those ceramics were closely related to the strength of the A -site cation vibration and the concentration of oxygen vacancies (B). Excellent microwave dielectric properties of $\epsilon_r = 72.2$, $Q \times f = 16480$ GHz, and $\tau_f = +14.3$ ppm/°C were achieved in BNT-AN ceramics with $z = 1.25$.

1 Introduction

Nowadays, the fifth-generation telecommunication (5G) technology has been developing rapidly, in which ceramic materials could play an important role [1]. Microwave dielectric ceramics with high $Q \times f$ value ($Q = 1/\tan \delta$, and f is the resonant frequency) and excellent temperature stability are widely used to manufacture 5G antennas and filters [2–5]. In order to meet the requirements of device miniaturization, microwave dielectric ceramics having medium/high relative dielectric constant (ϵ_r) have been a focus of research [6], including TiO_2 [7, 8], $\text{Ba}_{6-3x}\text{Ln}_{8+2x}\text{Ti}_{18}\text{O}_{54}$ (BLT, where Ln = rare earth element) [9, 10], $\text{CaO-Li}_2\text{O-Ln}_2\text{O}_3\text{-TiO}_2$ [11, 12], $\text{Ca}_{1-x}\text{Ln}_{2x/3}\text{TiO}_3$ (CLT) [13–15], lead-based perovskite [16, 17], etc. In recent years, BLT with a tungsten-bronze structure and CLT with a perovskite structure have been extensively studied [18–23]. Meanwhile, novel ceramic systems such as $\text{Bi}_2(\text{Li}_{0.5}\text{Ta}_{1.5})\text{O}_7$ [24, 25] and BiVO_4 [26, 27] have also been developed. However, the above-mentioned ceramic materials either have a relatively low $Q \times f$ value or a relatively large temperature coefficient of resonant frequency (τ_f), which cannot yet meet the application needs of 5G technology. It is necessary to develop microwave dielectric ceramics with better comprehensive performance.

The crystal structure of BLT ceramics is composed by three types of large cation sites: $A1$ rhombic sites, $A2$ pentagonal sites, and B sites (occupied by Ti^{4+}) in the center of TiO_6 octahedra [10]. According to Ohsato's report [10], Ln^{3+} and Ba^{2+} respectively occupy the $A1$ and $A2$ sites when $x = 2/3$, and the ordering of Ln^{3+} and Ba^{2+} reduces the internal strain and leads to the largest $Q \times f$ value. To further improve the $Q \times f$ value of BLT ceramics, a large amount of doping modification research was displayed, especially the substitution of low-valence cations for Ti^{4+} at the B sites. Chen et al. [28] and Tao et al. [29] replaced Ti^{4+} with the same amount of Al^{3+} to improve the $Q \times f$ value, while the condition of charge balance was not achieved. In order to meet the condition of charge balance, one method was using composite ions such

as $(\text{Cr}_{1/2}\text{Nb}_{1/2})^{4+}$, $(\text{Mg}_{1/3}\text{Nb}_{2/3})^{4+}$ or $(\text{Al}_{1/2}\text{Nb}_{1/2})^{4+}$ to substitute Ti^{4+} [30–32], yet it complicated the synthesis process. The other method is using excessive trivalent cations (4/3 times in stoichiometry) such as Cr^{3+} , Al^{3+} or Ga^{3+} to substitute Ti^{4+} [33–36], yet none of the studies have explained which site these cations entered. Considering that the A1 sites of BLT structure are usually not fully filled, the excessive cations might enter the A1 sites. However, the radii of those cations are much smaller than the size of the A1 sites, which might affect the stability of the crystal lattice and lead to the deterioration of the $Q \times f$ value. Therefore, it is important to conduct a further study on the ion occupancy during these doping process.

The present study proposes a new method to maintain the condition of charge balance in the doping process in $\text{Ba}_4\text{Nd}_{9.33}\text{Ti}_{18}\text{O}_{54}$ (BNT) ceramics, with a chemical formula of $\text{Ba}_4\text{Nd}_{9.33+z/3}\text{Ti}_{18-z}\text{Al}_z\text{O}_{54}$ (BNT-AN, $0 \leq z \leq 2$): using the same amount of Al^{3+} to substitute Ti^{4+} , and adding Nd^{3+} to fill the vacancies at the A1 site simultaneously. Correspondingly, $\text{Ba}_4\text{Nd}_{9.33}\text{Ti}_{18-z}\text{Al}_{4z/3}\text{O}_{54}$ (BNT-A, $0 \leq z \leq 2$) ceramics are also prepared for comparison. The theoretical solid solubility should reach when $z = 2$, at which the vacancies at the A1 site could be completely filled. Rietveld refinement, Raman spectroscopy and thermally stimulated depolarization current (TSDC) are applied to analyze the crystal structure and the strength of the A-site cation vibration. Microwave dielectric ceramics with better comprehensive performance are obtained through Al/Nd co-doping, and the relationship between the structure and the microwave dielectric properties of the ceramics is discussed in the present work.

2 Experimental Procedure

The BNT-A and BNT-AN ceramics were prepared through the traditional solid-state processing. High-purity powders including BaCO_3 (99.8%, Alfa Aesar), Nd_2O_3 (99.9%, Aladdin), TiO_2 (99.99%, Macklin), and Al_2O_3 (99.99%, Aladdin) were used as the raw materials. All the raw powders were calcined at 600 °C for 4 hours, weighed according to the stoichiometric composition and ball milled for 4 hours in ethanol. After drying, the mixture was calcined at 1150 °C for 4 hours, then re-milled and dried. The dried powders were ground with polyvinyl alcohol solution (PVA, 5 wt%) and uniaxially pressed into cylinders with a diameter of 10 mm and an appropriate thickness. Finally the specimens were preheated at 600 °C for 4 hours to remove the binder and sintered in the range of 1350 °C and 1550 °C for 4 hours.

The surfaces of the sintered ceramics were observed by scanning electron microscopy (SEM; MERLIN VP Compact, Carl Zeiss, Germany). The phase compositions and crystal structures of the ceramics were analyzed by X-ray diffraction (XRD; D8 Advance, Bruker, Karlsruhe, Germany) with Cu K α radiation. Rietveld refinement were executed using the FullProf program [37] with XRD data collected over a 2θ range of 10°~120°. The bulk densities of the ceramics were determined by the Archimedes method, and the relative densities were calculated by the measured and theoretical ones. The ϵ_r and τ_f values at microwave range were measured using the Hakki-Coleman method [38] by exciting the TE_{011} resonant mode [39] using a vector network analyzer (HP8720ES, Hewlett-Packard, Santa Rosa, CA, USA). The $Q \times f$ values were measured using the $\text{TE}_{01\delta}$ mode in the cavity method [40]. Raman spectra (20 ~ 1200 cm^{-1})

of the ceramics were measured on a high-resolution Raman spectrometer (LabRAM HR800, Horiba Jobin-Yvon, France) with the existing line at 523 nm of a Nd/YAG laser at room temperature.

TSDC measurements were accomplished using a pA meter (6517B, Keithley, Cleveland, OH), and the temperature was controlled by a quarto temperature controller of Novocontrol Technologies (Montabaur, Germany). The ceramic pellets were polished and gold electrodes were sputtered on both sides. The specimens were initially polarized under a dc electric field (E_p) at a constant temperature (T_p) for a period of time t_p ($100 \text{ V/mm} \leq E_p \leq 350 \text{ V/mm}$, $T_p = 300 \text{ }^\circ\text{C}$, $t_p = 10 \text{ minutes}$), then rapidly cooled to $-100 \text{ }^\circ\text{C}$ with E_p maintained to freeze the polarized defects. After E_p removed and being short-circuited for 10 minutes, the specimens were heated to $300 \text{ }^\circ\text{C}$ with a constant heating rate of $5 \text{ }^\circ\text{C/min}$, with the depolarization currents continually recorded.

3 Results And Discussion

Figure 1 presents the SEM photographs of the surface morphology of the ceramic samples. All BNT-A and BNT-AN samples show a single phase of rod-like grains. As shown in Fig. 1(a)-(c), BNT-A ceramics with different z values could be well-sintered at $1400 \text{ }^\circ\text{C}$, indicating that the sintering temperature of the BNT-A ceramics is stable at around $1400 \text{ }^\circ\text{C}$, and basically does not change with the doping amount. In comparison, BNT-AN ceramics with $z = 2$ are well-sintered at $1550 \text{ }^\circ\text{C}$ as shown in Fig. 1(f), illustrating that the sintering temperature of the BNT-AN ceramics increases with increasing doping amounts. Figure 1(d)(e) show that the grain size of the ceramics with the same composition becomes larger as the sintering temperature gets higher.

The XRD patterns of the ceramic samples are shown in Fig. 2. All samples can be confirmed as a single phase with a tungsten-bronze structure ($\text{Ba}_{3.99}\text{Sm}_{9.34}\text{Ti}_{18}\text{O}_{54}$, PDF#89-4356). The detailed XRD data with a 2θ range of $31^\circ \sim 35^\circ$ are presented in Fig 2(b), which shows that the peaks shift towards higher degrees as z value increases, indicating that the cell volume decreases. This demonstrates that Al^{3+} with a smaller ionic radius ($0.54 \text{ \AA}$, CN=6) successfully enters into the lattice and substitutes for Ti^{4+} with a larger ionic radius ($0.61 \text{ \AA}$, CN=6). Rietveld refinement was performed to further explore the changes of phase composition and lattice parameters with doping amount. Figure 3(a)-(c) shows the refined results of the BNT, BNT-A ($z = 1.25$) and BNT-AN ($z = 1.25$) ceramics as examples, respectively. The fitting results are in good agreement with experimental XRD patterns. Figure 3(d) shows that there are a few peaks that cannot be fitted in the experimental data of the BNT-A ceramics, together with χ^2 rises as z value increases, indicating that a small amount of unknown secondary phase appears. In contrast, Fig. 3(e) shows that there is no secondary phase peak in the experimental data of the BNT-AN ceramics. The above-mentioned unknown secondary phase may have an impact on the microwave dielectric properties of the BNT-A ceramics.

The lattice parameters and cell volumes calculated by Rietveld refinement are shown in Fig. 4. The lattice parameters and cell volumes of the BNT-A and BNT-AN ceramics both decrease with the increase in z value, and basically shows the same linear decrease trend as $z \leq 1.25$. This indicates that the type of

trivalent cations (Al^{3+} or Nd^{3+}) filling the vacancies at the *A*1 sites may have less influence on the lattice parameters in the doping process of the BNT ceramics. When $z \geq 1.25$, the lattice parameters and cell volumes of the BNT-AN ceramics continuously show a linear decreasing trend, while the decreasing trend of those of the BNT-A ceramics deviates from linearity. Combining with Fig. 3(d)(e), it can be demonstrated that such a deviation is caused by the secondary phase in the BNT-A ceramics. Therefore, the BNT-A ceramics cannot form a complete solid solution phase when more Al^{3+} ions are added, while the BNT-AN ceramics can form a continuous solid solution in the range of $0 \leq z \leq 2$. The detailed results of the structural parameters and reliability factors obtained by Rietveld refinement are shown in Table S1 and Table S2.

Figure 5 presents the relative densities and microwave dielectric properties of the BNT-A and BNT-AN ceramics. According to Fig. 5(a), the relative densities of almost all ceramic samples have reached higher than 97%, indicating the ceramics are all well densified. When $z \geq 1$, the relative densities of the BNT-AN ceramics is lower than those of BNT-A ceramics with the same doping amount. In addition, the sintering temperature of the BNT-AN ceramics is higher with large z values as illustrated in SEM results. Therefore, the BNT-AN ceramics are more difficult to be well sintered than the BNT-A ceramics. Figure 5(b)(d) show that the ε_r and τ_f values of the ceramics decrease in a similar trend with the increase in z value, which is consistent with the reports of low-valence cations doping at the *B* sites in BLT system [28-36]. According to Shannon's rule [41], ε_r is related to the ionic polarizability (α_D) and the molecular volume (V_m):

$$\alpha_D = \frac{V_m(\varepsilon_{rc} - 1)}{b(\varepsilon_{rc} + 2)} \quad (1)$$

where ε_{rc} is the corrected dielectric constant and b is a constant equal to $4\pi/3$. According to Eq. (1), ε_{rc} increases when α_D increases or V_m decreases. Although the cell volume of the ceramics decreases slightly when z value increases as shown in Fig. 4, the decrease in α_D [$\alpha(\text{Al}^{3+}) < \alpha(\text{Ti}^{4+})$] may mainly dominate the decrease in ε_r . Reaney et al. [6] reported that τ_f is usually determined by ε_r , and the change trends of ε_r and τ_f are often similar in the same ceramic system. When $z \geq 1.25$, the decrease in ε_r of the BNT-A ceramics slows down, and may be related to the small amount of secondary phase, consistent with the previous results of Al-doping in BLT system [35]. Figure 5(c) shows that when $z \leq 1.5$, the $Q \times f$ values of the ceramics significantly increase as z value increases, which may be related to the decline in the activity of illustrated by TSDC technique in our past research [35]. As $z \geq 1.5$, the continuous doping makes the $Q \times f$ values of the ceramics decrease slightly. The decrease in the $Q \times f$ values of the BNT-A ceramics may be affected by the secondary phase, and that of BNT-AN ceramics may be related to the decline of densification. BNT-AN ceramics with $z = 1.25$ have reached excellent microwave dielectric properties: $\varepsilon_r = 72.2$, $Q \times f = 16480$ GHz, and $\tau_f = +14.3$ ppm/°C.

It is noticed from Fig. 5(b)(c) that when $z \leq 1.5$, the ε_r and $Q \times f$ values of the BNT-AN ceramics are both higher than those of the BNT-A ceramics with the same doping amount, indicating that Al/Nd co-doping may be a superior strategy for substitution in the BNT ceramics. The comparison of the ε_r and $Q \times f$ values

of these ceramics is visually presented in Fig. 6. This important difference in microwave dielectric properties may be related to factors such as the composition, structure and defects of the ceramics. The trivalent cations filling the vacancies at the *A*1 sites have different polarizabilities [$\alpha(\text{Al}^{3+}) < \alpha(\text{Nd}^{3+})$], which results in higher ϵ_r values of BNT-AN ceramics according to Shannon's rule [41]. As for the $Q \times f$ values, the determinants may become more complicated: in addition to the secondary phase and porosity that have been discussed, the defects and stability of crystal lattice may also play an important role [6]. Bond length, bond strength and bond energy are important factors that reflect the stability of crystal lattice, and have been used to explore the relationship between the structure and properties of microwave dielectric properties [42-44]. However, according to the results of Rietveld refinement, the variation of the average bond length of the ceramics related to *z* value is less than 0.01 Å, which is roughly equivalent to the uncertainty of Rietveld refinement method (~0.006 Å). The average bond length of *A*1-O is shown in Fig. S1 as an example. These data could hardly be used for further analysis. Therefore, Raman spectroscopy and TSDC technique are performed to further explore the relationship among the crystal structure, defects and $Q \times f$ values of the ceramics.

Raman spectroscopy can reflect the lattice vibration information of materials. The polarization mechanism of dielectrics in the microwave frequency band is mainly ion displacement polarization [45], which is closely related to the vibration of ions in the crystal lattice. Therefore, Raman spectroscopy is a powerful tool for studying the relationship between the structure and properties of microwave dielectric ceramics [20,32,46-52]. The space group of the BLT superlattice with tungsten-bronze structure is *Pbnm* (No. 62), and there are 24 Raman active vibration modes: $7A_g + 7B_g + 5B_{2g} + 5B_{3g}$ [53]. The Raman spectra results of the BNT-A and BNT-AN ceramics are presented in Fig. 7. A total of 17 Raman vibration modes were observed in the experimental data. As the Raman spectra of the BLT system are excessively complex, previous studies had different opinions on the identification of Raman modes. Nevertheless, most studies considered that the Raman vibration modes in the region of 100~200 cm^{-1} correspond to *A*-site cations translation. The vibration modes in the regions of 200~400 cm^{-1} and 400~600 cm^{-1} were attributed to the rotation and the internal vibration of the TiO_6 octahedra, respectively. The mode at 757 cm^{-1} might correspond to the second order scatter [20,32,50-52]. Limited by the test conditions, vibration modes between 50 cm^{-1} and 100 cm^{-1} in BLT system have not been reported yet. Previous studies on perovskite systems such as SmAlO_3 , NdNiO_3 , LaGaO_3 and BaCeO_3 , which also have the space group symmetry *Pbnm*, reported Raman modes in the region of 50~100 cm^{-1} and identified all those modes as *A*-site cations translation [54-58]. Therefore, in the BNT-A and BNT-AN systems, the vibration modes between 50 cm^{-1} and 100 cm^{-1} are identified as *A*-site cations translation as well as the vibration modes between 100 cm^{-1} and 200 cm^{-1} . It is reported that the mode at 234 cm^{-1} was considered as the tilting vibration of the TiO_6 octahedra when the *A* sites are occupied by Ba^{2+} [47,53]. The doping methods in the present work have not made any changes to the Ba^{2+} cations occupying the *A*2 sites, so it can be considered that this mode does not change significantly. In order to compare the intensities of the Raman modes, the relative intensities of the Raman spectra in Fig. 7 were obtained by normalizing the experimental intensities based on the peak values of the Raman mode at 234 cm^{-1} .

As shown in Fig. 7, with the increase in z value, most of the Raman modes present a blue-shift, which indicates that the cell volume decreases [20,32,48,51,52], consistent with the XRD results. The relative intensities of the vibration modes in the region of $300\sim 400\text{ cm}^{-1}$ increase slightly as z value increases, implying that the tilting vibration of the TiO_6 octahedra becomes stronger, and the decline of τ_f is related to this phenomenon [47,50,52]. The more obvious changes appear in the vibration modes between 50 cm^{-1} and 200 cm^{-1} , which are identified as A -site cations translation. As z value increases, the relative intensities of these Raman modes are significantly reduced, where the variation of relative intensities of the Raman modes at 80 cm^{-1} and 94 cm^{-1} is shown in Fig. 8 as an example. It represents that the A -site cations translation is weakened, indicating that the binding force towards the A -site cations is strengthened, and accordingly the contribution to the microwave dielectric loss is reduced and the $Q \times f$ values increase. Comparing the Raman spectra of BNT-A and BNT-AN ceramics with the same z value, it is found that the relative intensities of the Raman modes at 80 cm^{-1} and 94 cm^{-1} of the BNT-AN ceramics are lower than those of the BNT-A ceramics, as shown in Fig. 8. It is implied that the strength of the A -site cation vibration in the BNT-AN ceramics is weaker, so the contribution to the microwave dielectric loss is lower and the $Q \times f$ values is higher. Briefly, the present work has established the relationship between the $Q \times f$ values and the strength of the A -site cation vibration in the BNT-A and BNT-AN systems through Raman spectroscopy.

TSDC technique can provide valuable information on the types and concentrations of defects in dielectrics, and has been widely used to explore the dielectric response mechanism of ceramics [35,59-66]. Liu et al. [59] firstly reported the method for determining the types of defects in inorganic dielectrics through the changes in peak position (T_m , the temperature at which the absolute value of current density is maximized) and peak intensity (J_m , the maximum of the absolute value of current density) of the TSDC curves with various polarization conditions (T_p and E_p), and Zhang et al. [64] applied this method to microwave dielectric ceramics for the first time. Figure 9 shows the TSDC curves of the BNT, BNT-A ($z = 1.25$) and BNT-AN ($z = 1.25$) ceramics. The curves of all samples show three or four TSDC peaks, indicating that there are at least three or four defect relaxation mechanisms, respectively. In the range of $50\text{ }^\circ\text{C} < T_m < 150\text{ }^\circ\text{C}$, there is a weak peak (referred to as peaks A_1 , A_2 and A_3) in each figure. And peaks similar to each other (referred to as peaks B_1 , B_2 and B_3) are displayed in the range of $160\text{ }^\circ\text{C} < T_m < 200\text{ }^\circ\text{C}$. The TSDC curves of different samples are quite different in the high temperature section above $200\text{ }^\circ\text{C}$. The curves of undoped sample exhibit a very strong peak (referred to as peak D_1), and its T_m values have exceeded the test range. The curves of two doped samples both show peaks with similar changes (referred to as peaks C_2 and C_3) at around $240\text{ }^\circ\text{C}$. The TSDC curves of the BNT-A ($z = 1.25$) ceramics also show a weak peak (referred to as peak D_2) with $T_m > 280\text{ }^\circ\text{C}$.

The T_m and J_m of peaks A_1 and A_3 both increase with an increase in E_p , indicating that these peaks are likely related to the relaxation of . As E_p increases, the J_m of peak A_2 increases while the T_m decreases, indicating that peak A_2 may be related to the relaxation of trapped charges. Using the initial rise method [64,67], the activation energies of peaks A_1 , A_2 and A_3 are calculated as $0.43\sim 0.50\text{ eV}$, $0.14\sim 0.17\text{ eV}$ and

0.24~0.36 eV, respectively. Based on previous results [35,62,63], the activation energies of peaks A_1 and A_3 are close to those of the in-grain, and it can be inferred that these peaks are related to the relaxation of the in-grain. The T_m and activation energy of peak A_2 are similar to those of peaks A_1 and A_3 , and it is speculated that peak A_2 may correspond to trap charges associated with the in-grain. Peaks B_1 , B_2 , B_3 , C_2 and C_3 have T_m values which basically unchanged with polarization conditions, while their J_m values increase with an increase in E_p , indicating that they may be related to the relaxation of defect dipoles. The calculated activation energies of peaks B_1 , B_2 and B_3 are 0.58~0.80 eV, 0.64~0.75 eV and 0.59~0.75 eV, respectively. According to the results from previous studies [35,61,68], it can be inferred that peak B is related to the relaxation of the defect dipoles. Although the activation energies of peaks C_2 and C_3 are difficult to calculate by the initial rise method, the type of defects related to peak C could be determined by the defect reactions in the doping process, considering that peak C appears only after doping. During the substitution process of Al^{3+} for Ti^{4+} at the B sites, point defects are formed. Meanwhile, excess trivalent cations (Al^{3+} or Nd^{3+}) were added to fill the vacancies at the A1 sites, forming or point defects. Thus the condition of charge balance could be ensured, without ion valence changing or producing. Therefore, peak C_2 and C_3 are considered as the relaxation peaks of the and defect dipoles, respectively. As for peak D_1 , the current density rises slower when E_p is higher, indicating that it will reach a peak value at a higher temperature with higher E_p , which signifies that peak D_1 may be related to the relaxation of. The calculated activation energy of peak D_1 is 0.98~1.19 eV, similar to that of the across-grain-boundary (1.1 eV) [35,60]. It is implied that peak D_1 is likely related to the relaxation of the across-grain-boundary. Since the position of peak D_2 is similar to peak D_1 , it is speculated that the relaxation mechanisms of the two are the same, so that it can be considered that peak D_2 is also related to the relaxation of the across-grain-boundary.

TSDC peaks with higher J_m imply a higher concentration of the corresponding defects [66,69]. Comparing the TSDC curves of the three ceramic samples, the BNT ceramics with peak D_1 in Fig. 9(a) show an extremely high concentration of the across-grain-boundary, while the BNT-A ($z = 1.25$) ceramics with peak D_2 in Fig. 9(b) show only a small amount of across-grain-boundary, and the BNT-AN ($z = 1.25$) ceramics show no peaks corresponding to across-grain-boundary in Fig. 9(c). It is generally believed that oxygen vacancies could cause the extrinsic loss of dielectric ceramics and affect the $Q \times f$ values at microwave frequency bands [6]. The TSDC results in the present work are consistent with it. It is noticed that each O^{2-} in the crystal lattice is adjacent to several A-site cations in BLT system. Associating the results of TSDC with the aforementioned Raman spectroscopy of the BNT-A and BNT-AN ceramics, it can be found that with the strengthening of binding force between the A-site cations and O^{2-} , the formation of becomes difficult, indicating that the results of TSDC and Raman spectroscopy are consistent. It is demonstrated for the first time that in the BNT-A and BNT-AN ceramics, the formation of in the crystal lattice is closely related to the strength of the A-site cation vibration, and affects the lattice vibration then affects the microwave dielectric loss.

4 Conclusions

The Al-doped and Al/Nd co-doped BNT ceramics are prepared through the solid state processing. The microwave dielectric properties of the BNT-A and BNT-AN ceramics are compared, and the relationship among the composition, structure, defects and microwave dielectric properties of the ceramics was explored through Rietveld refinement, Raman spectroscopy and TSDC technique. As the doping amount increases, the ϵ_r and τ_f values of the ceramics decrease, and the $Q \times f$ values first increase and then slightly decrease. The ϵ_r and $Q \times f$ values of BNT-AN ceramics are both higher than those of BNT-A ceramics, indicating that Al/Nd co-doping is a novel and superior doping method that maintains the condition of charge balance. The results of Rietveld refinement show that there is a small amount of unknown secondary phase in the BNT-A ceramics, and the relative density data show that the BNT-AN ceramics are more difficult to densify, which may result in the deterioration of microwave dielectric performance when $z \geq 1.5$. Raman spectroscopy and TSDC measurement together show that the $Q \times f$ values of the BNT-A and BNT-AN ceramics are closely related to the strength of the A-site cation vibration and the concentration of . With the strengthening of binding force between the A-site cations and O^{2-} , the contribution of the A-site cations to the microwave dielectric loss reduces and the $Q \times f$ values decrease, together with that the formation of becomes difficult. It is also proved that in microwave frequency bands, oxygen vacancies affect the dielectric loss by affecting the lattice vibration. Microwave dielectric ceramics with excellent performance in the field of medium/high ϵ_r were obtained: $\epsilon_r = 72.2$, $Q \times f = 16480$ GHz, and $\tau_f = +14.3$ ppm/°C, which could have outstanding application prospects in the 5G technology.

Declarations

Acknowledgements

This work was supported by the National Key Research and Development Program of China (Grant No. 2017YFB0406301), Key-Area Research and Development Program of Guangdong Province (Grant No. 2020B010176001), and the National Natural Science Foundation of China (Grant No.51872160).

Electronic Supplementary Material

Supplementary material (add a brief description) is available in the online version of this article.

References

1. Hill MD, Cruickshank DB, MacFarlane IA (2020) Perspective on ceramic materials for 5G wireless communication systems. Appl Phys Lett 118:120501
2. Jin DH, Hu CC, Liu B (2021) Improved sinterability and temperature stability in Zn^{2+}/Ti^{4+} -co-substituted $CaAl_2O_4$ ceramics and their 5G antenna applications. J Mater Sci: Mater Electron 32:18205–18211

3. Clavet Y, Manchec A, Favenne J-F et al (2009) Design of high-permittivity ceramic UHF microstrip filter for a space application. In *Proc Asia Pacific Microwave Conf.* Singapore, 2160–2163
4. Medeiros JLG (2012) Microstrip fractal patch antennas using high permittivity ceramic substrate. In *Proc IEEE Antennas and Propagation Society Int Symp (APSURSI)*. Chicago, 1–2
5. Rhbanou A, Fadl AE, Jebbor N et al (2021) New design of miniature C-band substrate integrated waveguide bandpass filters using ceramic material. *FME Trans* 49:103–112
6. Reaney IM (2006) Microwave dielectric ceramics for resonators and filters in mobile phone networks. *J Am Ceram Soc* 89:2063–2072
7. Cohn SB (1968) Microwave bandpass filters containing high-*Q* dielectric resonators. *IEEE Trans Microw Theory Tech* 16:218–227
8. Zhao E, Hao J, Xue X et al (2021) Rutile TiO₂ microwave dielectric ceramics prepared via cold sintering assisted two step sintering. *J Eur Ceram Soc* 41:3459–3465
9. Ohsato H, Ohhashi T, Nishigaki et al (1993) Formation of solid solutions of new tungsten bronze-type microwave dielectric compounds Ba_{6-3xR8+2x}Ti₁₈O₅₄ (*R* = Nd and Sm, 0 ≤ *x* ≤ 1). *Jpn J Appl Phys* 32:4323–4326
10. Ohsato H (2001) Science of tungstenbronze-type like Ba_{6-3xR8+2x}Ti₁₈O₅₄ (*R* = rare earth) microwave dielectric solid solutions. *J Eur Ceram Soc* 21:2703–2711
11. Ezaki K, Baba Y, Takahashi H et al (1993) Microwave dielectric properties of CaO-Li₂O-Ln₂O₃-TiO₂ ceramics. *Jpn J Appl Phys* 32:4319–4322
12. Zhou C, Chen G, Cen Z et al (2013) Structure and microwave dielectric characteristics of lithium-excess Ca_{0.6}Nd_{0.8/3}TiO₃/(Li_{0.5}Nd_{0.5})TiO₃ ceramics. *Mater Res Bull* 48:4924–4929
13. Yoshida M, Hara N, Takada T et al (1997) Structure and dielectric properties of (Ca_{1-x}Nd_{2x/3})TiO₃. *Jpn J Appl Phys* 36:6818–6823
14. Kim WS, Kim ES, Yoon KH (1999) Effects of Sm³⁺ substitution on dielectric properties of Ca_{1-x}Sm_{2x/3}TiO₃ ceramics at microwave frequencies. *J Am Ceram Soc* 82:2111–2115
15. Huang C-L, Tsai J-T, Chen Y-B (2001) Dielectric properties of (1-*y*)Ca_{1-x}La_{2x/3}TiO₃-*y*(Li,Nd)_{1/2}TiO₃ ceramic system at microwave frequency. *Mater Res Bull* 36:547–556
16. Kato J, Kagata H, Nishimoto K (1992) Dielectric properties of (PbCa)(MeNb)O₃ at microwave frequencies. *Jpn J Appl Phys* 31:3144–3147
17. Kucheiko S, Choi J-W, Kim H-J et al (1997) Microwave characteristics of (Pb,Ca)(Fe,Nb,Sn)O₃ dielectric materials. *J Am Ceram Soc* 80:2937–2940
18. Huang X, Liu X, Liu F et al (2017) Microstructures and microwave dielectric properties of (Ba_{1-x}Sr_x)₄(Sm_{0.4}Nd_{0.6})_{28/3}Ti₁₈O₅₄ solid solutions. *J Adv Ceram* 6:50–58
19. He T, Lv C, Li W et al (2020) The dielectric constant of Ba_{6-3x}(Sm_{1-y}Nd_y)_{8+2x}Ti₁₈O₅₄ (*x* = 2/3) ceramics for microwave communication by linear regression analysis. *Materials* 13:5733

20. Wang G, Fu Q, Guo P et al (2021) Crystal structure, spectra analysis and dielectric characteristics of $\text{Ba}_4\text{M}_{28/3}\text{Ti}_{18}\text{O}_{54}$ (M = La, Pr, Nd, and Sm) microwave ceramics. *Ceram Int* 47:1750–1757
21. Chen Y, Guo W, Luo Y et al (2021) Microwave and terahertz properties of porous $\text{Ba}_4(\text{Sm},\text{Nd},\text{Bi})_{28/3}\text{Ti}_{18}\text{O}_{54}$ ceramics obtained by sacrificial template method. *J Am Ceram Soc* 00:1–10. <https://doi.org/10.1111/jace.17940>
22. Xiong Z, Zhang X, Tang B et al (2021) Characterization of structure and properties in $\text{CaO-Nd}_2\text{O}_3\text{-TiO}_2$ microwave dielectric ceramic modified by Al_2O_3 . *Mater Charact* 176:111108
23. Lin S-H, Lin Z-Q, Chen C-W (2021) Microwave dielectric characterization of $\text{Ca}_{0.6}(\text{La}_{1-x}\text{Y}_x)_{0.2667}\text{TiO}_3$ perovskite ceramics with high positive temperature coefficient. *Ceram Int* 47:16828–16832
24. Zhou D, Pang L-X, Wang D-W et al (2017) High permittivity and low loss microwave dielectrics suitable for 5G resonators and low temperature co-fired ceramic architecture. *J Mater Chem C* 5:10094–10098
25. Ullah A, Liu H, Manan A et al (2021) Microwave dielectric properties of $\text{Bi}_2(\text{Li}_{0.5}\text{Ta}_{1.5})\text{O}_7\text{-TiO}_2$ -based ceramics for 5G cellular base station resonator application. *Ceram Int* 47:8416–8423
26. Structure-property relationships (2017) of low sintering temperature scheelite-structured $(1-x)\text{BiVO}_4\text{-xLaNbO}_4$ microwave dielectric ceramics. *J Mater Chem C* 5:2695–2701
27. Pang L-X, Zhou D, Liu W-G et al (2018) Crystal structure and microwave dielectric behaviors of scheelite structured $(1-x)\text{BiVO}_4\text{-xLa}_{2/3}\text{MoO}_4$ ($0.0 \leq x \leq 1.0$) ceramics with ultra-low sintering temperature. *J Eur Ceram Soc* 38:1535–1540
28. Chen H, Tang B, Gao A et al (2015) Aluminum substitution for titanium in $\text{Ba}_{3.75}\text{Nd}_{9.5}\text{Ti}_{18}\text{O}_{54}$ microwave dielectric ceramics. *J Mater Sci: Mater Electron* 26:405–410
29. Tao J, Mu M, Wang X et al (2018) Improved microwave dielectric properties of anti-reduction $\text{Ba}_4(\text{Ce}_{0.5}\text{Sm}_{0.5})_{9.3}\text{Ti}_{18-z}\text{Al}_z\text{O}_{54}$ ceramics sintered in nitrogen atmosphere. *J Mater Sci: Mater Electron* 29:1392–1398
30. Guo X, Tang B, Liu J et al (2015) Microwave dielectric properties and microstructure of $\text{Ba}_6 - 3x\text{Nd}_{8+2x}\text{Ti}_{18-y}(\text{Cr}_{1/2}\text{Nb}_{1/2})_y\text{O}_{54}$ ceramics. *J Alloy Compd* 646:512–516
31. Chen H, Tang B, Duan S et al (2015) Microstructure and microwave dielectric properties of $\text{Ba}_{3.75}\text{Nd}_{9.5}\text{Ti}_{18-z}(\text{Mg}_{1/3}\text{Nb}_{2/3})_z\text{O}_{54}$ Ceramics. *J electron mater* 44:1081–1087
32. Xiong Z, Tang B, Fang Z et al (2017) Crystal structure, Raman spectroscopy and microwave dielectric properties of $\text{Ba}_{3.75}\text{Nd}_{9.5}\text{Ti}_{18-z}(\text{Al}_{1/2}\text{Nb}_{1/2})_z\text{O}_{54}$ ceramics. *J Alloy Compd* 723:580–588
33. Chen H, Xiong Z, Yuan Y et al (2016) Dependence of microwave dielectric properties on site substitution in $\text{Ba}_{3.75}\text{Nd}_{9.5}\text{Ti}_{18}\text{O}_{54}$ ceramic. *J Mater Sci: Mater Electron* 27:10951–10957
34. Tang B, Xiang Q, Fang Z et al (2018) Microwave dielectric properties of $\text{Ba}_{3.75}\text{Nd}_{9.5}\text{Ti}_{18-z}\text{Cr}_{4z/3}\text{O}_{54}$ ceramics. *J Mater Sci: Mater Electron* 29:535–540
35. Guo W, Zhang J, Luo Y et al (2019) Microwave dielectric properties and thermally stimulated depolarization of Al-doped $\text{Ba}_4(\text{Sm},\text{Nd})_{9.33}\text{Ti}_{18}\text{O}_{54}$ ceramics. *J Am Ceram Soc* 102:5494–5502

36. Wang G, Fu Q, Shi H et al (2020) Novel thermally stable, high quality factor $\text{Ba}_4(\text{Pr}_{0.4}\text{Sm}_{0.6})_{28/3}\text{Ti}_{18-y}\text{Ga}_{4y/3}\text{O}_{54}$ microwave dielectric ceramics. *J Am Ceram Soc* 103:2520–2527
37. Rodriguez-Carvajal J. FullProf suite 2000 (Version September 2020, Laboratoire Leon Brillouin)
38. Hakki BW, Coleman PD (1960) A dielectric resonator method of measuring inductive capacities in the millimeter range. *IRE Trans Microwave Theory Tech* 8:402–410
39. Courtney WE (1970) Analysis and evaluation of a method of measuring the complex permittivity and permeability microwave insulators. *IEEE Trans Microwave Theory Tech* 18:476–485
40. Krupka J, Derzakowski K, Riddle B et al (1998) A dielectric resonator for measurements of complex permittivity of low loss dielectric materials as a function of temperature. *Meas Sci Technol* 9:1751–1756
41. Shannon RD (1993) Dielectric polarizabilities of ions in oxides and fluorides. *J Appl Phys* 73:348–366
42. Xia W-S, Li L-X, Ning P-F et al (2012) Relationship between bond ionicity, lattice energy, and microwave dielectric properties of $\text{Zn}(\text{Ta}_{1-x}\text{Nb}_x)_2\text{O}_6$ ceramics. *J Am Ceram Soc* 95:2587–2592
43. Zheng J, Yang Y, Wu H et al (2020) Structure, infrared spectra and microwave dielectric properties of the novel Eu_2TiO_5 ceramics. *J Am Ceram Soc* 103:4333–4341
44. Liu L, Du J, Tao B et al (2021) Structure, microwave dielectric properties, and infrared reflectivity spectrum of W^{6+} substituted $\text{Ce}_2\text{Zr}_3(\text{MoO}_4)_9$ ceramics. *Ceram Int* 47:19142–19152
45. Sebastian MT (2008) Dielectric materials for wireless communication. Elsevier, Amsterdam
46. Chen MY, Chia CT, Lin IN et al (2006) Microwave properties of $\text{Ba}(\text{Mg}_{1/3}\text{Ta}_{2/3})\text{O}_3$, $\text{Ba}(\text{Mg}_{1/3}\text{Nb}_{2/3})\text{O}_3$ and $\text{Ba}(\text{Co}_{1/3}\text{Nb}_{2/3})\text{O}_3$ ceramics revealed by Raman scattering. *J Eur Ceram Soc* 26:1965–1968
47. Wu SY, Li Y, Chen XM (2004) Raman spectra of Nd/Sn cosubstituted $\text{Ba}_{6-3x}\text{Sm}_{8+2x}\text{Ti}_{18}\text{O}_{54}$ microwave dielectric ceramics. *J Appl Phys* 96:5683–5686
48. Liao Q, Li L (2012) Structural dependence of microwave dielectric properties of ixiolite structured $\text{ZnTiNb}_2\text{O}_8$ materials: crystal structure refinement and Raman spectra study. *Dalton Trans* 41:6963–6969
49. Ning F, Gan L, Yuan S et al (2017) Correlation between vibrational modes of A-site ions and microwave dielectric properties in $(1-x)\text{CaTiO}_3-x(\text{Li}_{0.5}\text{Sm}_{0.5})\text{TiO}_3$ ceramics. *J Alloy Compd* 729:742–748
50. Wang G, Fu Q, Shi H et al (2019) Suppression of oxygen vacancies generation in $\text{Ba}_{6-3x}\text{Sm}_{8+2x}\text{Ti}_{18}\text{O}_{54}$ ($x = 2/3$) microwave dielectric ceramics through Pr substitution. *Ceram Int* 45:22148–22155
51. Wang G, Fu Q, Guo P et al (2020) A/B-site cosubstituted $\text{Ba}_4\text{Pr}_{28/3}\text{Ti}_{18}\text{O}_{54}$ microwave dielectric ceramics with temperature stable and high Q in a wide range. *Ceram Int* 46:11474–11483
52. Xiong Z, Tang B, Yang C et al (2018) Correlation between structures and microwave dielectric properties of $\text{Ba}_{3.75}\text{Nd}_{9.5-x}\text{Sm}_x\text{Ti}_{17.5}(\text{Cr}_{1/2}\text{Nb}_{1/2})_{0.5}\text{O}_{54}$ ceramics. *J Alloy Compd* 740:492–499

53. Wu SY, Li Y, Chen XM (2003) Raman spectra of $\text{Ba}_{6-3x}\text{Sm}_{8+2x}\text{Ti}_{18}\text{O}_{54}$ solid solution. *J Phys Chem Solids* 64:2365–2368
54. Scott JF (1970) High-temperature Raman study of samarium aluminate. *Phys Rev B* 1:4182–4185
55. Zaghrioui M, Bulou A, Laffez P et al (2000) Raman study of metal-insulator transition in NdNiO_3 thin films. *J Magn Magn Mater* 211:238–242
56. Sanjuán ML, Orera VM, Merino RI et al (1998) Raman and x-ray study of $\text{La}_{1-x}\text{Nd}_x\text{GaO}_3$ ($0 \leq x \leq 1$) perovskite solid solutions. *J Phys: Condens Matter* 10:11687–11702
57. Tompsett GA, Sammes NM, Phillips RJ (1999) Raman spectroscopy of the LaGaO_3 phase transition. *J Raman Spectrosc* 30:497–500
58. Loidant S, Abello L, Lucazeau G (1997) Polarized Raman spectra of single crystals of BaCeO_3 . *J Raman Spectrosc* 28:283–288
59. Liu W, Randall CA (2008) Thermally stimulated relaxation in Fe-doped SrTiO_3 systems: I. single crystals. *J Am Ceram Soc* 91:3245–3250
60. Yoon S-H, Randall CA, Hur K-H (2010) Correlation between resistance degradation and thermally stimulated depolarization current in acceptor (Mg)-doped BaTiO_3 submicrometer fine-grain ceramics. *J Am Ceram Soc* 93:1950–1956
61. Lee H, Kim JR, Lanagan MJ et al (2013) High-energy density dielectrics and capacitors for elevated temperatures: $\text{Ca}(\text{Zr,Ti})\text{O}_3$. *J Am Ceram Soc* 96:1209–1213
62. Zhang X, Zhang Y, Zhang J et al (2014) Microwave dielectric properties and thermally stimulated depolarization currents study of $(1-x)\text{Ba}_{0.6}\text{Sr}_{0.4}\text{La}_4\text{Ti}_4\text{O}_{15}-x\text{TiO}_2$ ceramics. *J Am Ceram Soc* 97:3170–3176
63. Zhang X, Zhang J, Xie Z et al (2015) Structure, microwave dielectric properties and thermally stimulated depolarization currents of $(1-x)\text{Ba}_{0.6}\text{Sr}_{0.4}\text{La}_4\text{Ti}_4\text{O}_{15}-x\text{Ba}_5\text{Nb}_4\text{O}_{15}$ solid solutions. *J Am Ceram Soc* 98:1245–1252
64. Zhang J, Zhou Y, Peng B et al (2014) Microwave dielectric properties and thermally stimulated depolarization currents of MgF_2 -doped diopside ceramics. *J Am Ceram Soc* 97:3537–3543
65. Zhang J, Yue Z, Luo Y et al (2017) Understanding the thermally stimulated relaxation and defect behavior of Ti-containing microwave dielectrics: a case study of BaTi_4O_9 . *Mater Des* 130:479–487
66. Luo Y, Zhang J, Yue Z et al (2018) Improvement in microwave dielectric properties of Sr_2TiO_4 ceramics through post-annealing treatment. *J Electroceram* 41:67–72
67. Hino T (1980) Thermally stimulated characteristics in solid dielectrics. *IEEE Trans Electr Insul* 15:301–311
68. Lee S-J, Kang K-Y, Han S-K (1999) Low-frequency dielectric relaxation of BaTiO_3 thin-film capacitors. *Appl Phys Lett* 75:1784–1786

Figures

Figure 1

SEM photographs of the BNT, BNT-A and BNT-AN ceramics: (a) BNT, sintered at 1400 °C; (b) BNT-A, $z = 1.25$, sintered at 1400 °C; (c) BNT-A, $z = 2$, sintered at 1400 °C; (d) BNT-AN, $z = 1.25$, sintered at 1400 °C; (e) BNT-AN, $z = 1.25$, sintered at 1500 °C; (f) BNT-A, $z = 2$, sintered at 1550 °C;

Figure 2

(a) XRD patterns of the BNT, BNT-A and BNT-AN ceramics ($z = 0, 0.25, 0.75, 1.25, 1.75$); (b) XRD peaks shift in the range of $31^\circ \leq 2\theta \leq 35^\circ$.

Figure 3

The Rietveld refinement results of (a) the BNT ceramics, (b) the BNT-A ($z = 1.25$) ceramics, and (c) the BNT-AN ($z = 1.25$) ceramics; the detailed Rietveld refinements of (d) the BNT-A ($0.5 \leq z \leq 2$) ceramics and (e) the BNT-AN ($0.5 \leq z \leq 2$) ceramics.

Figure 4

The lattice parameters (a) a , (b) b , (c) c , and (d) the cell volume of the BNT-A and BNT-AN ($0 \leq z \leq 2$) ceramics.

Figure 5

(a) Relative densities, (b) ϵ_r values, (c) $Q \times f$ values and (d) τ_f values of the BNT-A and BNT-AN ($0 \leq z \leq 2$) ceramics.

Figure 6

The ϵ_r and $Q \times f$ values of the BNT-A and BNT-AN ($0 \leq z \leq 2$) ceramics.

Figure 7

Raman spectra of the BNT-A and BNT-AN ($z = 0, 0.25, 0.75, 1.25, 1.75$) ceramics.

Figure 8

The relative intensities of Raman modes at 80 cm⁻¹ and 94 cm⁻¹ of the BNT-A and BNT-AN (z = 0.25, 0.75, 1.25, 1.75) ceramics.

Figure 9

TSDC curves of (a) the BNT ceramics, (b) the BNT-A ($z = 1.25$) ceramics, and (c) the BNT-AN ($z = 1.25$) ceramics under $T_p = 300^{\circ}C$ and $100 V/mm \leq E_p \leq 350 V/mm$.

Supplementary Files

This is a list of supplementary files associated with this preprint. Click to download.

- [FigS1.tif](#)
- [SupplementMaterial.docx](#)
- [TableS1.docx](#)
- [TableS2.docx](#)