The Characterization of Amorphous AZO-n/Si-p Hetrojunction Diode for Solar Cell Application

Soghra Hosseini

Islamic Azad University

Laya Dejam (✉ layadejam@gmail.com)

islamic azad university <https://orcid.org/0000-0003-3925-1838>

Hossain Elahi

Arak University of Technology

Research Article

Keywords: AZO-n/Si-p hetrojunction, Amorphous, Annealing conditions, Sputtering procedure

Posted Date: December 23rd, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-980950/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Version of Record: A version of this preprint was published at Optical and Quantum Electronics on February 26th, 2022. See the published version at <https://doi.org/10.1007/s11082-022-03550-w>.

The characterization of amorphous AZO-n/Si-p heterojunction diode for solar cell application

Soghra Hosseini¹, Laya Dejam^{* 2}, Hossain Elahi³.

¹ Department of Physics, Science and Research Branch, Islamic Azad University, Tehran, Iran

² Department of Physics, West Tehran Branch, Islamic Azad University, Tehran, Iran

³ Assistant professor, Department of Mechanical engineering, Arak University of Technology, Arak, Iran

Abstract

The aim of the present study is to verify the effect of annealing temperature variation on zinc oxide doped with aluminum (AZO) thin films deposited on p-type silicon (Si) substrates. Here, AZO/p-Si heterojunction was annealed in nitrogen environment and its structural, electrical, and optical characterizations were investigated. The results of XRD patterns showed the amorphous structure of AZO thin films. FE-SEM images illustrated the increase of grain size by increasing annealing temperature up to 500°C. The reflectance analysis showed that for this annealing temperature, that the energy band gap of AZO thin film was moved to higher energy level. The electrical properties were investigated by I–V measurement carried out in the light at room temperatures. The short circuit current (I_{SC}), ideality factor, saturation current, and open circuit voltage (V_{OC}) of the AZO/p-Si heterojunction strongly depended on annealing conditions due to charge carrier trapping and density of defect on interface. By considering I_R and I_F as reverse and forward current, the ration of I_F/I_R had the maximum value at 1 V which was belonged to n-AZO/p-Si heterojunction at 500°C annealing temperature.

Keywords: AZO-n/Si-p heterojunction, Amorphous, Annealing conditions, Sputtering procedure.

1. Introduction

Transparent conducting oxide (TCO) films have attracted a lot of attention in recent decades. Zinc oxide is a good candidate for TCO films due to excellent electrical, structural, and optical properties like doping suitability and non-toxicity, as well as

* Layadejam@gmail.com

high thermal, mechanical, and chemical stability [1-2]. Therefore, ZnO can be considered as suitable choice in optoelectronic and electronic devices like, gas sensors, transparent electrodes, light emitting diodes, varistors, nanolasers heterojunctions, and etc. [3–4] Moreover, ZnO thin film deposited on p/n silicon substrate can be applied in optoelectronic devices and solar cells as a useful heterojunctions whose main advantages are the low cost of silicon and the high energy of band gap of ZnO thin films [5].

Because of high sensitivity of pure ZnO thin films to the oxidation and also its high transmittance in the visible area, ZnO thin films were doped with aluminum initially. Then, all samples were annealed in order to decrease resistivity and increase band gap energy, carrier concentration, and stability [6]. On the other hand, Al:ZnO (AZO) is a promising material for light emitting diodes, solar cells, and gas sensors along with general optoelectronic applications [7-8].

The advantages of silicon-based solar cells are like non-toxicity and low cost make them to be applied in photovoltaic systems [9]. AZO thin films as a front electrode must be conductive enough to allow lateral transfer of electron from sufficient light (80%) to the incoming light [10].

Several methods have been applied to fabricate AZO thin films including pulsed laser deposition (PLD), evaporation, chemical vapor deposition, magnetron sputtering, and spray pyrolysis [11-12]. Among these methods, thin films with high-quality are prepared by magnetron sputtering technique because of its special conditions like low temperature deposition, large-area fabrication adaptability, repeatability, and uniformity as well as working power and sputtering pressure [13].

Specific interest of ZnO/Si and AZO/p-Si heterojunctions is observed in the optoelectronic devices strong adhesion. So far, a lot of researches have been focused on AZO/p-Si heterojunction. Bo et. al. [14] fabricated Al-doped n-ZnO/p-Si heterojunctions by the deposition of AZO film on p-Si (1 0 0) wafer and investigated their optical, microstructural, and electrical properties. They found good quality of samples and their rectifying behavior under dark condition. Urper et. al. [15] also fabricated ZnO:Al thin film by sol-gel dip coating method and studied the relationship between Al content and optical band gap of the films. They also analyzed crystalline structure and electrical resistivity of samples under different annealing conditions. Baydogan et. al. [16] found hexagonal wurtzite crystal structure of ZnO:Al thin films prepared by sol-gel dip coating method. They also demonstrated that the optical band gap was broadened by increasing Al concentration. The novelty of our work is that we have focused on the optical, structural and electrical properties of amorphous AZO thin films prepared by sputtering. So far, according to our studies, amorphous AZO thin films has not been

considered as a diode and making amorphous thin films is easier and cheaper. Also we have investigated the improvement of amorphous AZO/p-Si heterojunction and find the best structural conditions for AZO/p-Si as a diode and solar cell.

In the present work, AZO thin films were deposited on p type silicon substrate by RF magnetron sputtering method. AZO thin films were annealed with nitrogen gas at three different temperatures. Then, their electrical, optical, and structural properties as well as their morphology were investigated. For this purpose, every junction of AZO amorphous thin film and Si was taken into consideration and Si/AZO heterojunction diode properties were determined. As can be seen, annealing in nitrogen atmosphere and Al dopant ends to the extreme enhancement of blue, violet and green emissions.

2. Experimental details

AZO thin films were deposited by radio-frequency (RF) magnetron sputtering on p-type silicon substrate for 75 minutes. The diameter of circle-shaped target was 2.5 cm with the thickness of 3 mm. The weight ratio of Al and Zn were ~10% and 90%, respectively. The working gas was constant amount of ($O_2 + Ar$) where the ratio of O_2 was 30% and the power was 175 W. The initial vacuum and basic pressure were set as 6.4×10^{-3} mbar and 6.5×10^{-5} mbar, respectively. The substrates were initially cleaned and then placed in acetone and ethanol bath for 15 minutes. They were finally dried in a clean room. In order to remove any oxide residues, samples were pre-sputtered 30 minutes. Afterward, samples were annealed for 60 minutes at 400 °C, 500 °C, and 600 °C annealing temperatures at the presence of nitrogen gas and then, they were cooled down to room temperature gradually. The details of sputtering process are presented in Table 1. The thickness of prepared AZO thin film was measured 200 ± 5 nm.

To characterize the crystalline nature of samples, XRD patterns were extracted from STOE-XRD diffractometer using Cu-K α line ($\lambda = 0.15406$ nm). Also, the topography of AZO thin films was investigated by the non-contact mode atomic force microscopy (AFM) (Veeco-AutoProbe-research) and field emission scanning microscopy (FESEM) (MIRA3 TESCAN). Energy dispersive X-ray (EDX) analysis was performed by MIRA3 TESCAN to analyze the information about the elements of samples. The optical transmittance spectra of the deposited films were recorded by the UV–VIS–NIR spectrophotometer (CARY-500 UV-VIS-NIR) in the range of 200–1600 nm. Photoluminescence (PL) was also used to reveal the luminescence characteristics of samples by Cary Eclipse spectrometer equipped with a xenon lamp with 320 nm (AZO) excites wavelength. The current–voltage (I–V) measurement was finally carried out by solar simulator (SIM-1030) and Palm Sense.

Table .1 .The technical details of sputtering process for each sample

Substrate	Base Pressure (mbar)	Work Pressure (mbar)	Power (W)	Time (min)	Gas	Thickness (± 5 nm)	Rat (A° / S)
Si	6.5×10^{-5}	6×10^{-3}	175	75	oxygen% 30 argon% 70	200	0.37

3. Results and discussion

3.1 Structure properties

Fig. 1 illustrates XRD patterns of AZO thin films on silicon substrates. As can be seen, there is just one peak at 68 degree related to silicon substrate and there is no peak related ZnO (hexagonal wurtzite) crystal structure. Therefore, amorphous nature of AZO thin films is demonstrated by XRD patterns. The crystalline peak of Si is of very high intensity. Therefore, the AZO thin films on the glass substrate were also grown and annealed under the same conditions to examine their XRD spectrum, which may indicate ZnO crystalline peaks. But no specific peak was observed for the crystal structure of ZnO on the glass substrates. The method of preparing the AZO thin films can be the reason for the amorphous structure of the thin films. Existence of Zn/Al target and oxygen gas enters the environment during sputtering. For thin thicknesses, it is not possible to form the crystal structure of AZO thin films. In the same manufacturing and annealing conditions with thicker thicknesses, we prepared the crystal structure of AZO thin films [10,13]. Similar results have been gained by other researchers who prepared AZO thin films without annealing process [8-10]. Incidentally, the interesting point of the research is that although there is no change in thin film structure up to 600 °C annealing temperature, the electrical and optical properties of samples have been changed. Most research focus on the amorphous nature of AZO thin films. However, their crystalline structure has been studied extensively [14-16].

Fig. 1 XRD patterns of AZO thin films with different annealing temperatures

Fig. 2. The EDX spectra of (a) as deposited, and annealed AZO/p-Si heterojunction at (b) 400°C (c) 500°C, and (d) 600°C.

As can be seen in Fig. 2 (a-d), EDX data approved the existence of Zn and Al in as-deposited and annealed thin films and determined their stoichiometry. Moreover, any significant variation were observed in weight and atomic percentage of AZO thin films after annealing process.

Fig.3. FESEM images (a-d) of as deposited and annealed AZO/p-Si heterojunction at different annealing temperatures

FESEM images in Fig. 3 (a-d) represent the topography of as deposited and annealed AZO thin films. As can be seen, there are irregular and non-uniform nanograins in the as deposited sample whose average size is ~55 nm. Increasing annealing temperature up to 500°C increases the average diameter because of agglomeration and the best grain adhesion is occurred at 500°C and the grain boundaries are much smaller, which is very important for electrical properties because they control the movement of electrical charges. By increasing annealing temperature to 600°C, the distribution is disrupted due to grain movements. In fact, at this temperature, the particles have not become smaller, but have dispersed, and the grain boundaries have increased. This is also confirmed in the AFM particle distribution diagram (Table 2).

Fig .4. 3D AFM images (a-d) of as deposited and annealed of AZO/p-Si heterojunction

Fig .5. Distribution of topology for as deposited and annealed of AZO/p-Si heterojunction

Surface morphology of AZO films was examined by their 3-D AFM images (a-d) as illustrated in Fig. 4. As can be seen, surface roughness is increased by increasing annealing temperature (Table 2) which may be due to the grains stickiness, the creation of a rough surface, and the variation of RMS roughness under nitrogen gas flow range from 0.42 to 1.61 nm. In addition, the surface of as-deposited AZO thin film is smoother and more interconnected which is formed by annealing particles at the grain boundaries, resulting in a variety of sizes. Fig. 5 shows the morphological changes of thin film surface. Particle distributions differ from the Gaussian diagram by increasing annealing temperature. Especially at 600°C, the dispersion of nanoparticles is much higher which is exactly the behavior observed in FESEM images. Increasing annealing temperature increases the energy and surface mobility which results in particle size enhancement. The increase in thermal and kinetic energy has also increased the dispersion of particles on the surface which is a key factor in changing the shape of the Gaussian distribution. On the other hand,

increasing the size of particles and their dispersion on the surface is because of the adhesion of nanoparticles to each other.

3.2 Optical properties

Fig. 6 indicates the reflectance spectra of as deposited and annealed AZO thin films. In the reflectance spectra, a sharp band edge of about 350-400 nm in the as deposited and 400, 600 °C annealed thin films is due to strong adsorption. An obvious blue shift is only observed in AZO thin film annealed at 500 °C which is because of the suffering of its absorption edge. The reflection of AZO thin film at 550-800 nm decreases with annealing. The reduction of the reflection spectrum after annealing may be due to the nano-scaled morphology of the sample which has improved the light traps.

Fig.6. Reflectance of as deposited and annealed AZO/p-Si heterojunction.

Fig.7. Tauc's Plot of as deposited and annealed AZO/p-Si heterojunction

The UV–Vis spectra were inquired by Kubelka- Munk theory to convert thin film reflectance to Kubelka- Munk function ($F(R)$), by Eq (1) [17-19]:

$$F(R) = \frac{(1-R)^2}{2R} \quad (1)$$

where R is the reflectance of sample and depends on wavelength. Eq (2) shows the relationship between $F(R)$ and the absorption coefficient (α) as [17]:

$$\alpha = \frac{F(R)}{t} \quad (2)$$

Where 't' is the thickness of AZO thin films. To evaluate the dependency of band gap to direct allowed transition, the diagram of $(\alpha h\nu)^2$ vs. $h\nu$ is illustrated in Fig. 7 and the band gap was calculated via the linear $h\nu$ -intercept. The value of band gap increases gently from 3.2 eV to 3.9 eV by the increase of annealing temperature up to 500°C. But when the annealing temperature increases to 600°C, the value of band gap decreases. Hence, a critical state has occurred at 500 °C which is also confirmed in previous research [10]. In fact, annealing process decreases the defects while increasing temperature reduces the density of the localized states and decreases their band tail energy. Here, increasing annealing temperature to 500°C decrease the density of the localized states and defects and increases the band gap.

However, AFM and FESEM images of sample annealed at 600°C indicate surface irregularity and uneven distribution of nanoparticles and hence, the increase of defects replacement and localized states as well as decrease of band gap are expected. It should be noted that the results of PL analysis confirms these changes in defects, localized states, and band gap.

Table. 2. Structural, optical and electrical parameters of as deposited and annealed AZO/p-Si heterojunction

Sample	RMS Roughness(nm)	E _g (eV)	E _{g(emiss ion)} (eV)	V _{oc} (V)	I _{sc} (μA)	Ideality factor (n)	I _F /I _R	I _s (μA)
As-Dep	0.42	3.2	3.318	0.05	0.23	29.72	0.82	0.29
400°C	1.03	3.3	3.27	0.06	0.81	24.15	0.39	0.17
500°C	1.53	3.9	4.02	0.21	1.84	22.72	1.72	0.30
600°C	1.61	3.3	3.32	0.13	1.017	21.46	0.38	0.46

Fig.8. PL spectra of as deposited and annealed AZO/p-Si heterojunction

PL spectra in Fig. 8 are applied at room temperature to estimate any annihilation or defect created by annealing. PL emission proved the center of defects that act as centers of recombining charge carrier. For as-deposited and annealed AZO thin films excited at 320 nm, the PL spectra show four emission bands at UV, Violet, Blue and Green emissions. Fitting PL spectra with Gaussian diagram gives valuable information about FWHM and peak positions as summarized in Table 3. The peak at around 374 nm corresponds to UV emission or to the transition of electron from the substitution level below the conduction band to the valence band [20]. The near band-edge emission with the peak at around 393-398 nm results in UV emission because of its dependency to the recombination of free-exciton [21]. The peak around 400nm in all samples is a violet emission which appears because of the electron transition from conduction tail states to the valence states [22]. Moreover, the blue emission observed around (467-489) is revealed by the transition from shallow donor levels of oxygen vacancy to valence band which is in agreement with Xue's report [23]. The peak at around (528-534nm) belongs to green emission which is appeared by the transition from deep donor levels of oxygen vacancies to valence band [24]. Annealing in nitrogen gas flow also affects the presence of green emission [25]. With increasing annealing temperature up to 500°C, the PL centers remarkably increase which are related to the increase in PL intensity. Therefore, increasing density of defects at 500°C results in the increase of recombination and hence, hence, the increase of V_{oc} that can be seen in Table 2 where the maximum V_{oc} is revealed in 500 °C.

Table 3. PL peak positions of as-deposited and annealed AZO/p-Si heterojunction

Sample	Peak positions (nm)	FWHM (nm)
AZO/Si As-Dep	389.55	0.23784
	424.46	72.416
	481.66	21.105
	522.67	69.589
AZO/Si 400°C	379.05	25.211
	422.31	57.583
	478.54	37.693
	521.49	72.36
AZO/Si 500°C	307.85	1.5903
	414.33	67.642
	488.86	43.849
	510.8	121.87
AZO/Si 600°C	372.7	113.92
	415.12	64.947
	439.54	652.71
	491.05	79.492

3.3 The hetrojunction properties of AZO/p-Si

In order to find remarkable information about Schottky diode behavior, current-voltage I-V diagram were measured under illumination at room temperature and presented in Fig. 9 (a) for all samples. An almost photoelectric and rectifying behavior is illustrated in n-AZO/ p-Si heterojunctions. Fig. 9(b) also illustrates the semi-logarithmic forward and reverse bias of the experimental I–V for the n-AZO/ p-Si Schottky diodes.

Fig. 9. (a) I–V diagram and (b) Semi-logarithmic I–V diagram of as-deposited and annealed AZO/p-Si heterojunction.

Fig. 10. Logarithmic I–V plot of as-deposited and annealed AZO/p-Si heterojunction

By considering IR and IF for reverse and forward current, the rectification IF/IR ratio at 1 V is in the range of 0.38 to 1.42. Based on p–n junction theory, the I–V relation of standard diodes is as follow [26]:

$$I = I_s \exp\left(\frac{qV}{nk_B T} - 1\right) \quad (4)$$

where I_s and V is the saturation current and voltage bias, respectively. I_s is measured from the straight line intercept of $\ln I$ at $V = 0$ as:

$$I_s = A^* S T^2 \exp\left(\frac{q\phi_b}{k_B T}\right) \quad (5)$$

Here, q and T are the absolute value of electron charge (1.6×10^{-19} C) and temperature, respectively. Also, V , I , and S are applied voltage, net current, and the diode area, respectively. The value of Boltzmann's constant (k_B) is 1.38×10^{-23} J/K and the barrier height (eV) is labeled as ϕ_b . Also, the value of effective Richardson constant (A^*) for ZNO is $32 \text{ A cm}^{-2} \text{ K}^{-2}$ [27]. The ideality factor (n) of heterojunctions is calculated in Eq. 6 from the slope of the straight line in the forward bias Ln I–V diagram [26]

$$n = \frac{q}{k_B T} \left(\frac{dV}{d \ln I} \right) \quad (6)$$

The values of I_s and n are represented in table 2. The value of I_s for n-AZO/p-Si heterojunction was also reported by for O.Urper et al.[15] and N. Baydogan et al.[16] as 1.5×10^{-6} A and 0.3×10^{-6} A, respectively and they are comparable to the value of I_s in the present study. As it is known, the value of n for an ideal diode is unity and for other devices is bigger than one. Here, the value of ideality factor is similar to the previous research as 38[16] and 20.1[14] which demonstrates that the present diode is not ideal and the reason is the existence of surface states and oxide layer [28].

In order to find the response of photoelectrical parameters, the values of open circuit voltage (V_{OC}) and short circuit current (I_{SC}) were calculated for AZO/p-Si Schottky diodes under 1000 W/m^2 of light source for as deposited and annealed AZO/p-Si heterojunctions. The values of these two parameters have been measured by the results of I-V diagram in Table 2. The values of I_{SC} and V_{OC} are in the regions from 0.23 to $1.84 \mu\text{A}$ and 0.05 to 0.13 V, respectively. The adsorption results also show the maximum and minimum values of I_{SC} at AZO/p-Si annealed at 500°C and as-deposited AZO/p-Si, respectively.

In addition, V_{OC} is related directly to the band gap so that the increase of band gap increases V_{OC} . As can be seen in Table 2, the maximum band gap and hence, the maximum value of V_{OC} are indicated in sample annealed at 500°C . In an ideal device, V_{OC} is limited by radiative recombination. Because of the unique photoelectrical properties of AZO/p-Si annealed at 500°C , it is considered as a suitable candidate in solar cell and photodiode applications.

High values of n in AZO/p-Si diodes maybe be due to the presence of surface states or interfacial layers and demonstrates that the transport mechanism is no longer controlled by thermionic emission [29]. The forward bias $\log I$ vs- $\log V$ plot reveals the dominate mechanisms of transport charge in AZO/p-Si diodes along with a power law treatment of current $I \propto V^{m+1}$ where $(m + 1)$ changes with the injection level and corresponds to trapping centers distribution [29]. As shown in Fig. 10, AZO/p-Si diodes follow three regimes: ohmic, space-charge-limited current (SCLC), and trap filling limit (TFL) [29].

In the low range of voltage, for as-deposited and annealed AZO/p-Si at 400°C in region 1 ($0.05 < \log V < 0.08$), annealed AZO/p-Si at 500°C in ($0.2 < \log V < 0.3$), and annealed AZO/p-Si at 600°C ($0.1 < \log V < 0.15$), an ohmic mechanism controlled the increase of current with voltage. This is because comparing to background thermal carrier density, the value of perfused effective carrier density is lower [30] and it is associated with trapping centers distribution [30]. As the intensity and density of the trap distribution centers for different annealing temperatures

varied in PL analysis, the ohmic region range was also different. In the intermediate range of voltages, for as-deposited and annealed AZO/p-Si at 400°C ($0.08 < \log V < 0.1$), annealed AZO/p-Si at 500°C ($0.3 < \log V < 0.4$), and annealed AZO/p-Si at 600°C ($0.15 < \log V < 0.1$) in region 2, SCLC is the dominate mechanism and the role of voltages is more than region 1. Moreover, comparing to thermal-generated free charge carrier density, the density of perfused free charge is much higher [29] which increases the current. In region 3 with high voltages, for as-deposited and annealed AZO/p-Si at 400°C ($0.1 < \log V < 1$), annealed AZO/p-Si at 500°C ($0.4 < \log V < 1$), and annealed AZO/p-Si at 600°C ($0.2 < \log V < 1$), the exponential increase of current is observed. Here, the trap filling limit controlled the mechanism. Injected electrons fills the deep traps until all trap sites become fully occupied. Interestingly, comparing different regions of voltage for all samples shows that they change with almost the same slope and hence, the behavior of their occupied and trap sites are the same.

Conclusion

The effect of annealing process on structural, electrical, and optical properties of n-AZO/p-Si heterojunction was investigated in the preset study. The fabrication of n-AZO/p-Si heterojunction was carried out by the deposition of AZO thin films on p-Si substrate with magnetron sputtering technique. The XRD results indicated the amorphous structure of as deposited and annealed AZO thin films. FESEM images demonstrated that increasing annealing temperature up to 500°C increased the average diameter because of agglomeration so that the distribution of particles was disrupted. AFM images also illustrated that RMS roughness of samples was increased from 0.42 to 1.61 by the increase of annealing temperature. Also, by increasing temperature to 500°C, the band gap of thin films varied from 3.2 to 3.9 eV. Moreover, PL spectra showed that the PL centers and intensity were considerably increased by increasing annealing temperature. Good rectifying behavior of AZO/p-Si heterojunction annealed at 500 °C was also confirmed. Ideality factor, saturation current, rectification ratio IF/IR , open circuit voltage (V_{OC}), and short circuit current (I_{SC}) were the parameters optimized by the I–V measurements. The dominate mechanisms was transport charge in AZO/p-Si diodes. Since the AZO thin film is in amorphous structure, charge transfers are limited and therefore diode structures could not exhibit very good rectification and photovoltaic properties. However, since making amorphous thin films is easier and cheaper, it has been studied and the remarkable result is that by changing the surface structure of amorphous thin films and eliminating or reducing grain boundaries, electrical properties can be improved.

Declaration of interest: The authors report no conflict of interests. The authors alone are responsible for the content and writing of the paper.

References

- [1] P.P. Sahay, R.K. Nath, *Sens Actuators B*, 134 (2008) 654–659
- [2] L. Dejam, S. M. Elahi, M. M. Larijani and Y. S. Jalili, *Bull. Mater. Sci.* 38 (2015) 1821–1830
- [3] M.S. Wang, K.E. Lee, H.S Hahn, E.J Kim, S. Kim, J.S. Chung, E.W Shin, C. Park, *Mater Lett.* 61(2007) 1118–1121
- [4] O. Kluth, G. Schoöpe, J. Huöpkkes, C. Agashe, J. Muöller, B. Rech, *Thin Solid Films*, 442 (2003) 80–85
- [5] TH. Breivik, S. Diplas, AG. Ulyashin, AE. Gunnæs, BR. Olaisen, DN. Wright, A. Holt, A. Olsen, *Thin Solid Films* 515(2007) 8479–8483
- [6] M. Ilkhani , L. Dejam, *J Mater Sci: Mater Electron*, 32 (2021) 3460–3474
- [7] N.H. Al-Hardan, M.A.A. Hamid, N.M. Ahmed, R. Shamsudin, N.K. Othman, *Sensor. Actuator. A*, 242 (2016) 50–57.
- [8] L. Dejam, A. A. Shokri , H. Honarvar Nazari, S. M. Elahi, *J Mater Sci: Mater Electron*, 28 (2017) 9378–9386
- [9] B.F. Liu, L.S. Bai, T.T. Li, C.C. Wei, B.Z. Li, Q. Huang, D.K. Zhang, G.C. Wang, Y. Zhao, X.D. Zhang, *Energy Environ. Sci.* 10 (2017) 1134–1141.
- [10] L. Dejam, S. M. Elahi, H. Honarvar Nazari, H. Elahi, Sh. Solaymani, A. Ghaderi, *J Mater Sci: Mater Electron* 27 (2016) 685–696
- [11] X.-H. Lu, D. Wang, G.-R. Li, C.-Y. Su, D.-B. Kuang, Y.-X. Tong, *J. Phys. Chem. C*, 113 (2009) 13574–13582
- [12] L. Dejam, Sh. Solaymani, A. Achour, S. Stach, Ş. Ŧälue, N. Beryani Nezafat, V. Dalouji, A. A. Shokri, A. Ghaderi, *Chemical Physics Letters* 719 (2019) 78–90
- [13] S. Talu, M. Bramowicz, S. Kulesza ,Sh. Solaymani, A. Ghaderi, L. Dejam, S. M. Elahi , A. Boochani, *Superlattices and Microstructures* 93 (2016) 109–121
- [14] H. Bo, M. Zh. Quan , X. Jing, Zh. Lei, Zh. N. Sheng, L. Feng, Sh. Cheng, Sh. Ling, Zh. Ch. Yue, Y. Zh. Shan, Y.Y. Ting, *Materials Science in Semiconductor Processing* 12 (2009) 248–252
- [15] O. Urper, O. Karacasu, H. Cimenoglu, N. Baydogan, *Superlattices and Microstructures* 125 (2019) 81–87

- [16] N. Baydogan , O. Karacasu , H. Cimenoglu, J Sol-Gel Sci Technol, 61 (2012) 620–627
- [17] G. K. Williamson, W. H. Hall, Acta Metall., 1 (1953) 22-31.
- [18] A.S. Baranski, M.S. Bennet, W.R. Fawcett, J. Appl. Phys. 54 (1983) 6390; <https://doi.org/10.1063/1.331916>
- [19] R. Choudhary, R. P. Chauhan, J Mater Sci: Mater Electron, 27 (2016)11674–11681
- [20] X.D. Gao, X.M. Li, W.D. Yu, Journal of Solid State Chemistry, 177 (2004)3830–3834.
- [21] H. Zeng, G. Duan, Y. Li, S. Yang, X. Xu, W. Cai, ‘Blue Luminescence of ZnO Nanoparticles Based on Non-Equilibrium Processes: Defect Origins and Emission Controls’
Adv. Funct. Mater., 20 (2010) 561
- [22] S. Cho, J. Ma, Y. Kim, Y. Sun, K. L. Wong, J. B. Ketterson, Applied Physics Letters, 75 (2010) 18.
- [23] Z.Y. Xue, D.H. Zhang, Q.P. Wang, J.H. Wang, Appl. Surf. Sci., 195 (2002)126-129
- [24] Z. Liang, X. Yu, B. Lei, P. Liu, W. Mai, 509 (2011) 5437-5440.
- [25] L. E. Greene, M. Law, J. Goldberger, F. Kim, J. C. Johnson, Y. Zhang, R. J. Saykally, P. Yang, Angewandte Chemie International Edition, 42 (2003) 3031-3034
- [26] N. Baydogan, O. Karacasu, H. Cimenoglu, J Sol-Gel Sci Technol, 61 (2012) 620–627
- [27] C.S. Singh, G. Agarwal, G. Durga Rao, S. Chaudhary, R. Singh, Materials Science in Semiconductor Processing, 4 (2011)1–4.
- [28] S. Majumdar, P. Banerji, S. Majumdar, P. Banerji, J. Appl. Phys., (2009) 043704.
- [29] I. Missoum, Y.S. Ocak, M. Benhaliliba, C.E. Benouis, A. Chaker, Synthetic Metals, 214 (2016) 76–81
- [30] J. Lee, S. S. Kim, K. Kim, J. Hoon Kim, and S. Im, Appl. Phys. Lett., 84 (2004)1701.