Investigation of the Transmission Accuracy of Ball Screw Considering Errors and Preloading Level

Kai Wang

Department of Mechanical Engineering. Nanjing University of Science and Technology, Nanjing, 210094, China

Chang-Guang Zhou

Department of Mechanical Engineering. Nanjing University of Science and Technology, Nanjing, 210094, China

Yi Ou (✉ ouyi3281289@163.com)

Department of Mechanical Engineering. Nanjing University of Science and Technology, Nanjing, 210094, China

Hu-Tian Feng

Department of Mechanical Engineering. Nanjing University of Science and Technology, Nanjing, 210094, China

Research Article

Keywords: Ball screw, transmission accuracy, error analysis, contact deformation

Posted Date: March 17th, 2021

DOI: <https://doi.org/10.21203/rs.3.rs-306460/v1>

License: © ⓘ This work is licensed under a Creative Commons Attribution 4.0 International License.

[Read Full License](#)

Version of Record: A version of this preprint was published at The International Journal of Advanced Manufacturing Technology on October 20th, 2021. See the published version at <https://doi.org/10.1007/s00170-021-08088-x>.

Investigation of the transmission accuracy of ball screw considering errors and preloading level

Kai Wang¹, Chang-Guang Zhou¹, Yi Ou^{*1}, Hu-Tian Feng¹

(1) Department of Mechanical Engineering. Nanjing University of Science and Technology, Nanjing, 210094, China

*Corresponding author. Tel: +86 13914778699; fax: +86 2584315619

E-mail address: ouyi3281289@163.com.

Abstract:

Transmission accuracy is one of the most important parameters in ball screw mechanism (BSM), however, very few researches can be found on the transmission accuracy modelling for BSM. Therefore, this paper proposes a novel model to predicate the transmission accuracy of BSM considering the manufacturing errors, installation errors, as well as the errors due to the contact deformation under different loading status. Meanwhile, the transmission accuracy of a typical BSM under five different preloading levels is measured on the basis of a transmission accuracy measuring system. The experimental results show that the difference is 21.6% under no preload condition, and is less than 11% under different preload conditions, largely owing to the uneven distribution of clearance can increase the travel deviation. Further analysis shows that the eccentricity error, which belongs to the installation error, is the most important factor, mainly generating the periodic fluctuation and amplitude of the transmission error. More importantly, the travel deviation increases with the increase of the preload, which indicates that the transmission accuracy of the BSM deteriorates when the load is increased.

Keywords: Ball screw, transmission accuracy, error analysis, contact deformation

1. Introduction

Ball screws, which are widely used in CNC machine tools, have a great performance on dynamic stability and reliability [1]. Transmission error is an important index of acceptance conditions to evaluate the transmission accuracy of the ball screw, which can generate the velocity and position fluctuation of the worktable and affect its dynamic characteristics. Therefore, it is of significance to study the transmission accuracy of ball screw individually without drive, bearing and external load.

In the study of transmission accuracy for the functional elements of machine tools, existing researches mainly involve linear guide, spindle and roller screw. Hu et al. provided a new method based on the parallel mechanism to study the motion errors of the linear guideway, and developed the relationship between the straightness error and the motion error [4]. Choi et al. proposed a modified volumetric error model that includes spindle error motions and geometric errors to predict the positioning errors at a given axis position [5]. Ma et al. studied the transmission accuracy of a planetary roller screw mechanism under different working conditions, considering the elastic deformations, manufacturing errors and assembly errors [6]. Fu et al. proposed a kinematic model of the planetary roller screw, which accounted for the run-out errors of the screw, roller, nut, ring gear, and carrier, and the position errors of the nut and the pinhole in the carrier [7].

For the transmission accuracy of ball screw, Zhao et al. studied the position precision including travel deviation and variation by considering the load distribution of ball screw under axial and radial loads conditions, based on the measurement of initial precision without applied load [8]. Zhang et al. developed a predicted model considering geometric error and thermal error, which can compensate for the positioning error during the temperature rising of the ball screw [9]. For the assembly of the ball screw, different preload will change the contact status between ball and raceway, which will affect the transmission error. Although lots of research have been carried out on the load distribution of BSM due to manufacturing errors [10], very few researches can be found on the transmission accuracy modelling for BSM considering the manufacturing errors, installation errors, as well as the errors due to the contact deformation under different loading status.

Therefore, this paper provides a detailed analysis to estimate the transmission accuracy of ball screw caused by errors and preloading level. In section 2, the transmission error caused by the manufacturing error, installation

error and contact deformation is discussed, and the transmission accuracy models of the screw shaft and ball screw are analyzed. In section 3, a measuring system for transmission accuracy of ball screw is used to verify the proposed model, and the error of the system and ball screw are analyzed and calibrated. In section 4, an error simulation is conducted, and the experimental results are compared with the theoretical values. Finally, section 5 is the conclusion of the paper.

2. Theoretical analysis

The transmission error of the ball screw refers to the difference between the theoretical position and the actual position of the nut during the screw rotation and nut axial movement [18]. Similarly, the transmission error of the screw shaft can be measured with the position difference of the measuring ball contacting with the raceway. Combined with the industrial application of ball screw, the transmission error may originate from machining and installation [19], and the preload can change the contact state, which affect the actual position of the nut. All factors affecting the transmission error can be analyzed after being converted to the axial direction.

2.1 Analysis of error source

2.1.1 Manufacturing errors

2.1.1.1 Profile error

Considering the relative length of the nut, the manufacturing error can be ignored compared with the screw shaft. During the machining of screw shaft, due to the grinding wheel with errors, and the relative motion of the grinding wheel and ball screw, the raceway error, contact angle, lead error may be affected. As presented in Fig. 1, a gothic arc profile and a standard circle are in the $X_2O_2Z_2$ plane, where O_2 is the ball center; r_b is the ball radius; G_L and G_R are the centers of left and right arc respectively; e is the eccentricity; β is the contact angle; θ is the central angle corresponding to the point on the profile. The contact angle can be obtained from:

$$e = (r_G - r_b) \sin \alpha^0 \quad (1)$$

where r_G is the arc radius of the raceway.

Fig. 1 Contact between ball and raceway on the normal section

The coordinate system in normal section is established according to the ball center, and the left arc of the raceway can be expressed by the function:

$$A_{RC_L}(\theta) = \begin{cases} (r_{LG} - r_b) \cos \alpha^0 - r_{LG} \cos \theta \\ 0 \\ e - r_{LG} \sin \theta \end{cases} \quad (2)$$

Accordingly, the points on the right arc of the raceway can be obtained. As presented in Fig. 2, a global coordinate system XYZ , with its origin fixed on the screw axis, is established such that its Z -axis is along the screw axis, and the XOY plane is vertical to the screw axis. A local coordinate system $X_2Y_2Z_2$, with its origin on the ball center trace, is established such that its Y_2 -axis is tangent to the helical line of the ball center trace, and its X_2 -axis is along the line from screw axis to ball center. The raceway error in normal section is mainly in two cases. The raceway contact angle is constant, while the raceway arc radius has machining error Δr , as shown in the arc ①; the raceway contact angle and raceway arc radius have errors at the same time, as shown in the arc ②. And the ball center can be obtained by the tangency relation between the ball and two arcs, which can be expressed as:

$$\begin{cases} (x_{Lc} - x_b)^2 + (y_{Lc} - y_b)^2 = (r_{LG} - r_b)^2 \\ (x_{Rc} - x_b)^2 + (y_{Rc} - y_b)^2 = (r_{RG} - r_b)^2 \end{cases} \quad (3)$$

where (x_{Lc}, y_{Lc}) and (x_{Rc}, y_{Rc}) are the center of the left and right arc of the raceway, respectively; r_{LG} and r_{RG} are the radii of the left and right arc respectively; (x_b, y_b) is the coordinate of the ball center. By combining the tangent condition, the variation δ_{bi} of the ball center O_b relative to the initial position in the b direction can be obtained.

Fig. 2 Manufacturing errors of ball screw raceway profile

2.1.1.2 Lead error

The lead error reflects the difference between the actual position and the theoretical position of ball center when the ball rolling through each raceway along the axial single generatrix, which has an impact on the load distribution and transmission accuracy of the ball screw. By measuring the raceway along a single generatrix with 300 mm or the whole effective travel, the accumulative error ΔP_L in the axial direction can be obtained, and the travel error caused by the lead error can be calculated as:

$$\Delta d_l = \Delta P_L / L \quad (4)$$

2.1.1.3 Eccentricity error of screw shaft

During the machining of ball screw, the misalignment between the central line of the tip hole and the axis of the spiral raceways is inevitable. The error can cause the raceway runout during the screw rotation, which has a periodic impact on the transmission error. For the raceway at different positions, the phase angle λ (rad) is introduced to represent the location of the ball center. The ball center trajectory in coordinate system XYZ

which follows the helical line is given by the function:

$$\begin{cases} X = r_m \cdot \cos \lambda \\ Y = r_m \cdot \sin \lambda \\ Z = \frac{\lambda}{2\pi} P_h \end{cases} \quad (5)$$

where r_m is half of the theoretical pitch diameter of the screw; P_h is the lead. Since the projection of the helical line on the axial section is a sinusoidal curve, the projected sinusoidal curve will move along the axis as the screw rotates around the axis. Due to the axis eccentricity, the nut will move slightly forward or backward from the original position, that is, causing an error in the axial direction. As presented in Fig. 3, the error can be obtained by the trigonometric function.

Fig. 3 Diagram of eccentricity error of screw shaft

$$\Delta d_e' = e_{sc} \sin \lambda_s \tan \theta_l \quad (6)$$

where e_{sc} is the eccentricity of the screw, λ_s is the circumference angle of the screw around the axis, θ_l is the inclination angle of the sinusoidal curve caused by the eccentricity. Considering the angle θ_l which changes with Z coordinate is hard to determine, to accurately analyze the travel deviation, the relationship of transmission error is expressed by the curve difference. This paper takes the measuring rod connecting with the nut or ball as the measuring reference. The circular motion of the measuring reference around the axis can be regarded as an additional eccentricity is added to the X coordinate. The travel affected by the eccentricity is expressed as:

$$x_e = r_m \cdot \sin(z \cdot 2\pi / P_h) + e_{sc} \cdot \sin \lambda_s \quad (7)$$

When x_e is equal to 0, the corresponding Z coordinate represents the current travel, and the difference with the nominal lead can be considered as the travel error caused by the eccentricity error.

$$\Delta d_e = z \Big|_{x_e=0} - P_h \quad (8)$$

2.1.1.4 Roundness error of raceway

Since the error of the machine tool spindle on the error sensitive direction, or the unreasonable support during processing, the helical line of the screw has a roundness error. Assuming the axial view is the ellipse shape, the radius of the helical line can be expressed as follows.

$$\rho_r = \frac{r_m(r_m + e_r)}{\sqrt{r_m^2 \cos^2 \lambda_s + (r_m + e_r)^2 \sin^2 \lambda_s}} \quad (9)$$

Combining with the influence of eccentricity, the travel and travel error caused by the roundness error of raceway are as follows:

$$x_r = \rho_r \cdot \sin(z \cdot 2\pi / P_h) + e_{sc} \cdot \sin \lambda_s \quad (10)$$

$$\Delta d_r = z \Big|_{x_r=0} - P_h \quad (11)$$

2.1.2 Installation errors

2.1.2.1 Error caused by the support unit

For the ball screw with a large aspect ratio, support is necessary to reduce the bending deformation. Considering the fluctuation in the radial direction, the bending trend can be regarded as a quasi sinusoidal curve. As shown in Fig. 4, when the middle support unit is higher than the allowable value, the measured screw will move upward as a whole. Since the raceway is right-handed, the measuring reference will move downward obliquely, which will cause the opposite trend of the travel error for the forward and reverse measurement.

Fig. 4 Diagram of bending error caused by the support unit

Due to the influence of gravity, the deflection of ball screw is as follows:

$$x_g = \frac{1}{EI} \left(\frac{q}{24} z^4 - \frac{ql}{12} z^3 + \frac{ql^3}{24} z \right) \quad (12)$$

where q is the gravity of the ball screw per unit length, E is the elastic modulus, and I is the polar moment of inertia. Then the travel caused by the screw support and weight is:

$$x_s = r_m \cdot \sin(z \cdot 2\pi / P_h) + (x_g - x_b) \cdot \sin(z \cdot 2\pi / 2L) \quad (13)$$

where x_b is the jacking height of the middle support unit. The travel error caused by the support unit is as follows:

$$\delta_{sg} = z \Big|_{x_s=0} - P_h \quad (14)$$

2.1.2.2 Inclined installation error

Since the ball screw is installed by the center hole, it will be inclined if the height of both apexes cannot be guaranteed. As shown in Fig. 5, to tilt coordinate system XOZ to coordinate system $X'O'Z'$, the error coordinate system can be obtained by translation and rotation sequentially:

Fig. 5 Diagram of error caused by inclined installation

$$\begin{bmatrix} z' \\ x' \end{bmatrix} = \begin{bmatrix} \cos \theta_t & -\sin \theta_t \\ \sin \theta_t & \cos \theta_t \end{bmatrix} \begin{bmatrix} Z - Z_o \\ X \end{bmatrix} + \begin{bmatrix} Z_o \\ 0 \end{bmatrix} \quad (15)$$

$$\theta_t = \arctan\left(\frac{e_{sc} \cdot \sin \lambda}{L}\right) \quad (16)$$

By changing Z_o , the intersection coordinate between the curve and Z-axis is obtained. The difference between the travel and the lead at the corresponding time is the variation of the travel error.

$$\delta_{in} = z'|_{x'=0} - P_h \quad (17)$$

2.1.3 Error caused by contact deformation

When the screw shaft is matched with the nut, the ball and raceway will be deformed under the axial force, which is different from merely taking the screw shaft into account. For a single-nut ball screw, assuming that the ball size is not large enough to produce preload, the load and deformation are analyzed as follows. As shown in Fig. 6, the screw is compressed and the nut is compressed, which corresponding to the C-C state.

Fig. 6 Diagram of force balance caused by F_a for ball screw

Under the static loading state, the total contact load of balls can be expressed as:

$$F_a = \sum_{i=1}^M Q_i \sin \alpha_i \cos \varphi \quad (18)$$

where F_a is the applied axial force; Q_i is the contact load of the i_{th} ball; M is the total number of balls; α_i is the contact angle between i_{th} ball and raceway; φ is the helical angle of ball screw.

According to Mei's model, the nut and screw are not regarded as rigid bodies, and the deformations of balls under different positions are various due to the plastic deformation [11]. To analyze the contact load between ball and raceway, the screw and nut can be divided into several parts, that is, each ball and its contact region with nut and screw are regarded as a force unit. The length of the screw and nut between two adjacent balls is:

$$\Delta L_{ni} = \Delta L_{si} = \frac{P_h}{z} \quad (19)$$

where ΔL_{si} and ΔL_{ni} are the unit length of screw and nut; P_h is the lead of ball screw; z is the effective bearing number of balls in one circle.

Fig. 7 Diagram of the deformation caused by F_a for ball screw

As shown in Fig. 7, the force acting on the screw or nut between adjacent balls is unequal.

$$F_{si} = \begin{cases} F_a - \sum_{j=1}^i Q_j \sin \alpha_j \cos \varphi, & i = 1, 2, 3, \dots, M-1 \\ 0, & i = M \end{cases} \quad (20)$$

$$F_{ni} = \begin{cases} F_a - \sum_{j=i+1}^M Q_j \sin \alpha_j \cos \varphi, & i = 1, 2, 3, \dots, M-1 \\ F_a, & i = M \end{cases} \quad (21)$$

where F_{si} and F_{ni} are the axial force submitted to the i_{th} unit, respectively. According to the deformation coordination relation, the following correlation can be obtained.

$$\Delta n_i - \Delta s_i = (\delta_{s,i+1} + \delta_{n,i+1}) - (\delta_{s,i} + \delta_{n,i}) \quad (22)$$

where Δs_i and Δn_i are the axial deformations for the unit length of screw and nut; $\delta_{s,i}$ and $\delta_{n,i}$ are the axial projection of the contact deformation between the i_{th} ball and the screw, nut.

$$\Delta n_i = \frac{\Delta L_{ni}}{E_n A_n} \cdot F_{ni} \quad (23)$$

$$\Delta s_i = \frac{\Delta L_{si}}{E_s A_s} \cdot F_{si} \quad (24)$$

where E_s and E_n are the elastic moduli of the screw and nut; A_s and A_n are the cross-section area of the screw and nut.

Fig. 8 Relationship of raceway centers on the normal section

For the contact between the ball and raceway, the deformation relation is constructed in Fig. 8. After the axial loading, the center of ball O_{bi} , raceway center of screw O_{si} and raceway center of nut O_{ni} move a

distance to O_{bi}' , O_{si}' and O_{ni}' , respectively. And the initial contact angle α^0 will become α_i .

$$\alpha_i = \sin^{-1} \frac{V_{bi}}{\sqrt{V_{ni}^2 + V_{bi}^2}} \quad (25)$$

where V_{ni} and V_{bi} are the projection distances of the center distance in n direction and b direction, respectively.

$$V_{ni} = V_{n0} + \delta_{ni} = L_{ns} \cos \alpha^0 + [\delta_{n-i} + (i-1)\Delta L \sin \theta'] \cos \psi_i \quad (26)$$

$$V_{bi} = V_{b0} + \delta_{bi} = L_{ns} \sin \alpha^0 + \delta_{bi} \quad (27)$$

$$L_{ns} = r_{Gs} + r_{Gn} - 2r_b \quad (28)$$

where V_{n0} and V_{b0} are the projection distances of the initial center distance in n direction and b direction, respectively; δ_{ni} and δ_{bi} are the displacements of screw center in n direction and b direction; L_{ns} is the center distance between the center of screw and nut; r_{Gs} and r_{Gn} are the radii of screw and nut. According to Hertz's contact and deformation geometry, the relationship between axial and normal deformation is obtained.

$$\delta_{i-a} = \delta_{s,i} + \delta_{n,i} \quad (29)$$

$$\delta_{i-a} = \frac{\delta_i}{\sin \alpha_i \cdot \cos \varphi} \quad (30)$$

$$\delta_i = c_K \cdot c_E^2 \cdot Q_i^{\frac{2}{3}} \quad (31)$$

$$c_K = Y_s \cdot \left(\sum \rho_s \right)^{\frac{1}{3}} + Y_n \cdot \left(\sum \rho_n \right)^{\frac{1}{3}} \quad (32)$$

$$Y_s = 1.282 \left[-0.154 (\sin \tau_s)^{1/4} + 1.348 (\sin \tau_s)^{1/2} - 0.194 \sin \tau_s \right] \quad (33)$$

$$Y_n = 1.282 \left[-0.154 (\sin \tau_n)^{1/4} + 1.348 (\sin \tau_n)^{1/2} - 0.194 \sin \tau_n \right] \quad (34)$$

where δ_{i-a} is the sum of axial deformation of the contact point between screw and nut; δ_i is the sum of normal deformation of the contact point between screw and nut; Y_s and Y_n are the auxiliary values of the screw and nut for the first and second type elliptic integrals in Hertzian contact theory; c_E is the material constant; ρ_s and ρ_n are the reciprocal of the curvature radius at the contact point with screw and nut respectively.

$$\sum \rho_s = \frac{4}{D_b} - \frac{1}{f_s D_b} + \frac{2 \cdot \cos \alpha_i}{D_{pw} - D_b \cos \alpha_i} \quad (35)$$

$$\sum \rho_n = \frac{4}{D_b} - \frac{1}{f_n D_b} - \frac{2 \cdot \cos \alpha_i}{D_{pw} + D_b \cos \alpha_i} \quad (36)$$

$$\cos \tau_s = \left| \frac{-(f_s \cdot D_b)^{-1} - 2 \cos \alpha_i \cdot (D_{pw} - D_b \cdot \cos \alpha_i)^{-1}}{\sum \rho_s} \right| \quad (37)$$

$$\cos \tau_n = \left| \frac{-(f_n \cdot D_b)^{-1} + 2 \cos \alpha_i \cdot (D_{pw} + D_b \cdot \cos \alpha_i)^{-1}}{\sum \rho_n} \right| \quad (38)$$

where D_{pw} is the ball pitch circle diameter; f_s and f_n are the conformities of screw and nut. The contact load and deformation corresponding to each ball can be solved by iterations using the Newton-Raphson method, which is shown as follows:

$$\mathbf{x}^{(t+1)} = \mathbf{x}^{(t)} - \mathbf{J}(\mathbf{x}^{(t)})^{-1} \cdot \mathbf{f}(\mathbf{x}^{(t)}) \quad (39)$$

When the screw and nut are stressed at the end, to analyze the displacement of the nut relative to the shaft end, the deformation of the ball, the raceway and the deformation of the non-contact area of the screw and nut need to be considered. While for the double-nut ball screw under no axial load, the axial deformation of the ball in the nuts on both sides presents the situation of that in the single nut, and the relative displacement of the nut can be regarded as that of the single-nut under axial load. The relative displacement under preload can be expressed as:

$$\Delta L_m = \delta_{M-a} + \sum_{i=1}^M (\Delta n_i + \Delta s_i) \quad (40)$$

2.2 Modelling of transmission accuracy

The transmission error of the ball screw is affected by many factors, the most important of which is temperature. The thermal deformation error is approximately linear, which can be expressed as:

$$\delta_c(t) = a + bt \quad (41)$$

Periodic error is a combination of multiple harmonic errors, which is mainly composed of the runout of the machine tool spindle, the master screw error of the feed ball screw, raceway error, eccentricity, shaft bending, etc. The periodic error can be expressed as the superposition of several sinusoidal functions:

$$\delta_p(t) = \sum_{i=0}^N A_i \sin(i\omega t + \theta_i) \quad (42)$$

Accidental error is caused by workpiece surface defects and interference of external vibration to the grinding wheel, which can be expressed as:

$$\delta_r \sim N(0, \sigma^2) \quad (43)$$

2.2.1 Transmission error of screw shaft

Assuming that the manufacturing errors and installation errors of the screw are independent of each other, the transmission error of the screw can be expressed as the sum of the various errors:

$$E_s = \Delta d_p + \Delta d_l + \Delta d_e + \Delta d_r + \delta_{sg} + \delta_{in} \quad (44)$$

Fig. 9 Main parameters of transmission accuracy for ball screw

As shown in Fig. 9, the regression line is calculated by the error curve, and then the average travel deviation is calculated by the regression line. e_p represents the travel deviation; T represents the temperature compensation of the travel.

$$\begin{cases} e_a = a + br \\ a = \frac{\sum r_i^2 \sum e_i^2 - \sum r_i \sum r_i e_i}{n \sum r_i^2 - \sum r_i \sum r_i}; b = \frac{n \sum r_i e_i - \sum r_i \sum e_i}{n \sum r_i^2 - \sum r_i \sum r_i} \end{cases} \quad (45)$$

where r is the rotation angle and r_i is the rotation angle of the i th measuring position, e_i is the travel deviation of the i th measuring position, and n is the number of measuring points. The residual value is obtained by the measured variation curve:

$$Z_i = e_i - (a + b \cdot r_i) \quad (46)$$

2.2.2 Transmission error of ball screw

When considering the transmission error with the nut, deformations between the ball, the screw and the nut raceway needs to be taken into account. Combined with the screw shaft error, the nut needs to overcome the influence of the manufacturing errors, installation errors and contact deformation during the axial movement. Therefore, the transmission error of the ball screw is as follows:

$$E_{bs} = \Delta d_p + \Delta d_l + \Delta d_e + \delta_{sg} + \delta_{in} + \Delta L_m \quad (47)$$

3. Experimental verification

3.1 Transmission accuracy measurement

To obtain the transmission accuracy, the principle is measuring the difference between the actual position and theoretical position of ball screw, which can be expressed in Fig. 10. Collecting the angular displacement θ of the screw rotation and the horizontal displacement along the screw raceway, the travel variation within the specified travel can be obtained. For the theoretical curve of transmission error, the abscissa X is the measured data from the length measuring system, and the ordinate Y is the difference between the actual travel and theoretical travel.

$$\begin{cases} X = x \\ Y = x - \frac{\theta}{2\pi} P_h \end{cases} \quad (48)$$

Fig. 10 The principle of the transmission accuracy measurement for ball screw

According to the measuring principle, a transmission accuracy measuring system for the ball screw is constructed, as shown in Fig. 11. The measuring system is composed of headstock, tailstock, support unit, mobile platform, laser length measuring system, circular grating, industrial computer, etc. The ball screw is installed by the headstock and tailstock, and the apex spring is used in the tailstock to eliminate the effect on the thermal elongation of the ball screw. A chuck is used in the headstock rotating device to connect one end of the ball screw. During the measurement, the ball screw is driven by a servo motor inside the headstock, and its angular displacement is measured by a circular grating connecting with the rotating device.

When measuring the transmission accuracy of the ball screw, the measuring reference is rigidly connected with the nut flange, and the rotation of the screw drives the measuring reference connected with the worktable to move along the axial direction. When measuring the transmission accuracy of the screw shaft, the same size ball on the measuring reference is meshed with the raceway. The worktable moves linearly with the rotation of the screw, and its horizontal displacement is measured by a laser measuring system. The angular and horizontal displacement are collected by an industrial control computer at the same time. The travel deviation of the ball screw can be obtained by software processing. For the ball screw with a large aspect ratio, a fixed support unit is used at the middle position when measuring the transmission error of the screw shaft. When measuring the transmission error of the ball screw, a movable support unit is placed under the nut to reduce the deflection caused by the weight.

Fig. 11 Measuring system of transmission accuracy for ball screw

For the gasket preloading ball screw R50-10, its structural parameters are shown in Table 1. The transmission error of the screw shaft and the ball screw are measured. The preload between two nuts can be changed by replacing the gaskets with incremental thickness, and the preload is calculated according to the friction torque of the ball screw. Combined with the proposed model, the predicted value of transmission error can be calculated. The difference between the experimental result and the theoretical value is compared to verify the validity of the calculated model.

Table 1 Specifications of the analyzed ball screw

Parameters	Value	Unit
Nominal radius of ball screw r_m	25	mm
Helical pitch P_h	10	mm
Lead angle β	3.64	degree
Radius of the ball r_b	5.953	mm
Radius of the raceway r_s	3.274	mm
Eccentricity of the raceway e	0.21	mm
Contact angle α^0	45	degree
Length of raceways	1100	mm
Accuracy grade	P2	
Circle's number i	4	

3.2 Error analysis of measuring system

Considering the performance of the measuring system is significantly influenced by the accuracy of the component assembly, systematic errors are analyzed and calibrated. Systematic errors mainly come from static errors and motion errors, which are related to the accuracy of the sensors and their installation mechanism.

3.2.1 Straightness error of the mobile platform

The measuring module is carried by the air-floating platform. This means that its vertical straightness will make the measuring reference move slightly along the raceway of the ball screw, resulting in the axial error and affecting the data accuracy. Since the measuring reference in the horizontal direction is compressed by the spring, the horizontal straightness of the platform will not affect the accuracy. Therefore, the air floating platform is calibrated by Renishaw laser interferometer system XL-80, and the whole measurement curve is analyzed. Considering the lead of the measured ball screw is 10 mm, the mobile platform error is $e_1 = 0.73\mu\text{m}$.

3.2.2 Abbe error

The length measuring laser should be parallel with the platform mobile direction during measurement, which enables the displacement record accurately. By calibrating the angle error of the laser and the axis of the ball screw, the displacement measured results can be compensated. The installation deflection angle can be ensured within 0.1° after calibration. Considering the measuring distance is within 1000mm, and combining the relationship between real and measured displacement, the abbe error is $e_2 = 0.015\mu\text{m}$.

3.2.3 Laser measuring system error

According to the index of the laser length measuring system, the error in the effective length is $0.7\mu\text{m/m}$. Considering the lead of the measured ball screw is 10 mm, the maximum measurement error in the axial direction is $e_3 = 0.007\mu\text{m}$.

3.2.4 Circular grating error

According to the index of Heidenhain circular grating, the measurement accuracy is 5" for circumferential

displacement. Considering the lead of the measured ball screw is 10 mm, the maximum measurement error in the axial direction is $e_4 = 0.039\mu\text{m}$.

Assuming that the errors are independent of each other, the accuracy of the measurement system can be calculated as $\sqrt{e_1^2 + e_2^2 + e_3^2 + e_4^2} = 0.73\mu\text{m}$.

Considering the accuracy grade of the ball screw is P2 and the measured travel is 1000mm, the system measuring error $0.73\mu\text{m}$ can meet the tolerance of measurement requirements [18].

3.3 Error analysis of ball screw

3.3.1 Measurement of the raceway profile of screw shaft

For the measured ball screw R50-10, the manufacturing errors and installation error can be obtained only by measurement. As shown in Fig. 12, the axial profile of the screw was measured using a Hommel-Etamic T8000 roughness profilometer, at a speed of 12mm min^{-1} . The probe was set to move the travel of 300 mm and the whole travel along the screw generatrix, and the lead error under a specific travel is analyzed. Furthermore, the normal profile of raceways in the middle and ends were measured at five different positions with the distance between two adjacent positions set as 200 mm. To reflect the roundness error of the raceways, the pitch diameter was measured by the NNY hand-held measuring instrument at the same measured raceway, and each raceway was measured at three positions with the angle between two positions set as 120° .

According to the measurement and analysis, the cumulative lead error is 0.004mm, and the maximum roundness error of raceways is 0.003mm. Maximum raceway asymmetry of arc and contact angle are 0.003mm and 0.49° respectively, within the acceptable range.

Fig. 12 Measurement of profile error and roundness error for ball screw

3.3.2 Eccentricity error and installation error of screw shaft

As shown in Fig. 13, the eccentricity error and installation error can be measured on the workbench. The screw shaft was installed on the headstock and tailstock through the center hole. The dial gauge can move along the axial direction by fixing with the mobile platform.

During the measurement, the screw shaft was driven to rotate at the speed of 10r/min. Meanwhile, the dial gauge was set to contact with the precision surface of the screw shaft to record the runout. In the process of screw shaft rotation, half of the indication difference of the maximum and the minimum of the dial indicator was taken as the run-out error, and the mean value of three times was taken as the eccentric error. The height indication of the apex for the headstock and tailstock was recorded respectively, and the difference was taken as the tilt installation error of the ball screw. The height difference of the middle support and two ends are

regarded as the support error. The measuring results are listed in Table 2.

Fig. 13 Measurement of the tilt error and eccentricity error

Table 2 Measuring results of eccentricity error and installation error (mm)

Measuring indexes	1	2	3	Average
Eccentric error of screw	0.011	0.010	0.010	0.010
Inclined error of ball screw	0.011	0.012	0.011	0.011
Support error of ball screw	0.016	0.013	0.015	0.015

4. Results and discussion

4.1 Simulation of transmission accuracy

Based on the above analysis, the simulation is conducted by substituting the measured errors into eq. (44), and the results calculated by the program are shown in Fig. 14. The theoretical transmission error curve within 10 cycles is given, which shows a descending periodic fluctuation of transmission error. The maximum amplitude of the curve is about $1.3\mu\text{m}$, and the frequency is $2\pi/T$, where T is the time consumption for one revolution of screw. The descending trend of the curve is mainly caused by the negative lead error. The eccentric error has an important influence on the amplitude of the transmission error. That is because the eccentric error will produce the end jitter, and the transmission error caused by other errors affects the fluctuation based on the periodic variation.

Fig. 14 Theoretical transmission error curve of the ball screw

4.2 Experimental results

In the experiment, considering the influence of the environment on the laser measuring system and the ball screw, all the related experiments were carried out in the constant temperature chamber with $20\pm0.5^{\circ}\text{C}$ and $50\pm10\%$ humidity. Considering the temperature is the main factor affecting the travel deviation of the ball screw, it is necessary to keep the real-time temperature of the ball screw at about 20°C . When the temperature of the ball screw is lower than the required value, it should be heated by a period of high-speed running. When the temperature of the ball screw is higher than the required value, it should be cooled by a fan.

The transmission error measurements of the ball screw under different preload level were carried out at the speed of 20r/min, in which the preload is adjusted by inserting different gaskets [20]. After the measuring system running smoothly, the forward transmission error of the ball screw within 1000mm was measured three times. After analyzing the average, the measurement curves of the first 10 cycles under no preload are shown in Fig. 15, and curves under each preload level are shown in Fig. 16. The transmission error of ball screw under no preload and different preload shows a regular periodicity, which is in accordance with the rotational cycle. Different from the theoretical curve, the actual curves present the characteristics of sharp peaks and burrs, which may be caused by the superposition of several eccentricity errors and the external vibration on the grinding wheel.

Fig. 15 Transmission accuracy of ball screw with no preload

(a) 2kN

(b) 4kN

(c) 6kN

(d) 8kN

Fig. 16 Transmission accuracy of ball screw with different preload

The travel deviation of the ball screw is $-2.68\mu\text{m}$ under no preload, while the deviation obviously increases with the preload increase. The travel deviations are $-7.61\mu\text{m}$ at 2kN, $-9.92\mu\text{m}$ at 4kN, $-12.7\mu\text{m}$ at 6kN and $-14.4\mu\text{m}$ at 8kN. The comparison between the experimental results and the theoretical values is shown in Table 3. In absolute terms, the increased trend of the theoretical results is consistent with the experimental results, which shows the travel deviation increases with the increase of the preload, and the predicted values are smaller than the experimental results. The largest difference between the theoretical results and the experimental results is 21.6% under no preload condition, which is probably because the uneven distribution of clearance between ball and screw, nut can increase the travel deviation. The other predicted differences are less than 11%, which shows the accuracy of the proposed model.

Table 3 Comparison of the experimental results with the theoretical results

Preload level(N)	Travel deviation (μm)		Difference
	Experimental	Predicted	
0	-2.68	-2.1	21.6%
2000	-7.61	-6.7	10.8%
4000	-9.92	-9.4	5.2%
6000	-12.7	-11.8	7.1%
8000	-14.4	-13.8	4.2%

5. Conclusions

In this paper, the transmission accuracy model of ball screw under no preload and different preload conditions considering the manufacturing errors, installation errors and contact deformation are proposed based on the error formulas and measurement. The error analysis shows the eccentric error takes the most important role in the amplitude of the transmission error, and the fluctuation period of the curve is in accordance with the rotational speed.

Furthermore, the transmission errors of the ball screw under different preload conditions are measured based on a measuring system. After the systematic error analysis and calibration, total measuring accuracy can meet the measurement requirements. The experimental results show the travel deviation is related to the preload, that is, travel deviation increases with increasing the preload. Except for the no preload condition, the difference

between the experimental results and the predicted values is less than 11%, which indicates the uneven distribution of clearance between ball and screw, nut can increase the travel deviation under the no preload condition. The study can provide a reliable theoretical basis for further analysis concerning the effect of transmission error on the performance of CNC machine tools.

Declarations

Funding. This project is supported by the National Science and Technology Major Projects of China (No. 2019ZX0401001), National Natural Science Foundation of China (Grant No. 51705252, 51905274).

Conflicts of interest/Competing interests. The authors declare that they have no conflicts of interest.

Availability of data and material. Data transparency.

Code availability. Custom code.

References

- [1] Rahmani M, Bleicher F. Experimental and numerical studies of the influence of geometric deviations in the performance of machine tools linear guides[J]. *Procedia CIRP*, 2016, 41: 818-823.
<https://doi.org/10.1016/j.procir.2015.08.089>.
- [2] Cheng Q, Qi B, Liu Z, et al. An accuracy degradation analysis of ball screw mechanism considering time-varying motion and loading working conditions[J]. *Mechanism and Machine Theory*, 2019, 134: 1-23.
<https://doi.org/10.1016/j.mechmachtheory.2018.12.024>.
- [3] Min, X., & Jiang, S. (2011). A thermal model of a ball screw feed drive system for a machine tool. *Proceedings of the Institution of Mechanical Engineers, Part C: Journal of Mechanical Engineering Science*, 225(1), 186-193.
<https://doi.org/10.1177/09544062JMES2148>.
- [4] Hu P H, Lei Y J, Ou Y K. Analysis of Motion Errors of Linear Guide Pair Based on Parallel Mechanism[J]. *Machines*, 2021, 9(2): 33.
<https://doi.org/10.3390/machines9020033>.
- [5] Choi J P, Lee S J, Kwon H D. Roundness error prediction with a volumetric error model including spindle error motions of a machine tool[J]. *The International Journal of Advanced Manufacturing Technology*, 2003, 21(12): 923-928.
<https://doi.org/10.1007/s00170-002-1407-y>.
- [6] Ma S, Cai W, Wu L, et al. Modelling of transmission accuracy of a planetary roller screw mechanism considering errors and elastic deformations[J]. *Mechanism and Machine Theory*, 2019, 134: 151-168.
<https://doi.org/10.1016/j.mechmachtheory.2018.12.025>
- [7] Fu X, Liu G, Ma S, et al. Kinematic model of planetary roller screw mechanism with run-out and position errors[J]. *Journal of Mechanical Design*, 2018, 140(3).
<https://doi.org/10.1115/1.4039005>.
- [8] Zhao J, Lin M, Song X, et al. A novel approach to predict the precision sustainability of ball screw under multidirectional load states[J]. *Proceedings of the Institution of Mechanical Engineers, Part C: Journal of Mechanical Engineering Science*, 2020: 0954406220943238.
<https://doi.org/10.1177/0954406220943238>.
- [9] Zhang J, Li B, Zhou C, et al. Positioning error prediction and compensation of ball screw feed drive system with different mounting conditions[J]. *Proceedings of the Institution of Mechanical Engineers, Part B: Journal of Engineering Manufacture*, 2016, 230(12): 2307-2311.
<https://doi.org/10.1177/0954405416679444>.

- [10] Lin, B., Okwudire, C. E., & Wou, J. S. (2018). Low order static load distribution model for ball screw mechanisms including effects of lateral deformation and geometric errors. *Journal of Mechanical Design*, 140(2).
<https://doi.org/10.1115/1.4038071>.
- [11] Mei X, Tsutsumi M, Tao T, et al. Study on the load distribution of ball screws with errors[J]. *Mechanism and machine theory*, 2003, 38(11): 1257-1269.
[https://doi.org/10.1016/S0094-114X\(03\)00070-3](https://doi.org/10.1016/S0094-114X(03)00070-3).
- [12] Zhen N, An Q. Analysis of stress and fatigue life of ball screw with considering the dimension errors of balls[J]. *International Journal of Mechanical Sciences*, 2018, 137: 68-76.
<https://doi.org/10.1016/j.ijmecsci.2017.12.038>.
- [13] Zhao J, Lin M, Song X, et al. Investigation of load distribution and deformations for ball screws with the effects of turning torque and geometric errors[J]. *Mechanism and Machine Theory*, 2019, 141: 95-116.
<https://doi.org/10.1016/j.mechmachtheory.2019.07.006>.
- [14] B. Lin, et al. Low order static load distribution model for ball screw mechanisms including effects of lateral deformation and geometric errors. *Journal of Mechanical Design*, 2018, 140.2: 022301.
<https://doi.org/10.1115/1.4038071>.
- [15] Sobolewski J Z, MALKINSKI J. Estimation of the influence of machining errors on ball screw rigidity[J]. *Journal of Machine Engineering*, 2006, 6(2): 37-44.
- [16] Denisenko A. Impact of manufacturing errors of ball screw system on performance characteristics[C]//*MATEC Web of Conferences*. EDP Sciences, 2018, 224: 01042.
<https://doi.org/10.1051/mateconf/201822401042>
- [17] Sobolewski J Z. Some Remarks on the Ball Screw Rigidity[J]. *Machine Dynamics Problems*, 2006, 30(4): 122-130.
- [18] BS ISO3408-3 Acceptance conditions and acceptance tests, 2006.
- [19] Tao, L., Wang, Y., He, Y., et al. (2016). A numerical method for evaluating effects of installation errors of grinding wheel on rotor profile in screw rotor grinding. *Proceedings of the Institution of Mechanical Engineers, Part B: Journal of Engineering Manufacture*, 230(8), 1381-1398.
<https://doi.org/10.1177/0954405416654418>
- [20] Zhou C G, Feng H T, Chen Z T, et al. Correlation between preload and no-load drag torque of ball screws[J]. *International Journal of Machine Tools and Manufacture*, 2016, 102: 35-40.
<https://doi.org/10.1016/j.ijmachtools.2015.11.010>

Figures

Figure 1

Contact between ball and raceway on the normal section

Figure 2

Manufacturing errors of ball screw raceway profile

Figure 3

Diagram of eccentricity error of screw shaft

Figure 4

Diagram of bending error caused by the support unit

Figure 5

Diagram of error caused by inclined installation

Figure 6

please see the manuscript file for the full caption

Figure 7

please see the manuscript file for the full caption

Figure 8

Relationship of raceway centers on the normal section

Figure 9

Main parameters of transmission accuracy for ball screw

Figure 10

The principle of the transmission accuracy measurement for ball screw

Figure 11

Measuring system of transmission accuracy for ball screw

Figure 12

Measurement of profile error and roundness error for ball screw

Figure 13

Measurement of the tilt error and eccentricity error

Figure 14

Theoretical transmission error curve of the ball screw

Figure 15

Transmission accuracy of ball screw with no preload

(a) 2kN

(b) 4kN

(c) 6kN

(d) 8kN

Figure 16

Transmission accuracy of ball screw with different preload